

Keysight D9010EBSC IEEE802.3 bs/cd Test Application

Notices

© Keysight Technologies 2014-2021

No part of this manual may be reproduced in any form or by any means (including electronic storage and retrieval or translation into a foreign language) without prior agreement and written consent from Keysight Technologies as governed by United States and international copyright laws.

Trademarks

UNIX is a registered trademark of UNIX System Laboratories in the U.S.A. and other countries. Target is copyrighted by Thru-Put Systems, Inc.

Version

Version 2.10.24.0

Edition

June 2021

Available in electronic format only

Keysight Technologies, Inc.
1900 Garden of the Gods Road
Colorado Springs, CO 80907 USA

Warranty

THE MATERIAL CONTAINED IN THIS DOCUMENT IS PROVIDED "AS IS," AND IS SUBJECT TO BEING CHANGED, WITHOUT NOTICE, IN FUTURE EDITIONS. FURTHER, TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, KEYSIGHT DISCLAIMS ALL WARRANTIES, EITHER EXPRESS OR IMPLIED WITH REGARD TO THIS MANUAL AND ANY INFORMATION CONTAINED HEREIN, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. KEYSIGHT SHALL NOT BE LIABLE FOR ERRORS OR FOR INCIDENTAL OR CONSEQUENTIAL DAMAGES IN CONNECTION WITH THE FURNISHING, USE, OR PERFORMANCE OF THIS DOCUMENT OR ANY INFORMATION CONTAINED HEREIN. SHOULD KEYSIGHT AND THE USER HAVE A SEPARATE WRITTEN AGREEMENT WITH WARRANTY TERMS COVERING THE MATERIAL IN THIS DOCUMENT THAT CONFLICT WITH THESE

TERMS, THE WARRANTY TERMS IN THE SEPARATE AGREEMENT WILL CONTROL.

Technology Licenses

The hardware and/or software described in this document are furnished under a license and may be used or copied only in accordance with the terms of such license.

U.S. Government Rights

The Software is "commercial computer software," as defined by Federal Acquisition Regulation ("FAR") 2.101. Pursuant to FAR 12.212 and 27.405-3 and Department of Defense FAR Supplement ("DFARS") 227.7202, the U.S. government acquires commercial computer software under the same terms by which the software is customarily provided to the public. Accordingly, Keysight provides the Software to U.S. government customers under its standard commercial license, which is embodied in its End User License Agreement (EULA), a copy of which can be found at <http://www.keysight.com/find/sweula>. The license set forth in the EULA represents the exclusive authority by which the U.S. government may use, modify, distribute, or disclose the Software. The EULA and the license set forth therein, does not require or permit, among other things, that Keysight: (1) Furnish technical information related to commercial computer software or commercial computer software documentation that is not customarily provided to the public; or (2) Relinquish to, or otherwise provide, the government rights in excess of these rights customarily provided to the public to use, modify, reproduce, release, perform, display, or disclose commercial computer software or commercial computer software documentation. No additional government requirements beyond those set forth in the EULA shall apply, except to the extent that those terms, rights, or licenses are explicitly required from all providers of commercial computer software pursuant to the FAR and the DFARS and are set forth specifically in writing elsewhere in the EULA. Keysight shall be under no obligation to update, revise or otherwise modify the Software. With respect to any technical data as defined by FAR 2.101, pursuant to FAR 12.211 and 27.404.2 and DFARS 227.7102, the U.S. government acquires no

greater than Limited Rights as defined in FAR 27.401 or DFAR 227.7103-5 (c), as applicable in any technical data.

Safety Notices

CAUTION

A CAUTION notice denotes a hazard. It calls attention to an operating procedure, practice, or the like that, if not correctly performed or adhered to, could result in damage to the product or loss of important data. Do not proceed beyond a CAUTION notice until the indicated conditions are fully understood and met.

WARNING

A WARNING notice denotes a hazard. It calls attention to an operating procedure, practice, or the like that, if not correctly performed or adhered to, could result in personal injury or death. Do not proceed beyond a WARNING notice until the indicated conditions are fully understood and met.

Contents

1 Overview

IEEE802.3 bs/cd Automated Testing—At a Glance / 10

Required Equipment and Software / 11

Hardware / 11

Software / 11

Licensing information / 11

2 Installing the Test Application and Licenses

Installing the Test Application / 14

Installing the License Key / 15

Using Keysight License Manager 5 / 15

Using Keysight License Manager 6 / 16

3 Preparing to Take Measurements

Calibrating the Oscilloscope / 20

Starting the IEEE802.3 bs/cd Test Application / 21

Configuring IEEE802.3 bs/cd Test Application for test runs / 24

Exporting Measurement Results to Repository / 28

KS6800A Series Analytics Service Software / 36

List of tests for Standard Option - Signal Type combinations / 37

4 PAM4 Transmitter Characteristics at TP0a

C2C transmitter characteristics / 42

PAM4 GAUI-x tests / 42

For CR tests / 43

For PAM4 KR tests / 44

Jitter and Signaling Rate Measurements TP0a / 45

Signaling Rate / 46

JRMS / 47

J4u / 48

Even-Odd Jitter / 49

Output Voltage Measurements EYE TP0a / 50

- Level - PRBS Pattern / 51
- Level RMS - PRBS Pattern / 52
- Level Separation Mismatch Ratio - RLM / 53

Output Waveform Measurements TP0a / 54

- Steady State Voltage Vf / 55
- Linear Fit Pulse Peak / 56
- Signal-to-noise-and-distortion ratio / 57
- SNR_ISI Tests / 58
- Pre and Post Equalization Tests / 59

Main Voltage Measurements TP0a / 70

- Differential Peak-to-Peak Output Voltage Test with TX Disabled / 71
- DC Common Mode Output Voltage Test / 72
- AC Common Mode Output Voltage Test / 73
- Differential Peak-to-Peak Output Voltage Test / 74

Return Loss ENA/PNA Measurements / 75

- Differential Output Return Loss / 76
- Common-mode Output Return Loss / 77

5 PAM4 Host Output Characteristics at TP1a

200GAUI-4 and 400GAUI-8 C2M host output electrical characteristics / 80

Main Voltage Measurements TP1a / 81

- Differential Peak-to-Peak Output Voltage Test with TX Disabled / 82
- Differential Peak-to-Peak Output Voltage Test / 83
- AC Common Mode Output Voltage Test / 84
- DC Common Mode Output Voltage Test / 85
- Single-ended Output Voltage Test / 86

Transition Time Measurements TP1a / 87

- Minimum Output Rise Time (20%-80%) / 88
- Minimum Output Fall Time (20%-80%) / 89

Signaling Rate and Eye Mask Measurements TP1a / 90

- Signaling Rate / 91
- Eye Height A / 92
- Eye Width / 93
- ESMW / 94

Return Loss ENA/PNA Measurements / 95

- Differential Output Return Loss / 96
- Common-mode to Differential Output Return Loss / 97

6 PAM4 Transmitter Characteristics at TP2

C2C transmitter characteristics / 100

For CR tests / 100

Jitter and Signaling Rate Measurements TP2 / 102

Signaling Rate / 103

JRMS / 104

J4u / 105

Even-Odd Jitter / 106

Output Voltage Measurements EYE TP2 / 107

Level - PRBS Pattern / 108

Level RMS - PRBS Pattern / 109

Level Separation Mismatch Ratio - RLM / 110

Output Waveform Measurements TP2 / 111

Steady State Voltage Vf / 112

Linear Fit Pulse Peak / 113

Signal-to-noise-and-distortion ratio / 114

SNR_ISI Tests / 115

Pre and Post Equalization Tests / 116

Main Voltage Measurements TP2 / 127

Differential Peak-to-Peak Output Voltage Test with TX Disabled / 128

DC Common Mode Output Voltage Test / 129

AC Common Mode Output Voltage Test / 130

Differential Peak-to-Peak Output Voltage Test / 131

Return Loss ENA/PNA Measurements / 132

Differential Output Return Loss / 133

Common-mode Output Return Loss / 134

7 PAM4 Module Output Characteristics at TP4

200GAUI-4 and 400GAUI-8 C2M module output electrical characteristics / 136

Main Voltage Measurements TP4 / 137

Differential Output Voltage Test / 138

AC Common Mode Output Voltage Test / 139

DC Common Mode Voltage Test / 140

Transition Time Measurements TP4 / 141

Minimum Output Rise Time (20%-80%) / 142

Minimum Output Fall Time (20%-80%) / 143

Signaling Rate and Eye Mask Measurements TP4 / 144

- Signaling Rate / 145
- Near-end Eye Height / 146
- Near-end Eye Width / 147
- Near-end ESMW / 148
- Vertical Eye Closure / 149
- Far-end Eye Height / 150
- Far-end Eye Width / 151
- Far-end ESMW / 152
- Far-end pre-cursor ISI ratio / 153

Return Loss ENA/PNA Measurements / 154

- Differential Output Return Loss / 155
- Common-mode to Differential Output Return Loss / 156

8 NRZ Transmitter Characteristics at TP0a

CAUI-4 C2C transmitter electrical characteristics / 158

200GAUI-8 and 400GAUI-16 C2C transmitter characteristics / 159

Jitter and Signaling Rate Measurements TP0a / 160

- Signaling Rate / 161
- Even-Odd Jitter / 162
- Effective bounded uncorrelated jitter / 163
- Effective total uncorrelated jitter / 164

Output Waveform Measurements TP0a / 165

- Steady State Voltage Vf / 166
- Linear Fit Pulse Peak / 167
- Signal-to-noise-and-distortion ratio / 168
- Pre and Post Equalization Tests / 169

Main Voltage Measurements TP0a / 180

- Differential Peak-to-Peak Output Voltage Test with TX Disabled / 181
- DC Common Mode Output Voltage Test / 182
- AC Common Mode Output Voltage Test / 183
- Differential Peak-to-Peak Output Voltage Test / 184

Return Loss ENA/PNA Measurements / 185

- Differential Output Return Loss / 186
- Common-mode Output Return Loss / 187

9 NRZ Host Output Characteristics at TP1a

CAUI-4 C2M host output electrical characteristics / 190

200GAUI-8 and 400GAUI-16 C2M host output characteristics / 191

Main Voltage Measurements TP1a / 192

- Differential Peak-to-Peak Output Voltage Test with TX Disabled / 193
- Differential Peak-to-Peak Output Voltage Test / 194
- AC Common Mode Output Voltage Test / 195
- DC Common Mode Output Voltage Test / 196
- Single-ended Output Voltage Test / 197

Transition Time Measurements TP1a / 198

- Minimum Output Rise Time (20%-80%) / 199
- Minimum Output Fall Time (20%-80%) / 200

Signaling Rate and Eye Mask Measurements TP1a / 201

- Signaling Rate / 202
- Eye Height A / 203
- Eye Width / 204

Return Loss ENA/PNA Measurements / 205

- Differential Output Return Loss / 206
- Common-mode to Differential Output Return Loss / 207

10 NRZ Module Output Characteristics at TP4

CAUI-4 module output characteristics / 210

200GAUI-8 and 400GAUI-16 C2M module output characteristics / 211

Main Voltage Measurements TP4 / 212

- Differential Output Voltage Test / 213
- AC Common Mode Output Voltage Test / 214
- DC Common Mode Voltage Test / 215

Transition Time Measurements TP4 / 216

- Minimum Output Rise Time (20%-80%) / 217
- Minimum Output Fall Time (20%-80%) / 218

Signaling Rate and Eye Mask Measurements TP4 / 219

- Signaling Rate / 220
- Near-end Eye Height / 221
- Near-end Eye Width / 222
- Vertical Eye Closure / 223
- Far-end Eye Height / 224
- Far-end Eye Width / 225
- Far-end ESMW / 226

Return Loss ENA/PNA Measurements / 227

- Differential Output Return Loss / 228
- Common-mode to Differential Output Return Loss / 229

11 Utilities

Utilities in IEEE Tests / 232

Find Optimal CTLE Eye Opening / 233

Find Optimal Far-end CTLE Eye Opening / 235

12 Debug Mode

Index

1 Overview

IEEE802.3 bs/cd Automated Testing—At a Glance 10
Required Equipment and Software 11

IEEE802.3 bs/cd Automated Testing—At a Glance

The Keysight D9010EBSC IEEE802.3 bs/cd Test Application is an Ethernet test solution that covers the electrical timing parameters for PAM4 and NRZ specification (IEEE 802.3bs/IEEE 802.3cd).

The main features of the IEEE802.3 bs/cd Test Application are:

- Data Analytics
- IEEE802.3bs/cd, update for final release specification
- Complete coverage of specification-based chip-to-chip (C2C) and chip-to-module (C2M) tests
- Test coverage for PAM4 and NRZ signals
- Coverage of Signal-to-Noise Distortion Ratio (SNDR) and SNDR_ISI at test point TP0a
- Support for User Interactive Pulse Response

The Keysight D9010EBSC IEEE802.3 bs/cd Test Application:

- Lets you select individual or multiple tests to run.
- Lets you identify the device being tested and its configuration.
- Shows you how to make oscilloscope connections to the device under test.
- Automatically checks for proper oscilloscope configuration.
- Automatically sets up the oscilloscope for each test.
- Provides detailed information for each test that has been run and lets you specify the thresholds at which marginal or critical warnings appear.
- Creates a printable HTML report of the tests that have been run.

NOTE

The tests performed by the Keysight D9010EBSC IEEE802.3 bs/cd Test Application are intended to provide a quick check of the electrical health of the DUT. This testing is not a replacement for an exhaustive test validation plan.

Required Equipment and Software

To run automated tests on PAM4 and NRZ signals, you need the following equipment and software:

Hardware

- Use one of the following Oscilloscope models. Refer to www.keysight.com for the respective bandwidth ranges.
 - Keysight DSO-Z series Real-Time Infiniium Oscilloscopes:
 - Channels: Either 2 or 4
 - Bandwidth of up to 63GHz
 - Sample Rate of up to 160 GSa/s
 - Keysight UXR series Real-Time Infiniium Oscilloscopes:
 - Channels: 2
 - Minimum Bandwidth of 50GHz
 - Sample Rate of up to 160 GSa/s
- Keyboard, qty = 1, (provided with the Keysight Infiniium oscilloscope)
- Mouse, qty = 1, (provided with the Keysight Infiniium oscilloscope)
- Keysight also recommends using a second monitor to view the test application.

Software

- The minimum version of Infiniium Oscilloscope Software (see the Keysight D9010EBSC IEEE802.3 bs/cd Test Application Release Notes)
- Keysight D9010EBSC IEEE802.3 bs/cd Test Application software

Licensing information

Refer to the *Data Sheet* pertaining to IEEE802.3 bs/cd Test Application to know about the licenses you must install along with other optional licenses. Visit "<http://www.keysight.com/find/D9010EBSC>" and in the web page's **Document Library** tab, you may view the associated Data Sheet.

To procure a license, you require the Host ID information that is displayed in the Keysight License Manager application installed on the same machine where you wish to install the license.

The licensing format for Keysight License Manager 6 differs from its predecessors. See "[Installing the License Key](#)" on page 15 to see the difference in installing a license key using either of the applications on your machine.

2 Installing the Test Application and Licenses

Installing the Test Application 14
Installing the License Key 15

If you purchased the D9010EBSC IEEE802.3 bs/cd Test Application separate from your Infiniium oscilloscope, you must install the software and license key.

Installing the Test Application

- 1 Make sure you have the minimum version of Infiniium Oscilloscope software (see the D9010EBSC release notes). To ensure that you have the minimum version, select **Help > About Infiniium...** from the main menu.
- 2 To obtain the IEEE802.3 bs/cd Test Application, go to Keysight website:
“<http://www.keysight.com/find/D9010EBSC>”.
- 3 In the web page's **Trials & Licenses** tab, click the **Details and Download** button to view instructions for downloading and installing the application software.

Installing the License Key

To procure a license, you require the Host ID information that is displayed in the Keysight License Manager application installed on the same machine where you wish to install the license.

Using Keysight License Manager 5

To view and copy the Host ID from Keysight License Manager 5:

- 1 Launch Keysight License Manager on your machine, where you wish to run the Test Application and its features.
- 2 Copy the Host ID that appears on the top pane of the application. Note that x indicates numeric values.




Figure 1 Viewing the Host ID information in Keysight License Manager 5

To install one of the procured licenses using Keysight License Manager 5 application,

- 1 Save the license files on the machine, where you wish to run the Test Application and its features.
- 2 Launch Keysight License Manager.
- 3 From the configuration menu, use one of the options to install each license file.




Figure 2 Configuration menu options to install licenses on Keysight License Manager 5

For more information regarding installation of procured licenses on Keysight License Manager 5, refer to [Keysight License Manager 5 Supporting Documentation](#).

Using Keysight License Manager 6

To view and copy the Host ID from Keysight License Manager 6:

- 1 Launch Keysight License Manager 6 on your machine, where you wish to run the Test Application and its features.
- 2 Copy the Host ID, which is the first set of alphanumeric value (as highlighted in Figure 3) that appears in the Environment tab of the application. Note that x indicates numeric values.




Figure 3 Viewing the Host ID information in Keysight License Manager 6

To install one of the procured licenses using Keysight License Manager 6 application,

- 1 Save the license files on the machine, where you wish to run the Test Application and its features.
- 2 Launch Keysight License Manager 6.
- 3 From the Home tab, use one of the options to install each license file.




Figure 4 Home menu options to install licenses on Keysight License Manager 6

For more information regarding installation of procured licenses on Keysight License Manager 6, refer to [Keysight License Manager 6 Supporting Documentation](#).

3 Preparing to Take Measurements

Calibrating the Oscilloscope	20
Starting the IEEE802.3 bs/cd Test Application	21
Configuring IEEE802.3 bs/cd Test Application for test runs	24
Exporting Measurement Results to Repository	28
List of tests for Standard Option - Signal Type combinations	37

Before running the automated tests, you should calibrate the oscilloscope and probe. No test fixture is required for this application. After the oscilloscope and probe have been calibrated, you are ready to start the IEEE802.3 bs/cd Test Application and perform the measurements.

Calibrating the Oscilloscope

If you have not already calibrated the oscilloscope, refer to the *User Guide* for the respective Oscilloscope you are using.

NOTE

If the ambient temperature changes more than 5 degrees Celsius from the calibration temperature, internal calibration should be performed again. The delta between the calibration temperature and the present operating temperature is shown in the **Utilities > Calibration** menu.

NOTE

If you switch cables between channels or other Oscilloscopes, it is necessary to perform cable and probe calibration again. Keysight recommends that, once calibration is performed, you label the cables with the channel on which they were calibrated.

Starting the IEEE802.3 bs/cd Test Application

- 1 Ensure that the IEEE802.3 bs/cd Device Under Test (DUT) is operating and set to desired test modes.
- 2 To start the IEEE802.3 bs/cd Test Application: From the Infiniium Oscilloscope's main menu, select **Analyze > Automated Test Apps > D9010EBSC IEEE802.3 bs/cd Test App**.
 - **Figure 5** shows the Keysight D9010EBSC IEEE802.3 bs/cd Test Application window as it appears when launched within the Infiniium application of the DSO Z-Series Oscilloscope. The Instrument Setup area in the Set Up tab displays Real Edge, which indicates Channels 1R and 3R on the oscilloscope.




Figure 5 IEEE802.3 bs/cd Test Application main window on a Z-Series DSO

- **Figure 6** shows the Keysight D9010EBSC IEEE802.3 bs/cd Test Application window as it appears when launched within the Infiniium application of the UXR Oscilloscope. The Instrument Setup area in the Set Up tab displays the corresponding Channel assignments.




Figure 6 IEEE802.3 bs/cd Test Application main window on a UXR Oscilloscope

The task flow pane and the tabs in the main pane show the steps you take in running the automated tests:

Set Up	Lets you identify and set up the test environment, including information about the device under test. The Device Identifier , User Description , and Comments are all printed in the final HTML report. Select the Standard Option and SignalType to be tested. For UXR scopes, select the appropriate Channel option in Instrument Setup . Set up InfiniSim with the InfiniSim Setup button. With the Set Channel Skew button, the channels can be visually adjusted and skewed. The Saved Waveform Setup button enables easy setup of saved waveforms. When waveforms are set up, the application makes all measurements on the saved waveforms. The Select Lane Number drop down box enables you to select a specific lane for testing.
Select Tests	Lets you select the tests you want to run. The tests are organized hierarchically so you can select all tests in a group. After tests are run, status indicators show which tests have passed, failed, or not been run, and there are indicators for the test groups.
Configure	Lets you configure test parameters (for example, channels used in test, voltage levels, etc.).
Connect	Shows you how to connect the oscilloscope to the device under test for the tests that are to be run.
Run	Starts the automated tests. If the connections to the device under test need to be changed while multiple tests are running, the tests pause, show you how to change the connection, and wait for you to confirm that the connections have been changed before continuing.
Automate	Lets you construct scripts of commands that drive execution of the application.
Results	Contains more detailed information about the tests that have been run. You can change the thresholds at which marginal or critical warnings appear.
HTML Report	Shows a compliance test report that can be printed.

NOTE

In the **Configure** tab, the values for all such Configuration parameters that are Oscilloscope-dependent, will correspond to the Oscilloscope Model (DSOs or UXRs), where you are running the Test Application.

Configuring IEEE802.3 bs/cd Test Application for test runs

To run one or more compliance tests on the DUT, which is connected to Oscilloscope, proceed to configure the IEEE802.3 bs/cd Test Application:

- 1 In the **Set Up** tab (shown in [Figure 5](#) and [Figure 6](#)), select the **Standard Option** and **SignalType** to filter the test groups in accordance with the connected DUT. [Table 1](#), [Table 2](#), [Table 3](#) and [Table 4](#) show a comprehensive list of the tests that are filtered in the **Select Tests** tab for each combination of **Standard Option** and **SignalType**.

Optionally, you may configure the rest of the settings as described in the task flow table in the previous section.

- 2 In the **Select Tests** tab, select one or more tests, which appear according to the configuration done under the **Set Up** tab. Each section of this manual displays the appearance of the **Select Tests** tab for each test type.
- 3 In the **Configure** tab, you may change the values assigned to one or more options to cater to the compliance requirements for the selected tests. By default, the IEEE802.3 bs/cd Test Application sets optimum values for each configuration parameter.




Figure 7 Configure tab in the IEEE802.3 bs/cd Test Application

- 4 In the **Connect** tab, view the instructions along with the connection diagram to ensure that all requirements for the physical setup of the testing instruments and the DUT are met. Click **Connection Completed** to indicate to the Test Application that the required hardware setup is complete. The connection diagram for most of the tests matches the one shown in [Figure 5](#) for DSO-Z Series Oscilloscopes and [Figure 6](#) for UXR Series Oscilloscopes. However, it is a good

practice to verify the connection diagram and instructions displayed under this tab. The Test Application automatically indicates any changes in connections, if needed, during test runs.

- 5 Click **Run Tests** under this tab if you wish to start running tests. However, if you wish to modify the run settings before performing test runs, switch to the **Run** tab.




Figure 8 Connect tab in IEEE802.3 bs/cd Test Application on a Z-series DSO




Figure 9 Connect tab in IEEE802.3 bs/cd Test Application on a UXR scope

- 6 In the **Run** tab, you may optionally modify one or more settings as described below, else click **Run** to start the test runs:
- determine the number of times each test must be run,
 - automate specific actions in case of events,
 - store results for certain type of test trials only,
 - send email notifications if the test runs pause or stop during runs.




Figure 10 Run tab in IEEE802.3 bs/cd Test Application

- 7 In the **Automate** tab, you may optionally configure automation scripts to perform specific actions/sequences within the Test Application.
- 8 In the **Results** tab, which appears automatically after test runs are complete, view the test results displayed for each selected test.
- 9 In the **HTML Report** tab, view a comprehensive report for each test within the Application. The Test Application enables exporting these results in CSV or HTML format for the purpose of analysis.
- 10 To perform a high-level analysis on each measurement data, you may upload the results to the KS6800A Series Analytics Services Software. Refer to [“Exporting Measurement Results to Repository”](#) on page 28 to understand an overview on the functionality of this feature.

Exporting Measurement Results to Repository

The Upload Results To Repository feature is an add-on to the Keysight Test Application, where it expands the boundaries of storing and analyzing the measurement results to a wider audience, who may be based in multiple sites across various geographical locations. Along with the feature of exporting test results from the Test Application into your local disk in a CSV or HTML file format, you have the option to upload the test results to a Dataset on a Web Repository. Based on your requirements, you may either upload only a single measurement trial or upload huge volumes of measurement results to any Dataset.


Not only can remote users with an active Internet connection access these Datasets and the corresponding test results on the Web Repository, but they have the option to add and delete Datasets on the Web Server. In the Upload Results To Repository feature, you can even modify the Dataset properties, which are helpful especially when performing a graphical analysis of the uploaded data.

In combination with the *Keysight KS6800A Series Analytics Software*, the Upload Results To Repository feature provides a comprehensive solution to export, view and perform analysis of the measurement results, thereby resulting in qualitative data to ensure that the Device Under Test (DUT) is compliant to the industry standards.

Refer to the *Keysight KS6800A Series Analytics Software Online Help* for more information about the functionality of various features in this software.


To export measurement results to the Repository after the completion of test runs,

- 1 From the Test Application's main menu, click **File > Export Results... > Repository**.



The **Upload Results to Repository** window appears.


- 2 In the **Connect to Server** pane of the **Datasets** tab, click **Connect...** to login to the Dataset Repository server.




- 3 In the URL: drop-down text field that appears, replace the default text with the actual IP address or the URL along with the port number, if applicable.

You may enter the URL of the Web Repository server, which may be a self-hosted server on your machine (<http://localhost:5000/>), a remote server or an authentication server. Note that all such URLs accessed via this window appear as a drop-down list in the URL: field.

- 4 Click the Check button to verify that the KS6800A Series Analytics service is available on the specified web address. Repeat this step each time you edit the web address.




- For unrestricted access to the Repository
 - a If the server does not require authentication and the KS6800A Series Analytics service is found on the specified web address, the version information is displayed adjacent to the Check button.




- b If you click OK, the Upload Results to Repository window displays the connectivity status to the Dataset Repository.
- c Click Browse... to navigate directly to the URL.




- For restricted access to the Repository
 - a If service is found on the specified URL but access to the web server is restricted based on authentication, the version information is displayed along with the text Authentication Required adjacent to the Check button. Also, the Username: and Password: fields appear. The OK button remains disabled until the authentication credentials are entered.
 - b Enter the user credentials in the respective fields, which are required for authentication to access those Datasets that have been created on the web server you are connecting to. For each URL that you access, the Username: drop-down box keeps a record and displays all user names used to access the respective URL.




- c Click OK to connect to the entered URL/IP address.
The Connect to Server area displays the connection status along with the username.
- d Click Browse... to navigate directly to the URL.




- 5 In the Select Dataset area, click Select... to view the list of Datasets created on the connected repository. Click Refresh to update the list of Datasets that appear in the Test Application's user interface.
- 6 Select the Dataset name where you wish to upload measurement results to. Click OK.



The Select Dataset area displays the selected Dataset as Active. The Measurements and Properties tabs are enabled after a Dataset is selected.




- 7 Click the **Measurements** tab where the test results from the last test run are displayed.
- 8 You may select and export multiple test results to the repository. You may change the format for the display of measurement data using the drop-down options in the **Group by:** field.




- 9 After selecting one or more measurements, either click **Upload** or switch to the **Properties** tab to associate one or more properties to the measurements that are being uploaded to the Web Server.

To perform an enhanced analysis on the measurement data using the *KS6800A Series Analytics Service Software*, Keysight recommends assigning properties to the measurements.



- Click the **Properties** tab to assign properties for your measurement results that you select to upload. By default, the **App-Defined** properties are selected to be uploaded in association with the measurement data, wherein only certain aspects of the selected measurements are uploaded. However, you may switch to **Globals** to include as properties one or more options configured under the rest of the tabs of the Compliance Test Application or define one or more custom property values to be associated with the selected measurement data.




- Click **Upload** to begin uploading measurement results.
- Click **Close** to exit the **Upload Results to Repository** window and to return to the Compliance Test Application.

You may access the Dataset Repository using the Internet browser on your machine to view the measurement results graphically on the *KS6800A Series Analytics Service Software*.

KS6800A Series Analytics Service Software

The KS6800A Series Analytics Service software supports multiple data sources and also a wide range of data import clients. This web-based software provides various types of charts, such as Histogram, Box-and-Whisker, Line, Scatter, Eye Diagram and Constellation, each with split capability to enable data analysis. Once you upload the measurement results to a Dataset on the *KS6800A Series Analytics Service Software* via the **Upload Results to Repository** window of the Test Application, the measurement results can be viewed graphically as shown below:



For more information on the Data Analytics Web Service Software, visit [KS6800A Series Analytics Service Software](#) page on the Keysight website. You may refer to the Help manual provided within the software to understand the functionality of its features.

List of tests for Standard Option – Signal Type combinations

Following tables display the test list that appears under the **Select Tests** tab for each combination of **Standard Option** and **Signal Type** under the **Set Up** tab:

Table 1 Filtered test list for combinations of Standard Option and Signal Type at Test Point TP0a

Standard Option	Signal Type	Tests
<ul style="list-style-type: none"> ▪ 200GAUI-x and 400GAUI-x ▪ 50GAUI-x and 100GAUI-x ▪ 50GBASE-KR, 100GBASE-KR2, and 200GBASE-KR4 	PAM4	PAM4 Transmitter Characteristics at TP0a <ul style="list-style-type: none"> ▪ Jitter and Signaling Rate Measurements TP0a (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Signaling Rate ▪ JRMS ▪ J4u ▪ Even-Odd Jitter ▪ Output Voltage Measurements EYE TP0a (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Level - PRBS Pattern ▪ Level RMS - PRBS Pattern ▪ Level Separation Mismatch Ratio - RLM ▪ Output Waveform Measurements TP0a (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Steady State Voltage Vf ▪ Linear Fit Pulse Peak ▪ Signal-to-noise-and-distortion ratio ▪ SNR_ISI Tests ▪ Pre and Post Equalization Tests ▪ Main Voltage Measurements TP0a (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Differential Peak-to-Peak Output Voltage Test with TX Disabled ▪ DC Common Mode Output Voltage Test ▪ AC Common Mode Output Voltage Test ▪ Differential Peak-to-Peak Output Voltage Test ▪ Return Loss PNA/ENA Measurements <ul style="list-style-type: none"> ▪ Differential Output Return Loss ▪ Common-mode Output Return Loss
<ul style="list-style-type: none"> ▪ 200GAUI-x and 400GAUI-x ▪ LAUI 2 ▪ 50GAUI-x and 100GAUI-x 	NRZ	NRZ Transmitter Characteristics at TP0a <ul style="list-style-type: none"> ▪ Jitter and Signaling Rate Measurements TP0a (pattern: PRBS9) <ul style="list-style-type: none"> ▪ Signaling Rate ▪ Even-Odd Jitter ▪ Effective bounded uncorrelated jitter ▪ Effective total uncorrelated jitter ▪ Output Waveform Measurements TP0a (pattern: PRBS9) <ul style="list-style-type: none"> ▪ Steady State Voltage Vf ▪ Linear Fit Pulse Peak ▪ Signal-to-noise-and-distortion ratio ▪ Pre and Post Equalization Tests ▪ Main Voltage Measurements TP0a (pattern: PRBS9) <ul style="list-style-type: none"> ▪ Differential Peak-to-Peak Output Voltage Test with TX Disabled ▪ DC Common Mode Output Voltage Test ▪ AC Common Mode Output Voltage Test ▪ Differential Peak-to-Peak Output Voltage Test ▪ Return Loss PNA/ENA Measurements <ul style="list-style-type: none"> ▪ Differential Output Return Loss ▪ Common-mode Output Return Loss

Table 2 Filtered test list for combinations of Standard Option and Signal Type at Test Point TP1a

Standard Option	Signal Type	Tests
<ul style="list-style-type: none"> ▪ 200GAUI-x and 400GAUI-x ▪ 50GAUI-x and 100GAUI-x 	PAM4	<p>PAM4 Host Output Characteristics at TP1a</p> <ul style="list-style-type: none"> ▪ Main Voltage Measurements TP1a (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Differential Peak-to-Peak Output Voltage Test with TX Disabled ▪ Differential Peak-to-Peak Output Voltage Test ▪ AC Common Mode Output Voltage Test ▪ DC Common Mode Output Voltage Test ▪ Single-ended Output Voltage Test ▪ Transition Time Measurements TP1a (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Minimum Output Rise Time (20%-80%) ▪ Minimum Output Fall Time (20%-80%) ▪ Signaling Rate and Eye Mask Measurements TP1a (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Signaling Rate ▪ Eye Height A ▪ Eye Width ▪ ESMW ▪ Return Loss PNA/ENA Measurements <ul style="list-style-type: none"> ▪ Differential Output Return Loss ▪ Common-mode to Differential Output Return Loss
<ul style="list-style-type: none"> ▪ 200GAUI-x and 400GAUI-x ▪ LAUI 2 ▪ 50GAUI-x and 100GAUI-x 	NRZ	<p>NRZ Host Output Characteristics at TP1a</p> <ul style="list-style-type: none"> ▪ Main Voltage Measurements TP1a (pattern: PRBS9) <ul style="list-style-type: none"> ▪ Differential Peak-to-Peak Output Voltage Test with TX Disabled ▪ Differential Peak-to-Peak Output Voltage Test ▪ AC Common Mode Output Voltage Test ▪ DC Common Mode Output Voltage Test ▪ Single-ended Output Voltage Test ▪ Transition Time Measurements TP1a (pattern: PRBS9) <ul style="list-style-type: none"> ▪ Minimum Output Rise Time (20%-80%) ▪ Minimum Output Fall Time (20%-80%) ▪ Signaling Rate and Eye Mask Measurements TP1a (pattern: PRBS9) <ul style="list-style-type: none"> ▪ Signaling Rate ▪ Eye Height A ▪ Eye Width ▪ Return Loss PNA/ENA Measurements <ul style="list-style-type: none"> ▪ Differential Output Return Loss ▪ Common-mode to Differential Output Return Loss

Table 3 Filtered test list for combinations of Standard Option and Signal Type at Test Point TP4

Standard Option	Signal Type	Tests
<ul style="list-style-type: none"> ▪ 200GAUI-x and 400GAUI-x ▪ 50GAUI-x and 100GAUI-x 	PAM4	<p>PAM4 Module Output Characteristics at TP4</p> <ul style="list-style-type: none"> ▪ Main Voltage Measurements TP4 (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Differential Output Voltage Test ▪ AC Common Mode Output Voltage Test ▪ DC Common Mode Voltage Test ▪ Transition Time Measurements TP4 (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Minimum Output Rise Time (20%-80%) ▪ Minimum Output Fall Time (20%-80%) ▪ Signaling Rate and Eye Mask Measurements TP4 (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Signaling Rate ▪ Near-end Eye Height ▪ Near-end Eye Width ▪ Near-end ESMW ▪ Vertical Eye Closure ▪ Far-end Eye Height ▪ Far-end Eye Width ▪ Far-end ESMW ▪ Return Loss PNA/ENA Measurements <ul style="list-style-type: none"> ▪ Differential Output Return Loss ▪ Common-mode to Differential Output Return Loss
<ul style="list-style-type: none"> ▪ 200GAUI-x and 400GAUI-x ▪ LAUI 2 ▪ 50GAUI-x and 100GAUI-x 	NRZ	<p>NRZ Module Output Characteristics at TP4</p> <ul style="list-style-type: none"> ▪ Main Voltage Measurements TP4 (pattern: PRBS9) <ul style="list-style-type: none"> ▪ Differential Output Voltage Test ▪ AC Common Mode Output Voltage Test ▪ DC Common Mode Voltage Test ▪ Transition Time Measurements TP4 (pattern: PRBS9) <ul style="list-style-type: none"> ▪ Minimum Output Rise Time (20%-80%) ▪ Minimum Output Fall Time (20%-80%) ▪ Signaling Rate and Eye Mask Measurements TP4 (pattern: PRBS9) <ul style="list-style-type: none"> ▪ Signaling Rate ▪ Near-end Eye Height ▪ Near-end Eye Width ▪ Vertical Eye Closure ▪ Far-end Eye Height ▪ Far-end Eye Width ▪ Far-end ESMW ▪ Return Loss PNA/ENA Measurements <ul style="list-style-type: none"> ▪ Differential Output Return Loss ▪ Common-mode to Differential Output Return Loss

Table 4 Filtered test list for combinations of Standard Option and Signal Type at Test Point TP2

Standard Option	Signal Type	Tests
<ul style="list-style-type: none"> ▪ 50GBASE-CR, 100GBASE-CR2, and 200GBASE-CR 	PAM4	PAM4 Transmitter Characteristics at TP2 <ul style="list-style-type: none"> ▪ Jitter and Signaling Rate Measurements TP2 (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Signaling Rate ▪ JRMS ▪ J4u ▪ Even-Odd Jitter ▪ Output Voltage Measurements EYE TP2 (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Level - PRBS Pattern ▪ Level RMS - PRBS Pattern ▪ Level Separation Mismatch Ratio - RLM ▪ Output Waveform Measurements TP2 (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Steady State Voltage Vf ▪ Linear Fit Pulse Peak ▪ Signal-to-noise-and-distortion ratio ▪ SNR_ISI Tests ▪ Pre and Post Equalization Tests ▪ Main Voltage Measurements TP2 (pattern: PRBS13Q) <ul style="list-style-type: none"> ▪ Differential Peak-to-Peak Output Voltage Test with TX Disabled ▪ DC Common Mode Output Voltage Test ▪ AC Common Mode Output Voltage Test ▪ Differential Peak-to-Peak Output Voltage Test ▪ Return Loss PNA/ENA Measurements <ul style="list-style-type: none"> ▪ Differential Output Return Loss ▪ Common-mode Output Return Loss

4 PAM4 Transmitter Characteristics at TP0a

Jitter and Signaling Rate Measurements TP0a 45

Output Voltage Measurements EYE TP0a 50

Output Waveform Measurements TP0a 54

Main Voltage Measurements TP0a 70

Return Loss ENA/PNA Measurements 75

This section provides the Methods of Implementation (MOIs) for the IEEE PAM4 Transmitter Characteristics at TP0a. Measurements are made at test point TP0a.

NOTE

Ensure that the **Signaling Rate** setting in the **Configure** tab of the Compliance Test Application must match the frequency of the acquired input signal.

C2C transmitter characteristics

PAM4 GAUI-x tests

See [Table 5](#) for pass limits pertaining to 200GAUI-x and 400GAUI-x PAM4 tests, which are specified in IEEE P802.3bs™ /D3.5 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 200Gb/s and 400Gb/s Operation), Annex 120D.3.1, Table 120D-1.

Table 5 200GAUI-4 and 400GAUI-8 C2C transmitter characteristics at TP0a

Parameter	Reference	Value	Units
Signaling rate per lane (range)		26.5625 ± 100 ppm	GBd
Differential peak-to-peak output voltage ^a (max)	See Sec. 93.8.1.3 of the IEEE specification	30	mV
Transmitter disabled		1200	mV
Transmitter enabled			
Common-mode voltage ^a (max)	See Sec. 93.8.1.3 of the IEEE specification	1.9	V
Common-mode voltage ^a (min)	See Sec. 93.8.1.3 of the IEEE specification	0	V
AC common-mode output voltage ^a (max, RMS)	See Sec. 93.8.1.3 of the IEEE specification	30	mV
Differential output return loss (min)	See Sec. 120D.3.1.1 of the IEEE specification	See Equation (120D-2) of the IEEE specification	dB
Common-mode output return loss (min)	See Sec. 93.8.1.4 of the IEEE specification	See Equation (93-4) of the IEEE specification	dB
Output waveform ^b	See Sections		
Level separation mismatch ratio RLM(min)	120D.3.1.2	0.95	-
Steady state voltage vf (max)	120D.3.1.4	0.6	V
Steady state voltage vf (min)	120D.3.1.4	0.4	V
Linear fit pulse peak (min)	120D.3.1.4	0.76 × vf	V
Pre-cursor equalization	120D.3.1.5	Table 120D-2	-
Post-cursor equalization	120D.3.1.5	Table 120D-3	-
Signal-to-noise-and-distortion ratio SNDR (min)	See Sec.120D.3.1.6 of the IEEE specification	31.5	dB
Transmitter Output residual ISI SNRISI (min)	See Sec. 120D.3.1.7 of the IEEE specification	34.8	dB
Output jitter	See Sections		
JRMS (max)	120D.3.1.8	0.023	UI
J4u (max)	120D.3.1.8	0.118	UI
Even-odd jitter (max)	120D.3.1.8	0.019	UI

a. Measurement uses the method described in section 93.8.1.3 of IEEE specification with the exception that the PRBS13Q test pattern is used.

b. The state of the transmit equalizer is controlled by management interface.

For CR tests

See Table 6 for pass limits pertaining to 50GBASE-CR, 100GBASE-CR2, and 200GBASE-CR PAM4 tests, which are specified in IEEE P802.3cdTM/D3.0 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 50Gb/s, 100Gb/s, and 200Gb/s Operation) section 136.9.3, Table 136-11.

Table 6 50GBASE-CR, 100GBASE-CR2, and 200GBASE-CR C2C transmitter characteristics at TP0a

Parameter	Reference	Value	Units
Differential pk-to-pk output voltage (max) with TX disabled ^a	See Sec. 93.8.1.3 of the IEEE specification	30	mV
DC common-mode voltage (max) ^a	See Sec. 93.8.1.3 of the IEEE specification	1.9	V
AC common-mode RMS output voltage, v_{cmi} (max) ^a	See Sec. 93.8.1.3 of the IEEE specification	30	mV
Differential pk-to-pk, v_{di} (max) ^a	See Sec. 93.8.1.3 of the IEEE specification	1200	mV
Differential output return loss (min)	See Sec. 92.8.3.2 of the IEEE specification	See Equation (92-1) of the IEEE specification	dB
Common-mode to differential mode output return loss (min)	See Sec. 92.8.3.3 of the IEEE specification	See Equation (92-2) of the IEEE specification	dB
Common-mode to common-mode output return loss (min)	See Sec. 92.8.3.4 of the IEEE specification	See Equation (92-3) of the IEEE specification	dB
Transmitter steady-state voltage, v_f (min)	See Sec. 136.9.3.1.2 of the IEEE specification	0.34	V
Transmitter steady-state voltage, v_f (max)	See Sec. 136.9.3.1.2 of the IEEE specification	0.6	V
Linear fit pulse peak (min)	See Sec. 136.9.3.1.2 of the IEEE specification	$0.49 \times v_f$	V
Level separation mismatch ratio R_{LM} (min)	See Sec.120D.3.1.2 of the IEEE specification	0.95	-
Transmitter output waveform	See Sections		
abs step size for c(-1), c(0), and c(1) (min.)	136.9.3.1.4	0.005	-
abs step size for c(-1), c(0), and c(1) (max.)	136.9.3.1.4	0.05	-
abs step size for c(-2) (min.)	136.9.3.1.4	0.005	-
abs step size for c(-2) (max.)	136.9.3.1.4	0.025	-
value at maximum state for c(-1) and c(1) (max.)	136.9.3.1.5	-0.25	-
value at maximum state for c(-2) (min.)	136.9.3.1.5	0.1	-
Signal-to-noise-and-distortion ratio SNDR (min)	See Sec.120D.3.1.6 of the IEEE specification	33.3	dB
SNR_{ISI} (min) ^b	See Sec. 120D.3.1.7 of the IEEE specification	36.8	dB
Output jitter (max.)	See Sections		
JRMS	120D.3.1.8	0.023	UI
J4u	120D.3.1.8	0.118	UI
Even-odd jitter, pk-pk	120D.3.1.8	0.019	UI
Signaling rate per lane (range)		26.5625 ± 100 ppm	GBd

a. Measurement uses the method described in section 93.8.1.3 of IEEE specification with the exception that the PRBS13Q test pattern is used.

b. Measured only in unequalized setting.

For PAM4 KR tests

A 50GBASE-KR, 100GBASE-KR2, and 200GBASE-KR4 chip-to-chip transmitter shall meet all specifications in section 137.9.2 of the IEEE specification (refer to [Table 5](#) for limits corresponding to Table 120D-1) with the following exceptions:

- The value for the “Linear fit pulse peak (min)” is $0.75 \times v_f$.
- The output waveform Pre-cursor equalization and Post-cursor equalization parameters are replaced by the “Transmitter output waveform” specifications detailed in section 136.9.3.1 of the IEEE specification and summarized in [Table 5](#), which corresponds to Table 136-11.
- SNR_{ISI} is computed with N_b set to 12 and D_p set to 3. The value of SNR_{ISI} (min) is 43dB.
- The value of SNDR (min) is 32.5dB.

Jitter and Signaling Rate Measurements TP0a

The Jitter and Signaling Rate Measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 11 Selecting Jitter and Signaling Rate Measurement Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Jitter and Signaling Rate Measurements TP0a (pattern: PRBS13Q) tests, see:

- [“Signaling Rate”](#) on page 46
- [“JRMS”](#) on page 47
- [“J4u”](#) on page 48
- [“Even-Odd Jitter”](#) on page 49

Signaling Rate

- Test Overview** The purpose of this test is to verify that the signaling rate meets the specified standards.
- Pass Condition** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Check that the signal is connected, has a bit-rate of 53.125 GHz and that data pattern exists (PRBS13Q must be used for this test).
 - 3 In the **Configure** tab, set **Signaling Rate** to 26.5625 Gb/s.
 - 4 Measure minimum and maximum data rate.
 - 5 Report minimum and maximum values.
 - 6 Compare the mean data rate value with the specified standards. Report the resulting value.

JRMS

Test Overview	The purpose of this test is to verify that differential signal's JRMS meets the specified standards. All jitter tests are run in a single measurement. However, each test can be run individually.
Pass Conditions	Refer to the section C2C transmitter characteristics for the pass limits pertaining to each standard option.
Measurement Algorithm	1 Obtain sample or acquire signal data. Set acquisition depth to five times the length of the PRBS13Q pattern.

NOTE

For DSO-Z Series Oscilloscopes, connections must be established between Data+ to Channel 1R and Data- to Channel 3R to measure the defined 12 edges.

For UXR Series Oscilloscopes, connections must be established between Data+ to Channel 1 and Data- to Channel 2 to measure the defined 12 edges.

Irrespective of the Oscilloscope used, the signal must be of PRBS13Q pattern.

-
- 2 In the **Configure** tab, set the value for the Signaling Rate as that of the Symbol Rate of the acquired signal.
 - 3 On the Oscilloscope,
 - a Set Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Using PAM4 jitter measurements, at least 10,000 PRBS13Q patterns are captured to collect the measurement data of 12 edges.
 - c Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.

NOTE

This measurement can run for a duration of 8-10 minutes.

-
- 4 Compare and report the JRMS value to the specified standards.

J4u

Test Overview The purpose of this test is to verify that differential signal's J4u meets the specified standards. All jitter tests are run in a single measurement. However, each test can be run individually.

Pass Conditions Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Obtain sample or acquire signal data. Set acquisition depth to five times the length of the PRBS13Q pattern.

NOTE

For DSO-Z Series Oscilloscopes, connections must be established between Data+ to Channel 1R and Data- to Channel 3R to measure the defined 12 edges.

For UXR Series Oscilloscopes, connections must be established between Data+ to Channel 1 and Data- to Channel 2 to measure the defined 12 edges.

Irrespective of the Oscilloscope used, the signal must be of PRBS13Q pattern.

- 2 In the **Configure** tab, set the value for the Signaling Rate as that of the Symbol Rate of the acquired signal.
- 3 On the Oscilloscope,
 - a Set Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Using PAM4 jitter measurements, at least 10,000 PRBS13Q patterns are captured to collect the measurement data of 12 edges.
 - c Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.

NOTE

This measurement can run for a duration of 8-10 minutes.

- 4 Compare and report the J4u value meets the specified standards.

Even-Odd Jitter

- Test Overview** The purpose of this test is to verify that differential signal's Even-Odd Jitter meets the specified standards. All jitter tests are run in a single measurement. However, each test can be run individually.
- Pass Conditions** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data. Set acquisition depth to five times the length of the PRBS13Q pattern.

NOTE

For DSO-Z Series Oscilloscopes, connections must be established between Data+ to Channel 1R and Data- to Channel 3R to measure the defined 12 edges.

For UXR Series Oscilloscopes, connections must be established between Data+ to Channel 1 and Data- to Channel 2 to measure the defined 12 edges.

Irrespective of the Oscilloscope used, the signal must be of PRBS13Q pattern.

- 2 In the **Configure** tab, set the value for the Signaling Rate as that of the Symbol Rate of the acquired signal.
- 3 On the Oscilloscope,
 - a Set Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Using PAM4 jitter measurements, at least 10,000 PRBS13Q patterns are captured to collect the measurement data of 12 edges.
 - c Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.

NOTE

This measurement can run for a duration of 8-10 minutes.

- 4 Compare and report the Even-Odd Jitter value to the specified standards.

Output Voltage Measurements EYE TP0a

The Output Voltage Measurement EYE procedures for a signal with PRBS13Q pattern that are described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 12 Selecting Output Voltage Measurements EYE Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Output Voltage Measurements EYE TP0a (pattern: PRBS13Q) tests, see:

- “[Level - PRBS Pattern](#)” on page 51
- “[Level RMS - PRBS Pattern](#)” on page 52
- “[Level Separation Mismatch Ratio - RLM](#)” on page 53

NOTE

The tests [Level - PRBS pattern](#) and [Level RMS - PRBS pattern](#) are considered as “Information-Only” tests and cannot be used for compliance validation.

Level - PRBS Pattern

Test Overview The purpose of this test is to obtain the mean voltage of each level of the signal with PRBS13Q pattern.

Pass Condition Not applicable as the test result is considered as “Information Only”.

- Measurement Algorithm**
- 1 Check that signal is connected and proper data pattern exists (PRBS13Q pattern must be used for this test).
 - 2 V_0 , V_1 , V_2 and V_3 are the mean signal levels of the symbols corresponding to the PAM4 symbol levels 0, 1, 2 and 3 respectively, as defined in IEEE P802.3bs™ /D3.5 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 200Gb/s and 400Gb/s Operation), Annex 120D.3.1.2. The calculation of mean signal levels is also defined in section 120D.3.1.2.1.
 - 3 The mean level V_{mid} is defined by equation (120D-3), which is,

$$V_{mid} = (V_0 + V_3) / 2$$
 - 4 Report this value for information-only purpose.

Level RMS - PRBS Pattern

Test Overview The purpose of this test is to obtain the of the RMS level of the signal with PRBS13Q pattern.

Pass Condition Not applicable as the test result is considered as “Information Only”.

- Measurement Algorithm**
- 1 Run the Level - PRBS Pattern test as a prerequisite to this test.
 - 2 The minimum signal level RMS is calculated, as defined in IEEE P802.3bs™ /D3.5 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 200Gb/s and 400Gb/s Operation), Annex 120D.3.1.2.
 - 3 Report this value for information-only purpose.

Level Separation Mismatch Ratio - RLM

Test Overview The purpose of this test is to obtain the of the Separation Mismatch Ratio level (RLM) of the signal with PRBS13Q pattern.

Pass Condition Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Run the Level - PRBS Pattern as a prerequisite to this test to calculate the mid-range level.
- 2 The mean signal levels are normalized so that V_0 corresponds to -1, V_1 to -ES1, V_2 to ES2 and V_3 to 1.
- 3 ES1 and ES2 are calculated using equations (120D-4) and (120D-5), respectively of the IEEE P802.3bs™ /D3.5 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 200Gb/s and 400Gb/s Operation), Annex 120D.3.1.2.

$$ES1 = (V_1 - V_{mid}) / (V_0 - V_{mid})$$

$$ES2 = (V_2 - V_{mid}) / (V_3 - V_{mid})$$

4 The level separation mismatch ratio R_{LM} is defined by equation (120D-5).

$$R_{LM} = \min [(3 \times ES1), (3 \times ES2), (2 - 3 \times ES1), (2 - 3 \times ES2)]$$

5 Report this value for information-only purpose.

Output Waveform Measurements TP0a

The Output Waveform Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 13 Selecting Transmitter Output Waveform Measurement Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Output Waveform Measurements TP0a (pattern: PRBS13Q) tests, see:

- “Steady State Voltage Vf” on page 55
- “Linear Fit Pulse Peak” on page 56
- “Signal-to-noise-and-distortion ratio” on page 57
- “SNR_ISI Tests” on page 58
- “Pre and Post Equalization Tests” on page 59

Steady State Voltage V_f

Test Overview The purpose of this test is to verify that the Steady State Voltage is between 0.4V and 0.6V.

Pass Condition Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

- Measurement Algorithm**
- 1 Check that signal is connected and proper data pattern exists (PRBS13Q must be used for this test).
 - 2 Set memory depth and sample rate to capture the 8191 bits of the PRBS13Q pattern.
 - 3 Calculate V_f using the equations in section 85.8.3.3.5. The resulting value is the sum of columns of $p(k)/M$. $N_p = 200$, $D_p = 2$.
 - 4 Compare and report the resulting value in the range between 0.4V and 0.6V.

Linear Fit Pulse Peak

Test Overview The purpose of this test is to verify that the Linear Fit Pulse meets the specified standards.

NOTE

Run the Steady-State Voltage Vf test as a prerequisite to running the Linear Fit Pulse Peak test.

Pass Conditions Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Check that signal is connected and proper data pattern exists (PRBS13Q must be used for this test).
- 2 Set memory depth and sample rate to capture the 8191 bits of the PRBS13Q pattern.
- 3 Calculate Linear Fit Pulse using the equations in section 85.8.3.3.5. The resulting value is the peak value of $p(k)$. $N_p = 200$, $D_p = 2$.
- 4 Compare the specified standards to the resulting value.

Signal-to-noise-and-distortion ratio

- Test Overview** The purpose of this test is to verify that the Signal-to-noise-and-distortion ratio (SNDR) meets the specified standards.
- Pass Condition** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Calculate SNDR using measurements from Level RMS - PRBS pattern test and error from Linear Fit Pulse Peak test.
 - 2 Compare the resulting value of SNDR to the specified standards.

SNR_ISI Tests

Test Overview The purpose of this test is to verify that the Transmitter Output residual ratio (SNR_ISI) for each value of Output Gain (in decibels) meets the specified standards.




Figure 14 Selecting SNR_ISI Tests

Pass Condition Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

- Measurement Algorithm**
- 1 Select one or more tests that pertain to a specific Output Gain value.
 - 2 Calculate SNRISI for each selected test using measurements from Level RMS - PRBS pattern test and error from Linear Fit Pulse Peak test.
 - 3 Compare the resulting value to the specified standards.

Pre and Post Equalization Tests

Test Overview The purpose of this test is to verify the Pre-cursor and Post-cursor equalization ratios.




Figure 15 Selecting Pre and Post Equalization Tests

To know about the measurement algorithm for each Pre and Post Equalization Tests, see:

- “Pre-cursor equalization Local_eq_cm1(0)” on page 60
- “Pre-cursor equalization Local_eq_cm1(1)” on page 61
- “Pre-cursor equalization Local_eq_cm1(2)” on page 62
- “Pre-cursor equalization Local_eq_cm1(3)” on page 63
- “Pre-cursor equalization Local_eq_c1(0)” on page 64
- “Post-cursor equalization Local_eq_c1(1)” on page 65
- “Post-cursor equalization Local_eq_c1(2)” on page 66
- “Post-cursor equalization Local_eq_c1(3)” on page 67
- “Post-cursor equalization Local_eq_c1(4)” on page 68
- “Post-cursor equalization Local_eq_c1(5)” on page 69

Pre-cursor equalization Local_eq_cm1(0)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is 0 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 0, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within 0 ± 0.04 .
- Measurement Algorithm**
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 0.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with 0 ± 0.04 .

Pre-cursor equalization Local_eq_cm1(1)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is -0.05 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 1, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.05 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 1.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with -0.05 ± 0.04 .

Pre-cursor equalization Local_eq_cm1(2)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is -0.1 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 2, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.1 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 2.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with -0.1 ± 0.04 .

Pre-cursor equalization Local_eq_cm1(3)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is -0.15 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 3, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.15 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 3.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with -0.15 ± 0.04 .

Pre-cursor equalization Local_eq_c1(0)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is 0 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 0, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within 0 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 0.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with 0 ± 0.04 .

Post-cursor equalization Local_eq_c1(1)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.05 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 1, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.05 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 1.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.05 ± 0.04 .

Post-cursor equalization Local_eq_c1(2)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.1 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 2, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.1 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 2.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.1 ± 0.04 .

Post-cursor equalization Local_eq_c1(3)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.15 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 3, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.15 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 3.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.15 ± 0.04 .

Post-cursor equalization Local_eq_c1(4)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.2 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 4, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.2 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 4.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.2 ± 0.04 .

Post-cursor equalization Local_eq_c1(5)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.25 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 5, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.25 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 5.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.25 ± 0.04 .

Main Voltage Measurements TP0a

The Main Voltage measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 16 Selecting Main Voltage Measurement Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Main Voltage Measurements TP0a (pattern: PRBS13Q) tests, see:

- [“Differential Peak-to-Peak Output Voltage Test with TX Disabled”](#) on page 71
- [“DC Common Mode Output Voltage Test”](#) on page 72
- [“AC Common Mode Output Voltage Test”](#) on page 73
- [“Differential Peak-to-Peak Output Voltage Test”](#) on page 74

Differential Peak-to-Peak Output Voltage Test with TX Disabled

- Test Overview** The purpose of this test is to verify that when TX is disabled, the peak-to-peak voltage meets the specified standards.
- Pass Condition** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Obtain a sample or acquire the signal data.
 - 2 Ensure that TX is disabled on the acquired signal (no valid data transitions).
 - 3 Measure peak-to-peak voltage of the signal.
 - 4 Compare the maximum peak-to-peak voltage to the specified standards.

DC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal meets the specified standards.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the DC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement to the specified standards.

AC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal meets the specified standards.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the AC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement to the specified standards.

Differential Peak-to-Peak Output Voltage Test

- Test Overview** The purpose of this test is to verify that the peak-to-peak voltage of the differential signal on a PRBS13Q pattern meets the specified standards.
- Pass Condition** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is connected, has TX enabled and has a PRBS13Q pattern.
 - 3 Measure the peak-to-peak voltage of the differential signal on DUT+ and DUT-.
 - 4 Compare the maximum peak-to-peak voltage to the specified standards.

Return Loss ENA/PNA Measurements

The Return Loss ENA/PNA Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope, PNA or ENA and the IEEE802.3 bs/cd Test Application. The Compliance Test Application controls the PNA/ENA to set the test limits and run the tests. You must ensure that the connected PNA/ENA is calibrated.




Figure 17 Selecting Return Loss PNA/ENA Measurements Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Return Loss PNA/ENA Measurements tests, see:

- [“Differential Output Return Loss”](#) on page 76
- [“Common-mode Output Return Loss”](#) on page 77

Differential Output Return Loss

- | | |
|----------------------------------|---|
| Measurement
Algorithm | <ol style="list-style-type: none">1 Ensure that the PNA/ENA is physically connected and calibrated.2 In the Set Up tab of the Compliance Test Application, click Connect PNA or Connect ENA to establish connectivity to the connected equipment.3 Click the Select Tests tab and check the tests to measure the Return Loss Measurements.4 Click Run under the Run tab. The Compliance Test Application automatically calculates the return loss.5 Compare the reported values with the specification to check for compliance. |
|----------------------------------|---|

Common-mode Output Return Loss

- Measurement Algorithm**
- 1 Ensure that the PNA/ENA is physically connected and calibrated.
 - 2 In the **Set Up** tab of the Compliance Test Application, click **Connect PNA** or **Connect ENA** to establish connectivity to the connected equipment.
 - 3 Click the **Select Tests** tab and check the tests to measure the Return Loss Measurements.
 - 4 Click **Run** under the **Run** tab. The Compliance Test Application automatically calculates the return loss.
 - 5 Compare the reported values with the specification to check for compliance.

5 PAM4 Host Output Characteristics at TP1a

Main Voltage Measurements TP1a	81
Transition Time Measurements TP1a	87
Signaling Rate and Eye Mask Measurements TP1a	90
Return Loss ENA/PNA Measurements	95

This section provides the Methods of Implementation (MOIs) for the PAM4 200GAUI and 400GAUI IEEE PAM4 Host Output Characteristics at TP1a as specified in IEEE P802.3bs™ /D3.5 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 200Gb/s and 400Gb/s Operation), Annex 120E.3.1, Table 120E-1. Measurements are made at TP1a.

NOTE

Ensure that the **Signaling Rate** setting in the **Configure** tab of the Compliance Test Application must match the frequency of the acquired input signal.

200GAUI-4 and 400GAUI-8 C2M host output electrical characteristics

Table 7 200GAUI-4 and 400GAUI-8 C2M host output characteristics at TP1a

Parameter	Reference	Value	Units
Signaling rate per lane (range)	See Sec. 120E.3.1.1 of the IEEE specification	26.5625 ± 100 ppm	GBd
DC common-mode output voltage (max)	See Sec. 120E.3.1.2 of the IEEE specification	2.8	V
DC common-mode output voltage (min)	See Sec. 120E.3.1.2 of the IEEE specification	-0.3	V
Single-ended output voltage (max)	See Sec. 120E.3.1.2 of the IEEE specification	3.3	V
Single-ended output voltage (min)	See Sec. 120E.3.1.2 of the IEEE specification	-0.4	V
AC common-mode output voltage (max, RMS)	See Sec. 120E.3.1.2 of the IEEE specification	17.5	mV
Differential peak-to-peak output voltage (max) Transmitter disabled Transmitter enabled	See Sec. 120E.3.1.2 of the IEEE specification	35 880	mV
ESMW (Eye symmetry mask width)	See Sec. 120E.4.2 of the IEEE specification	0.22	UI
Eye height, differential (min)	See Sec. 120E.4.2 of the IEEE specification	32	mV
Differential output return loss (min)	See Sec. 83E.3.1.3 of the IEEE specification	See Equation (83E-2) of the IEEE specification	dB
Common to differential mode conversion return loss (min)	See Sec. 83E.3.1.3 of the IEEE specification	See Equation (83E-3) of the IEEE specification	dB
Transition time (min, 20% to 80%)	See Sec. 120E.3.1.5 of the IEEE specification	10	ps

Main Voltage Measurements TP1a

The Main Voltage measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 15 Selecting Main Voltage Measurement Tests

Refer to [Table 7](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Main Voltage Measurements TP1a (pattern: PRBS13Q) tests, see:

- “Differential Peak-to-Peak Output Voltage Test with TX Disabled” on page 82
- “Differential Peak-to-Peak Output Voltage Test” on page 83
- “AC Common Mode Output Voltage Test” on page 84
- “DC Common Mode Output Voltage Test” on page 85

Differential Peak-to-Peak Output Voltage Test with TX Disabled

Test Overview The purpose of this test is to verify that when TX is disabled, the peak-to-peak voltage must be less than 35mV.

Pass Condition Refer to [Table 7](#).

- Measurement Algorithm**
- 1 Obtain a sample or acquire the signal data.
 - 2 Ensure that TX is disabled on the acquired signal (no valid data transitions).
 - 3 Measure peak-to-peak voltage of the signal.
 - 4 Compare the maximum peak-to-peak voltage to 35mV.

Differential Peak-to-Peak Output Voltage Test

- Test Overview** The purpose of this test is to verify that the peak-to-peak voltage of the differential signal on a PRBS13Q pattern is less than 880mV.
- Pass Condition** Refer to [Table 7](#).
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is connected, has TX enabled and has a PRBS13Q pattern.
 - 3 Measure the peak-to-peak voltage of the differential signal on DUT+ and DUT-.
 - 4 Compare the maximum peak-to-peak voltage with 880mV.

AC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal does not exceed 17.5mV.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 7](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the AC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement with 17.5mV.

DC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal is between -300mV and 2.8V.

NOTE

This measurement can be done only with dual-single ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 7](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Measure the DC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 3 Compare the voltage measurement to the range between -300mV and 2.8V.

Single-ended Output Voltage Test

Test Overview The purpose of this test is to verify that the minimum voltage on a single-ended signal is greater than -400mV and that the maximum voltage is less than 3.3V.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 7](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that there is a signal and that the connection is dual single-ended.
 - 3 Measure the minimum and maximum voltage on each single-ended signal.
 - 4 Compare the voltage measurements with the range between -400mV and 3.3V.

Transition Time Measurements TP1a

The Transition Time Measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 16 Selecting Transition Time Measurement Tests

Refer to [Table 7](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Transition Time Measurements TP1a (pattern: PRBS13Q) tests, see:

- “Minimum Output Rise Time (20%-80%)” on page 88
- “Minimum Output Fall Time (20%-80%)” on page 89

Minimum Output Rise Time (20%-80%)

Test Overview The purpose of this test is to verify that the minimum rise fall time is 10ps.

Pass Condition Refer to [Table 7](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is PRBS13Q.
 - 3 Find pattern 000333 for the rising edge.
 - 4 Measure rise time from 20% to 80% of the signal amplitude.
 - 5 Compare the minimum rise time with 10ps.

Minimum Output Fall Time (20%-80%)

Test Overview The purpose of this test is to verify that the minimum rise and fall times are 10ps.

Pass Condition Refer to [Table 7](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is PRBS13Q.
 - 3 Find pattern 333000 for the falling edge.
 - 4 Measure fall time from 20% to 80% of the signal amplitude.
 - 5 Compare the minimum rise time with 10ps.

Signaling Rate and Eye Mask Measurements TP1a

The Signaling Rate and Eye Mask Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 17 Selecting Signaling Rate and Eye Mask Measurement Tests

Refer to [Table 7](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Signaling Rate and Eye Mask Measurements TP1a (pattern: PRBS13Q) tests, see:

- “[Signaling Rate](#)” on page 91
- “[Eye Height A](#)” on page 92
- “[Eye Width](#)” on page 93
- “[ESMW](#)” on page 94

Signaling Rate

Test Overview The purpose of this test is to verify that the signaling rate mean is between $26.5625 \pm 100\text{ppm}$ GBd.

Pass Condition Refer to [Table 7](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Check that the signal is connected, has a bit-rate of 53.125 GHz and that data pattern exists (PRBS13Q must be used for this test).
 - 3 In the **Configure** tab, set **Signaling Rate** to 26.5625 Gb/s.
 - 4 Measure minimum, maximum and mean data rate.
 - 5 Report minimum and maximum values.
 - 6 Compare the mean data rate value with $26.5625 \pm 100\text{ppm}$ GBd.
 - 7 Report the resulting value.

Eye Height A

- Test Overview** The purpose of this test is to verify that for a defined range of CTLE settings, the Eye Height A is greater than 32mV. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.
- Pass Conditions** Refer to [Table 7](#).
- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'. See IEEE 802.3bs D3.0, Section 120E, Table 120E-2 (Reference CTLE Coefficients).
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Eye Height A at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Compare the Eye Height A with 32mV. Report the resulting value.

Eye Width

Test Overview The purpose of this test is to measure the Eye Width for a defined range of CTLE settings. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Not applicable as the test result is considered as “Information Only”.

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as ‘User-defined optimal CTLE’. See IEEE 802.3bs D3.0, Section 120E, Table 120E-2 (Reference CTLE Coefficients).
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Eye Width at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Report the resulting value of Eye Width.

NOTE

The Eye Width measurement is considered as an “Information-Only” test and cannot be used for compliance validation.

ESMW

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the ESMW is greater than 220mUI (that is, 110mUI each for the left and right eye). The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 7](#).

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'. See IEEE 802.3bs D3.0, Section 120E, Table 120E-2 (Reference CTLE Coefficients).
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the ESMW at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Calculate ESMW for each given eye (left and right) using the equations:

$$\text{Left} = (\text{Eye Width} / 2) - \text{Eye Skew}$$

$$\text{Right} = (\text{Eye Width} / 2) + \text{Eye Skew}$$
 - 6 Compare the ESMW with 220mUI (that is, 110mUI each for the left and right eye). Report the resulting value.

Return Loss ENA/PNA Measurements

The Return Loss ENA/PNA Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope, PNA or ENA and the IEEE802.3 bs/cd Test Application. The Compliance Test Application controls the PNA/ENA to set the test limits and run the tests. You must ensure that the connected PNA/ENA is calibrated.




Figure 18 Selecting Return Loss Measurement Tests

Refer to [Table 7](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Return Loss PNA/ENA Measurements tests, see:

- [“Differential Output Return Loss”](#) on page 96
- [“Common-mode to Differential Output Return Loss”](#) on page 97

Differential Output Return Loss

- | | |
|----------------------------------|---|
| Measurement
Algorithm | <ol style="list-style-type: none">1 Ensure that the PNA/ENA is physically connected and calibrated.2 In the Set Up tab of the Compliance Test Application, click Connect PNA or Connect ENA to establish connectivity to the connected equipment.3 Click the Select Tests tab and check the tests to measure the Return Loss Measurements.4 Click Run under the Run tab. The Compliance Test Application automatically calculates the return loss.5 Compare the reported values with the specification to check for compliance. |
|----------------------------------|---|

Common-mode to Differential Output Return Loss

- Measurement Algorithm**
- 1 Ensure that the PNA/ENA is physically connected and calibrated.
 - 2 In the **Set Up** tab of the Compliance Test Application, click **Connect PNA** or **Connect ENA** to establish connectivity to the connected equipment.
 - 3 Click the **Select Tests** tab and check the tests to measure the Return Loss Measurements.
 - 4 Click **Run** under the **Run** tab. The Compliance Test Application automatically calculates the return loss.
 - 5 Compare the reported values with the specification to check for compliance.

6 PAM4 Transmitter Characteristics at TP2

Jitter and Signaling Rate Measurements TP2 102

Output Voltage Measurements EYE TP2 107

Output Waveform Measurements TP2 111

Main Voltage Measurements TP2 127

Return Loss ENA/PNA Measurements 132

This section provides the Methods of Implementation (MOIs) for the IEEE PAM4 Transmitter Characteristics at TP2. Measurements are made at test point TP2.

NOTE

Ensure that the **Signaling Rate** setting in the **Configure** tab of the **Compliance Test Application** must match the frequency of the acquired input signal.

C2C transmitter characteristics

For CR tests

See Table 8 for pass limits pertaining to 50GBASE-CR, 100GBASE-CR2, and 200GBASE-CR PAM4 tests, which are specified in IEEE P802.3cd™ /D3.0 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 50Gb/s, 100Gb/s, and 200Gb/s Operation) section 136.9.3, Table 136-11.

Table 8 50GBASE-CR, 100GBASE-CR2, and 200GBASE-CR C2C transmitter characteristics at TP2

Parameter	Reference	Value	Units
Differential pk-to-pk output voltage (max) with TX disabled ^a	See Sec. 93.8.1.3 of the IEEE specification	30	mV
DC common-mode voltage (max) ^a	See Sec. 93.8.1.3 of the IEEE specification	1.9	V
AC common-mode RMS output voltage, v_{cmi} (max) ^a	See Sec. 93.8.1.3 of the IEEE specification	30	mV
Differential pk-to-pk, v_{di} (max) ^a	See Sec. 93.8.1.3 of the IEEE specification	1200	mV
Differential output return loss (min)	See Sec. 92.8.3.2 of the IEEE specification	See Equation (92-1) of the IEEE specification	dB
Common-mode to differential mode output return loss (min)	See Sec. 92.8.3.3 of the IEEE specification	See Equation (92-2) of the IEEE specification	dB
Common-mode to common-mode output return loss (min)	See Sec. 92.8.3.4 of the IEEE specification	See Equation (92-3) of the IEEE specification	dB
Transmitter steady-state voltage, v_f (min)	See Sec. 136.9.3.1.2 of the IEEE specification	0.34	V
Transmitter steady-state voltage, v_f (max)	See Sec. 136.9.3.1.2 of the IEEE specification	0.6	V
Linear fit pulse peak (min)	See Sec. 136.9.3.1.2 of the IEEE specification	$0.49 \times v_f$	V
Level separation mismatch ratio R_{LM} (min)	See Sec.120D.3.1.2 of the IEEE specification	0.95	-
Transmitter output waveform	See Sections		
abs step size for c(-1), c(0), and c(1) (min.)	136.9.3.1.4	0.005	-
abs step size for c(-1), c(0), and c(1) (max.)	136.9.3.1.4	0.05	-
abs step size for c(-2) (min.)	136.9.3.1.4	0.005	-
abs step size for c(-2) (max.)	136.9.3.1.4	0.025	-
value at maximum state for c(-1) and c(1) (max.)	136.9.3.1.5	-0.25	-
value at maximum state for c(-2) (min.)	136.9.3.1.5	0.1	-
Signal-to-noise-and-distortion ratio SNDR (min)	See Sec.120D.3.1.6 of the IEEE specification	33.3	dB
SNR_{ISI} (min) ^b	See Sec. 120D.3.1.7 of the IEEE specification	36.8	dB
Output jitter (max.)	See Sections		
JRMS	120D.3.1.8	0.023	UI
J4u	120D.3.1.8	0.118	UI
Even-odd jitter, pk-pk	120D.3.1.8	0.019	UI
Signaling rate per lane (range)		26.5625 ± 100 ppm	GBd

- a. Measurement uses the method described in section 93.8.1.3 of IEEE specification with the exception that the PRBS13Q test pattern is used.
- b. Measured only in unequalized setting.

Jitter and Signaling Rate Measurements TP2

The Jitter and Signaling Rate Measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 19 Selecting Jitter and Signaling Rate Measurement Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Jitter and Signaling Rate Measurements TP2 (pattern: PRBS13Q) tests, see:

- “[Signaling Rate](#)” on page 103
- “[JRMS](#)” on page 104
- “[J4u](#)” on page 105
- “[Even-Odd Jitter](#)” on page 106

Signaling Rate

- Test Overview** The purpose of this test is to verify that the signaling rate meets the specified standards.
- Pass Condition** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Check that the signal is connected, has a bit-rate of 53.125 GHz and that data pattern exists (PRBS13Q must be used for this test).
 - 3 In the **Configure** tab, set **Signaling Rate** to 26.5625 Gb/s.
 - 4 Measure minimum and maximum data rate.
 - 5 Report minimum and maximum values.
 - 6 Compare the mean data rate value with the specified standards. Report the resulting value.

JRMS

Test Overview The purpose of this test is to verify that differential signal's JRMS meets the specified standards. All jitter tests are run in a single measurement. However, each test can be run individually.

Pass Conditions Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Obtain sample or acquire signal data. Set acquisition depth to five times the length of the PRBS13Q pattern.

NOTE

For DSO-Z Series Oscilloscopes, connections must be established between Data+ to Channel 1R and Data- to Channel 3R to measure the defined 12 edges.

For UXR Series Oscilloscopes, connections must be established between Data+ to Channel 1 and Data- to Channel 2 to measure the defined 12 edges.

Irrespective of the Oscilloscope used, the signal must be of PRBS13Q pattern.

- 2 In the **Configure** tab, set the value for the Signaling Rate as that of the Symbol Rate of the acquired signal.
- 3 On the Oscilloscope,
 - a Set Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Using PAM4 jitter measurements, at least 10,000 PRBS13Q patterns are captured to collect the measurement data of 12 edges.
 - c Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.

NOTE

This measurement can run for a duration of 8-10 minutes.

- 4 Compare and report the JRMS value to the specified standards.

J4u

Test Overview The purpose of this test is to verify that differential signal's J4u meets the specified standards. All jitter tests are run in a single measurement. However, each test can be run individually.

Pass Conditions Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Obtain sample or acquire signal data. Set acquisition depth to five times the length of the PRBS13Q pattern.

NOTE

For DSO-Z Series Oscilloscopes, connections must be established between Data+ to Channel 1R and Data- to Channel 3R to measure the defined 12 edges.

For UXR Series Oscilloscopes, connections must be established between Data+ to Channel 1 and Data- to Channel 2 to measure the defined 12 edges.

Irrespective of the Oscilloscope used, the signal must be of PRBS13Q pattern.

- 2 In the **Configure** tab, set the value for the Signaling Rate as that of the Symbol Rate of the acquired signal.
- 3 On the Oscilloscope,
 - a Set Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Using PAM4 jitter measurements, at least 10,000 PRBS13Q patterns are captured to collect the measurement data of 12 edges.
 - c Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.

NOTE

This measurement can run for a duration of 8-10 minutes.

- 4 Compare and report the J4u value meets the specified standards.

Even-Odd Jitter

- Test Overview** The purpose of this test is to verify that differential signal's Even-Odd Jitter meets the specified standards. All jitter tests are run in a single measurement. However, each test can be run individually.
- Pass Conditions** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data. Set acquisition depth to five times the length of the PRBS13Q pattern.

NOTE

For DSO-Z Series Oscilloscopes, connections must be established between Data+ to Channel 1R and Data- to Channel 3R to measure the defined 12 edges.

For UXR Series Oscilloscopes, connections must be established between Data+ to Channel 1 and Data- to Channel 2 to measure the defined 12 edges.

Irrespective of the Oscilloscope used, the signal must be of PRBS13Q pattern.

- 2 In the **Configure** tab, set the value for the Signaling Rate as that of the Symbol Rate of the acquired signal.
- 3 On the Oscilloscope,
 - a Set Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Using PAM4 jitter measurements, at least 10,000 PRBS13Q patterns are captured to collect the measurement data of 12 edges.
 - c Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.

NOTE

This measurement can run for a duration of 8-10 minutes.

- 4 Compare and report the Even-Odd Jitter value to the specified standards.

Output Voltage Measurements EYE TP2

The Output Voltage Measurement EYE procedures for a signal with PRBS13Q pattern that are described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 20 Selecting Output Voltage Measurements EYE Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Output Voltage Measurements EYE TP2 (pattern: PRBS13Q) tests, see:

- [“Level - PRBS Pattern”](#) on page 108
- [“Level RMS - PRBS Pattern”](#) on page 109
- [“Level Separation Mismatch Ratio - RLM”](#) on page 110

NOTE

The tests [Level - PRBS pattern](#) and [Level RMS - PRBS pattern](#) are considered as “Information-Only” tests and cannot be used for compliance validation.

Level - PRBS Pattern

- Test Overview** The purpose of this test is to obtain the mean voltage of each level of the signal with PRBS13Q pattern.
- Pass Condition** Not applicable as the test result is considered as “Information Only”.
- Measurement Algorithm**
- 1 Check that signal is connected and proper data pattern exists (PRBS13Q pattern must be used for this test).
 - 2 V_0 , V_1 , V_2 and V_3 are the mean signal levels of the symbols corresponding to the PAM4 symbol levels 0, 1, 2 and 3 respectively, as defined in IEEE P802.3bs™ /D3.5 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 200Gb/s and 400Gb/s Operation), Annex 120D.3.1.2. The calculation of mean signal levels is also defined in section 120D.3.1.2.1.
 - 3 The mean level V_{mid} is defined by equation (120D-3), which is,

$$V_{mid} = (V_0 + V_3) / 2$$
 - 4 Report this value for information-only purpose.

Level RMS - PRBS Pattern

- Test Overview** The purpose of this test is to obtain the of the RMS level of the signal with PRBS13Q pattern.
- Pass Condition** Not applicable as the test result is considered as “Information Only”.
- Measurement Algorithm**
- 1 Run the Level - PRBS Pattern test as a prerequisite to this test.
 - 2 The minimum signal level RMS is calculated, as defined in IEEE P802.3bs™ /D3.5 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 200Gb/s and 400Gb/s Operation), Annex 120D.3.1.2.
 - 3 Report this value for information-only purpose.

Level Separation Mismatch Ratio - RLM

Test Overview The purpose of this test is to obtain the of the Separation Mismatch Ratio level (RLM) of the signal with PRBS13Q pattern.

Pass Condition Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Run the Level - PRBS Pattern as a prerequisite to this test to calculate the mid-range level.
- 2 The mean signal levels are normalized so that V_0 corresponds to -1, V_1 to -ES1, V_2 to ES2 and V_3 to 1.
- 3 ES1 and ES2 are calculated using equations (120D-4) and (120D-5), respectively of the IEEE P802.3bs™ /D3.5 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 200Gb/s and 400Gb/s Operation), Annex 120D.3.1.2.

$$ES1 = (V_1 - V_{mid}) / (V_0 - V_{mid})$$

$$ES2 = (V_2 - V_{mid}) / (V_3 - V_{mid})$$

4 The level separation mismatch ratio R_{LM} is defined by equation (120D-5).

$$R_{LM} = \min [(3 \times ES1), (3 \times ES2), (2 - 3 \times ES1), (2 - 3 \times ES2)]$$

5 Report this value for information-only purpose.

Output Waveform Measurements TP2

The Output Waveform Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 21 Selecting Transmitter Output Waveform Measurement Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Output Waveform Measurements TP2 (pattern: PRBS13Q) tests, see:

- [“Steady State Voltage Vf”](#) on page 112
- [“Linear Fit Pulse Peak”](#) on page 113
- [“Signal-to-noise-and-distortion ratio”](#) on page 114
- [“SNR_ISI Tests”](#) on page 115
- [“Pre and Post Equalization Tests”](#) on page 116

Steady State Voltage V_f

- Test Overview** The purpose of this test is to verify that the Steady State Voltage is between 0.4V and 0.6V.
- Pass Condition** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Check that signal is connected and proper data pattern exists (PRBS13Q must be used for this test).
 - 2 Set memory depth and sample rate to capture the 8191 bits of the PRBS13Q pattern.
 - 3 Calculate V_f using the equations in section 85.8.3.3.5. The resulting value is the sum of columns of $p(k)/M$. $N_p = 200$, $D_p = 2$.
 - 4 Compare and report the resulting value in the range between 0.4V and 0.6V.

Linear Fit Pulse Peak

Test Overview The purpose of this test is to verify that the Linear Fit Pulse meets the specified standards.

NOTE

Run the Steady-State Voltage Vf test as a prerequisite to running the Linear Fit Pulse Peak test.

Pass Conditions Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Check that signal is connected and proper data pattern exists (PRBS13Q must be used for this test).
- 2 Set memory depth and sample rate to capture the 8191 bits of the PRBS13Q pattern.
- 3 Calculate Linear Fit Pulse using the equations in section 85.8.3.3.5. The resulting value is the peak value of $p(k)$. $N_p = 200$, $D_p = 2$.
- 4 Compare the specified standards to the resulting value.

Signal-to-noise-and-distortion ratio

- Test Overview** The purpose of this test is to verify that the Signal-to-noise-and-distortion ratio (SNDR) meets the specified standards.
- Pass Condition** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Calculate SNDR using measurements from Level RMS - PRBS pattern test and error from Linear Fit Pulse Peak test.
 - 2 Compare the resulting value of SNDR to the specified standards.

SNR_ISI Tests

Test Overview The purpose of this test is to verify that the Transmitter Output residual ratio (SNR_ISI) for each value of Output Gain (in decibels) meets the specified standards.




Figure 22 Selecting SNR_ISI Tests

Pass Condition Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

- Measurement Algorithm**
- 1 Select one or more tests that pertain to a specific Output Gain value.
 - 2 Calculate SNRISI for each selected test using measurements from Level RMS - PRBS pattern test and error from Linear Fit Pulse Peak test.
 - 3 Compare the resulting value to the specified standards.

Pre and Post Equalization Tests

Test Overview The purpose of this test is to verify the Pre-cursor and Post-cursor equalization ratios.




Figure 23 Selecting Pre and Post Equalization Tests

To know about the measurement algorithm for each Pre and Post Equalization Tests, see:

- “Pre-cursor equalization Local_eq_cm1(0)” on page 117
- “Pre-cursor equalization Local_eq_cm1(1)” on page 118
- “Pre-cursor equalization Local_eq_cm1(2)” on page 119
- “Pre-cursor equalization Local_eq_cm1(3)” on page 120
- “Pre-cursor equalization Local_eq_c1(0)” on page 121
- “Post-cursor equalization Local_eq_c1(1)” on page 122
- “Post-cursor equalization Local_eq_c1(2)” on page 123
- “Post-cursor equalization Local_eq_c1(3)” on page 124
- “Post-cursor equalization Local_eq_c1(4)” on page 125
- “Post-cursor equalization Local_eq_c1(5)” on page 126

Pre-cursor equalization Local_eq_cm1(0)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is 0 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 0, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within 0 ± 0.04 .
- Measurement Algorithm**
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix R_m using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 0.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with 0 ± 0.04 .

Pre-cursor equalization Local_eq_cm1(1)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is -0.05 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 1, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.05 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 1.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with -0.05 ± 0.04 .

Pre-cursor equalization Local_eq_cm1(2)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is -0.1 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 2, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.1 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 2.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with -0.1 ± 0.04 .

Pre-cursor equalization Local_eq_cm1(3)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is -0.15 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 3, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.15 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 3.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with -0.15 ± 0.04 .

Pre-cursor equalization Local_eq_c1(0)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is 0 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 0, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within 0 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 0.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with 0 ± 0.04 .

Post-cursor equalization Local_eq_c1(1)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.05 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 1, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.05 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 1.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.05 ± 0.04 .

Post-cursor equalization Local_eq_c1(2)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.1 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 2, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.1 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 2.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.1 ± 0.04 .

Post-cursor equalization Local_eq_c1(3)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.15 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 3, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.15 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 3.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.15 ± 0.04 .

Post-cursor equalization Local_eq_c1(4)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.2 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 4, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.2 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 4.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.2 ± 0.04 .

Post-cursor equalization Local_eq_c1(5)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.25 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 5, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.25 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS13Q pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 5.
 - 6 Calculate linear fit pulse response 85.8.3.3.5 with $N_p = 200$, $D_p = 2$. The value for ES is defined to be $(|ES1| + |ES2|)/2$ where ES1 and ES2 are defined in section 120D.3.1.2 of the IEEE P802.3bs™ /D3.5 document.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.25 ± 0.04 .

Main Voltage Measurements TP2

The Main Voltage measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 24 Selecting Main Voltage Measurement Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Main Voltage Measurements TP2 (pattern: PRBS13Q) tests, see:

- “Differential Peak-to-Peak Output Voltage Test with TX Disabled” on page 128
- “DC Common Mode Output Voltage Test” on page 129
- “AC Common Mode Output Voltage Test” on page 130
- “Differential Peak-to-Peak Output Voltage Test” on page 131

Differential Peak-to-Peak Output Voltage Test with TX Disabled

- Test Overview** The purpose of this test is to verify that when TX is disabled, the peak-to-peak voltage meets the specified standards.
- Pass Condition** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Obtain a sample or acquire the signal data.
 - 2 Ensure that TX is disabled on the acquired signal (no valid data transitions).
 - 3 Measure peak-to-peak voltage of the signal.
 - 4 Compare the maximum peak-to-peak voltage to the specified standards.

DC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal meets the specified standards.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the DC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement to the specified standards.

AC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal meets the specified standards.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the AC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement to the specified standards.

Differential Peak-to-Peak Output Voltage Test

- Test Overview** The purpose of this test is to verify that the peak-to-peak voltage of the differential signal on a PRBS13Q pattern meets the specified standards.
- Pass Condition** Refer to the section [C2C transmitter characteristics](#) for the pass limits pertaining to each standard option.
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is connected, has TX enabled and has a PRBS13Q pattern.
 - 3 Measure the peak-to-peak voltage of the differential signal on DUT+ and DUT-.
 - 4 Compare the maximum peak-to-peak voltage to the specified standards.

Return Loss ENA/PNA Measurements

The Return Loss ENA/PNA Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope, PNA or ENA and the IEEE802.3 bs/cd Test Application. The Compliance Test Application controls the PNA/ENA to set the test limits and run the tests. You must ensure that the connected PNA/ENA is calibrated.




Figure 25 Selecting Return Loss PNA/ENA Measurements Tests

Refer to the section [C2C transmitter characteristics](#) for information on the pass limits for each test that is displayed for the selected standard option.

To know about the measurement algorithm for each Return Loss PNA/ENA Measurements tests, see:

- [“Differential Output Return Loss”](#) on page 133
- [“Common-mode Output Return Loss”](#) on page 134

Differential Output Return Loss

- Measurement Algorithm**
- 1 Ensure that the PNA/ENA is physically connected and calibrated.
 - 2 In the **Set Up** tab of the Compliance Test Application, click **Connect PNA** or **Connect ENA** to establish connectivity to the connected equipment.
 - 3 Click the **Select Tests** tab and check the tests to measure the Return Loss Measurements.
 - 4 Click **Run** under the **Run** tab. The Compliance Test Application automatically calculates the return loss.
 - 5 Compare the reported values with the specification to check for compliance.

Common-mode Output Return Loss

- | | |
|----------------------------------|---|
| Measurement
Algorithm | <ol style="list-style-type: none">1 Ensure that the PNA/ENA is physically connected and calibrated.2 In the Set Up tab of the Compliance Test Application, click Connect PNA or Connect ENA to establish connectivity to the connected equipment.3 Click the Select Tests tab and check the tests to measure the Return Loss Measurements.4 Click Run under the Run tab. The Compliance Test Application automatically calculates the return loss.5 Compare the reported values with the specification to check for compliance. |
|----------------------------------|---|

7 PAM4 Module Output Characteristics at TP4

Main Voltage Measurements TP4	137
Transition Time Measurements TP4	141
Signaling Rate and Eye Mask Measurements TP4	144
Return Loss ENA/PNA Measurements	154

This section provides the Methods of Implementation (MOIs) for the PAM4 200GAUI and 400GAUI IEEE PAM4 Module Output Characteristics at TP4 as specified in IEEE P802.3bs™ /D3.5 (Draft Standard for Ethernet Amendment 10: Media Access Control Parameters, Physical Layers and Management Parameters for 200Gb/s and 400Gb/s Operation), Annex 120E.3.2, Table 120E-3. Measurements are made at TP4.

NOTE

Ensure that the **Signaling Rate** setting in the **Configure** tab of the Compliance Test Application must match the frequency of the acquired input signal.

200GAUI-4 and 400GAUI-8 C2M module output electrical characteristics

Table 9 200GAUI-4 and 400GAUI-8 C2M module output characteristics at TP4

Parameter	Reference	Value	Units
Signaling rate per lane (range)	See Sec. 120E.3.1.1 of the IEEE specification	26.5625 ± 100 ppm	GBd
AC common-mode output voltage (max, RMS)	See Sec. 120E.3.1.2 of the IEEE specification	17.5	mV
Differential peak-to-peak output voltage (max)	See Sec. 120E.3.1.2 of the IEEE specification	900	mV
Near-end ESMW (Eye symmetry mask width)	See Sec. 120E.4.2 of the IEEE specification	0.265	UI
Near-end Eye height, differential (min)	See Sec. 120E.4.2 of the IEEE specification	70	mV
Far-end ESMW (Eye symmetry mask width)	See Sec. 120E.4.2 of the IEEE specification	0.2	UI
Far-end Eye height, differential (min)	See Sec. 120E.4.2 of the IEEE specification	30	mV
Differential output return loss (min)	See Sec. 83E.3.1.3 of the IEEE specification	See Equation (83E-2) of the IEEE specification	dB
Common to differential mode conversion return loss (min)	See Sec. 83E.3.1.3 of the IEEE specification	See Equation (83E-3) of the IEEE specification	dB
Transition time (min, 20% to 80%)	See Sec. 120E.3.1.5 of the IEEE specification	9.5	ps
DC common mode voltage (min) ^a	See Sec. 120E.3.1.2 of the IEEE specification	-350	mV
DC common mode voltage (max) ^a	See Sec. 120E.3.1.2 of the IEEE specification	2850	mV

a. DC common mode voltage is generated by the host. Specification includes effects of ground offset voltage.

Main Voltage Measurements TP4

The Main Voltage measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 26 Selecting Main Voltage Measurement Tests

Refer to [Table 9](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Main Voltage Measurements TP4 (pattern: PRBS13Q) tests, see:

- “[Differential Output Voltage Test](#)” on page 138
- “[AC Common Mode Output Voltage Test](#)” on page 139
- “[DC Common Mode Voltage Test](#)” on page 140

Differential Output Voltage Test

Test Overview The purpose of this test is to verify that the peak-to-peak voltage of the differential signal on a PRBS13Q pattern is less than 900mV.

Pass Condition Refer to [Table 9](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is connected, has TX enabled and has a PRBS13Q pattern.
 - 3 Measure the peak-to-peak voltage of the differential signal of DUT+ and DUT-.
 - 4 Compare the maximum peak-to-peak voltage to 900mV.

AC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common-mode voltage of the signal does not exceed 17.5mV.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 9](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the peak-to-peak voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement with 17.5mV.

DC Common Mode Voltage Test

Test Overview The purpose of this test is to verify that the common-mode voltage of the signal is between -350mV and 2.85V.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 9](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the peak-to-peak voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement to the range between -350mV and 2.85V.

Transition Time Measurements TP4

The Transition Time Measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 27 Selecting Transition Time Measurement Tests

Refer to [Table 9](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Transition Time Measurements TP4 (pattern: PRBS13Q) tests, see:

- “Minimum Output Rise Time (20%-80%)” on page 142
- “Minimum Output Fall Time (20%-80%)” on page 143

Minimum Output Rise Time (20%-80%)

Test Overview The purpose of this test is to verify that the minimum rise time is 9.5ps.

Pass Condition Refer to [Table 9](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is PRBS13Q.
 - 3 Find pattern 000333 for rising edge.
 - 4 Measure rise time from 20% to 80% of the signal amplitude.
 - 5 Compare the minimum rise time with 9.5ps.

Minimum Output Fall Time (20%-80%)

Test Overview The purpose of this test is to verify that the minimum fall time is 9.5ps.

Pass Condition Refer to [Table 9](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is PRBS13Q.
 - 3 Find pattern 333000 for the falling edge.
 - 4 Measure fall time from 20% to 80% of the signal amplitude.
 - 5 Compare the minimum fall time with 9.5ps.

Signaling Rate and Eye Mask Measurements TP4

The Signaling Rate and Eye Mask Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 28 Selecting Signaling Rate and Eye Mask Measurement Tests

Refer to [Table 9](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Signaling Rate and Eye Mask Measurements TP4 (pattern: PRBS13Q) tests, see:

- “[Signaling Rate](#)” on page 145
- “[Near-end Eye Height](#)” on page 146
- “[Near-end Eye Width](#)” on page 147
- “[Near-end ESMW](#)” on page 148
- “[Vertical Eye Closure](#)” on page 149
- “[Far-end Eye Height](#)” on page 150
- “[Far-end Eye Width](#)” on page 151
- “[Far-end ESMW](#)” on page 152
- “[Far-end pre-cursor ISI ratio](#)” on page 153

Signaling Rate

- Test Overview** The purpose of this test is to verify that the signaling rate mean is between $26.5625 \pm 100\text{ppm}$ GBd.
- Pass Condition** Refer to [Table 9](#).
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Check that the signal is connected, has a bit-rate of 53.125 GHz and that data pattern exists (PRBS13Q must be used for this test).
 - 3 In the **Configure** tab, set **Signaling Rate** to 26.5625 Gb/s.
 - 4 Measure minimum, maximum and mean data rate.
 - 5 Report minimum and maximum values.
 - 6 Compare the mean data rate value with $26.5625 \pm 100\text{ppm}$ GBd.
 - 7 Report the resulting value.

Near-end Eye Height

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Near-end Eye Height is greater than 70mV. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 9](#).

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Near-end Eye Height at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Compare the Near-end Eye Height with 70mV. Report the resulting value.

Near-end Eye Width

Test Overview The purpose of this test is to measure the Near-end Eye Width for a defined range of CTLE settings. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Not applicable as the test result is considered as “Information Only”.

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as ‘User-defined optimal CTLE’.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Near-end Eye Width at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Report the resulting value of Near-end Eye Width.

NOTE

The Near-end Eye Width measurement is considered as an “Information-Only” test and cannot be used for compliance validation.

Near-end ESMW

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Near-end ESMW is greater than 265mUI (that is, 132.5mUI each for the left and right eye). The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 9](#).

NOTE

The Near-end ESMW test checks for margins to the left and right of TC_{min} . Therefore, the limit used for measurements in this test is 0.1325UI.

Measurement Algorithm

- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
- 2 Obtain sample or acquire signal data.
- 3 Measure the Near-end ESMW ESMW at an **Eye Height/Width Probability** setting of 1E-5.
- 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
- 5 Calculate Near-end ESMW for each given eye (left and right) using the equations:

$$\text{Left} = (\text{Eye Width} / 2) - \text{Eye Skew}$$

$$\text{Right} = (\text{Eye Width} / 2) + \text{Eye Skew}$$
- 6 Compare the Near-end ESMW with 265mUI (that is, 132.5mUI each for the left and right eye). Report the resulting value.

Vertical Eye Closure

- Test Overview** The purpose of this test is to measure the Vertical Eye Closure at EH15 (1E-15).
- Pass Conditions** Not applicable as the test result is considered as “Information Only”.
- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as ‘User-defined optimal CTLE’.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Vertical Eye Closure at an **Eye Height/Width Probability** setting of 1E-15 (EH15).
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Measure and calculate AV as the mean value of logic 1 minus the mean value of logic 0 at the central 5% of the eye.
 - 6 Calculate Vertical Eye Closure (VEC) using the equation:

$$VEC = 20\log(AV/EH15)$$
 - 7 Report the resulting value of Vertical Eye Closure.

NOTE

The Vertical Eye Closure measurement is considered as an “Information-Only” test and cannot be used for compliance validation.

Far-end Eye Height

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Far-end Eye Height is greater than 30mV. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 9](#).

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Far-end Eye Height at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Compare the Far-end Eye Height with 30mV. Report the resulting value.

Far-end Eye Width

Test Overview The purpose of this test is to measure the Far-end Eye Width for a defined range of CTLE settings. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Not applicable as the test result is considered as “Information Only”.

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as ‘User-defined optimal CTLE’.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Far-end Eye Width at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Report the resulting value of Far-end Eye Width.

NOTE

The Far-end Eye Width measurement is considered as an “Information-Only” test and cannot be used for compliance validation.

Far-end ESMW

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Far-end ESMW is greater than 200mUI (that is, 100mUI each for the left and right eye). The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 9](#).

NOTE

The Far-end ESMW test checks for margins to the left and right of TC_{min} . Therefore, the limit used for measurements in this test is 0.1UI.

Measurement Algorithm

- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
- 2 Obtain sample or acquire signal data.
- 3 Measure the Far-end ESMW ESMW at an **Eye Height/Width Probability** setting of 1E-5.
- 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
- 5 Calculate Far-end ESMW for each given eye (left and right) using the equations:

$$\text{Left} = (\text{Eye Width} / 2) - \text{Eye Skew}$$

$$\text{Right} = (\text{Eye Width} / 2) + \text{Eye Skew}$$

- 6 Compare the Far-end ESMW with 200mUI (that is, 100mUI each for the left and right eye). Report the resulting value.

Far-end pre-cursor ISI ratio

Test Overview The purpose of this test is to verify that for a selected CTLE settings, the Far-end ESMW is greater than 200mUI (that is, 100mUI each for the left and right eye). The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 9](#).

NOTE

The Far-end ESMW test checks for margins to the left and right of TC_{min} . Therefore, the limit used for measurements in this test is 0.1UI.

Measurement Algorithm

- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
- 2 Obtain sample or acquire signal data.
- 3 Measure the Far-end ESMW ESMW at an **Eye Height/Width Probability** setting of 1E-5.
- 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
- 5 Calculate Far-end ESMW for each given eye (left and right) using the equations:

$$\text{Left} = (\text{Eye Width} / 2) - \text{Eye Skew}$$

$$\text{Right} = (\text{Eye Width} / 2) + \text{Eye Skew}$$
- 6 Compare the Far-end ESMW with 200mUI (that is, 100mUI each for the left and right eye). Report the resulting value.

Return Loss ENA/PNA Measurements

The Return Loss ENA/PNA Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope, PNA or ENA and the IEEE802.3 bs/cd Test Application. The Compliance Test Application controls the PNA/ENA to set the test limits and run the tests. You must ensure that the connected PNA/ENA is calibrated.




Figure 29 Selecting Return Loss Measurement Tests

Refer to [Table 9](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Return Loss PNA/ENA Measurements tests, see:

- [“Differential Output Return Loss”](#) on page 155
- [“Common-mode to Differential Output Return Loss”](#) on page 156

Differential Output Return Loss

- Measurement Algorithm**
- 1 Ensure that the PNA/ENA is physically connected and calibrated.
 - 2 In the **Set Up** tab of the Compliance Test Application, click **Connect PNA** or **Connect ENA** to establish connectivity to the connected equipment.
 - 3 Click the **Select Tests** tab and check the tests to measure the Return Loss Measurements.
 - 4 Click **Run** under the **Run** tab. The Compliance Test Application automatically calculates the return loss.
 - 5 Compare the reported values with the specification to check for compliance.

Common-mode to Differential Output Return Loss

- | | |
|----------------------------------|---|
| Measurement
Algorithm | <ol style="list-style-type: none">1 Ensure that the PNA/ENA is physically connected and calibrated.2 In the Set Up tab of the Compliance Test Application, click Connect PNA or Connect ENA to establish connectivity to the connected equipment.3 Click the Select Tests tab and check the tests to measure the Return Loss Measurements.4 Click Run under the Run tab. The Compliance Test Application automatically calculates the return loss.5 Compare the reported values with the specification to check for compliance. |
|----------------------------------|---|

8 NRZ Transmitter Characteristics at TP0a

Jitter and Signaling Rate Measurements TP0a	160
Output Waveform Measurements TP0a	165
Main Voltage Measurements TP0a	180
Return Loss ENA/PNA Measurements	185

This section provides the Methods of Implementation (MOIs) for the 200GAUI and 400GAUI IEEE NRZ Transmitter Characteristics at TP0a as specified in IEEE Std. 802.3-2015 (IEEE standard for Ethernet), Annex 83D.3.1, Table 83D-1 with 120B.3.1. Measurements are made at TP0a.

NOTE

Ensure that the **Signaling Rate** setting in the **Configure** tab of the Compliance Test Application must match the frequency of the acquired input signal.

CAUI-4 C2C transmitter electrical characteristics

Table 10 CAUI-4 C2C transmitter characteristics at TP0a

Parameter	Reference	Value	Units
Signaling rate per lane (range)	See Sec. 93.8.1.2 of the IEEE specification	25.78125 ± 100 ppm	GBd
Differential peak-to-peak output voltage (max)	See Sec. 93.8.1.3 of the IEEE specification	30	mV
Transmitter disabled		1200	mV
Transmitter enabled			
Common-mode voltage (max)	See Sec. 93.8.1.3 of the IEEE specification	1.9	V
Common-mode voltage (min)	See Sec. 93.8.1.3 of the IEEE specification	0	V
AC common-mode output voltage (max, RMS)	See Sec. 93.8.1.3 of the IEEE specification	12	mV
Differential output return loss (min)	See Sec. 93.8.1.4 of the IEEE specification	See Equation (93-3) of the IEEE specification	dB
Common-mode output return loss (min)	See Sec. 93.8.1.4 of the IEEE specification	See Equation (93-4) of the IEEE specification	dB
Output waveform ^a	See Sections		
Steady state voltage v_f (max)	93.8.1.5.2 ^b	0.6	V
Steady state voltage v_f (min)	93.8.1.5.2 ^b	0.4	V
Linear fit pulse peak (min)	93.8.1.5.2 ^b	$0.71 \times v_f$	V
Pre-cursor equalization	83D.3.1.1	Table 83D-2	-
Post-cursor equalization	83D.3.1.1	Table 83D-3	-
Signal-to-noise-and-distortion ratio (min)	See Sec. 93.8.1.6 ^b of the IEEE specification	27	dB
Output jitter (max)	See Sec. 92.8.3.8 of the IEEE specification		
Even-odd jitter		0.035	UI
Effective bounded uncorrelated jitter, peak-to-peak ^c		0.1	UI
Effective total uncorrelated jitter, peak-to-peak ^{c,d}		0.26	UI

a. The state of the transmit equalizer is controlled by management interface.

b. The values of the parameters are measured as defined in the referenced sub-clause except that the values of N_p and N_w are 5.

c. Effective bounded uncorrelated jitter and effective total uncorrelated jitter are measured as defined in section 92.8.3.8.2 of the IEEE specification except that the range for fitting CDF_{Li} and CDF_{Ri}, (as defined in section 92.8.3.8.2 c), shall be from 10^{-6} to 10^{-4} .

d. Effective total uncorrelated jitter, peak-to-peak is specified to a probability of 10^{-15} .

200GAUI-8 and 400GAUI-16 C2C transmitter characteristics

A 200GAUI-8 or a 400GAUI-16 chip-to-chip transmitter shall meet all specifications in section 83D.3.1 of the IEEE specification (refer to [Table 10](#) for limits corresponding to Table 83D-1) with the following exceptions:

- The signaling rate per lane is $26.5625 \text{ Gbd} \pm 100 \text{ ppm}$.
- The value for the “Linear fit pulse peak (min)” in Table 83D-1 is $0.75 \times \text{vf}$.
- The value for the “Effective total uncorrelated jitter, peak-to-peak” in [Table 10](#) is 0.19 UI.
- The value of the probability in footnote ‘d’ of [Table 10](#) is 10^{-6} .
- The high-pass filter used for the jitter measurements in section 92.8.3.8 of the IEEE specification has a 3 dB frequency of 4 MHz.

If a Clause 45 MDIO is implemented, *Local_eq_cm1* and *Local_eq_c1* for each lane (0 through 7 for 200GAUI-8 and 0 through 15 for 400GAUI-16) and direction (transmit and receive) are accessible through registers 1.500 through 1.531 (see sections 45.2.1.116d through 45.2.1.116g of the IEEE specification).

Jitter and Signaling Rate Measurements TP0a

The Jitter and Signaling Rate Measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 30 Selecting Main Voltage Measurement Tests

Refer to [Table 10](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Jitter and Signaling Rate Measurements TP0a (pattern: PRBS9) tests, see:

- “[Signaling Rate](#)” on page 161
- “[Even-Odd Jitter](#)” on page 162
- “[Effective bounded uncorrelated jitter](#)” on page 163
- “[Effective total uncorrelated jitter](#)” on page 164

Signaling Rate

- Test Overview** The purpose of this test is to verify that the signaling rate is between $26.5625 \pm 100\text{ppm}$ GBd.
- Pass Condition** Refer to the exceptions described in “200GAUI-8 and 400GAUI-16 C2C transmitter characteristics” on page 159.
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Check that the signal is connected, has a bit-rate of 53.125 GHz and that data pattern exists (PRBS9 must be used for this test).
 - 3 In the **Configure** tab, set **Signaling Rate** to 26.5625 Gb/s.
 - 4 Measure minimum and maximum data rate.
 - 5 Report minimum and maximum values.
 - 6 Compare the mean data rate value with $26.5625 \pm 100\text{ppm}$ GBd. Report the resulting value.

Even-Odd Jitter

Test Overview The purpose of this test is to verify that differential signal's Even-Odd Jitter is less than 0.035 UI. All jitter tests are run in a single measurement. However, each test can be run individually.

Pass Conditions Refer to [Table 10](#).

Measurement Algorithm 1 Obtain sample or acquire signal data. Set acquisition depth to five times the length of the PRBS9 pattern.

NOTE

For DSO-Z Series Oscilloscopes, connections must be established between Data+ to Channel 1R and Data- to Channel 3R to measure the defined 12 edges.

For UXR Series Oscilloscopes, connections must be established between Data+ to Channel 1 and Data- to Channel 2 to measure the defined 12 edges.

Irrespective of the Oscilloscope used, the signal must be of PRBS9 pattern.

-
- 2 In the **Configure** tab, set the value for the Signaling Rate as that of the Symbol Rate of the acquired signal.
 - 3 On the Oscilloscope,
 - a Set Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Using PAM4 jitter measurements, at least 10,000 PRBS9 patterns are captured to collect the measurement data of 12 edges.
 - c Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.

NOTE

This measurement can run for a duration of 8-10 minutes.

-
- 4 Compare and report the Even-Odd Jitter value to the respective maximum specification.

Effective bounded uncorrelated jitter

Test Overview The purpose of this test is to verify that differential signal's peak-to-peak effective bounded uncorrelated jitter is less than 0.1 UI. All jitter tests are run in a single measurement. However, each test can be run individually.

Pass Conditions Refer to [Table 10](#).

Measurement Algorithm 1 Obtain sample or acquire signal data. Set acquisition depth to five times the length of the PRBS9 pattern.

NOTE

For DSO-Z Series Oscilloscopes, connections must be established between Data+ to Channel 1R and Data- to Channel 3R to measure the defined 12 edges.

For UXR Series Oscilloscopes, connections must be established between Data+ to Channel 1 and Data- to Channel 2 to measure the defined 12 edges.

Irrespective of the Oscilloscope used, the signal must be of PRBS9 pattern.

-
- 2 In the **Configure** tab, set the value for the Signaling Rate as that of the Symbol Rate of the acquired signal.
 - 3 On the Oscilloscope,
 - a Set Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Using PAM4 jitter measurements, at least 10,000 PRBS9 patterns are captured to collect the measurement data of 12 edges.
 - c Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.

NOTE

This measurement can run for a duration of 8-10 minutes.

-
- 4 Compare and report the effective bounded uncorrelated jitter value to the respective maximum specification.

Effective total uncorrelated jitter

Test Overview The purpose of this test is to verify that differential signal's peak-to-peak effective total uncorrelated jitter is less than 0.19 UI. All jitter tests are run in a single measurement. However, each test can be run individually.

Pass Conditions Refer to [Table 10](#) and the exceptions described in “[200GAUI-8 and 400GAUI-16 C2C transmitter characteristics](#)” on page 159.

Measurement Algorithm

- 1 Obtain sample or acquire signal data. Set acquisition depth to five times the length of the PRBS9 pattern.

NOTE

For DSO-Z Series Oscilloscopes, connections must be established between Data+ to Channel 1R and Data- to Channel 3R to measure the defined 12 edges.

For UXR Series Oscilloscopes, connections must be established between Data+ to Channel 1 and Data- to Channel 2 to measure the defined 12 edges.

Irrespective of the Oscilloscope used, the signal must be of PRBS9 pattern.

- 2 In the **Configure** tab, set the value for the Signaling Rate as that of the Symbol Rate of the acquired signal.
- 3 On the Oscilloscope,
 - a Set Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Using PAM4 jitter measurements, at least 10,000 PRBS9 patterns are captured to collect the measurement data of 12 edges.
 - c Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.

NOTE

This measurement can run for a duration of 8-10 minutes.

- 4 Compare and report the effective total uncorrelated jitter value to the respective maximum specification.

Output Waveform Measurements TP0a

The Output Waveform Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 31 Selecting Jitter and Signaling Rate Measurement Tests

Refer to [Table 10](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Output Waveform Measurements TP0a (pattern: PRBS9) tests, see:

- “Steady State Voltage Vf” on page 166
- “Linear Fit Pulse Peak” on page 167
- “Signal-to-noise-and-distortion ratio” on page 168
- “Pre and Post Equalization Tests” on page 169

Steady State Voltage V_f

Test Overview The purpose of this test is to verify that the Steady State Voltage is between 0.4V and 0.6V.

Pass Condition Refer to [Table 10](#).

- Measurement Algorithm**
- 1 Check that signal is connected and proper data pattern exists (PRBS9 must be used for this test).
 - 2 Set memory depth and sample rate to capture the 511 bits of the PRBS9 pattern.
 - 3 Calculate V_f using the equations in section 85.8.3.3.5. The resulting value is the sum of columns of $p(k)/M$. $N_p = 200$, $D_p = 2$.
 - 4 Compare and report the resulting value in the range between 0.4V and 0.6V.

Linear Fit Pulse Peak

Test Overview The purpose of this test is to verify that the Linear Fit Pulse is greater than ($V_f \times 0.75$).

NOTE

Run the Steady-State Voltage Vf test as a prerequisite to running the Linear Fit Pulse Peak test.

Pass Conditions Refer to [Table 10](#) and the exceptions described in “[200GAUI-8 and 400GAUI-16 C2C transmitter characteristics](#)” on page 159.

Measurement Algorithm

- 1 Check that signal is connected and proper data pattern exists (PRBS9 must be used for this test).
- 2 Set memory depth and sample rate to capture the 511 bits of the PRBS9 pattern.
- 3 Calculate Linear Fit Pulse using the equations in section 85.8.3.3.5. The resulting value is the peak value of $p(k)$. $N_p = 200$, $D_p = 2$.
- 4 Compare and report the resulting value with ($V_f \times 0.75$).

Signal-to-noise-and-distortion ratio

- Test Overview** The purpose of this test is to verify that the Signal-to-noise-and-distortion ratio (SNDR) is greater than 27 dB.
- Pass Condition** Refer to [Table 10](#).
- Measurement Algorithm**
- 1 Calculate SNDR using measurements from Level RMS - PRBS pattern test and error from Linear Fit Pulse Peak test.
 - 2 Compare and report the value of SNDR with 27 dB.

Pre and Post Equalization Tests

Test Overview The purpose of this test is to verify the Pre-cursor and Post-cursor equalization ratios.




Figure 32 Selecting Transmitter Output Waveform Tests

To know about the measurement algorithm for each Pre and Post Equalization Tests, see:

- “Pre-cursor equalization Local_eq_cm1(0)” on page 170
- “Pre-cursor equalization Local_eq_cm1(1)” on page 171
- “Pre-cursor equalization Local_eq_cm1(2)” on page 172
- “Pre-cursor equalization Local_eq_cm1(3)” on page 173
- “Pre-cursor equalization Local_eq_c1(0)” on page 174
- “Post-cursor equalization Local_eq_c1(1)” on page 175
- “Post-cursor equalization Local_eq_c1(2)” on page 176
- “Post-cursor equalization Local_eq_c1(3)” on page 177
- “Post-cursor equalization Local_eq_c1(4)” on page 178
- “Post-cursor equalization Local_eq_c1(5)” on page 179

Pre-cursor equalization Local_eq_cm1(0)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is 0 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 0, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within 0 ± 0.04 .
- Measurement Algorithm**
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 0.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with 0 ± 0.04 .

Pre-cursor equalization Local_eq_cm1(1)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is -0.05 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 1, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.05 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 1.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with -0.05 ± 0.04 .

Pre-cursor equalization Local_eq_cm1(2)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is -0.1 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 2, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.1 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 2.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with -0.1 ± 0.04 .

Pre-cursor equalization Local_eq_cm1(3)

- Test Overview** The purpose of this test is to verify that the Pre-cursor equalization ratio is -0.15 ± 0.04 .
- Pass Condition** When the Pre-cursor equalization with weight Local_eq_cm1 = 3, the ratio defined by $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.15 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Pre-cursor equalization with weight local_eq_cm1 = 3.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate pre-cursor ratio using the equation $C(-1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of pre-cursor ratio with -0.15 ± 0.04 .

Pre-cursor equalization Local_eq_c1(0)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is 0 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 0, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within 0 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 0.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with 0 ± 0.04 .

Post-cursor equalization Local_eq_c1(1)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.05 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 1, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.05 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 1.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.05 ± 0.04 .

Post-cursor equalization Local_eq_c1(2)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.1 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 2, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.1 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 2.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.1 ± 0.04 .

Post-cursor equalization Local_eq_c1(3)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.15 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 3, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.15 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 3.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.15 ± 0.04 .

Post-cursor equalization Local_eq_c1(4)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.2 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 4, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.2 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 4.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.2 ± 0.04 .

Post-cursor equalization Local_eq_c1(5)

- Test Overview** The purpose of this test is to verify that the Post-cursor equalization ratio is -0.25 ± 0.04 .
- Pass Condition** When the Post-cursor equalization with weight Local_eq_c1 = 5, the ratio defined by $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$ must be within -0.25 ± 0.04 .
- Measurement Algorithm** Skip to step 5 if the first four steps have already been measured/calculated in a previous equalization test of the same trial.
- 1 Request Transmitter to be set to "PRESET" condition.
 - 2 Set memory depth to capture one full PRBS9 pattern and scale.
 - 3 Calculate linear fit pulse response at "PRESET" condition.
 - 4 Define matrix Rm using equation (92-4) from IEEE 802.3.
 - 5 Request to change the eq setting to Post-cursor equalization with weight local_eq_c1 = 5.
 - 6 Calculate linear fit pulse response as per section 93.8.1.5.2 of the IEEE Std. 802.3-2015 specification document, with $N_p = 200$, $D_p = 2$.
 - 7 Calculate coefficients using equation (92-5) from IEEE 802.3.
 - 8 Calculate post-cursor ratio using the equation $C(1) / [|C(-1)| + |C(0)| + |C(1)|]$.
 - 9 Compare and report the value of post-cursor ratio with -0.25 ± 0.04 .

Main Voltage Measurements TP0a

The Main Voltage measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 33 Selecting Transmitter Output Voltage Measurement EYE Tests

Refer to [Table 10](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Main Voltage Measurements TP0a (pattern: PRBS9) tests, see:

- “[Differential Peak-to-Peak Output Voltage Test with TX Disabled](#)” on page 181
- “[DC Common Mode Output Voltage Test](#)” on page 182
- “[AC Common Mode Output Voltage Test](#)” on page 183
- “[Differential Peak-to-Peak Output Voltage Test](#)” on page 184

Differential Peak-to-Peak Output Voltage Test with TX Disabled

- Test Overview** The purpose of this test is to verify that when TX is disabled, the peak-to-peak voltage must be less than 30mV.
- Pass Condition** Refer to [Table 10](#).
- Measurement Algorithm**
- 1 Obtain a sample or acquire the signal data.
 - 2 Ensure that TX is disabled on the acquired signal (no valid data transitions).
 - 3 Measure peak-to-peak voltage of the signal.
 - 4 Compare the maximum peak-to-peak voltage with 30mV.

DC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal is between 0V to 1.9V.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 10](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the DC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement to the range from 0V to 1.9 V.

AC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal does not exceed 12mV.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 10](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the AC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement with 12mV.

Differential Peak-to-Peak Output Voltage Test

Test Overview The purpose of this test is to verify that the peak-to-peak voltage of the differential signal on a PRBS9 pattern is less than 1200mV.

Pass Condition Refer to [Table 10](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is connected, has TX enabled and has a PRBS9 pattern.
 - 3 Measure the peak-to-peak voltage of the differential signal on DUT+ and DUT-.
 - 4 Compare the maximum peak-to-peak voltage with 1200mV.

Return Loss ENA/PNA Measurements

The Return Loss ENA/PNA Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope, PNA or ENA and the IEEE802.3 bs/cd Test Application. The Compliance Test Application controls the PNA/ENA to set the test limits and run the tests. You must ensure that the connected PNA/ENA is calibrated.




Figure 34 Selecting Return Loss Measurement Tests

Refer to [Table 10](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Return Loss PNA/ENA Measurements tests, see:

- “[Differential Output Return Loss](#)” on page 186
- “[Common-mode Output Return Loss](#)” on page 187

Differential Output Return Loss

- | | |
|----------------------------------|---|
| Measurement
Algorithm | <ol style="list-style-type: none">1 Ensure that the PNA/ENA is physically connected and calibrated.2 In the Set Up tab of the Compliance Test Application, click Connect PNA or Connect ENA to establish connectivity to the connected equipment.3 Click the Select Tests tab and check the tests to measure the Return Loss Measurements.4 Click Run under the Run tab. The Compliance Test Application automatically calculates the return loss.5 Compare the reported values with the specification to check for compliance. |
|----------------------------------|---|

Common-mode Output Return Loss

- Measurement Algorithm**
- 1 Ensure that the PNA/ENA is physically connected and calibrated.
 - 2 In the **Set Up** tab of the Compliance Test Application, click **Connect PNA** or **Connect ENA** to establish connectivity to the connected equipment.
 - 3 Click the **Select Tests** tab and check the tests to measure the Return Loss Measurements.
 - 4 Click **Run** under the **Run** tab. The Compliance Test Application automatically calculates the return loss.
 - 5 Compare the reported values with the specification to check for compliance.

9 NRZ Host Output Characteristics at TP1a

Main Voltage Measurements TP1a [192](#)

Transition Time Measurements TP1a [198](#)

Signaling Rate and Eye Mask Measurements TP1a [201](#)

Return Loss ENA/PNA Measurements [205](#)

This section provides the Methods of Implementation (MOIs) for the 200GAUI and 400GAUI IEEE NRZ Host Output Characteristics at TP1a as specified in IEEE Std. 802.3-2015 (IEEE standard for Ethernet), Annex 83E.3.1, Table 83E-1 with 120C.3.1. Measurements are made at TP1a.

NOTE

Ensure that the **Signaling Rate** setting in the **Configure** tab of the Compliance Test Application must match the frequency of the acquired input signal.

CAUI-4 C2M host output electrical characteristics

Table 11 CAUI-4 C2C host output characteristics at TP1a

Parameter	Reference	Value	Units
Signaling rate per lane (range)	See Sec. 83E.3.1.1 of the IEEE specification	25.78125 ± 100 ppm	GBd
DC Common-mode voltage (max)	See Sec. 83E.3.1.2 of the IEEE specification	2.8	V
DC Common-mode voltage (min)	See Sec. 83E.3.1.2 of the IEEE specification	-0.3	V
Single-ended output voltage (max)	See Sec. 83E.3.1.2 of the IEEE specification	3.3	V
Single-ended output voltage (min)	See Sec. 83E.3.1.2 of the IEEE specification	-0.4	V
AC common-mode output voltage (max, RMS)	See Sec. 83E.3.1.2 of the IEEE specification	17.5	mV
Differential peak-to-peak output voltage (max) Transmitter disabled Transmitter enabled	See Sec. 83E.3.1.2 of the IEEE specification	35 900	mV mV
Eye width (min)	See Sec. 83E.3.1.6 of the IEEE specification	0.46	UI
Eye height A, differential (min)	See Sec. 83E.3.1.6 of the IEEE specification	95	mV
Differential output return loss (min)	See Sec. 83E.3.1.3 of the IEEE specification	See Equation (83E-2) of the IEEE specification	dB
Common to differential mode conversion return loss (min)	See Sec. 83E.3.1.3 of the IEEE specification	See Equation (83E-3) of the IEEE specification	dB
Transition time (min, 20% to 80%)	See Sec. 83E.3.1.5 of the IEEE specification	10	dB

200GAUI-8 and 400GAUI-16 C2M host output characteristics

A 200GAUI-8 or a 400GAUI-16 chip-to-module host output shall meet all specifications in section 83E.3.1 of the IEEE specification (refer to [Table 11](#) for limits corresponding to Table 83E-1) with the following exceptions:

- The signaling rate per lane is $26.5625 \text{ Gbd} \pm 100 \text{ ppm}$.
- The clock recovery unit corner frequency is 4 MHz.

If a Clause 45 MDIO is implemented, the variable *Recommended_CTLE_value* is accessible in the module for lanes 0 through 7 for 200GAUI-8 and 0 through 15 for 400GAUI-16 through registers 1.400 to 1.415 (see sections 45.2.1.116a and 45.2.1.116b of the IEEE specification).

Main Voltage Measurements TP1a

The Main Voltage measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 35 Selecting Main Voltage Measurement Tests

Refer to [Table 11](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Main Voltage Measurements TP1a (pattern: PRBS9) tests, see:

- “Differential Peak-to-Peak Output Voltage Test with TX Disabled” on page 193
- “Differential Peak-to-Peak Output Voltage Test” on page 194
- “AC Common Mode Output Voltage Test” on page 195
- “DC Common Mode Output Voltage Test” on page 196
- “Single-ended Output Voltage Test” on page 197

Differential Peak-to-Peak Output Voltage Test with TX Disabled

- Test Overview** The purpose of this test is to verify that when TX is disabled, the peak-to-peak voltage must be less than 35mV.
- Pass Condition** Refer to [Table 11](#).
- Measurement Algorithm**
- 1 Obtain a sample or acquire the signal data.
 - 2 Ensure that TX is disabled on the acquired signal (no valid data transitions).
 - 3 Measure peak-to-peak voltage of the signal.
 - 4 Compare the maximum peak-to-peak voltage to 35mV.

Differential Peak-to-Peak Output Voltage Test

Test Overview The purpose of this test is to verify that the peak-to-peak voltage of the differential signal on a PRBS9 pattern is less than 900mV.

Pass Condition Refer to [Table 11](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is connected, has TX enabled and has a PRBS9 pattern.
 - 3 Measure the peak-to-peak voltage of the differential signal on DUT+ and DUT-.
 - 4 Compare the maximum peak-to-peak voltage with 900mV.

AC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal does not exceed 17.5mV.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 11](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the AC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement with 17.5mV.

DC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common mode signal is between -300mV and 2.8V.

NOTE

This measurement can be done only with dual-single ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 11](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the DC common-mode voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement to the range between -300mV and 2.8V.

Single-ended Output Voltage Test

Test Overview The purpose of this test is to verify that the minimum voltage on a single-ended signal is greater than -400mV and that the maximum voltage is less than 3.3V.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 11](#).

**Measurement
Algorithm**

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the minimum and maximum voltage on each single-ended signal.
- 4 Compare the voltage measurements with the range between -400mV and 3.3V.

Transition Time Measurements TP1a

The Transition Time Measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 36 Selecting Transition Time Measurement Tests

Refer to [Table 11](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Transition Time Measurements TP1a (pattern: PRBS9) tests, see:

- “Minimum Output Rise Time (20%-80%)” on page 199
- “Minimum Output Fall Time (20%-80%)” on page 200

Minimum Output Rise Time (20%-80%)

Test Overview The purpose of this test is to verify that the minimum rise fall time is 10ps.

Pass Condition Refer to [Table 11](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is PRBS9.
 - 3 Find pattern 000333 for the rising edge.
 - 4 Measure rise time from 20% to 80% of the signal amplitude.
 - 5 Compare the minimum rise time with 10ps.

Minimum Output Fall Time (20%-80%)

Test Overview The purpose of this test is to verify that the minimum rise and fall times are 10ps.

Pass Condition Refer to [Table 11](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is PRBS9.
 - 3 Find pattern 333000 for the falling edge.
 - 4 Measure fall time from 20% to 80% of the signal amplitude.
 - 5 Compare the minimum rise time with 10ps.

Signaling Rate and Eye Mask Measurements TP1a

The Signaling Rate and Eye Mask Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 37 Selecting Eye Mask Measurement Tests

Refer to [Table 11](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Signaling Rate and Eye Mask Measurements TP1a (pattern: PRBS9) tests, see:

- “[Signaling Rate](#)” on page 202
- “[Eye Height A](#)” on page 203
- “[Eye Width](#)” on page 204

Signaling Rate

Test Overview The purpose of this test is to verify that the signaling rate mean is between $26.5625 \pm 100\text{ppm}$ GBd.

Pass Condition Refer to the exceptions described in “200GAUI-8 and 400GAUI-16 C2M host output characteristics” on page 191.

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Check that the signal is connected, has a bit-rate of 53.125 GHz and that data pattern exists (PRBS9 must be used for this test).
 - 3 In the **Configure** tab, set **Signaling Rate** to 26.5625 Gb/s.
 - 4 Measure minimum, maximum and mean data rate.
 - 5 Report minimum and maximum values.
 - 6 Compare the mean data rate value with $26.5625 \pm 100\text{ppm}$ GBd.
 - 7 Report the resulting value.

Eye Height A

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Eye Height A is greater than 95mV. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 11](#).

Measurement Algorithm

- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
- 2 Obtain sample or acquire signal data.
- 3 Measure the Eye Height A at an **Eye Height/Width Probability** setting of 1E-5.
- 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
- 5 Compare the Eye Height A with 95mV. Report the resulting value.

Eye Width

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Eye Width is greater than 460mUI. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Not applicable as the test result is considered as “Information Only”.

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as ‘User-defined optimal CTLE’.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Eye Width at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Compare the Eye Width with 460mUI. Report the resulting value.

Return Loss ENA/PNA Measurements

The Return Loss ENA/PNA Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope, PNA or ENA and the IEEE802.3 bs/cd Test Application. The Compliance Test Application controls the PNA/ENA to set the test limits and run the tests. You must ensure that the connected PNA/ENA is calibrated.




Figure 38 Selecting Return Loss Measurement Tests

Refer to [Table 11](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Return Loss PNA/ENA Measurements tests, see:

- “[Differential Output Return Loss](#)” on page 206
- “[Common-mode to Differential Output Return Loss](#)” on page 207

Differential Output Return Loss

- | | |
|----------------------------------|---|
| Measurement
Algorithm | <ol style="list-style-type: none">1 Ensure that the PNA/ENA is physically connected and calibrated.2 In the Set Up tab of the Compliance Test Application, click Connect PNA or Connect ENA to establish connectivity to the connected equipment.3 Click the Select Tests tab and check the tests to measure the Return Loss Measurements.4 Click Run under the Run tab. The Compliance Test Application automatically calculates the return loss.5 Compare the reported values with the specification to check for compliance. |
|----------------------------------|---|

Common-mode to Differential Output Return Loss

- Measurement Algorithm**
- 1 Ensure that the PNA/ENA is physically connected and calibrated.
 - 2 In the **Set Up** tab of the Compliance Test Application, click **Connect PNA** or **Connect ENA** to establish connectivity to the connected equipment.
 - 3 Click the **Select Tests** tab and check the tests to measure the Return Loss Measurements.
 - 4 Click **Run** under the **Run** tab. The Compliance Test Application automatically calculates the return loss.
 - 5 Compare the reported values with the specification to check for compliance.

10 NRZ Module Output Characteristics at TP4

Main Voltage Measurements TP4 212
Transition Time Measurements TP4 216
Signaling Rate and Eye Mask Measurements TP4 219
Return Loss ENA/PNA Measurements 227

This section provides the Methods of Implementation (MOIs) for the 200GAUI and 400GAUI IEEE NRZ Transmitter Characteristics at TP4 as specified in IEEE Std. 802.3-2015 (IEEE standard for Ethernet), Annex 83E.3.2, Table 83E-3 with 120C.3.2. Measurements are made at TP4.

NOTE

Ensure that the **Signaling Rate** setting in the **Configure** tab of the **Compliance Test Application** must match the frequency of the acquired input signal.

CAUI-4 module output characteristics

Table 12 CAUI-4 module output characteristics at TP4

Parameter	Reference	Value	Units
Signaling rate per lane (range)	See Sec. 83E.3.1.1 of the IEEE specification	25.78125 ± 100 ppm	GBd
AC common-mode output voltage (max, RMS)	See Sec. 83E.3.1.2 of the IEEE specification	17.5	mV
Differential output voltage (max)	See Sec. 83E.3.1.2 of the IEEE specification	900	mV
Eye-width (min)	See Sec. 83E.3.2.1 of the IEEE specification	0.57	UI
Eye height, differential (min)	See Sec. 83E.3.2.1 of the IEEE specification	228	mV
Vertical Eye Closure (max)	See Sec. 83E.4.2.1 of the IEEE specification	5.5	dB
Differential output return loss (min)	See Sec. 83E.3.1.3 of the IEEE specification	See Equation (83E-2) of the IEEE specification	dB
Common to differential mode conversion return loss (min)	See Sec. 83E.3.1.3 of the IEEE specification	See Equation (83E-3) of the IEEE specification	dB
Transition time (min, 20% to 80%)	See Sec. 83E.3.1.5 of the IEEE specification	12	ps
DC common mode voltage (min) ^a	See Sec. 83E.3.1.2 of the IEEE specification	-350	mV
DC common mode voltage (max) ^a	See Sec. 83E.3.1.2 of the IEEE specification	2850	mV

a. DC common mode voltage is generated by the host. Specification includes effects of ground offset voltage.

200GAUI-8 and 400GAUI-16 C2M module output characteristics

A module output of 200GAUI-8 or a 400GAUI-16 chip-to-module shall meet all specifications in section 83E.3.2 of the IEEE specification (refer to [Table 12](#) for limits corresponding to Table 83E-3) with the following exceptions:

- The signaling rate per lane is $26.5625 \text{ Gbd} \pm 100 \text{ ppm}$.
- The eye height, eye width, and vertical eye closure are as specified in section 109B.3.2.1 of the IEEE specification, for a PHY that includes an RS-FEC sublayer.
- The clock recovery unit corner frequency is 4 MHz.

Main Voltage Measurements TP4

The Main Voltage measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 39 Selecting Main Voltage Measurement Tests

Refer to [Table 12](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Main Voltage Measurements TP4 (pattern: PRBS9) tests, see:

- “[Differential Output Voltage Test](#)” on page 213
- “[AC Common Mode Output Voltage Test](#)” on page 214
- “[DC Common Mode Voltage Test](#)” on page 215

Differential Output Voltage Test

- Test Overview** The purpose of this test is to verify that the peak-to-peak voltage of the differential signal on a PRBS9 pattern is less than 900mV.
- Pass Condition** Refer to [Table 12](#).
- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is connected, has TX enabled and has a PRBS9 pattern.
 - 3 Measure the peak-to-peak voltage of the differential signal of DUT+ and DUT-.
 - 4 Compare the maximum peak-to-peak voltage to 900mV.

AC Common Mode Output Voltage Test

Test Overview The purpose of this test is to verify that the common-mode voltage of the signal does not exceed 17.5mV.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 12](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the peak-to-peak voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement with 17.5mV.

DC Common Mode Voltage Test

Test Overview The purpose of this test is to verify that the common-mode voltage of the signal is between -350mV and 2.85V.

NOTE

This measurement can be done only with dual single-ended connection but not with a differential probing connection.

Pass Condition Refer to [Table 12](#).

Measurement Algorithm

- 1 Obtain sample or acquire signal data.
- 2 Verify that there is a signal and that the connection is dual single-ended.
- 3 Measure the peak-to-peak voltage.
 - If the Test Application is running on the DSO-Z Series Oscilloscope, the **Instrument Setup** is preset to **Real Edge**.
 - If the Test Application is running on the UXR Series Oscilloscope, perform the measurement with the **Instrument Setup** set to **Channels 1 and 2**. Repeat the measurement with the **Instrument Setup** set to **Channels 3 and 4**.
- 4 Compare the voltage measurement to the range between -350mV and 2.85V.

Transition Time Measurements TP4

The Transition Time Measurement procedures described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 40 Selecting Transition Time Measurement Tests

Refer to [Table 12](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Transition Time Measurements TP4 (pattern: PRBS9) tests, see:

- “Minimum Output Rise Time (20%-80%)” on page 217
- “Minimum Output Fall Time (20%-80%)” on page 218

Minimum Output Rise Time (20%-80%)

Test Overview The purpose of this test is to verify that the minimum rise time is 12ps.

Pass Condition Refer to [Table 12](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is PRBS9.
 - 3 Find pattern 000333 for rising edge.
 - 4 Measure rise time from 20% to 80% of the signal amplitude.
 - 5 Compare the minimum rise time with 12ps.

Minimum Output Fall Time (20%-80%)

Test Overview The purpose of this test is to verify that the minimum fall time is 12ps.

Pass Condition Refer to [Table 12](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Verify that the signal is PRBS9.
 - 3 Find pattern 333000 for the falling edge.
 - 4 Measure fall time from 20% to 80% of the signal amplitude.
 - 5 Compare the minimum fall time with 12ps.

Signaling Rate and Eye Mask Measurements TP4

The Signaling Rate and Eye Mask Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope and the IEEE802.3 bs/cd Test Application.




Figure 41 Selecting Eye Mask Measurement Tests

Refer to [Table 12](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Signaling Rate and Eye Mask Measurements TP4 (pattern: PRBS9) tests, see:

- “[Signaling Rate](#)” on page 220
- “[Near-end Eye Height](#)” on page 221
- “[Near-end Eye Width](#)” on page 222
- “[Vertical Eye Closure](#)” on page 223
- “[Far-end Eye Height](#)” on page 224
- “[Far-end Eye Width](#)” on page 225
- “[Far-end ESMW](#)” on page 226

Signaling Rate

Test Overview The purpose of this test is to verify that the signaling rate mean is between $26.5625 \pm 100\text{ppm}$ GBd.

Pass Condition Refer to [Table 12](#).

- Measurement Algorithm**
- 1 Obtain sample or acquire signal data.
 - 2 Check that the signal is connected, has a bit-rate of 53.125 GHz and that data pattern exists (PRBS9 must be used for this test).
 - 3 In the **Configure** tab, set **Signaling Rate** to 26.5625 Gb/s.
 - 4 Measure minimum, maximum and mean data rate.
 - 5 Report minimum and maximum values.
 - 6 Compare the mean data rate value with $26.5625 \pm 100\text{ppm}$ GBd.
 - 7 Report the resulting value.

Near-end Eye Height

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Near-end Eye Height is greater than 228mV. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 12](#).

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Near-end Eye Height at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Compare the Near-end Eye Height with 228mV. Report the resulting value.

Near-end Eye Width

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Near-end Eye Width is greater than 570mUI. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 12](#).

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Near-end Eye Width at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Compare the Near-end Eye Width with 570mUI. Report the resulting value.

Vertical Eye Closure

- Test Overview** The purpose of this test is to verify that the Vertical Eye Closure at EH15 (1E-15) is less than 5.5 dB.
- Pass Conditions** Refer to [Table 12](#).
- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Vertical Eye Closure at an **Eye Height/Width Probability** setting of 1E-15 (EH15).
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Measure and calculate AV as the mean value of logic 1 minus the mean value of logic 0 at the central 5% of the eye.
 - 6 Calculate Vertical Eye Closure (VEC) using the equation:

$$VEC = 20\log(AV/EH15)$$
 - 7 Compare the Vertical Eye Closure with 5.5 dB. Report the resulting value.

Far-end Eye Height

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Far-end Eye Height is greater than 30mV. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 9](#).

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Far-end Eye Height at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Compare the Far-end Eye Height with 30mV. Report the resulting value.

Far-end Eye Width

Test Overview The purpose of this test is to measure the Far-end Eye Width for a defined range of CTLE settings. The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Not applicable as the test result is considered as “Information Only”.

- Measurement Algorithm**
- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as ‘User-defined optimal CTLE’.
 - 2 Obtain sample or acquire signal data.
 - 3 Measure the Far-end Eye Width at an **Eye Height/Width Probability** setting of 1E-5.
 - 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
 - 5 Report the resulting value of Far-end Eye Width.

NOTE

The Far-end Eye Width measurement is considered as an “Information-Only” test and cannot be used for compliance validation.

Far-end ESMW

Test Overview The purpose of this test is to verify that for a defined range of CTLE settings, the Far-end ESMW is greater than 200mUI (that is, 100mUI each for the left and right eye). The CTLE values range from 1dB lower than the user-defined optimal CTLE to 1dB higher than the user-defined optimal CTLE.

Pass Conditions Refer to [Table 9](#).

NOTE

The Far-end ESMW test checks for margins to the left and right of TC_{min} . Therefore, the limit used for measurements in this test is 0.1UI.

Measurement Algorithm

- 1 Manually select the optimal CTLE setting from the **Use Optimized CTLE for Eye Opening** drop-down options in the **Configure** tab. The selected CTLE setting is called as 'User-defined optimal CTLE'.
- 2 Obtain sample or acquire signal data.
- 3 Measure the Far-end ESMW ESMW at an **Eye Height/Width Probability** setting of 1E-5.
- 4 On the Oscilloscope,
 - a set the Clock Recovery to OJTF First Order PLL with Nominal Data Rate (26.5625 Gbps) and Loop Bandwidth to 4 MHz.
 - b Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
- 5 Calculate Far-end ESMW for each given eye (left and right) using the equations:

$$\text{Left} = (\text{Eye Width} / 2) - \text{Eye Skew}$$

$$\text{Right} = (\text{Eye Width} / 2) + \text{Eye Skew}$$

- 6 Compare the Far-end ESMW with 200mUI (that is, 100mUI each for the left and right eye). Report the resulting value.

Return Loss ENA/PNA Measurements

The Return Loss ENA/PNA Measurement procedures that are described in this section are performed using a Keysight Infiniium oscilloscope, PNA or ENA and the IEEE802.3 bs/cd Test Application. The Compliance Test Application controls the PNA/ENA to set the test limits and run the tests. You must ensure that the connected PNA/ENA is calibrated.




Figure 42 Selecting Return Loss Measurement Tests

Refer to [Table 12](#) for information on the pass limits for each test.

To know about the measurement algorithm for each Return Loss PNA/ENA Measurements tests, see:

- [“Differential Output Return Loss”](#) on page 228
- [“Common-mode to Differential Output Return Loss”](#) on page 229

Differential Output Return Loss

- | | |
|----------------------------------|---|
| Measurement
Algorithm | <ol style="list-style-type: none">1 Ensure that the PNA/ENA is physically connected and calibrated.2 In the Set Up tab of the Compliance Test Application, click Connect PNA or Connect ENA to establish connectivity to the connected equipment.3 Click the Select Tests tab and check the tests to measure the Return Loss Measurements.4 Click Run under the Run tab. The Compliance Test Application automatically calculates the return loss.5 Compare the reported values with the specification to check for compliance. |
|----------------------------------|---|

Common-mode to Differential Output Return Loss

- Measurement Algorithm**
- 1 Ensure that the PNA/ENA is physically connected and calibrated.
 - 2 In the **Set Up** tab of the Compliance Test Application, click **Connect PNA** or **Connect ENA** to establish connectivity to the connected equipment.
 - 3 Click the **Select Tests** tab and check the tests to measure the Return Loss Measurements.
 - 4 Click **Run** under the **Run** tab. The Compliance Test Application automatically calculates the return loss.
 - 5 Compare the reported values with the specification to check for compliance.

11 Utilities

Utilities in IEEE Tests [232](#)

This section provides the Methods of Implementation (MOIs) for the Utilities available for each combination of Standard Option and Signal Type to find the optimal CTLE Eye Opening.

NOTE

Ensure that the **Signaling Rate** setting in the **Configure** tab of the Compliance Test Application must match the frequency of the acquired input signal.

Utilities in IEEE Tests

The procedures described in this section to find Optimal CTLE Eye Opening and Far-end CTLE Eye Opening are performed using a Keysight Infiniium oscilloscope and the D9010EBSC IEEE802.3 bs/cd Test Application.




Figure 43 Selecting Utilities under the Select Tests tab

NOTE

The test group **Utilities**, is available for each combination of **Standard Option** and **Signal Type** under the **Set Up** tab.


Find Optimal CTLE Eye Opening

Test Overview The purpose of this test is to loop through CTLE settings to find the optimal CTLE setting for the largest area of the Eye.


NOTE

This test describes the procedure for the option **200GAUI-x and 400GAUI-x, NRZ** signals only. However, you can apply the same procedure for the rest of the combinations as well.

Measurement Algorithm 1 Set the CTLE value to match the value set for the option **Start value for CTLE utility for Eye Opening** in the **Configure** tab.



- 2 Obtain or acquire signal data.
- 3 Set memory depth to capture 1 million UI.
- 4 On the Oscilloscope, Clock Recovery is set to OJTF First Order PLL with Nominal Data Rate and Loop Bandwidth. Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
- 5 Measure Eye Height and Eye Width.
- 6 Calculate area of the center eye using the formula $EH1 \cdot EW1$.
- 7 Repeat the previous steps for each CTLE setting until the CTLE value attains the value set for the option **Stop value for CTLE utility for Eye Opening** in the **Configure** tab.



- 8 Report the CTLE setting with the largest eye area. The Application automatically changes the configured CTLE setting to the optimal value.


Find Optimal Far-end CTLE Eye Opening

Test Overview The purpose of this test is to measure the eye width and height with each CTLE setting and report the optimal setting to use in Eye Width and Eye Height measurements. The optimal value is automatically set in the **Configure** tab after this test has run.


NOTE

The **Find Optimal Far-end CTLE Eye Opening** test, is available only for **200GAUI-x** and **400GAUI-x, PAM4** signals under the **Set Up** tab.

Measurement Algorithm 1 Set the CTLE value to match the value set for the option **Start value for CTLE utility for Far-end Eye Opening** in the **Configure** tab.



- 2 Add Far-end channel tf4.
- 3 Obtain or acquire signal data.
- 4 Set memory depth to capture 1 million UI.
- 5 On the Oscilloscope, Clock Recovery is set to OJTF First Order PLL with Nominal Data Rate and Loop Bandwidth. Set 4th Order Bessel Thompson filter to 33 GHz with 3 dB gain.
- 6 Measure Eye Height and Eye Width.
- 7 Calculate area of the center eye using the formula $EH1 \cdot EW1$.
- 8 Repeat the previous steps for each CTLE setting until the CTLE value attains the value set for the option **Stop value for CTLE utility for Far-end Eye Opening** in the **Configure** tab.



- 9 Report the CTLE setting with the largest eye area. The Application automatically changes the configured CTLE setting to the optimal value.

12 Debug Mode

Debug mode can be selected to make enable the ability to change jitter measurement options. In the **Configure** tab, select the **Debug** radio button. This will add the following options:

- **Rj Bandwidth** – Choose the Rj Filter. Options are Narrow (Pink) or Wide (White). This changes the amount of DC jitter in the Rj measurement.
- **Jitter Pattern Length** – Choose Periodic or Arbitrary. Periodic is used for data patterns that are periodic and repeat through the scope memory. Arbitrary is used for random data patterns or long data patterns (for example, PRBS31) that do not repeat through the scope memory. If Arbitrary is selected, set the ISI filters.
- **ISI Filter Lead** – When using Arbitrary mode for the Jitter Pattern Length, set the Leading ISI filter coefficient. To help select the correct ISI filter, see [Application Note 1574: Choosing the ISI Filter Size for EZJIT Plus Arbitrary Data Jitter Analysis](#) (at www.keysight.com, literature part number 5989-4974EN).
- **ISI Filter Lag** – When using Arbitrary mode for the Jitter Pattern Length, set the Lagging ISI filter coefficient. Again, to help select the correct ISI filter, see [Application Note 1574: Choosing the ISI Filter Size for EZJIT Plus Arbitrary Data Jitter Analysis](#).

Index

A

AC Common Mode Output Voltage Test, [73](#),
[84](#), [130](#), [139](#), [183](#), [195](#), [214](#)
application software, installing, [14](#)
application software, starting, [21](#)
Automation tab, [23](#)

B

bounded uncorrelated jitter, [46](#), [47](#), [48](#),
[49](#), [103](#), [104](#), [105](#), [106](#), [161](#), [162](#),
[163](#), [164](#)

C

calibrating the oscilloscope, [20](#)
CEI VSR Tx TPOa measurements, [157](#)

D

D2.1 Tx TPOa measurements, [41](#), [99](#)
data rate, [46](#), [103](#), [161](#)
DC Common Mode Output Voltage
Test, [72](#), [85](#), [129](#), [140](#), [182](#), [196](#),
[215](#)
Debug Mode, [231](#), [237](#)
Differential Peak-to-Peak Output Voltage
Test, [83](#), [138](#), [194](#), [213](#)
Differential Peak-to-Peak Output Voltage
Test with TX Disabled, [71](#), [82](#), [128](#),
[181](#), [193](#)

E

even-odd jitter, [46](#), [47](#), [48](#), [49](#), [103](#), [104](#),
[105](#), [106](#), [161](#), [162](#), [163](#), [164](#)

I

installation, [9](#), [13](#)
ISI Filter Lag, [237](#)
ISI Filter Lead, [237](#)

J

jitter, [46](#), [47](#), [48](#), [49](#), [103](#), [104](#), [105](#), [106](#),
[161](#), [162](#), [163](#), [164](#)
Jitter Pattern Length, [237](#)

L

license key, installing, [15](#)

M

measurements, preparing, [19](#)
Minimum Output Rise and Fall Time, [88](#),
[89](#), [142](#), [143](#), [199](#), [200](#), [217](#), [218](#)
mouse, [11](#)

O

oscilloscope calibration, [20](#)

R

random jitter, [46](#), [47](#), [48](#), [49](#), [103](#), [104](#),
[105](#), [106](#), [161](#), [162](#), [163](#), [164](#)
Results tab, [23](#)
Rj Bandwidth, [237](#)
Run Tests tab, [23](#)

S

Set Up tab, [23](#)
Single-ended Output Voltage Test, [86](#), [197](#)

