

SCPI Command Reference Volume 3

Agilent Technologies E4428C/38C ESG Signal Generators

This guide applies to the following signal generator models:

E4428C ESG Analog Signal Generator

E4438C ESG Vector Signal Generator

Due to our continuing efforts to improve our products through firmware and hardware revisions, signal generator design and operation may vary from descriptions in this guide. We recommend that you use the latest revision of this guide to ensure you have up-to-date product information. Compare the print date of this guide (see bottom of page) with the latest revision, which can be downloaded from the following website:

<http://www.agilent.com/find/esg>



Agilent Technologies

Manufacturing Part Number: E4400-90594

Printed in USA

October 2007

© Copyright 2001–2007 Agilent Technologies, Inc.

Notice

The material contained in this document is provided “as is”, and is subject to being changed, without notice, in future editions.

Further, to the maximum extent permitted by applicable law, Agilent disclaims all warranties, either express or implied with regard to this manual and to any of the Agilent products to which it pertains, including but not limited to the implied warranties of merchantability and fitness for a particular purpose. Agilent shall not be liable for errors or for incidental or consequential damages in connection with the furnishing, use, or performance of this document or any of the Agilent products to which it pertains. Should Agilent have a written contract with the User and should any of the contract terms conflict with these terms, the contract terms shall control.

SCPI Command Reference, Volume 1

1. SCPI Basics	1
Command Reference Information	2
SCPI Command Listings	2
Key and Data Field Cross Reference	2
Supported Field	2
SCPI Basics	3
Common Terms	3
Command Syntax	4
Command Types	5
Command Tree	6
Command Parameters and Responses	7
Program Messages	12
File Name Variables	13
File Types and Directory Structure	14
MSUS (Mass Storage Unit Specifier) Variable	16
Quote Usage with SCPI Commands	17
Binary, Decimal, Hexadecimal, and Octal Formats	18
2. Basic Function Commands	19
Correction Subsystem ([:SOURce]:CORRection)	20
:FLATness:LOAD	20
:FLATness:PAIR	20
:FLATness:POINts	20
:FLATness:PRESet	21
:FLATness:STORe	21
[:STATe]	21
Digital Modulation Subsystem—E4438C ([:SOURce])	22
:BURSt:SOURce	22
:BURSt:STATe	22
:DM:EXTernal:ALC:BANDwidth BWIDth	22
:DM:EXTernal:HCRest[:STATe]	23
:DM:EXTernal:FILTer	23
:DM:EXTernal:FILTer:AUTO	23
:DM:EXTernal:POLarity	24
:DM:EXTernal:SOURce	24

Contents

:DM:IQADjustment:BBG:QSKew	25
:DM:IQADjustment:EXTernal:COFFset	26
:DM:IQADjustment:EXTernal:DIOFFset	26
:DM:IQADjustment:EXTernal:DQOFFset	27
:DM:IQADjustment:EXTernal:GAIN	27
:DM:IQADjustment:EXTernal:IOFFset	27
:DM:IQADjustment:EXTernal:IQATten	28
:DM:IQADjustment:EXTernal:QOFFset	28
:DM:IQADjustment:GAIN	29
:DM:IQADjustment:IOFFset	29
:DM:IQADjustment:QOFFset	30
:DM:IQADjustment:QSKew	30
:DM:IQADjustment:SKEW	31
:DM:IQADjustment:SKEW:Path	32
:DM:IQADjustment[:STATe]	32
:DM:MODulation:FILTer	32
:DM:MODulation:FILTer:AUTO	33
:DM:MODulation:ATTen	33
:DM:MODulation:ATTen:AUTO	34
:DM:POLarity[:ALL]	34
:DM:SKEW:PATH	35
:DM:SKEW[:STATe]	35
:DM:SOURce	35
:DM:SRATio	36
:DM:STATe	37
Frequency Subsystem ([:SOURce])	38
:FREQuency:CHANnels:BAND	38
:FREQuency:CHANnels:NUMBer	40
:FREQuency:CHANnels[:STATe]	41
:FREQuency:FIXed	41
:FREQuency:MODE	42
:FREQuency:MULTiplier	42
:FREQuency:OFFSet	43
:FREQuency:OFFSet:STATe	43
:FREQuency:REFErence	43
:FREQuency:REFErence:STATe	44
:FREQuency:STARt	44
:FREQuency:STOP	45

:FREQuency:SYNThesis	45
:FREQuency[:CW]	46
:FREQuency[:CW]:STEP[:INCRement]	47
:PHASe:REFerence	47
:PHASe[:ADJust]	47
:ROSCillator:SOURce	47
:ROSCillator:SOURce:AUTO	48
List/Sweep Subsystem ([:SOURce])	49
:LIST:DIRection	50
:LIST:DWELl	50
:LIST:DWELl:POINts	51
:LIST:DWELl:TYPE	51
:LIST:FREQuency	51
:LIST:FREQuency:POINts	52
:LIST:MANual	52
:LIST:MODE	53
:LIST:POWer	53
:LIST:POWer:POINts	53
:LIST:RETRace	54
:LIST:TRIGger:SOURce	54
:LIST:TYPE	55
:LIST:TYPE:LIST:INITialize:FSTep	55
:LIST:TYPE:LIST:INITialize:PRESet	56
:SWEep:DWELl	56
:SWEep:POINts	57
Power Subsystem ([:SOURce]:POWer)	58
:ALC:BANdwidth BWIDth	58
:ALC:BANdwidth	59
:ALC:LEVel	60
:ALC:SEARch	60
:ALC:SEARch:REFerence	61
:ALC:SEARch:SPAN:START	61
:ALC:SEARch:SPAN:STOP:SPAN:STOP	61
:ALC:SEARch:SPAN:TYPE	62
:ALC:SEARch:SPAN[:STATe]	62
:ALC[:STATe]	62
:ALTernte:AMPLitude	63
:ALTernte:MANual	63

Contents

:ALternate:STATe	64
:ALternate:TRIGger[:SOURce].	64
:ATTenuation.	65
:ATTenuation:AUTO	65
:MODE	66
:REFerence	66
:REFerence:STATe	67
:STARt	67
:STOP	68
[:LEVel][:IMMediate]:OFFSet	68
[:LEVel][:IMMediate][:AMPLitude]	69
[:LEVel][:IMMediate][:AMPLitude]:STEP	69
3. System Commands	71
Calibration Subsystem (:CALibration).	72
:DCFM	72
:IQ	72
:IQ:DC	72
:IQ:DEFault	73
:IQ:FULL	73
:IQ:STARt.	74
:IQ:STOP	74
Communication Subsystem (:SYSTem:COMMunicate)	75
:GPIB:ADDRess	75
:GTLocal	75
:LAN:CONFig	75
:LAN:GATEway.	76
:LAN:HOSTname	76
:LAN:IP	76
:LAN:SUBNet	77
:PMETer:ADDRess.	77
:PMETer:CHANnel	77
:PMETer:IDN	78
:PMETer:TIMEout	78
:SERial:BAUD	79
:SERial:ECHO	79
:SERial:RESet.	79
:SERial:TOUT	80

Diagnostic Subsystem (:DIAGnostic[:CPU]:INFORMATION)	81
:BOARDs	81
:CCOut:ATTenuator	81
:CCOut:PON	81
:CCOut:PROTection	81
:DISPlay:OTIME	82
:LIcense:AUXiliary	82
:LIcense:WAVeform	82
:OPTions	83
:OPTions:DETail	83
:OTIME	83
:REVision	83
:SDATe	84
:WLICence[:VALue]	84
Display Subsystem (:DISPlay)	85
:ANNOtation:AMPLitude:UNIT	85
:ANNOtation:CLOCK:DATE:FORMat	85
:ANNOtation:CLOCK[:STATe]	85
:BRIGHtness	86
:CAPTure	86
:CONTRast	86
:INVerse	87
:REMote	87
[:WINDow][:STATe]	87
IEEE 488.2 Common Commands	88
*CLS	88
*ESE	88
*ESE?	88
*ESR?	89
*IDN?	89
*OPC	89
*OPC?	90
*OPT?	90
*PSC	90
*PSC?	90
*RCL	90
*RST	91
*SAV	91

Contents

*SRE	91
*SRE?	92
*STB?	92
*TRG	92
*TST?	92
*WAI	93
Memory Subsystem (:MEMory)	94
:CATalog:BINary	94
:CATalog:BIT	94
:CATalog:CDMa	95
:CATalog:CDMA	95
:CATalog:DMOD	95
:CATalog:DWCDma	96
:CATalog:FCDMa	96
:CATalog:FIR	97
:CATalog:FSK	97
:CATalog:IQ	98
:CATalog:LIST	98
:CATalog:MCDMa	99
:CATalog:MDMod	99
:CATalog:MDWCdma	100
:CATalog:MFCdma	100
:CATalog:MTONe	101
:CATalog:RCDMa	101
:CATalog:SEQ	102
:CATalog:SHApe	102
:CATalog:STATe	103
:CATalog:UFLT	103
:CATalog:UWCDma	104
:CATalog[:ALL]	104
:COPY[:NAME]	105
:DATA	105
:DATA:APPend	106
:DATA:BIT	107
:DATA:FIR	108
:DATA:FSK	109
:DATA:IQ	110
:DATA:PRAM:FILE:BLOCK	112

:DATA:PRAM:FILE:LIST	113
:DATA:PRAM	114
:DATA:PRAM:BLOCK	114
:DATA:PRAM:LIST	114
:DATA:SHAPE	114
:DATA:SHAPE	115
:DATA:UNPRotected	116
:DELeTe:ALL	117
:DELeTe:BINary	118
:DELeTe:BIT	118
:DELeTe:CDMa	118
:DELeTe:CDMA	118
:DELeTe:DMOD	118
:DELeTe:DWCDma	119
:DELeTe:FCDMa	119
:DELeTe:FIR	119
:DELeTe:FSK	119
:DELeTe:IQ	119
:DELeTe:LIST	120
:DELeTe:MCDMa	120
:DELeTe:MDMod	120
:DELeTe:MDWCdma	120
:DELeTe:MFCdma	120
:DELeTe:MTONe	121
:DELeTe:RCDMa	121
:DELeTe:SEQ	121
:DELeTe:SHAPE	121
:DELeTe:STATe	121
:DELeTe:UFLT	122
:DELeTe:UWCDma	122
:DELeTe[:NAME]	122
:FREE[:ALL]	122
:LOAD:LIST	123
:MOVE	123
:STATe:COMMeNt	123
:STORe:LIST	123
Mass Memory Subsystem (:MMEMory)	124
:CATalog	124

Contents

:COPY	124
:DATA	125
:DELeTe:NVWFm	125
:DELeTe:WFM	125
:DELeTe:WFM1	125
:DELeTe[:NAME]	126
:HEADer:CLEar	126
:HEADer:DESCription	126
:LOAD:LIST	127
:MOVE	127
:STORe:LIST	127
Output Subsystem (:OUTPut)	128
:BLANKing:AUTO	128
:BLANKing:STATe	128
:MODulation[:STATe]	129
[:STATe]	129
Route Subsystem (:ROUte:HARDWare:DGENerator)	130
:INPut:BPOLarity	130
:INPut:CPOLarity	130
:INPut:DPOLarity	131
:INPut:SPOLarity	131
:IPOLarity:BGATe	131
:IPOLarity:CLOCK	132
:IPOLarity:DATA	132
:IPOLarity:SSYNc	132
:OPOLarity:CLOCK	133
:OPOLarity:DATA	133
:OPOLarity:SSYNc	134
:OUTPut:CPOLarity	134
:OUTPut:DCS[:STATe]	135
:OUTPut:DPOLarity	135
:OUTPut:SPOLarity	135
Status Subsystem (:STATus)	136
:OPERation:BASeband:CONDition	136
:OPERation:BASeband:ENABle	136
:OPERation:BASeband:NTRansition	137
:OPERation:BASeband:PTRansition	137
:OPERation:BASeband[:EVENT]	138

:OPERation:CONDition	138
:OPERation:ENABle	139
:OPERation:NTRansition	139
:OPERation:PTRansition	140
:OPERation[:EVENT]	140
:PRESet	140
:QUEStionable:BERT:CONDition	141
:QUEStionable:BERT:ENABle	141
:QUEStionable:BERT:NTRansition	142
:QUEStionable:BERT:PTRansition	142
:QUEStionable:BERT[:EVENT]	143
:QUEStionable:CALibration:CONDition	143
:QUEStionable:CALibration:ENABle	143
:QUEStionable:CALibration:NTRansition	144
:QUEStionable:CALibration:PTRansition	144
:QUEStionable:CALibration[:EVENT]	145
:QUEStionable:CONDition	145
:QUEStionable:ENABle	146
:QUEStionable:FREQuency:CONDition	146
:QUEStionable:FREQuency:ENABle	146
:QUEStionable:FREQuency:NTRansition	147
:QUEStionable:FREQuency:PTRansition	147
:QUEStionable:FREQuency[:EVENT]	147
:QUEStionable:MODulation:CONDition	148
:QUEStionable:MODulation:ENABle	148
:QUEStionable:MODulation:NTRansition	149
:QUEStionable:MODulation:PTRansition	149
:QUEStionable:MODulation[:EVENT]	149
:QUEStionable:NTRansition	150
:QUEStionable:POWer:CONDition	150
:QUEStionable:POWer:ENABle	151
:QUEStionable:POWer:NTRansition	151
:QUEStionable:POWer:PTRansition	151
:QUEStionable:POWer[:EVENT]	152
:QUEStionable:PTRansition	152
:QUEStionable[:EVENT]	153
System Subsystem (:SYSTem)	154
:CAPability	154

Contents

:DATE	154
:ERRor[:NEXT]	155
:ERRor:SCPI[:SYNTax]	155
:FILEsystem:SAFEmode	155
:HELP:MODE	156
:IDN	156
:LANGuage	156
:OPT	157
:PON:TYPE	157
:PRESet	158
:PRESet:ALL	158
:PRESet:LANGuage	158
:PRESet:PERSistent	159
:PRESet:PN9	159
:PRESet:TYPE	160
:PRESet[:USER]:SAVE	160
:SECurity:DISPlay	160
:SECurity:ERASeall	161
:SECurity:LEVel	161
:SECurity:LEVel:STATe	162
:SECurity:OVERwrite	163
:SECurity:SANitize	163
:SSAVer:DELay	163
:SSAVer:MODE	164
:SSAVer:STATe	164
:TIME	165
:VERSion	165
Trigger Subsystem	166
:ABORt	166
:INITiate:CONTInuous[:ALL]	166
:INITiate[:IMMediate][:ALL]	167
:TRIGger:OUTPut:POLarity	167
:TRIGger[:SEQuence]:SLOPe	168
:TRIGger[:SEQuence]:SOURce	168
:TRIGger[:SEQuence][:IMMediate]	169
Unit Subsystem (:UNIT)	170
:POWer	170

4. Analog Commands	171
Amplitude Modulation Subsystem ([:SOURce])	172
:AM[1]2.....	172
:AM:INTErnal:FREQuency:STEP[:INCRement]	172
:AM:WIDeband:STATe.....	173
:AM[1]2:EXTErnal[1]2:COUPLing	173
:AM[1]2:INTErnal[1]:FREQuency	174
:AM[1]2:INTErnal[1]:FREQuency:ALTErnatE.....	174
:AM[1]2:INTErnal[1]:FREQuency:ALTErnatE:AMPLitude:PERCent.....	175
:AM[1]2:INTErnal[1]:FUNCTion:SHAPE.....	175
:AM[1]2:INTErnal[1]:SWEep:TIME	175
:AM[1]2:INTErnal[1]:SWEep:TRIGger.....	176
:AM[1]2:SOURce.....	176
:AM[1]2:STATe	177
:AM[1]2[:DEPTh]	177
:AM[1]2[:DEPTh]:TRACk	178
:AM[:DEPTh]:STEP[:INCRement]	178
Frequency Modulation Subsystem ([:SOURce])	179
:FM[1]2.....	179
:FM:INTErnal:FREQuency:STEP[:INCRement]	180
:FM[1]2:EXTErnal[1]2:COUPLing	180
:FM[1]2:INTErnal[1]:FREQuency	181
:FM[1]2:INTErnal[1]:FREQuency:ALTErnatE	181
:FM[1]2:INTErnal[1]:FREQuency:ALTErnatE:AMPLitude:PERCent	182
:FM[1]2:INTErnal[1]:FUNCTion:SHAPE.....	182
:FM[1]2:INTErnal[1]:SWEep:TIME	183
:FM[1]2:INTErnal[1]:SWEep:TRIGger	183
:FM[1]2:SOURce.....	184
:FM[1]2:STATe.....	184
:FM[1]2[:DEViation]	185
:FM[1]2[:DEViation]:TRACk	185
Low Frequency Output Subsystem ([:SOURce]:LFOutput)	186
:AMPLitude.....	186
:FUNCTion[1]:FREQuency	186
:FUNCTion[1]:FREQuency:ALTErnatE	187
:FUNCTion[1]:FREQuency:ALTErnatE:AMPLitude:PERCent.....	187
:FUNCTion[1]:PERiod.....	188
:FUNCTion[1]:PWIDth	188

Contents

:FUNction[1]:SHAPE	189
:FUNction[1]:SWEep:TIME	189
:FUNction[1]:SWEep:TRIGger	189
:SOURce	190
:STATe	190
Phase Modulation Subsystem ([:SOURce])	191
:PM[1]2:.....	191
:PM:INternal:FREQuency:STEP[:INCRement]	192
:PM[1]2:BANdwidth BWIDth	192
:PM[1]2:EXternal[1]:COUPling	193
:PM[1]2:INternal[1]:FREQuency	193
:PM[1]2:INternal[1]:FREQuency:ALtErnate	194
:PM[1]2:INternal[1]:FREQuency:ALtErnate:AMPLitude:PERCent	194
:PM[1]2:INternal[1]:FUNction:SHAPE	195
:PM[1]2:INternal[1]:SWEep:TIME	195
:PM[1]2:INternal[1]:SWEep:TRIGger	195
:PM[1]2:SOURce	196
:PM[1]2:STATe	196
:PM[1]2[:DEViation]	197
:PM[1]2[:DEViation]:TRACk	197
:PM[:DEViation]:STEP[:INCRement]	198
Pulse Modulation Subsystem ([:SOURce]:PULM)	199
:INternal[1]:FREQuency	199
:INternal[1]:FREQuency:STEP	199
:INternal[1]:FUNction:SHAPE	200
:INternal[1]:PERiod	200
:INternal[1]:PERiod:STEP[:INCRement]	200
:INternal[1]:PWIDth	201
:INternal[1]:PWIDth:STEP	201
:SOURce	202
:STATe	202
5. Component Test Digital Commands	203
All Subsystem–Option 001/601 or 002/602 ([:SOURce])	204
:RADio:ALL:OFF	204
AWGN ARB Subsystem–Option 403 ([:SOURce]:RADio:AWGN:ARB)	205
:BWIDth	205
:IQ:EXternal:FILTer	205

:IQ:EXternal:FILTer:AUTO	206
:HEADer:CLear	206
:HEADer:SAVE	206
:IQ:MODulation:ATTen	207
:IQ:MODulation:ATTen:AUTO	207
:IQ:MODulation:FILTer	208
:IQ:MODulation:FILTer:AUTO	208
:MDEStination:AAMPLitude	209
:MDEStination:ALCHold	209
:MDEStination:PULSe	210
:MPOLarity:MARKer1 2 3 4	212
:LENgth	212
:REFeRence:EXTernal:FREQUency	212
:REFeRence[:SOURce]	213
:SCLock:RATE	213
:SEED	214
[:STATE]	214
CDMA ARB Subsystem–Option 401 ([:SOURce]:RADio:CDMA:ARB)	215
:CLIPping:I	215
:CLIPping:POSition	215
:CLIPping:Q	215
:CLIPping:TYPE	216
:CLIPping[:IJQ]	216
:CRATe	216
:IQ:EXTernal:FILTer	217
:IQ:EXTernal:FILTer:AUTO	217
:FILTer	218
:FILTer:ALPHa	219
:FILTer:BBT	219
:FILTer:CHANnel	220
:HEADer:CLear	220
:HEADer:SAVE	220
:IQMap	221
:IQ:MODulation:ATTen	221
:IQ:MODulation:ATTen:AUTO	221
:IQ:MODulation:FILTer	222
:IQ:MODulation:FILTer:AUTO	222
:MDEStination:AAMPLitude	222

Contents

:MDEStination:ALCHold	223
:MDEStination:PULSe	224
:MPOLarity:MARKer1 2 3 4	226
:OSAMple	226
:REFeRence:EXTeRnal:FREQUency	226
:REFeRence[:SOURce]	227
:RETRigger	227
:SCLock:RATE	228
:SETup	228
:SETup:CHANnel	229
:SETup:MCARrier	230
:SETup:MCARrier:STORE	231
:SETup:MCARrier:TABLE	231
:SETup:STORE	232
:TRIGger:TYPE	233
:TRIGger:TYPE:CONTInuous[:TYPE]	234
:TRIGger:TYPE:GATE:ACTive	235
:TRIGger[:SOURce]	235
:TRIGger[:SOURce]:EXTeRnal:DELay	236
:TRIGger[:SOURce]:EXTeRnal:DELay:STATE	237
:TRIGger[:SOURce]:EXTeRnal:SLOPe	237
:TRIGger[:SOURce]:EXTeRnal[:SOURce]	238
:WLENgth	238
[:STATE]	239
CDMA2000 ARB Subsystem–Option 401 ([:SOURce]:RADio:CDMA2000:ARB)	240
:CLIPping:I	240
:CLIPping:POSition	240
:CLIPping:Q	240
:CLIPping:TYPE	241
:CLIPping[:IJQ]	241
:IQ:EXTeRnal:FILTer	241
:IQ:EXTeRnal:FILTer:AUTO	242
:FILTer	242
:FILTer:ALPHa	243
:FILTer:BBT	244
:FILTer:CHANnel	244
:HEADer:CLEar	245
:HEADer:SAVE	245

:IQ:MODulation:ATTen	245
:IQ:MODulation:ATTen:AUTO	246
:IQ:MODulation:FILTer	246
:IQ:MODulation:FILTer:AUTO	246
:IQMap	247
:LINK	247
:LINK:FORWard:SETup	247
:LINK:FORWard:SETup:MCARrier	248
:LINK:FORWard:SETup:MCARrier:STORE	249
:LINK:FORWard:SETup:MCARrier:TABLE	249
:LINK:FORWard:SETup:MCARrier:TABLE:NCARriers	250
:LINK:FORWard:SETup:STORE	251
:LINK:FORWard:SETup:TABLE:APPLY	251
:LINK:FORWard:SETup:TABLE:CHANnel	252
:LINK:FORWard:SETup:TABLE:NCHannels	253
:LINK:FORWard:SETup:TABLE:PADJust	253
:LINK:REVerse:RCONfig	253
:LINK:REVerse:SETup	254
:LINK:REVerse:SETup:STORE	254
:LINK:REVerse:SETup:TABLE:APPLY	255
:LINK:REVerse:SETup:TABLE:CHANnel	255
:LINK:REVerse:SETup:TABLE:NCHannels	256
:LINK:REVerse:SETup:TABLE:PADJust	256
:MDEStination:AAMPLitude	257
:MDEStination:ALCHold	257
:MDEStination:PULSe	258
:MPOLarity:MARKer1 2 3 4	260
:REFerence:EXTernal:FREQuency	260
:REFerence[:SOURce]	260
:RETRigger	261
:REVision	261
:SCLock:RATE	262
:SPReading:RATE	262
:SPReading:TYPE	263
:SPReading:TYPE:MCARrier:SPACing	263
:TRIGger:TYPE	263
:TRIGger:TYPE:CONTinuous[:TYPE]	265
:TRIGger:TYPE:GATE:ACTive	266

Contents

:TRIGger[:SOURce]	266
:TRIGger[:SOURce]:EXTernal:DELay	267
:TRIGger[:SOURce]:EXTernal:DELay:STATe	268
:TRIGger[:SOURce]:EXTernal:SLOPe	268
:TRIGger[:SOURce]:EXTernal[:SOURce]	269
[:STATe]	269
Dmodulation Subsystem–Option 001/601 or 002/602 ([:SOURce]:RADio:DMODulation:ARB)	270
:IQ:EXTernal:FILTer	270
:IQ:EXTernal:FILTer:AUTO	270
:FILTer	271
:FILTer:ALPHa	272
:FILTer:BBT	272
:FILTer:CHANnel	273
:HEADer:CLear	273
:HEADer:SAVE	273
:IQ:MODulation:ATTen	274
:IQ:MODulation:ATTen:AUTO	274
:IQ:MODulation:FILTer	275
:IQ:MODulation:FILTer:AUTO	275
:MDESTination:AAMPLitude	276
:MDESTination:ALCHold	276
:MDESTination:PULSe	277
:MODulation:FSK[:DEViation]	279
:MODulation[:TYPE]	279
:MPOLarity:MARKer1 2 3 4	280
:REFerence:EXTernal:FREQuency	280
:REFerence[:SOURce]	281
:RETRigger	281
:SCLock:RATE	282
:SETup	282
:SETup:MCARrier	283
:SETup:MCARrier:PHASe	283
:SETup:MCARrier:STORE	284
:SETup:MCARrier:TABLE	284
:SETup:MCARrier:TABLE:NCARriers	285
:SETup:STORE	285
:SRATe	286
:TRIGger:TYPE	287

:TRIGger:TYPE:CONTInuous[:TYPE]	288
:TRIGger:TYPE:GATE:ACTive	289
:TRIGger[:SOURce]	290
:TRIGger[:SOURce]:EXTErnal:DELay	291
:TRIGger[:SOURce]:EXTErnal:DELay:STATe	291
:TRIGger[:SOURce]:EXTErnal:SLOPe	292
:TRIGger[:SOURce]:EXTErnal[:SOURce]	292
[:STATe]	293
Dual ARB Subsystem—Option 001/601 or 002/602 ([:SOURce]:RADio:ARB)	294
:CLIPping	294
:GENerate:SINE	294
:HEADer:CLEar	295
:HEADer:RMS	295
:HEADer:SAVE	297
:HCRest[:STATe]	297
:IQ:EXTErnal:FILTer	298
:IQ:EXTErnal:FILTer:AUTO	298
:IQ:MODulation:ATTen	298
:IQ:MODulation:ATTen:AUTO	299
:IQ:MODulation:FILTer	299
:IQ:MODulation:FILTer:AUTO	300
:MARKer:CLEar	300
:MARKer:CLEar:ALL	301
:MARKer:ROtate	302
:MARKer:[SET]	302
:MDESTination:AAMPLitude	305
:MDESTination:ALCHold	305
:MDESTination:PULSe	306
:MPOLarity:MARKer1 2 3 4	308
:NOISe:BFACTOR	308
:NOISe:CBWidth	309
:NOISe:CN	309
:NOISe[:STATe]	310
:REFerence:EXTErnal:FREQUency	310
:REFerence[:SOURce]	311
:RETRigger	311
:RSCALing	312
:SCALing	312

Contents

:SCLock:RATE	313
:SEquence	313
:TRIGger:TYPE	315
:TRIGger:TYPE:CONTInuous[:TYPE]	317
:TRIGger:TYPE:GATE:ACTive	317
:TRIGger:TYPE:SADVance[:TYPE]	318
:TRIGger:TYPE:SADVance[:TYPE]	318
:TRIGger[:SOURce]	320
:TRIGger[:SOURce]:EXTernal:DELay:SAMPLEs	321
:TRIGger[:SOURce]:EXTernal:DELay:STATe OFF ON 1 0	321
:TRIGger[:SOURce]:EXTernal:DELay:STATe	321
:TRIGger[SOURce]:EXTernal:DELay[:TIME]	322
:TRIGger[:SOURce]:EXTernal:SLOPe	322
:TRIGger[:SOURce]:EXTernal[:SOURce]	323
:WAVEform	323
:Waveform:NHEADers	324
[:STATE]	324
Multitone Subsystem—Option 001/601 or 002/602 ([:SOURce]:RADio:MTONE:ARB)	326
Creating a Multitone Waveform	326
:HEADer:CLear	326
:HEADer:SAVE	326
:IQ:EXTernal:FILTer	327
:IQ:EXTernal:FILTer:AUTO	327
:IQ:MODulation:ATTen	328
:IQ:MODulation:ATTen:AUTO	328
:IQ:MODulation:FILTer	329
:IQ:MODulation:FILTer:AUTO	329
:MDESTination:AAMPLitude	329
:MDESTination:ALCHold	330
:MDESTination:PULSe	331
:MPOLarity:MARKer1 2 3 4	333
:REFerence:EXTernal:FREQUency	333
:REFerence[:SOURce]	333
:ROW	334
:RSCALing	335
:SCLock:RATE	335
:SETup	336
:SETup:STORe	336

:SETup:TABLE	336
:SETup:TABLE:FSPacing	337
:SETup:TABLE:NTONes	337
:SETup:TABLE:PHASe:INITialize	338
:SETup:TABLE:PHASe:INITialize:SEED	338
[:STATe]	339
Wideband CDMA ARB Subsystem–Option 400	
([:SOURce]:RADio:WCDMa:TGPP:ARB)	340
:CLIPping:I	340
:CLIPping:POSition	340
:CLIPping:Q	340
:CLIPping:TYPE	341
:CLIPping[:IJQ]	341
:CRATe	342
:FILTer	342
:FILTer:ALPHa	343
:FILTer:BBT	343
:FILTer:CHANnel	344
:HEADer:CLEar	344
:HEADer:SAVE	344
:IQ:EXTernal:FILTer	344
:IQ:EXTernal:FILTer:AUTO	345
:IQMap	345
:IQ:MODulation:ATTen	346
:IQ:MODulation:ATTen:AUTO	346
:IQ:MODulation:FILTer	346
:IQ:MODulation:FILTer:AUTO	347
:LINK	347
:LINK:DOWN:OACP	347
:LINK:DOWN:SETup	348
:LINK:DOWN:SETup:MCARrier	349
:LINK:DOWN:SETup:MCARrier:CLIPping:I	350
:LINK:DOWN:SETup:MCARrier:CLIPping:Q	351
:LINK:DOWN:SETup:MCARrier:CLIPping:TYPE	351
:LINK:DOWN:SETup:MCARrier:CLIPping[:IJQ]	351
:LINK:DOWN:SETup:MCARrier:SCODE:AINCrement	352
:LINK:DOWN:SETup:MCARrier:STORE	352
:LINK:DOWN:SETup:MCARrier:TABLE	353
:LINK:DOWN:SETup:MCARrier:TABLE:NCARriers	355

Contents

:LINK:DOWN:SETup:MCARrier:TOFFset:AINCrement	355
:LINK:DOWN:SETup:STORE	355
:LINK:DOWN:SETup:TABLE:APPLY	356
:LINK:DOWN:SETup:TABLE:CHANnel	356
:LINK:DOWN:SETup:TABLE:NCHannels?	361
:LINK:DOWN:SETup:TABLE:PADJust	361
:LINK:DOWN:TFCI	361
:LINK:UP:OACP	362
:LINK:UP:SCRAMBLE	362
:LINK:UP:SDPDch	362
:LINK:UP:SETup	363
:LINK:UP:SETup:STORE	364
:LINK:UP:SETup:TABLE:APPLY	364
:LINK:UP:SETup:TABLE:CHANnel	364
:LINK:UP:SETup:TABLE:GUNit	366
:LINK:UP:SETup:TABLE:NCHannel	366
:LINK:UP:TFCI	366
:MDEStination:AAMPLitude	367
:MDEStination:ALCHold	367
:MDEStination:PULSe	368
:MPOLarity:MARKer1 2 3 4	370
:REFerence:EXTernal:FREQuency	370
:REFerence[:SOURce]	370
:RETRigger	371
:REVision	371
:SCLock:RATE	372
:TRIGger:TYPE	372
:TRIGger:TYPE:CONTinuous[:TYPE]	374
:TRIGger:TYPE:GATE:ACTive	374
:TRIGger[:SOURce]	375
:TRIGger[:SOURce]:EXTernal:DELay	376
:TRIGger[:SOURce]:EXTernal:DELay:STATe	376
:TRIGger[:SOURce]:EXTernal:SLOPe	377
:TRIGger[:SOURce]:EXTernal[:SOURce]	377
[:STATe]	378

SCPI Command Reference, Volume 2

6. Digital Signal Interface Module Commands	379
Digital Subsystem—Option 003 and 004 ([:SOURCE])	380
:DIGital:CLOCK:CPS 11214	380
:DIGital:CLOCK:PHASe	380
:DIGital:CLOCK:POLarity	381
:DIGital:CLOCK:RATE	382
:DIGital:CLOCK:REFerence:FREQuency	382
:DIGital:CLOCK:SKEW	383
:DIGital:CLOCK:SOURCe	383
:DIGital:DATA:ALIGNment	384
:DIGital:DATA:BORDER	384
:DIGital:DATA:DIRection	385
:DIGital:DATA:IGain	385
:DIGital:DATA:INEGate	386
:DIGital:DATA:IOFFset	386
:DIGital:DATA:IQSWap	387
:DIGital:DATA:NFORmat	387
:DIGital:DATA:POLarity:FRAMe	387
:DIGital:DATA:POLarity:IQ	388
:DIGital:DATA:QGain	388
:DIGital:DATA:QNEGate	389
:DIGital:DATA:QOFFset	390
:DIGital:DATA:ROTation	390
:DIGital:DATA:SCALing	391
:DIGital:DATA:SIZE	391
:DIGital:DATA:STYPe	392
:DIGital:DATA:TYPE	392
:DIGital:DIAGnostic:LOOPback	393
:DIGital:LOGic[:TYPE]	393
:DIGital:PCONfig	394
:DIGital:PRESet:PTHROUGH	395
:DIGital[:STATe]	395
7. Bit Error Rate Test (BERT) Commands	397
Calculate Subsystem—Option UN7 and 300 (:CALCulate:BERT)	398

Contents

:BTS:LOOPback:EDGE:ETCH:F43:COMParator:CRITeria:ERATe	398
:BTS:LOOPback:EDGE:ETCH:F43:COMParator:CRITeria[:SElect]	398
:BTS:LOOPback:EDGE:MCS5:COMParator:CRITeria:ERATe	399
:BTS:LOOPback:EDGE:MCS5:COMParator:CRITeria[:SElect]	399
:BTS:LOOPback:EDGE:MCS9:COMParator:CRITeria:ERATe	399
:BTS:LOOPback:EDGE:MCS9:COMParator:CRITeria[:SElect]	400
:BTS:LOOPback:EDGE:UNCoded:COMParator:CRITeria:ERATe	400
:BTS:LOOPback:EDGE:UNCoded:COMParator:CRITeria[:SElect]	401
:BTS:LOOPback:GSM:CS1:COMParator:CRITeria:ERATe	401
:BTS:LOOPback:GSM:CS1:COMParator:CRITeria[:SElect]	402
:BTS:LOOPback:GSM:CS4:COMParator:CRITeria:ERATe	402
:BTS:LOOPback:GSM:CS4:COMParator:CRITeria[:SElect]	402
:BTS:LOOPback:GSM:MCS1:COMParator:CRITeria:ERATe	403
:BTS:LOOPback:GSM:MCS1:COMParator:CRITeria[:SElect]	403
:BTS:LOOPback:GSM:COMParator:CRITeria:CIB	404
:BTS:LOOPback:GSM:COMParator:CRITeria:CII	404
:BTS:LOOPback:GSM:COMParator:CRITeria:FERasure	404
:BTS:LOOPback:GSM:COMParator:CRITeria[:SElect]	405
[:BASEband]:COMParator:MODE	405
[:BASEband]:COMParator:THReshold	406
[:BASEband]:COMParator[:STATe]	406
[:BASEband]:DISPlay:MODE:	407
[:BASEband]:DISPlay:UPDate:	407
Data Subsystem–Option UN7 and 300 (:DATA)	408
:BERT:BTS:LOOPback:EDGE:ETCH:F43[:DATA]	408
:BERT:BTS:LOOPback:EDGE:MCS5[:DATA]	409
:BERT:BTS:LOOPback:EDGE:MCS9[:DATA]	410
:BERT:BTS:LOOPback:EDGE:UNCoded[:DATA]	410
:BERT:BTS:LOOPback:GSM[:DATA]	410
:BERT:BTS:LOOPback:GSM:CS1[:DATA]	412
:BERT:BTS:LOOPback:GSM:CS4[:DATA]	413
:BERT:BTS:LOOPback:GSM:MCS1[:DATA]	413
:BERT:AUXout	413
[:DATA]	415
Input Subsystem–Option UN7 (:INPut:BERT[: BASEband])	416
:CGATe:DELay:CLOCK	416
:CGATe:DELay:MODE	416
:CGATe:DELay:TIME	417

:CGATe:DELAy[:STATe].	417
:CGATe:POLarity	418
:CGATe[:STATe].	418
:CLOCK:DELAy:RESolution	418
:CLOCK:DELAy:TIME.	419
:CLOCK:DELAy[:STATe].	419
:CLOCK:POLarity	420
:DATA:POLarity	420
:IMPedance	420
:THReshold	421
Measure Subsystem–Option 300 (:MEASure[:SCALar]:BERT:BTS:LOOPback)	422
:EDGE:MCS5[:SENSitivity]	422
:EDGE:MCS9[:SENSitivity]	422
:EDGE:UNCoded[:SENSitivity].	423
:GSM[:SENSitivity]	424
Sense Subsystem–Options UN7 and 300 ([:SOURce]:SENSe:BERT)	425
:BTS:LOOPback:EDGE:ETCH:F43:BLOCK:COUNt	425
:BTS:LOOPback:EDGE:ETCH:F43:CONTAin	425
:BTS:LOOPback:EDGE:ETCH:F43:STOP:CRITeria:EBLOCK	426
:BTS:LOOPback:EDGE:ETCH:F43:STOP:CRITeria[:SElect]	426
:BTS:LOOPback:EDGE:FTRigger:EXTernal:DELAy	427
:BTS:LOOPback:EDGE:FTRigger:EXTernal:POLarity	427
:BTS:LOOPback:EDGE:FTRigger[SElect]	428
:BTS:LOOPback:EDGE:MCS5:BLOCK:COUNt.	428
:BTS:LOOPback:EDGE:MCS5:CONTAin	429
:BTS:LOOPback:EDGE:MCS5:ESENSitivity	429
:BTS:LOOPback:EDGE:MCS5:HAMPLitude	429
:BTS:LOOPback:EDGE:MCS5:LAMPLitude.	430
:BTS:LOOPback:EDGE:MCS5:PAMPLitude	430
:BTS:LOOPback:EDGE:MCS5:SBLock:COUNt	430
:BTS:LOOPback:EDGE:MCS5:SBLock:INITial.	431
:BTS:LOOPback:EDGE:MCS5:STOP:CRITeria:EBLOCK.	431
:BTS:LOOPback:EDGE:MCS5:STOP:CRITeria[:SElect]	431
:BTS:LOOPback:EDGE:MCS9:BLOCK:COUNt.	432
:BTS:LOOPback:EDGE:MCS9:CONTAin	432
:BTS:LOOPback:EDGE:MCS9:ESENSitivity	432
:BTS:LOOPback:EDGE:MCS9:HAMPLitude	433
:BTS:LOOPback:EDGE:MCS9:LAMPLitude.	433

Contents

:BTS:LOOPback:EDGE:MCS9:PAMPlitude	434
:BTS:LOOPback:EDGE:MCS9:SBLock:COUNT	434
:BTS:LOOPback:EDGE:MCS9:SBLock:INITial	434
:BTS:LOOPback:EDGE:MCS9:STOP:CRITeria:EBLock	435
:BTS:LOOPback:EDGE:MCS9:STOP:CRITeria[:SElect]	435
:BTS:LOOPback:EDGE:MEASurement:STOP	435
:BTS:LOOPback:EDGE:MEASurement:TSLot	436
:BTS:LOOPback:EDGE:MEASurement[:MODE]	436
:BTS:LOOPback:EDGE:SINVert	437
:BTS:LOOPback:EDGE:SYNC:AGain	437
:BTS:LOOPback:EDGE:SYNC:RF	437
:BTS:LOOPback:EDGE:SYNC[:SOURce]	438
:BTS:LOOPback:EDGE:TRIGger[:SOURce]	438
:BTS:LOOPback:EDGE:ULINK:OFFSet	439
:BTS:LOOPback:EDGE:UNCoded:BIT:COUNT	439
:BTS:LOOPback:EDGE:UNCoded:ESENSitivity	439
:BTS:LOOPback:EDGE:UNCoded:HAMPLitude	440
:BTS:LOOPback:EDGE:UNCoded:LAMPLitude	440
:BTS:LOOPback:EDGE:UNCoded:PAMPLitude	441
:BTS:LOOPback:EDGE:UNCoded:SBIT:COUNT	441
:BTS:LOOPback:EDGE:UNCoded:SBIT:INITial	441
:BTS:LOOPback:EDGE:UNCoded:STOP:CRITeria:EBIT	442
:BTS:LOOPback:EDGE:UNCoded:STOP:CRITeria[:SElect]	442
:BTS:LOOPback:EDGE[:STATe]	442
:BTS:LOOPback:GSM:CS1:BLOCK:COUNT	443
:BTS:LOOPback:GSM:CS1:CONTain	443
:BTS:LOOPback:GSM:CS1:STOP:CRITeria:EBLock	444
:BTS:LOOPback:GSM:CS1:STOP:CRITeria[:SElect]	444
:BTS:LOOPback:GSM:CS4:BLOCK:COUNT	444
:BTS:LOOPback:GSM:CS4:CONTain	445
:BTS:LOOPback:GSM:CS4:STOP:CRITeria:EBLock	445
:BTS:LOOPback:GSM:CS4:STOP:CRITeria[:SElect]	446
:BTS:LOOPback:GSM:ESENSitivity	446
:BTS:LOOPback:GSM:FRAME:CIB	446
:BTS:LOOPback:GSM:FRAME:CII	446
:BTS:LOOPback:GSM:FRAME:COUNT	447
:BTS:LOOPback:GSM:HAMPLitude	447
:BTS:LOOPback:GSM:LAMPLitude	447

:BTS:LOOPback:GSM:MCS1:BLOCK:COUNT	448
:BTS:LOOPback:GSM:MCS1:CONTain	448
:BTS:LOOPback:GSM:MCS1:STOP:CRITeria:EBLock	448
:BTS:LOOPback:GSM:MCS1:STOP:CRITeria[:SElect]	449
:BTS:LOOPback:GSM:MEASurement:STOP	449
:BTS:LOOPback:GSM:MEASurement:TSLot	449
:BTS:LOOPback:GSM:MEASurement[:MODE]	450
:BTS:LOOPback:GSM:PAMplitude	450
:BTS:LOOPback:GSM:SFRame:COUNT	450
:BTS:LOOPback:GSM:SFRame:INITial	451
:BTS:LOOPback:GSM:SINVert	451
:BTS:LOOPback:GSM:STOP:CRITeria:CIB	451
:BTS:LOOPback:GSM:STOP:CRITeria:CII	452
:BTS:LOOPback:GSM:STOP:CRITeria:FERasure	452
:BTS:LOOPback:GSM:STOP:CRITeria[:SElect]	452
:BTS:LOOPback:GSM:SYNC:RF	453
:BTS:LOOPback:GSM:SYNC[:SOURce]	454
:BTS:LOOPback:GSM:TRIGger[:SOURce]	454
:BTS:LOOPback:GSM:ULINK:OFFSet	455
:BTS:LOOPback:GSM[:STATe]	455
[:BAsEband]:PRBS:FUNCTion:SPIGnore:DATA	455
[:BAsEband]:PRBS:FUNCTion:SPIGnore[:STATe]	456
[:BAsEband]:PRBS[:DATA]	456
[:BAsEband]:RSYNc:THReshold	456
[:BAsEband]:RSYNc[:STATe]	457
[:BAsEband]:STATe	457
[:BAsEband]:STOP:CRITeria:EBIT	457
[:BAsEband]:STOP:CRITeria[:SElect]	458
[:BAsEband]:TBITs	458
[:BAsEband]:TRIGger:BDELay	459
[:BAsEband]:TRIGger:BDELay:STATe	459
[:BAsEband]:TRIGger:COUNT	459
[:BAsEband]:TRIGger:POLarity	460
[:BAsEband]:TRIGger[:SOURce]	460
8. Receiver Test Digital Commands	461
All Subsystem–Option 001/601 or 002/602 ([:SOURce])	462
:RADio:ALL:OFF	462

Contents

AWGN Real-Time Subsystem–Option 403 ([:SOURCE]:RADio:AWGN:RT)	463
:BWIDth	463
[:STATe]	463
Bluetooth Subsystem–Option 406 ([:SOURCE]:RADio:BLUEtooth:ARB)	464
:AMADdr	464
:BDADdr.	464
:BURSt[:STATe].	464
:CGDelay	465
:DATA	465
:IQ:EXTernal:FILTer.	466
:IQ:EXTernal:FILTer:AUTO	466
:HEADer:CLEar	467
:HEADer:SAVE	467
:IMPairments	467
:IMPairments:AWGN	468
:IMPairments:AWGN:CNR	468
:IMPairments:AWGN:NSEed.	469
:IMPairments:DDEViation	469
:IMPairments:FDType	470
:IMPairments:FOFFset	470
:IMPairments:MINdex.	471
:IMPairments:STERror.	472
:IQ:MODulation:ATTen	472
:IQ:MODulation:ATTen:AUTO	473
:IQ:MODulation:FILTer	473
:IQ:MODulation:FILTer:AUTO	474
:MDEStination:AAMPplitude	474
:MDEStination:ALCHold.	474
:MDEStination:PULSe	475
:MPOLarity:MARKer1 2 3 4	475
:MPOLarity:MARKer1.	475
:MPOLarity:MARKer2.	476
:MPOLarity:MARKer3.	476
:MPOLarity:MARKer4.	476
:PACKet	476
:REFernce:EXTernal:FREQuency	477
:REFerence[:SOURCE]	477
:RSYMBOLs	478

:SCLock:RATE	478
[:STATe]	478
CDMA2000 BBG Subsystem–Option 401 ([:SOURce]:RADio:CDMA2000[:BBG])	479
:LMODe	479
[:FORWard]:BBCLock	480
[:FORWard]:CHIPrate	480
[:FORWard]:ESDelay	480
[:FORWard]:FILTer	481
[:FORWard]:FILTer:ALPHa	482
[:FORWard]:FILTer:BBT	482
[:FORWard]:FILTer:CHANnel	482
[:FORWard]:LCSTate	483
[:FORWard]:FFCH:DATA	483
[:FORWard]:FFCH:DATA:FIX4	484
[:FORWard]:FFCH:EBNO	484
[:FORWard]:FFCH:FOFFset	485
[:FORWard]:FFCH:LCMask	485
[:FORWard]:FFCH:LCMask:ESN	486
[:FORWard]:FFCH:LCMask:HEADer	486
[:FORWard]:FFCH:POWER	486
[:FORWard]:FFCH:PRAMp	487
[:FORWard]:FFCH:PRTIME	487
[:FORWard]:FFCH:QOF	487
[:FORWard]:FFCH:RATE	488
[:FORWard]:FFCH:RCONfig	488
[:FORWard]:FFCH:WALSh	488
[:FORWard]:FFCH[:STATe]	489
[:FORWard]:FPCH:DATA	489
[:FORWard]:FPCH:EBNO	489
[:FORWard]:FPCH:LCMask	490
[:FORWard]:FPCH:LCMask:F1	490
[:FORWard]:FPCH:LCMask:F2	490
[:FORWard]:FPCH:LCMask:F3	491
[:FORWard]:FPCH:MESSAge	491
[:FORWard]:FPCH:POWER	491
[:FORWard]:FPCH:RATE	492
[:FORWard]:FPCH:WALSh	492
[:FORWard]:FPCH[:STATe]	492

Contents

[:FORWARD]:FPICH:ECNO	493
[:FORWARD]:FPICH:POWER	493
[:FORWARD]:FPICH[:STATE].	494
[:FORWARD]:FSCH[1]2:DATA.	494
[:FORWARD]:FSCH[1]2:DATA:FIX4.	494
[:FORWARD]:FSCH[1]2:EBNO	495
[:FORWARD]:FSCH[1]2:FOFFset.	495
[:FORWARD]:FSCH[1]2:LCMask.	496
[:FORWARD]:FSCH[1]2:LCMask:ESN	496
[:FORWARD]:FSCH[1]2:LCMask:HEADer	496
[:FORWARD]:FSCH[1]2:POWER.	497
[:FORWARD]:FSCH[1]2:QOF.	497
[:FORWARD]:FSCH[1]2:RATE.	497
[:FORWARD]:FSCH[1]2:RCONfig	498
[:FORWARD]:FSCH[1]2:TCODE	498
[:FORWARD]:FSCH[1]2:WALSh	498
[:FORWARD]:FSCH[1]2[:STATE]	499
[:FORWARD]:FSYNc:CFRequency	499
[:FORWARD]:FSYNc:DAYLt.	499
[:FORWARD]:FSYNc:EBNO	500
[:FORWARD]:FSYNc:ECFRequency	500
[:FORWARD]:FSYNc:LPSec	501
[:FORWARD]:FSYNc:LTMoff	501
[:FORWARD]:FSYNc:MPREv	501
[:FORWARD]:FSYNc:MSGType	502
[:FORWARD]:FSYNc:NID	502
[:FORWARD]:FSYNc:POWER.	502
[:FORWARD]:FSYNc:PRATe	503
[:FORWARD]:FSYNc:PREV	503
[:FORWARD]:FSYNc:RESErved	503
[:FORWARD]:FSYNc:SID	504
[:FORWARD]:FSYNc:STYPE.	504
[:FORWARD]:FSYNc:SYSTime.	504
[:FORWARD]:FSYNc:WALSh	505
[:FORWARD]:FSYNc[:STATE].	505
[:FORWARD]:NOISE:CN	505
[:FORWARD]:NOISE[:STATE]	506
[:FORWARD]:OCNS:EBNO	506

[:FORWard]:OCNS:POWer	507
[:FORWard]:OCNS:WALSh	508
[:FORWard]:OCNS[:STATe]	508
[:FORWard]:PADJust	508
[:FORWard]:POLarity	509
[:FORWard]:QPCH:CCI	509
[:FORWard]:QPCH:EBNO	509
[:FORWard]:QPCH:PI	510
[:FORWard]:QPCH:POWer	510
[:FORWard]:QPCH:RATE	511
[:FORWard]:QPCH:WALSh	511
[:FORWard]:QPCH[:STATe]	511
[:FORWard]:SRATe	511
:PNOFfset	512
:REVerse:BBCLock	512
:REVerse:CHIPrate	513
:REVerse:ESDdelay	513
:REVerse:FILTer	514
:REVerse:FILTer:ALPHa	515
:REVerse:FILTer:BBT	515
:REVerse:FILTer:CHANnel	516
:REVerse:LCMask	516
:REVerse:LCSTate	516
:REVerse:PADJust	517
:REVerse:POLarity[:ALL]	517
:REVerse:NOISe:CN	517
:REVerse:NOISe[:STATe]	518
:REVerse:RC12:ACCess:RACH:DATA	518
:REVerse:RC12:ACCess:RACH:DATA:FIX4	519
:REVerse:RC12:ACCess:RACH:EBNO	519
:REVerse:RC12:ACCess:RACH:FLENgth	520
:REVerse:RC12:ACCess:RACH:FOFFset	520
:REVerse:RC12:ACCess:RACH:POWer	520
:REVerse:RC12:ACCess:RACH:RCONfig	521
:REVerse:RC12:ACCess:RACH:RATE	521
:REVerse:RC12:ACCess:RACH[:STATe]	521
:REVerse:RC12:TRAFfic:RSCH:DATA	522
:REVerse:RC12:TRAFfic:RSCH:DATA:FIX4	522

Contents

:REVerse:RC12:TRAFfic:RSCH:FLENgth	522
:REVerse:RC12:TRAFfic:RSCH:FOFFset	523
:REVerse:RC12:TRAFfic:RSCH:POWer	523
:REVerse:RC12:TRAFfic:RSCH:RATE	523
:REVerse:RC12:TRAFfic:RSCH:RCONfig	524
:REVerse:RC12:TRAFfic:RSCH[:STATe]	524
:REVerse:RC34:CCONtrol:RCCCh:DATA	524
:REVerse:RC34:CCONtrol:RCCCh:DATA:FIX4	525
:REVerse:RC34:CCONtrol:RCCCh:EBNO	525
:REVerse:RC34:CCONtrol:RCCCh:FLENgth	526
:REVerse:RC34:CCONtrol:RCCCh:FOFFset	526
:REVerse:RC34:CCONtrol:RCCCh:POWer	526
:REVerse:RC34:CCONtrol:RCCCh:RCONfig	527
:REVerse:RC34:CCONtrol:RCCCh:RATE	527
:REVerse:RC34:CCONtrol:RCCCh:WALSh	527
:REVerse:RC34:CCONtrol:RCCCh[:STATe]	528
:REVerse:RC34:CCONtrol:RPICH:ECNO	528
:REVerse:RC34:CCONtrol:RPICH:GRATe	529
:REVerse:RC34:CCONtrol:RPICH:POWer	529
:REVerse:RC34:CCONtrol:RPICH:WALSh	529
:REVerse:RC34:CCONtrol:RPICH[:STATe]	530
:REVerse:RC34:EACCess:REACH:DATA	530
:REVerse:RC34:EACCess:REACH:DATA:FIX4	530
:REVerse:RC34:EACCess:REACH:EBNO	531
:REVerse:RC34:EACCess:REACH:FOFFset	531
:REVerse:RC34:EACCess:REACH:POWer	532
:REVerse:RC34:EACCess:REACH:RCONfig	532
:REVerse:RC34:EACCess:REACH:RATE	532
:REVerse:RC34:EACCess:REACH:WALSh	533
:REVerse:RC34:EACCess:REACH[:STATe]	533
:REVerse:RC34:EACCess:RPICH:ECNO	533
:REVerse:RC34:EACCess:RPICH:GRATe	534
:REVerse:RC34:EACCess:RPICH:POWer	534
:REVerse:RC34:EACCess:RPICH:WALSh	534
:REVerse:RC34:EACCess:RPICH[:STATe]	535
:REVerse:RC34:TRAFfic:RDCCh:DATA	535
:REVerse:RC34:TRAFfic:RDCCh:DATA:FIX4	535
:REVerse:RC34:TRAFfic:RDCCh:EBNO	536

:REVerse:RC34:TRAFfic:RDCCh:FLENgth	536
:REVerse:RC34:TRAFfic:RDCCh:FOFFset.	536
:REVerse:RC34:TRAFfic:RDCCh:POWer	537
:REVerse:RC34:TRAFfic:RDCCh:RATE.	537
:REVerse:RC34:TRAFfic:RDDCh:RCONfig.	537
:REVerse:RC34:TRAFfic:RDCCh:WALSh	538
:REVerse:RC34:TRAFfic:RDCCh[:STATe]	538
:REVerse:RC34:TRAFfic:RFCH:DATA.	538
:REVerse:RC34:TRAFfic:RFCH:DATA:FIX4	539
:REVerse:RC34:TRAFfic:RFCH:EBNO	539
:REVerse:RC34:TRAFfic:RFCH:FLENgth	540
:REVerse:RC34:TRAFfic:RFCH:FOFFset	540
:REVerse:RC34:TRAFfic:RFCH:POWer	540
:REVerse:RC34:TRAFfic:RFCH:RCONfig	541
:REVerse:RC34:TRAFfic:RFCH:RATE.	541
:REVerse:RC34:TRAFfic:RFCH:WALSh	541
:REVerse:RC34:TRAFfic:RFCH[:STATe]	541
:REVerse:RC34:TRAFfic:RSCH[1]2:DATA	542
:REVerse:RC34:TRAFfic:RSCH[1]2:DATA:FIX4	542
:REVerse:RC34:TRAFfic:RSCH[1]2:DATA:EBNO	542
:REVerse:RC34:TRAFfic:RSCH[1]2:FLENgth.	543
:REVerse:RC34:TRAFfic:RSCH[1]2:FOFFset	543
:REVerse:RC34:TRAFfic:RSCH[1]2:POWer	544
:REVerse:RC34:TRAFfic:RSCH[1]2:RCONfig	544
:REVerse:RC34:TRAFfic:RSCH[1]2:RATE	544
:REVerse:RC34:TRAFfic:RSCH[1]2:TCODE.	545
:REVerse:RC34:TRAFfic:RSCH[1]2:WALSh.	545
:REVerse:RC34:TRAFfic:RSCH[1]2[:STATe]	545
:REVerse:REFeRence:EXTeRnal:FREQuency	546
:REVerse:REFeRence[:SOURce].	546
:REVerse:TADVance	546
:REVerse:TEDGE	547
:REVerse:SRATE	547
[:STATe]	547
Custom Subsystem–Option 001/601or 002/602 ([:SOURce]:RADio:CUSTom).	548
:ALPha	548
:ASK	548
:BBCLock	549

Contents

:BBT	549
:BRATe	550
:BURSt:SHAPe:FALL:DELay	552
:BURSt:SHAPe:FALL:TIME	552
:BURSt:SHAPe:FDELay	553
:BURSt:SHAPe:FTIME	553
:BURSt:SHAPe:RDELay	554
:BURSt:SHAPe:RISE:DELay	554
:BURSt:SHAPe:RISE:TIME	555
:BURSt:SHAPe:RTIME	556
:BURSt:SHAPe[:TYPE]	556
:CHANnel	557
:DATA	557
:DATA:FIX4	558
:DATA:PRAM.	558
:DENCode.	559
:EDATa:DELay	559
:EDCLock	559
:EREFerence	560
:EREFerence:VALue.	560
:FILTer	561
:IQ:SCALE	562
:MODulation:FSK[:DEViation]	563
:MODulation:MSK[:PHASe]	563
:MODulation:UFSK	564
:MODulation:UIQ	564
:MODulation[:TYPE]	564
:POLarity[:ALL]	565
:SRATe	565
:STANdard:SELEct	567
:TRIGger:TYPE	567
:TRIGger:TYPE:CONTInuous[:TYPE]	568
:TRIGger:TYPE:GATE:ACTive.	568
:TRIGger[:SOURce]	569
:TRIGger[:SOURce]:EXTErnal:DELay	570
:TRIGger[:SOURce]:EXTErnal:DELay:STATe	570
:TRIGger[:SOURce]:EXTErnal:SLOPe	571
:TRIGger[:SOURce]:EXTErnal[:SOURce]	571

[:STATe]	572
DECT Subsystem–Option 402 ([:SOURce]:RADio:DECT)	573
:ALPha	573
:BBCLock	573
:BBT	574
:BRATe	574
:BURSt:PN9	575
:BURSt:SHAPe:FALL:DELay	576
:BURSt:SHAPe:FALL:TIME	576
:BURSt:SHAPe:FDELay	577
:BURSt:SHAPe:FTIME	577
:BURSt:SHAPe:RDELay	578
:BURSt:SHAPe:RISE:DELay	578
:BURSt:SHAPe:RISE:TIME	579
:BURSt:SHAPe:RTIME	580
:BURSt:SHAPe[:TYPE]	580
:BURSt[:STATe]	581
:CHANnel	581
:DATA	582
:DATA:FIX4	582
:DATA:PRAM	583
:DEFault	583
:EDATa:DELay	583
:EDCLock	584
:EREFerence	584
:EREFerence:VALue	585
:FILTer	585
:IQ:SCALE	586
:MODulation:FSK[:DEViation]	586
:MODulation:MSK[:PHASe]	587
:MODulation:UFSK	587
:MODulation:UIQ	588
:MODulation[:TYPE]	588
:POLarity[:ALL]	588
:PPart:SLOT0 [1] 2 3 4 5 6 7 8 9 10 11[:TYPE]	589
:PPart:SLOT0 [1] 2 3 4 5 6 7 8 9 10 11:CUSTom	589
:PPart:SLOT0 [1] 2 3 4 5 6 7 8 9 10 11:CUSTom:FIX4	590
:PPart:SLOT0 [1] 2 3 4 5 6 7 8 9 10 11:LCAPacity:A	590

Contents

:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity:P	591
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity:S	591
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity[:B]	592
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity[:B]:FIX4	592
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity:POWer	593
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:STATe	593
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic:A	593
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic:P	594
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic:S	594
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic[:B]	595
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic[:B]:FIX4	595
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity:A	596
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity:P	596
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity:A	596
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity[:B]	597
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity[:B]:FIX4	597
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRaffic:A	598
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRaffic:P	598
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRaffic:S	598
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRaffic[:B]	599
:PPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRaffic[:B]:FIX4	599
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11[:TYPE]	600
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:CUSTom	600
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:CUSTom:FIX4	601
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:DUMM2:A	601
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:DUMM2:P	602
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:DUMM2:S	602
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:DUMM[1]:A	602
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:DUMM[1]:P	603
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:DUMM[1]:S	603
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity:A	603
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity:P	604
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity:S	604
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity[:B]	604
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity[:B]:FIX4	605
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:LCAPacity:POWer	605
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:STATe	606
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic:A	606

:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic:P	606
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic:S	607
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic[:B]	607
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:TRAFfic[:B]:FIX4	608
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity:A	608
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity:P	608
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity:S	609
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity[:B]	609
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZLCapacity[:B]:FIX4	610
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRAffic:A	610
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRAffic:P	610
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRAffic:S	611
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRAffic[:B]	611
:RFPart:SLOT0[1] 2 3 4 5 6 7 8 9 10 11:ZTRAffic[:B]:FIX4	612
:SECondary:RECall	612
:SECondary:SAVE	612
:SECondary:TRIGger[:SOURce]	613
:SECondary[:STATe]	613
:SOUT	614
:SOUT:OFFSet	614
:SOUT:SLOT	615
:SRATe	615
:TRIGger:TYPE	616
:TRIGger:TYPE:CONTInuous[:TYPE]	617
:TRIGger:TYPE:GATE:ACTive	618
:TRIGger[:SOURce]	618
:TRIGger[:SOURce]:EXTernal:DELay	619
:TRIGger[:SOURce]:EXTernal:SLOPe	620
:TRIGger[:SOURce]:EXTernal[:SOURce]	620
:TRIGger[:SOURce]:EXTernal:DELay:STATe	621
[:STATe]	621
EDGE Subsystem–Option 402 ([:SOURce]:RADio:EDGE)	622
:ALPHa	622
:BBCLock	622
:BBT	623
:BURSt:SHAPe:FALL:DELay	623
:BURSt:SHAPe:FDELay	624
:BURSt:SHAPe:FALL:TIME	625

Contents

:BURSt:SHAPE:FTIME	625
:BURSt:SHAPE:RDElay	626
:BURSt:SHAPE:RISE:DElay	627
:BURSt:SHAPE:RISE:TIME	627
:BURSt:SHAPE:RTIME	628
:BURSt:SHAPE[:TYPE]	629
:BURSt[:STATE]	629
:CHANnel	630
:DATA	630
:DATA:PRAM.	631
:DATA:FIX4	631
:DEFault	632
:EDATa:DElay	632
:EDCLock	632
:EREFerence	633
:EREFerence:VALue	633
:FILTer	634
:IQ:SCALE	635
:MODulation:FSK[:DEViation]	635
:MODulation:MSK[:PHASe]	636
:MODulation:UFSK	636
:MODulation:UIQ	636
:MODulation[:TYPE]	637
:POLarity[:ALL]	637
:SECondary:RECall	638
:SECondary:SAVE	638
:SECondary:TRIGger[:SOURce]	638
:SECondary[:STATE]	639
:SLOT0[1 2 3 4 5 6 7]:CUSTom	639
:SLOT0[1 2 3 4 5 6 7]:CUSTom:FIX4	640
:SLOT0[1 2 3 4 5 6 7]:CUSTom:GUARd	640
:SLOT0[1 2 3 4 5 6 7]:GMSK:ENCRyption	641
:SLOT0[1 2 3 4 5 6 7]:GMSK:ENCRyption:CS1:DATA	642
:SLOT0[1 2 3 4 5 6 7]:GMSK:ENCRyption:CS4:DATA	643
:SLOT0[1 2 3 4 5 6 7]:GMSK:ENCRyption:DLINK:MCS1:DATA	643
:SLOT0[1 2 3 4 5 6 7]:GMSK:ENCRyption:FIX4	643
:SLOT0[1 2 3 4 5 6 7]:GMSK:ENCRyption:TCH:FS:DATA	644
:SLOT0[1 2 3 4 5 6 7]:GMSK:ENCRyption:ULINK:MCS1:DATA	644

:SLOT0[1]2 3 4 5 6 7:GMSK:STeal	645
:SLOT0[1]2 3 4 5 6 7:GMSK:TSEquence	645
:SLOT0[1]2 3 4 5 6 7:MULTIslot	646
:SLOT0[1]2 3 4 5 6 7:NORMAl:ENCryption	646
:SLOT0:NORMAl:ENCryption:BCH:BCC	648
:SLOT0:NORMAl:ENCryption:BCH:CELLid	649
:SLOT0:NORMAl:ENCryption:BCH:LAC	649
:SLOT0:NORMAl:ENCryption:BCH:MCC	649
:SLOT0:NORMAl:ENCryption:BCH:MNC	650
:SLOT0:NORMAl:ENCryption:BCH:PLMN	650
:SLOT0[1]2 3 4 5 6 7:NORMAl:ENCryption:DLINK:MCS5:DATA	650
:SLOT0[1]2 3 4 5 6 7:NORMAl:ENCryption:DLINK:MCS9:DATA	651
:SLOT0[1]2 3 4 5 6 7:NORMAl:ENCryption:ETCH:F43:DATA	651
:SLOT0[1]2 3 4 5 6 7:NORMAl:ENCryption:FIX4	652
:SLOT0[1]2 3 4 5 6 7:NORMAl:ENCryption:ULINK:MCS5:DATA	652
:SLOT0[1]2 3 4 5 6 7:NORMAl:ENCryption:ULINK:MCS9:DATA	653
:SLOT0[1]2 3 4 5 6 7:NORMAl:ENCryption:UNCodeD	653
:SLOT0[1]2 3 4 5 6 7:NORMAl:GUARd	654
:SLOT0[1]2 3 4 5 6 7:NORMAl:T1	654
:SLOT0[1]2 3 4 5 6 7:NORMAl:T2	655
:SLOT0[1]2 3 4 5 6 7:NORMAl:TSEquence	655
:SLOT0[1]2 3 4 5 6 7:LCAPacity:POWer	655
:SLOT0[1]2 3 4 5 6 7:STAtE	656
:SLOT0[1]2 3 4 5 6 7[:TYPE]	656
:SOUT:	657
:SOUT:OFFSet	657
:SOUT:SLOT	658
:SRATe	658
:TRIGger:TYPE	660
:TRIGger:TYPE:CONTInuous[:TYPE]	660
:TRIGger:TYPE:GATE:ACTive	661
:TRIGger[:SOURce]	662
:TRIGger[:SOURce]:EXTeRnal:DELay	663
:TRIGger[:SOURce]:EXTeRnal:DELay:FINe	663
:TRIGger[:SOURce]:EXTeRnal:DELay:STAtE	664
:TRIGger[:SOURce]:EXTeRnal:SLOPe	664
:TRIGger[:SOURce]:EXTeRnal[:SOURce]	665
[:STAtE]	665

SCPI Command Reference, Volume 3

9. Receiver Test Digital Commands (continued)	667
3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURce]:RADio:WCDMa:HSPA[:BBG]) ..	668
File Overview	668
Managing ESG Setting Conflicts and Error Messages	670
:DLINK:APPLy	671
:DLINK:AWGN:CN	671
:DLINK:AWGN[:STATe]	672
:DLINK:BBCLock[:SOURce]	672
:DLINK:CPICH:CCODE	672
:DLINK:CPICH:POWer	673
:DLINK:CPICH[:STATe]	673
:DLINK:DPCH:CCODE	673
:DLINK:DPCH:DATA	674
:DLINK:DPCH:DATA:FIX4	674
:DLINK:DPCH:DCH[1 2 3 4 5 6]:BSIZe	675
:DLINK:DPCH:DCH[1 2 3 4 5 6]:CRC	675
:DLINK:DPCH:DCH[1 2 3 4 5 6]:CTYPe	676
:DLINK:DPCH:DCH[1 2 3 4 5 6]:DATA	676
:DLINK:DPCH:DCH[1 2 3 4 5 6]:DATA:FIX4	677
:DLINK:DPCH:DCH[1 2 3 4 5 6]:NBLocks	677
:DLINK:DPCH:DCH[1 2 3 4 5 6]:RMATtribute	678
:DLINK:DPCH:DCH[1 2 3 4 5 6]:TTI	678
:DLINK:DPCH:DCH[1 2 3 4 5 6]:STATe]	678
:DLINK:DPCH:POWer	679
:DLINK:DPCH:SFORmat	679
:DLINK:DPCH:SSCoffset	680
:DLINK:DPCH:TFCI	680
:DLINK:DPCH:TOFFset	681
:DLINK:DPCH:TPC:NSTeps	681
:DLINK:DPCH:TPC:PATern	681
:DLINK:DPCH:TRPosition	682
:DLINK:DPCH[:STATe]	682
:DLINK:EAGCh:AGSCOpe	683
:DLINK:EAGCh:AGValue	683
:DLINK:EAGCh:CCODE	684
:DLINK:EAGCh:ERNTI	685

:DLINK:EAGCh:Power	685
:DLINK:EAGCh[:STATe]	685
:DLINK:EHICH:CCODE	686
:DLINK:EHICH:INDicator	686
:DLINK:EHICH:POWer	687
:DLINK:EHICH:SSINdex	687
:DLINK:EHICH:TOFFset	687
:DLINK:EHICH[:STATe]	688
:DLINK:ERGCh:CCODE	688
:DLINK:ERGCh:POWer	688
:DLINK:ERGCh:RGValue	689
:DLINK:ERGCh:SSINdex	689
:DLINK:ERGCh:TOFFset	690
:DLINK:ERGCh[:STATe]	690
:DLINK:FILTer	690
:DLINK:FILTer:ALPHa	691
:DLINK:FILTer:BBT	692
:DLINK:FILTer:CHANnel	692
:DLINK:HSBurst	692
:DLINK:HSDPa:AMC:CQIMapping:UECategory	693
:DLINK:HSDPa:AMC:CPATtern	693
:DLINK:HSDPa:FCONtrol	694
:DLINK:HSDPa:HARQ:APATtern	695
:DLINK:HSDPa:HARQ:MNHTrans	696
:DLINK:HSDPa:HARQ:RVSequence[1] 2 3 4 5 6 7 8	696
:DLINK:HSDPa[1] 2 3 4:BSINfo	697
:DLINK:HSDPa[1] 2 3 4:HSPDSch:COFFset	697
:DLINK:HSDPa[1] 2 3 4:HSPDSch:DATA	698
:DLINK:HSDPa[1] 2 3 4:HSPDSch:DATA:FIX4	698
:DLINK:HSDPa:HSPDSch:DSCH:DATA	699
:DLINK:HSDPa:HSPDSch:DSCH:DATA:FIX4	699
:DLINK:HSDPa:HSPDSch:DSCH:IRBSize	700
:DLINK:HSDPa:HSPDSch:NCODE	700
:DLINK:HSDPa[1] 2 3 4:HSPDSch:POWer	700
:DLINK:HSDPa[1] 2 3 4:HSPDSch:SFORmat	701
:DLINK:HSDPa[1] 2 3 4:HSPDSch[:STATe]	701
:DLINK:HSDPa[1] 2 3 4:HSSCch:CCODE	702
:DLINK:HSDPa[1] 2 3 4:HSSCch:DATA	702

Contents

:DLINK:HSDPa[1]2 3 4:HSSCch:DATA:FIX4	703
:DLINK:HSDPa[1]2 3 4:HSSCch:POWer	703
:DLINK:HSDPa[1]2 3 4:ITTI	704
:DLINK:HSDPa[1]2 3 4:ITTI:PATtern	704
:DLINK:HSDPa:NHPRocess	705
:DLINK:HSDPa[1]2 3 4:RVParameter	705
:DLINK:HSDPa[1]2 3 4:UEID	706
:DLINK:HSDPa[1]2 3 4[:STATe]	706
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:CCODE	707
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:DATA	707
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:MODulation	708
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:POWer	708
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:SF	708
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:SSCoffset	709
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:TOFFset	709
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16[:STATe]	710
:DLINK:PCCPch:BCH:DATA	710
:DLINK:PCCPch:BCH:DATA:FIX4	710
:DLINK:PCCPch:CCODE	711
:DLINK:PCCPch:POWer	711
:DLINK:PCCPch[:STATe]	712
:DLINK:PICH:CCODE	712
:DLINK:PICH:DATA	712
:DLINK:PICH:DATA:FIX4	713
:DLINK:PICH:POWer	713
:DLINK:PICH[:STATe]	714
:DLINK:POLarity	714
:DLINK:PSCH:POWer	714
:DLINK:PSCH[:STATe]	715
:DLINK:SCRamblecode	715
:DLINK:SSCH:POWer	715
:DLINK:SSCH[:STATe]	716
:DLINK:TXDiversity	716
:LINK	716
:ULINK:APPLY	717
:ULINK:AWGN:CN	717
:ULINK:AWGN[:STATe]	718
:ULINK:BBReference:EXternal:MRATE	718

:ULINK:BBReference:EXTeRnal[:SOURce]	718
:ULINK:CRATe	719
:ULINK:DPCCh:CCODE	719
:ULINK:DPCCh:DATA	719
:ULINK:DPCCh:DATA:FIX4	720
:ULINK:DPCCh:FBI:PATTeRn	720
:ULINK:DPCCh:FBI:PATTeRn:FIX	720
:ULINK:DPCCh:POWEr	721
:ULINK:DPCCh:SFORmat	721
:ULINK:DPCCh:TFCI	722
:ULINK:DPCCh:TPC:NSTePs	722
:ULINK:DPCCh:TPC:PATTeRn	722
:ULINK:DPCCh[:STATe]	723
:ULINK:DPDCh:DATA	724
:ULINK:DPDCh:DATA:FIX4	724
:ULINK:DPDCh:DCH[1]23456:BSIZE	725
:ULINK:DPDCh:DCH[1]23456:CRC	725
:ULINK:DPDCh:DCH[1]23456:CTYPE	726
:ULINK:DPDCh:DCH[1]23456:DATA	726
:ULINK:DPDCh:DCH[1]23456:DATA:FIX4	727
:ULINK:DPDCh:DCH[1]23456:NBLocks	727
:ULINK:DPDCh:DCH[1]23456:RMATtribute	728
:ULINK:DPDCh:DCH[1]23456:TTI	728
:ULINK:DPDCh:DCH23456[:STATe]	728
:ULINK:DPDCh:POWEr	729
:ULINK:DPDCh:SFORmat	729
:ULINK:DPDCh[:STATe]	730
:ULINK:FCLock:INTerval	730
:ULINK:FCLock:POLarity	730
:ULINK:FILTeR	731
:ULINK:FILTeR:ALPHa	731
:ULINK:FILTeR:BBT	732
:ULINK:FILTeR:CHANnel	732
:ULINK:FOFFset	733
:ULINK:HCONfig	733
:ULINK:HSDPcch:APATteRn	733
:ULINK:HSDPcch:APOWEr	734

Contents

:ULINK:HSDPcch:CCODE	734
:ULINK:HSDPcch:CPATtern	735
:ULINK:HSDPcch:CPOWer	735
:ULINK:HSDPcch:NPOWer	736
:ULINK:HSDPcch:SFDelay	736
:ULINK:HSDPcch[:STATe]	736
:ULINK:HSUPa:EDPCch:DATA:FIX4	737
:ULINK:HSUPa:EDPCch:POWer	737
:ULINK:HSUPa:EDPCch[:STATe]	738
:ULINK:HSUPa:EDPDch:DATA	738
:ULINK:HSUPa:EDPDch:DATA:FIX4	738
:ULINK:HSUPa:EDPDch:EDCH:DATA	739
:ULINK:HSUPa:EDPDch:EDCH:DATA:FIX4	739
:ULINK:HSUPa:EDPDch:MCCodes	740
:ULINK:HSUPa:EDPDch:PLNMax	741
:ULINK:HSUPa:EDPDch:POWer	741
:ULINK:HSUPa:EDPDch:SNPHchs	741
:ULINK:HSUPa:EDPDch[:STATe]	742
:ULINK:HSUPa:ETABle	742
:ULINK:HSUPa:ETFCi	743
:ULINK:HSUPa:HARQ:APATtern	743
:ULINK:HSUPa:HARQ:APATtern[:EXTErnal]:DELay	744
:ULINK:HSUPa:HARQ:APATtern[:EXTErnal]:INPut	744
:ULINK:HSUPa:HARQ:APATtern[:EXTErnal]:POLarity	745
:ULINK:HSUPa:HARQ:MNRTrans	745
:ULINK:HSUPa:HARQ[:MODE]	745
:ULINK:HSUPa:HARQ:HBIT	746
:ULINK:HSUPa:HPRocess	746
:ULINK:HSUPa:RSN	747
:ULINK:HSUPa:RVINdex	747
:ULINK:HSUPa:TFC:EPATtern[:EXTErnal]:DELay	747
:ULINK:HSUPa:TFC:EPATtern[:EXTErnal]:INPut	748
:ULINK:HSUPa:TFC:EPATtern[:EXTErnal]:POLarity	748
:ULINK:HSUPa:TFC:EPATtern	749
:ULINK:HSUPa:TFC[:ALT]:EDPCch:POWer	749
:ULINK:HSUPa:TFC[:ALT]:EDPDch:EDCH:DATA	750
:ULINK:HSUPa:TFC[:ALT]:EDPDch:EDCH:DATA:FIX4	750

:ULINK:HSUPa:TFC[:ALT]:EDPDch:POWer	751
:ULINK:HSUPa:TFC[:ALT]EDPDch:SNPHchs	751
:ULINK:HSUPa:TFC[:ALT]:ETABle	752
:ULINK:HSUPa:TFC[:ALT]:ETFCI	752
:ULINK:HSUPa:TTI	752
:ULINK:HSUPa[:STATe]	753
:ULINK:NMDPch	753
:ULINK:POLarity	753
:ULINK:SCRamblecode	754
:ULINK:SDELaY	754
:ULINK:SFNRst:POLarity	754
:ULINK:SYNC:MODE	755
:ULINK:SYNC[:SOURce]	755
:ULINK:TGAP:PSI[1]:CFN	756
:ULINK:TGAP:PSI[1]:D	756
:ULINK:TGAP:PSI[1]:L1	756
:ULINK:TGAP:PSI[1]:L2	757
:ULINK:TGAP:PSI[1]:PL1	757
:ULINK:TGAP:PSI[1]:PRC	757
:ULINK:TGAP:PSI[1]:PS	757
:ULINK:TGAP:PSI[1]:SN	758
:ULINK:TOFFset	758
:ULINK:TPControl:PATtern	759
:ULINK:TPControl:PATtern[:EXternal]:INPut	759
:ULINK:TPControl:PATtern[:EXternal]:POLarity	759
:ULINK:TPControl:POWer:INITial	760
:ULINK:TPControl:POWer:MAXimum	760
:ULINK:TPControl:POWer:MINimum	761
:ULINK:TPControl:POWer:STEP	761
:ULINK:TPControl[:STATe]	762
[:STATe]	762
Real Time GPS Subsystem–Option 409	
([:SOURce]:RADio[1] 2 3 4:GPS)	763
:DATA	763
:DMODE	763
:DSHift	764
:FILTer	764
:FILTer:ALPHa	765
:FILTer:BBT	766

Contents

:FILTer:CHANnel	766
:IQPHase	767
:PCODE	767
:RCODE	767
:REFClk	768
:REFFreq.	768
:SATid	769
[:STATe]	769
Real Time MSGPS Subsystem–Option 409	
([:SOURce]:RADio[1 2 3 4:MSGPs)	770
:IQPHase	770
:PMODE	770
:REFClk	771
:REFFreq.	771
:REStart	771
:SCENario	772
:SCENario:SATellites	772
:SCENario:STATus	772
[:STATe]	772
GSM Subsystem–Option 402 ([:SOURce]:RADio:GSM).	773
:ALPha	773
:BBCLock	773
:BBT	774
:BRATe	774
:BURSt:PN9	775
:BURSt:SHAPe:FALL:DELay	776
:BURSt:SHAPe:FALL:TIME	776
:BURSt:SHAPe:FDELay	777
:BURSt:SHAPe:FTIME	778
:BURSt:SHAPe:RDELay	778
:BURSt:SHAPe:RISE:DELay	779
:BURSt:SHAPe:RISE:TIME	780
:BURSt:SHAPe:RTIME	780
:BURSt:SHAPe[:TYPE].	781
:BURSt[:STATe].	781
:CHANnel	782
:DATA	782
:DATA:PRAM.	783
:DATA:FIX4	783

:DEFault	783
:DENCode	784
EDATa:DELay	784
:EDCLock	784
:EREFerence	785
:EREFerence:VALue	785
:FILTer	786
:IQ:SCALE	787
:MODulation:FSK[:DEViation]	787
:MODulation:MSK[:PHASe]	788
:MODulation:UFSK	788
:MODulation:UIQ	788
:MODulation[:TYPE]	789
:POLarity[:ALL]	789
:SECondary:RECall	790
:SECondary:SAVE	790
:SECondary:TRIGger[:SOURce]	790
:SECondary[:STATE]	791
:SLOT0[1]2 3 4 5 6 7:ACCess:ENCRyption	791
:SLOT0[1]2 3 4 5 6 7:ACCess:ENCRyption:FIX4	791
:SLOT0[1]2 3 4 5 6 7:ACCess:ETAil	792
:SLOT0[1]2 3 4 5 6 7:ACCess:SSEQuence	792
:SLOT0[1]2 3 4 5 6 7:ACCess:CUSTom	792
:SLOT0[1]2 3 4 5 6 7:CUSTom:FIX4	793
:SLOT0[1]2 3 4 5 6 7:DUMMy:TSEQuence	793
:SLOT0[1]2 3 4 5 6 7:MULTIslot	793
SLOT0[1]2 3 4 5 6 7:NORMal:ENCRyption	794
:SLOT0:NORMal:ENCRyption:BCH1:BCC	796
:SLOT0:NORMal:ENCRyption:BCH1:CELLid	796
:SLOT0:NORMal:ENCRyption:BCH1:LAC	796
:SLOT0:NORMal:ENCRyption:BCH1:MCC	797
:SLOT0:NORMal:ENCRyption:BCH1:MNC	797
:SLOT0:NORMal:ENCRyption:BCH1:PLMN	797
:SLOT0[1]2 3 4 5 6 7:NORMal:ENCRyption:CS1:DATA	798
:SLOT0[1]2 3 4 5 6 7:NORMal:ENCRyption:CS4:DATA	798
:SLOT0[1]2 3 4 5 6 7:NORMal:ENCRyption:DLINK:MCS1:DATA	798
:SLOT0[1]2 3 4 5 6 7:NORMal:ENCRyption:FIX4	799
:SLOT0[1]2 3 4 5 6 7:NORMal:ENCRyption:TCH:FS:DATA	799

Contents

:SLOT0[1]234567:NORMAl:ENCRyption:ULINK:MCS1:DATA	799
:SLOT0[1]234567:NORMAl:STeal	800
:SLOT0[1]234567:NORMAl:TSEquence.	800
:SLOT0[1]234567:POWer	801
:SLOT0[1]234567:STATe	801
:SLOT0[1]234567:SYNC:ENCRyption	801
:SLOT0[1]234567:SYNC:ENCRyption:FIX4	802
:SLOT0[1]234567:SYNC:TSEquence.	802
:SLOT0[1]234567[:TYPE]	802
:SOUT.	803
:SOUT:OFFSet	803
:SOUT:SLOT	804
:SRATe	804
:TRIGger:EXTernal:DELay	805
:TRIGger:TYPE	806
:TRIGger:TYPE:CONTInuous[:TYPE]	806
:TRIGger:TYPE:GATE:ACTive.	807
:TRIGger[:SOURce].	807
:TRIGger[:SOURce]:EXTernal:DELay	808
:TRIGger[:SOURce]:EXTernal:DELay:FINE	809
:TRIGger[:SOURce]:EXTernal:DELay:STATe	809
:TRIGger[:SOURce]:EXTernal:SLOPe	809
:TRIGger[:SOURce]:EXTernal[:SOURce]	810
[:STATe]	811
HSDPA over W-CDMA Subsystem–Option 418 ([:SOURce]:RADio:WCDMa:HSDPa[:BBG])	812
File Overview	812
Managing ESG Setting Conflicts and Error Messages.	814
:DLINK:APPLy	814
:DLINK:AWGN:CN	815
:DLINK:AWGN[:STATe]	815
:DLINK:BBCLock[:SOURce]	815
:DLINK:CPICH:CCODE	816
:DLINK:CPICH:POWer.	816
:DLINK:CPICH[:STATe].	816
:DLINK:DPCH:CCODE	816
:DLINK:DPCH:DATA.	817
:DLINK:DPCH:DATA:FIX4.	817
:DLINK:DPCH:DCH[1]23456:BSIZe	818

:DLINK:DPCH:DCH[1]23456:CTYPe	818
:DLINK:DPCH:DCH[1]23456:CRc	819
:DLINK:DPCH:DCH[1]23456:DATA	819
:DLINK:DPCH:DCH[1]23456:DATA:FIX4	819
:DLINK:DPCH:DCH[1]23456:NBLocks	820
:DLINK:DPCH:DCH[1]23456:RMATtribute	820
:DLINK:DPCH:DCH[1]23456:TTI	821
:DLINK:DPCH:DCH23456[:STATe]	821
:DLINK:DPCH:POWer	821
:DLINK:DPCH:SFORmat	822
:DLINK:DPCH:SSCOffset	822
:DLINK:DPCH:TFCI	823
:DLINK:DPCH:TOFFset	823
:DLINK:DPCH:TPC:NSTeps	824
:DLINK:DPCH:TPC:PATtern	824
:DLINK:DPCH:TRPosition	825
:DLINK:DPCH[:STATe]	825
:DLINK:FILTer	825
:DLINK:FILTer:ALPHa	826
:DLINK:FILTer:BBT	826
:DLINK:FILTer:CHANnel	827
:DLINK:HSBurst	827
:DLINK:HSDPa:AMC:CQIMapping:UECategory	828
:DLINK:HSDPa:AMC:CPATtern	828
:DLINK:HSDPa:FCONtrol	829
:DLINK:HSDPa:HARQ:APATtern	830
:DLINK:HSDPa:HARQ:MNHTrans	830
:DLINK:HSDPa:HARQ:RVSequence[1]2345678	831
:DLINK:HSDPa[1]234:BSINfo	832
:DLINK:HSDPa[1]234:HSPDSch:COFFset	832
:DLINK:HSDPa[1]234:HSPDSch:DATA	832
:DLINK:HSDPa[1]234:HSPDSch:DATA:FIX4	833
:DLINK:HSDPa:HSPDSch:DSCH:DATA	833
:DLINK:HSDPa:HSPDSch:DSCH:DATA:FIX4	834
:DLINK:HSDPa:HSPDSch:DSCH:IRBSize	834
:DLINK:HSDPa:HSPDSch:NCODe	835
:DLINK:HSDPa[1]234:HSPDSch:POWer	835
:DLINK:HSDPa[1]234:HSPDSch:SFORmat	836

Contents

:DLINK:HSDPa[1]2 3 4:HSPDsch[:STATe]	836
:DLINK:HSDPa[1]2 3 4:HSSCch:CCODE	837
:DLINK:HSDPa[1]2 3 4:HSSCch:DATA	837
:DLINK:HSDPa[1]2 3 4:HSSCch:DATA:FIX4	838
:DLINK:HSDPa[1]2 3 4:HSSCch:POWer	838
:DLINK:HSDPa[1]2 3 4:ITTI	839
:DLINK:HSDPa[1]2 3 4:ITTI:PATtern	839
:DLINK:HSDPa:NHPRocess	840
:DLINK:HSDPa[1]2 3 4:RVParameter	840
:DLINK:HSDPa[1]2 3 4:UEID	841
:DLINK:HSDPa[1]2 3 4[:STATe]	841
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:CCODE	842
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:DATA	842
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:POWer	843
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:SSCOffset	843
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:TOFFset	844
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16[:STATe]	844
:DLINK:PCCPch:BCH:DATA	844
:DLINK:PCCPch:BCH:DATA:FIX4	845
:DLINK:PCCPch:CCODE	845
:DLINK:PCCPch:POWer	846
:DLINK:PCCPch[:STATe]	846
:DLINK:PICH:CCODE	846
:DLINK:PICH:DATA	847
:DLINK:PICH:DATA:FIX4	847
:DLINK:PICH:POWer	848
:DLINK:PICH[:STATe]	848
:DLINK:POLarity	848
:DLINK:PSCH:POWer	849
:DLINK:PSCH[:STATe]	849
:DLINK:SCRamblecode	849
:DLINK:SSCH:POWer	850
:DLINK:SSCH[:STATe]	850
:DLINK:TXDiversity	850
:LINK	851
:ULINK:APPLy	851
:ULINK:AWGN:CN	851
:ULINK:AWGN[:STATe]	852

:ULINK:BBReference:EXTeRnal:MRATe	852
:ULINK:BBReference[:SOURce]	852
:ULINK:DPCCh:CCODE	853
:ULINK:DPCCh:DATA	853
:ULINK:DPCCh:DATA:FIX4	854
:ULINK:DPCCh:FBI:PATTeRn	854
:ULINK:DPCCh:FBI:PATTeRn:FIX	855
:ULINK:DPCCh:POWEr	855
:ULINK:DPCCh:SFORmat	856
:ULINK:DPCCh[:STATe]	856
:ULINK:DPCCh:TFCI	856
:ULINK:DPCCh:TPC:NSTePs	857
:ULINK:DPCCh:TPC:PATTeRn	857
:ULINK:DPDCh:CCODE	858
:ULINK:DPDCh:DATA	858
:ULINK:DPDCh:DATA:FIX4	858
:ULINK:DPDCh:DCH[1] 2 3 4 5 6:BSIZE	859
:ULINK:DPDCh:DCH[1] 2 3 4 5 6:CRC	859
:ULINK:DPDCh:DCH[1] 2 3 4 5 6:CTYPE	859
:ULINK:DPDCh:DCH[1] 2 3 4 5 6:DATA	860
:ULINK:DPDCh:DCH[1] 2 3 4 5 6:DATA:FIX4	860
:ULINK:DPDCh:DCH[1] 2 3 4 5 6:NBLocks	861
:ULINK:DPDCh:DCH[1] 2 3 4 5 6:RMATtribute	861
:ULINK:DPDCh:DCH[1] 2 3 4 5 6:TTL	862
:ULINK:DPDCh:DCH2 3 4 5 6[:STATe]	862
:ULINK:DPDCh:POWEr	863
:ULINK:DPDCh:SFORmat	863
:ULINK:DPDCh[:STATe]	863
:ULINK:FCLock:INTeRval	864
:ULINK:FCLock:POLarity	864
:ULINK:FILTeR	865
:ULINK:FILTeR:ALPHA	865
:ULINK:FILTeR:BBT	866
:ULINK:FILTeR:CHANnel	866
:ULINK:FOFFset	867
:ULINK:HSDPcch:APATteRn	867
:ULINK:HSDPcch:APOWEr	868
:ULINK:HSDPcch:CCODE	868

Contents

:ULINK:HSDPcch:CPATtern	868
:ULINK:HSDPcch:CPOWer	869
:ULINK:HSDPcch:NPOWer	869
:ULINK:HSDPcch:SFDelay	869
:ULINK:HSDPcch[:STATe]	870
:ULINK:POLarity	870
:ULINK:SCRamblecode	870
:ULINK:SDElay	871
:ULINK:SFNRst:POLarity	871
:ULINK:SYNC:MODE	872
:ULINK:SYNC[:SOURce]	872
:ULINK:TOFFset	872
[:STATe]	873
NADC Subsystem–Option 402 ([:SOURce]:RADio[:NADC])	874
:ALPha	874
:BBClock	874
:BBT	875
:BRATe	875
:BURSt:PN9	876
:BURSt:SHAPe[:TYPE]	877
:BURSt:SHAPe:FALL:DElay	877
:BURSt:SHAPe:FALL:TIME	878
:BURSt:SHAPe:FDElay	878
:BURSt:SHAPe:FTIME	879
:BURSt:SHAPe:RDElay	880
:BURSt:SHAPe:RISE:DElay	880
:BURSt:SHAPe:RISE:TIME	881
:BURSt:SHAPe:RTIME	882
:BURSt[:STATe]	882
:BURSt:SHAPe[:TYPE]	883
:CHANnel	883
:DATA	884
:DATA:PRAM	884
:DATA:FIX4	885
:DEFault	885
:EDATa:DElay	885
:EDCLock	886
:EREference	886

:EReference:VALue	887
:FILTer	887
:FRATe	888
:IQ:SCALE	888
:MODulation:FSK[:DEViation]	889
:MODulation:MSK[:PHASe]	889
:MODulation:UFSK	889
:MODulation:UIQ	890
:MODulation[:TYPE]	890
:REPeat	891
:POLarity[:ALL]	891
:SECondary:RECall	891
:SECondary:SAVE	892
:SECondary:TRIGger[:SOURce]	892
:SECondary[:STATe]	892
:SLOT[1] 2 3 4 5 6:DCUStom	893
:SLOT[1] 2 3 4 5 6:DCUStom:FIX4	893
:SLOT[1] 2 3 4 5 6:DTCHannel:CDLocator	894
:SLOT[1] 2 3 4 5 6:DTCHannel:CDVCcode	894
:SLOT[1] 2 3 4 5 6:DTCHannel:SACChannel	894
:SLOT[1] 2 3 4 5 6:DTCHannel:SWORd	895
:SLOT[1] 2 3 4 5 6:DTCHannel[:DATA]	895
:SLOT[1] 2 3 4 5 6:DTCHannel[:DATA]FIX4	896
:SLOT[1] 2 3 4 5 6:POWer	896
:SLOT[1] 2 3 4 5 6:STATe	896
:SLOT[1] 2 3 4 5 6:UCUStom	897
:SLOT[1] 2 3 4 5 6:UCUStom:FIX4	897
:SLOT[1] 2 3 4 5 6:UTCHannel:CDVCcode	897
:SLOT[1] 2 3 4 5 6:UTCHannel:SACChannel	898
:SLOT[1] 2 3 4 5 6:UTCHannel:SWORd	898
:SLOT[1] 2 3 4 5 6:UTCHannel[:DATA]	898
:SLOT[1] 2 3 4 5 6:UTCHannel[:DATA]:FIX4	899
:SLOT[1] 2 3 4 5 6[:TYPE]	899
:SOUT	900
:SOUT:OFFSet	900
:SOUT:SLOT	901
:SRATe	901
:TRIGger:TYPE	902

Contents

:TRIGger:TYPE:CONTInuous[:TYPE]	903
:TRIGger:TYPE:GATE:ACTive	904
:TRIGger[:SOURce]	904
:TRIGger[:SOURce]:EXTernal:DELay	905
:TRIGger[:SOURce]:EXTernal:DELay:STATe	906
:TRIGger[:SOURce]:EXTernal:SLOPe	906
:TRIGger[:SOURce]:EXTernal[:SOURce]	907
PDC Subsystem–Option 402 ([:SOURce]:RADio:PDC)	908
:ALPha	908
:BBCLock	908
:BBT	909
:BRATe	909
:BURSt:PN9	910
:BURSt:SHAPE:FALL:DELay	911
:BURSt:SHAPE:FALL:TIME	911
:BURSt:SHAPE:FDELay	912
:BURSt:SHAPE:FTIME	913
:BURSt:SHAPE:RDELay	913
:BURSt:SHAPE:RISE:DELay	914
:BURSt:SHAPE:RISE:TIME	915
:BURSt:SHAPE:RTIME	915
:BURSt:SHAPE[:TYPE]	916
:BURSt[:STATe]	916
:CHANnel	917
:DATA	917
:DATA:PRAM	918
:DATA:FIX4	918
:DEFault	918
:EDATa:DELay	919
:EDCLock	919
:EREFerence	919
:EREFerence:VALue	920
:FILTer	920
:FRATe	921
:IQ:SCALE	921
:MODulation:FSK[:DEViation]	922
:MODulation:MSK[:PHASe]	922

:MODulation:UFSK	923
:MODulation:UIQ	923
:MODulation[:TYPE]	923
:POLarity[:ALL]	924
:SECondary:RECall	924
:SECondary:SAVE	924
:SECondary:TRIGger[:SOURce]	925
:SECondary[:STATe]	925
:SLOT0[1] 2 3 4 5:DCUStom	926
:SLOT0[1] 2 3 4 5:DCUSTom:FIX4	926
:SLOT0[1] 2 3 4 5:DTCHannel:CCODE	926
:SLOT0[1] 2 3 4 5:DTCHannel:SACChannel	927
:SLOT0[1] 2 3 4 5:DTCHannel:SWORd	927
:SLOT0[1] 2 3 4 5:DTCHannel[:TCHannel]	927
:SLOT0[1] 2 3 4 5:DTCHannel[:TCHannel]:FIX4	928
:SLOT0[1] 2 3 4:POWEr	928
:SLOT0[1] 2 3 4 5:STATe	929
:SLOT0[1] 2 3 4 5:UCUStom	929
:SLOT0[1] 2 3 4 5:UCUStom:FIX4	929
:SLOT0[1] 2 3 4 5:UTCHannel:CCODE	930
:SLOT0[1] 2 3 4 5:UTCHannel:SACChannel	930
:SLOT0[1] 2 3 4 5:UTCHannel:SWORd	930
:SLOT0[1] 2 3 4 5:UTCHannel[:TCHannel]	931
:SLOT0[1] 2 3 4 5:UTCHannel[:TCHannel]:FIX4	931
:SLOT0[1] 2 3 4 5:UVOX:CCODE	932
:SLOT0[1] 2 3 4 5:UVOX:SACChannel	932
:SLOT0[1] 2 3 4 5:UVOX:SWORd	932
:SLOT0[1] 2 3 4 5[:TYPE]	933
:SOUT	933
:SOUT:OFFSet	933
:SOUT:SLOT	934
:SRATe	934
:TRIGger:TYPE	936
:TRIGger:TYPE:CONTInuous[:TYPE]	936
:TRIGger:TYPE:GATE:ACTive	937
:TRIGger[:SOURce]	937
:TRIGger[:SOURce]:EXTernal:DELay	938
:TRIGger[:SOURce]:EXTernal:DELay:STATe	939

Contents

:TRIGger[:SOURce]:EXTernal:SLOPe	939
:TRIGger[:SOURce]:EXTernal[:SOURce]	940
[:STATe]	940
PHS Subsystem–Option 402 ([:SOURce]:RADio:PHS)	941
:ALPha	941
:BBCLock	941
:BBT	942
:BRATe	942
:BURSt:PN9	943
:BURSt:SCRamble:SEED	944
:BURSt:SCRamble[:STATe]	944
:BURSt:SHAPE:FALL:DELay	945
:BURSt:SHAPE:FALL:TIME	945
:BURSt:SHAPE:FDELay	946
:BURSt:SHAPE:FTIME	947
:BURSt:SHAPE:RDELay	947
:BURSt:SHAPE:RISE:DELay	948
:BURSt:SHAPE:RISE:TIME	949
:BURSt:SHAPE:RTIME	949
:BURSt:SHAPE[:TYPE]	950
:BURSt[:STATe]	950
:CHANnel	951
:DATA	951
:DATA:PRAM	952
:DATA:FIX4	952
:DEFault	952
:DLINK:SLOT[1] 2 3 4:CUSTom	953
:DLINK:SLOT[1] 2 3 4:CUSTom:FIX4	953
:DLINK:SLOT[1] 2 3 4:POWer	953
:DLINK:SLOT[1] 2 3 4:SCHannel:CSID	954
:DLINK:SLOT[1] 2 3 4:SCHannel:IDLE	954
:DLINK:SLOT[1] 2 3 4:SCHannel:PSID	954
:DLINK:SLOT[1] 2 3 4:SCHannel:UWORD	955
:DLINK:SLOT[1] 2 3 4:STATe	955
:DLINK:SLOT[1] 2 3 4:TCHannel:SACChannel	955
:DLINK:SLOT[1] 2 3 4:TCHannel:UWORD	956
:DLINK:SLOT[1] 2 3 4:TCHannel[:TCHannel]	956
:DLINK:SLOT[1] 2 3 4:TCHannel[:TCHannel]:FIX4	956

:DLINK:SLOT[1] 2 3 4[:TYPE]	957
:EDATa:DELay	957
:EDCLock	957
:EREFerence	958
:EREFerence:VALue	958
:FILTer	959
:IQ:SCALE	960
:MODulation:FSK[:DEViation]	960
:MODulation:MSK[:PHASe]	961
:MODulation:UFSK	961
:MODulation:UIQ	961
:MODulation[:TYPE]	962
:POLarity[:ALL]	962
:SECOndary:RECall	962
:SECOndary:SAVE	963
:SECOndary:TRIGger[:SOURce]	963
:SECOndary[:STATe]	963
:SOUT	964
:SOUT:OFFSet	964
:SOUT:SLOT	965
:SRATE	965
:TRIGger:TYPE	966
:TRIGger:TYPE:CONTinuous[:TYPE]	967
:TRIGger:TYPE:GATE:ACTive	968
:TRIGger[:SOURce]:EXTeRnal:DELay	968
:TRIGger[:SOURce]:EXTeRnal:DELay:STATe	969
:TRIGger[:SOURce]:EXTeRnal:SLOPe	969
:TRIGger[:SOURce]:EXTeRnal[:SOURce]	969
:TRIGger[:SOURce]	970
:ULINK:SLOT[1] 2 3 4:CUSTom	971
:ULINK:SLOT[1] 2 3 4:CUSTom:FIX4	972
:ULINK:SLOT[1] 2 3 4:POWer	972
:ULINK:SLOT[1] 2 3 4:SCHannel:CSID	972
:ULINK:SLOT[1] 2 3 4:SCHannel:IDLE	973
:ULINK:SLOT[1] 2 3 4:SCHannel:PSID	973
:ULINK:SLOT[1] 2 3 4:SCHannel:UWORD	973
:ULINK:SLOT[1] 2 3 4:STATe	974
:ULINK:SLOT[1] 2 3 4:TCHannel:SACChannel	974

Contents

:ULINK:SLOT[1] 2 3 4:TCHannel:UWORD	974
:ULINK:SLOT[1] 2 3 4:TCHannel[:TCHannel]	975
:ULINK:SLOT[1] 2 3 4:TCHannel[:TCHannel:FIX4]	975
:ULINK:SLOT[1] 2 3 4[:TYPE]	975
[:STATe]	976
TETRA Subsystem–Option 402 ([:SOURce]:RADio:TETRa)	977
:ALPha	977
:BBCLock	977
:BBT	978
:BRATe	978
:BURSt:PN9	979
:BURSt:SCRamble:SEED	980
:BURSt:SCRamble[:STATe]	980
:BURSt:SHAPE:FALL:DELay	980
:BURSt:SHAPE:FALL:TIME	981
:BURSt:SHAPE:FDELay	982
:BURSt:SHAPE:FTIME	982
:BURSt:SHAPE:RDELay	983
:BURSt:SHAPE:RISE:DELay	984
:BURSt:SHAPE:RISE:TIME	984
:BURSt:SHAPE:RTIME	985
:BURSt:SHAPE[:TYPE]	986
:BURSt[:STATe]	986
:CHANnel	987
:DATA	987
:DATA:PRAM	988
:DATA:FIX4	988
:DEFault	989
:EDATa:DELay	989
:EDCLock	989
:EREFerence	990
:EREFerence:VALue	990
:FILTer	991
:IQ:SCALE	992
:MODulation:FSK[:DEViation]	992
:MODulation:MSK[:PHASe]	993
:MODulation:UFSK	993
:MODulation:UIQ	993

:MODulation[:TYPE]	994
:POLarity[:ALL]	994
:SECondary:RECall	995
:SECondary:SAVE	995
:SECondary:TRIGger[:SOURce]	995
:SECondary[:STATe]	996
:SLOT[1] 2 3 4:DCCustom	996
:SLOT[1] 2 3 4:DCCustom:FIX4	996
:DCNormal:B1	997
:DCNormal:B2	997
:SLOT[1] 2 3 4:DCNormal:TSEquence	997
:SLOT[1] 2 3 4:DCNormal[:DATA]	998
:SLOT[1] 2 3 4:DCNormal[:DATA]:FIX4	998
:SLOT[1] 2 3 4:DcSync:B	999
:SLOT[1] 2 3 4:DcSync:FCOR	999
:SLOT[1] 2 3 4:DcSync:SSB	999
:SLOT[1] 2 3 4:DcSync:STS	1000
:SLOT[1] 2 3 4:DcSync[:DATA]	1000
:SLOT[1] 2 3 4:DcSync[:DATA]:FIX4	1000
:SLOT[1] 2 3 4:DDCustom	1001
:SLOT[1] 2 3 4:DDCustom:FIX4	1001
:SLOT[1] 2 3 4:DDNormal:B1	1002
:SLOT[1] 2 3 4:DDNormal:B2	1002
:SLOT[1] 2 3 4:DDNormal:TSEquence	1002
:SLOT[1] 2 3 4:DDNormal[:DATA]	1003
:SLOT[1] 2 3 4:DDNormal[:DATA]:FIX4	1003
:SLOT[1] 2 3 4:DDSync:B	1004
:SLOT[1] 2 3 4:DDSync:FCOR	1004
:SLOT[1] 2 3 4:DDSync:SSB	1004
:SLOT[1] 2 3 4:DDSync:STS	1005
:SLOT[1] 2 3 4:DDSync[:DATA]	1005
:SLOT[1] 2 3 4:DDSync[:DATA]:FIX4	1005
:SLOT[1] 2 3 4:POWer	1006
:SLOT[1] 2 3 4:STATe	1006
:SLOT[1] 2 3 4:UC1:TSEquence	1006
:SLOT[1] 2 3 4:UC1[:DATA]	1007
:SLOT[1] 2 3 4:UC1[:DATA]:FIX4	1007
:SLOT[1] 2 3 4:UC2:TSEquence	1007

Contents

:SLOT[1] 2 3 4:UC2[:DATA]	1008
:SLOT[1] 2 3 4:UC2[:DATA]:FIX4	1008
:SLOT[1] 2 3 4:UCUStom	1008
:SLOT[1] 2 3 4:UCUStom:FIX4	1009
:SLOT[1] 2 3 4:UNORmal:TSEquence	1009
:SLOT[1] 2 3 4:UNORmal[:DATA]	1009
:SLOT[1] 2 3 4:UNORmal[:DATA]:FIX4	1010
:SLOT[1] 2 3 4[:TYPE]	1010
:SOUT	1011
:SOUT:OFFSet	1011
:SOUT:SLOT	1012
:SRATe	1012
:TRIGger:TYPE	1014
:TRIGger:TYPE:CONTInuous[:TYPE]	1014
:TRIGger:TYPE:GATE:ACTive	1015
:TRIGger[:SOURce]	1016
:TRIGger[:SOURce]:EXTernal:DELay	1017
:TRIGger[:SOURce]:EXTernal:DELay:STATe	1017
:TRIGger[:SOURce]:EXTernal:SLOPe	1018
:TRIGger[:SOURce]:EXTernal[:SOURce]	1018
[:STATe]	1019
Wideband CDMA Base Band Generator Subsystem–Option 400 ([:SOURce]:RADio:WCDMa:TGPP[:BBG])	1020
:BBCLock	1020
:BBCLock:EXT:RATE	1020
:DLINK:APPLy	1021
:DLINK:AWGN:CN	1021
:DLINK:AWGN:CPOWer	1021
:DLINK:AWGN:ECNO	1022
:DLINK:AWGN:ECRPower	1022
:DLINK:AWGN:ECRef	1022
:DLINK:AWGN:FNBW	1023
:DLINK:AWGN:NPOWer	1023
:DLINK:AWGN:TICPower	1023
:DLINK:AWGN[:STATe]	1024
:DLINK:BBCLock	1024
:DLINK:CARB:CMODE:CCODE	1024
:DLINK:CARB:CMODE:DATA	1025
:DLINK:CARB:CMODE:FOFFset	1025

:DLINK:CARB:CMODE:FSTRuct	1025
:DLINK:CARB:CMODE:POWer.	1026
:DLINK:CARB:CMODE:PRATio	1026
:DLINK:CARB:CMODE:SCTYpe.	1026
:DLINK:CARB:CMODE:SFORmat	1027
:DLINK:CARB:CMODE:SSCodeos	1027
:DLINK:CARB:CMODE:TFIRst.	1028
:DLINK:CARB:CMODE:TGL	1028
:DLINK:CARB:CMODE[:STATe].	1028
:DLINK:CPICH:CCODE	1029
:DLINK:CPICH:POWer	1029
:DLINK:CPICH[:STATe]	1029
:DLINK:CRATe	1030
:DLINK:DPCH[1]:BALance	1030
:DLINK:DPCH[1]:BINitalize	1030
:DLINK:DPCH[1]2:ALL[:STATe]	1031
:DLINK:DPCH[1]2:CCODE	1031
:DLINK:DPCH[1]2:DATA	1031
:DLINK:DPCH[1]2:DATA:FIX4	1032
:DLINK:DPCH[1]2:POWer	1032
:DLINK:DPCH[1]2:RCSetup.	1033
:DLINK:DPCH[1]2:SLOTformat	1034
:DLINK:DPCH[1]2:SRATe.	1034
:DLINK:DPCH[1]2:SSCodeos	1034
:DLINK:DPCH[1]2:TFCI:PATtern	1035
:DLINK:DPCH[1]2:TOFFset	1035
:DLINK:DPCH[1]2:TPC:NUMSteps	1036
:DLINK:DPCH[1]2:TPC:PATtern	1036
:DLINK:DPCH[1]2[:STATe]	1037
:DLINK:FILTer	1037
:DLINK:FILTer:ALPHa.	1038
:DLINK:FILTer:BBT	1038
:DLINK:FILTer:CHANnel.	1039
:DLINK:MSYNc	1039
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:ALL[:STATe].	1039
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:CCODE	1040
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:DATA	1040
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:POWer.	1040

Contents

:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:SRATe	1041
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:SSCodeos	1041
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16:TOFFset	1042
:DLINK:OCNS[1]2 3 4 5 6 7 8 9 10 11 12 13 14 15 16[:STATe].	1042
:DLINK:OOSTest[:STATe]	1042
:DLINK:OOSTest:DTXGate:POLarity	1043
:DLINK:PADJust.	1043
:DLINK:PCCPch:BCHData	1043
:DLINK:PCCPch:BCHData:FIX4.	1044
:DLINK:PCCPch:CCODE.	1044
:DLINK:PCCPch:POWer	1044
:DLINK:PCCPch[:STATe].	1045
:DLINK:PICH:CCODE	1045
:DLINK:PICH:DATA	1045
:DLINK:PICH:DATA:FIX4.	1046
:DLINK:PICH:PIBits	1046
:DLINK:PICH:PINDicator	1046
:DLINK:PICH:POWer.	1047
:DLINK:PICH[:STATe].	1047
:DLINK:POLarity	1047
:DLINK:PSCH:POWer	1048
:DLINK:PSCH[:STATe]	1048
:DLINK:RPANel:INPut:ALTPower	1048
:DLINK:RPANel:INPut:BBGRef	1049
:DLINK:RPANel:INPut:BGATe	1049
:DLINK:RPANel:INPut:PTRigger1	1049
:DLINK:RPANel:INPut:PTRigger2	1050
:DLINK:RPANel:OUTPut:DCLock	1050
:DLINK:RPANel:OUTPut:DOUT.	1052
:DLINK:RPANel:OUTPut:EVENT1	1053
:DLINK:RPANel:OUTPut:EVENT2	1053
:DLINK:RPANel:OUTPut:EVENT3	1054
:DLINK:RPANel:OUTPut:EVENT4	1054
:DLINK:RPANel:OUTPut:SSYNc	1055
:DLINK:SCH[:STATe]	1055
:DLINK:SCRamblecode	1055
:DLINK:SDElay	1056
:DLINK:SSCH:POWer	1056

:DLINK:SSCH:SSGRoup	1056
:DLINK:SSCH[:STATe]	1057
:DLINK:TGAP:FSTRuct	1057
:DLINK:TGAP:POFFset	1057
:DLINK:TGAP:PSI[1]:CFN	1058
:DLINK:TGAP:PSI[1]:CMMethod	1058
:DLINK:TGAP:PSI[1]:D	1059
:DLINK:TGAP:PSI[1]:L1	1059
:DLINK:TGAP:PSI[1]:L2	1059
:DLINK:TGAP:PSI[1]:PL1	1060
:DLINK:TGAP:PSI[1]:PL2	1060
:DLINK:TGAP:PSI[1]:PRC	1060
:DLINK:TGAP:PSI[1]:PS	1061
:DLINK:TGAP:PSI[1]:SN	1061
:DLINK:TGAP:RPARAMeter	1061
:DLINK:TGAP:SCFN	1062
:DLINK:TGAP:START:TRIGger	1062
:DLINK:TGAP:START:TRIGger:POLarity	1062
:DLINK:TGAP:STOP:TRIGger	1063
:DLINK:TGAP:STOP:TRIGger:POLarity	1063
:DLINK:TGAP[:STATe]	1063
:DLINK:TSETup	1064
:DLINK:TXDV	1065
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:BLKSize	1066
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:BPFRame	1067
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:BRATe	1067
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:BSSize	1067
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:CODE	1068
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:CRC	1069
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:DATA	1069
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:DATA:EINSert	1070
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:DATA:FIX4	1070
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:NBLocks	1071
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:POSITION	1072
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:PPERcentage	1072
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:RMATch	1073
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6:TTI	1073
:DLINK[:TGRoup [A]B]:DCH[1]2 3 4 5 6[:STATe]	1074

Contents

:LINK	1074
:POLarity[:ALL].	1074
:ULINK:APPLy	1075
:ULINK:AWGN:CN	1075
:ULINK:AWGN:CPOWer	1076
:ULINK:AWGN:DRATe	1076
:ULINK:AWGN:EBNO.	1076
:ULINK:AWGN:EBRef.	1077
:ULINK:AWGN:FNBW	1077
:ULINK:AWGN:NPOWer.	1078
:ULINK:AWGN:TICPower.	1078
:ULINK:AWGN[:STATe]	1078
:ULINK:CRATe.	1079
:ULINK:DPCCh:BETA.	1079
:ULINK:DPCCh:CCODe	1080
:ULINK:DPCCh:DATA.	1080
:ULINK:DPCCh:DATA:FIX4	1081
:ULINK:DPCCh:FBI:PATtern	1081
:ULINK:DPCCh:FBI:PATtern:FIX	1082
:ULINK:DPCCh:FBI[:STATe]	1082
:ULINK:DPCCh:POWer	1083
:ULINK:DPCCh:RATE.	1083
:ULINK:DPCCh:SLOTformat	1083
:ULINK:DPCCh:TFCI:PATtern	1084
:ULINK:DPCCh:TFCI:PATtern:FIX	1084
:ULINK:DPCCh:TFCI[:STATe]	1085
:ULINK:DPCCh:TPC:NSTeps	1085
:ULINK:DPCCh:TPC:PATtern.	1086
:ULINK:DPCCh:TPC:PATtern:FIX4.	1087
:ULINK:DPCCh:TPC:PATtern:TRIGger:POLarity	1087
:ULINK:DPCCh:TPC:PATtern:TRIGger[:STATe].	1088
:ULINK:DPCCh:TPOWer	1088
:ULINK:DPCCh[:STATe]	1089
:ULINK:DPDCh:BETA.	1089
:ULINK:DPDCh:CCODe	1090
:ULINK:DPDCh:DATA.	1091
:ULINK:DPDCh:DATA:FIX4.	1091
:ULINK:DPDCh:POWer.	1092

:ULINK:DPDCh:RATE	1092
:ULINK:DPDCh:RBER	1093
:ULINK:DPDCh:SLOTformat	1094
:ULINK:DPDCh:TBER[:CLENgth]	1095
:ULINK:DPDCh:TBER:ELENgth	1095
:ULINK:DPDCh:TPOWer	1096
:ULINK:DPDCh[:STATe]	1096
:ULINK:FClock:INTerval	1096
:ULINK:FClock:POLarity	1097
:ULINK:FILTer	1097
:ULINK:FILTer:ALPHa	1098
:ULINK:FILTer:BBT	1099
:ULINK:FILTer:CHANnel	1099
:ULINK:FOFFset	1100
:ULINK:PADJust	1100
:ULINK:PHYsical[1]:TYPE	1100
:ULINK:PMODE:TPControl:HOLD	1101
:ULINK:PMODE:TPControl:POWer:INITial	1101
:ULINK:PMODE:TPControl:POWer:MAXimum	1102
:ULINK:PMODE:TPControl:POWer:MINimum	1102
:ULINK:PMODE:TPControl:POWer:RESet	1103
:ULINK:PMODE:TPControl:POWer:STEP	1103
:ULINK:PMODE:TPControl:TRIGger:POLarity	1104
:ULINK:PMODE[:SElect]	1104
:ULINK:PRACH:AICH:NUMBer	1104
:ULINK:PRACH:AICH:POLarity	1105
:ULINK:PRACH:AWGN:CN	1105
:ULINK:PRACH:AWGN:CPOWer	1106
:ULINK:PRACH:AWGN:DRATE	1106
:ULINK:PRACH:AWGN:EBNO	1106
:ULINK:PRACH:AWGN:ECNO	1107
:ULINK:PRACH:AWGN:EREF	1107
:ULINK:PRACH:AWGN:NPOWer	1108
:ULINK:PRACH:AWGN:TICPower	1108
:ULINK:PRACH:AWGN[:STATe]	1108
:ULINK:PRACH:MESSAge:CPART:BETA	1109
:ULINK:PRACH:MESSAge:CPART:DATA	1109
:ULINK:PRACH:MESSAge:CPART:DATA:FIX4	1110

Contents

:ULINK:PRACH:MESSAge:CPARt:POWer	1110
:ULINK:PRACH:MESSAge:CPARt:RATE	1111
:ULINK:PRACH:MESSAge:CPARt:SLOTformat	1111
:ULINK:PRACH:MESSAge:CPARt:TFCI:PATtern	1112
:ULINK:PRACH:MESSAge:CPARt:TFCI:PATtern:FIX	1112
:ULINK:PRACH:MESSAge:CPARt:TFCI[:STATe]	1113
:ULINK:PRACH:MESSAge:DPARt:BETA	1113
:ULINK:PRACH:MESSAge:DPARt:DATA	1114
:ULINK:PRACH:MESSAge:DPARt:DATA:FIX4	1114
:ULINK:PRACH:MESSAge:DPARt:POWer	1115
:ULINK:PRACH:MESSAge:DPARt:RATE	1115
:ULINK:PRACH:MESSAge:DPARt:SLOTformat	1116
:ULINK:PRACH:MODE[:SElect]	1117
:ULINK:PRACH:MULTi:MESSAge:TPOWer	1118
:ULINK:PRACH:MULTi:MESSAge[:STATe]	1118
:ULINK:PRACH:MULTi:NUMBer	1118
:ULINK:PRACH:MULTi:PREAmble:NUMBer	1119
:ULINK:PRACH:MULTi:PREAmble:POWer:INITial	1119
:ULINK:PRACH:MULTi:PREAmble:POWer:MAX	1120
:ULINK:PRACH:MULTi:PREAmble:POWer:RSTep	1120
:ULINK:PRACH:MULTi:PREAmble:PPM	1120
:ULINK:PRACH:MULTi:UE[1] 2 3 4 5 6 7 8:MESSAge:CPARt:CCODE	1121
:ULINK:PRACH:MULTi:UE[1] 2 3 4 5 6 7 8:MESSAge:DPARt:CCODE	1121
:ULINK:PRACH:MULTi:UE[1] 2 3 4 5 6 7 8:PREAmble:SIGNature	1121
:ULINK:PRACH:MULTi:UE[1] 2 3 4 5 6 7 8:SPOStion[1] 2 3 4 5 6 7 8[:ASLot]	1122
:ULINK:PRACH:MULTi:UE[1] 2 3 4 5 6 7 8[:STATe]	1123
:ULINK:PRACH:PREAmble:POWer:AVERAge	1123
:ULINK:PRACH:PREAmble:POWer:MODE	1124
:ULINK:PRACH:RPARAmeter	1124
:ULINK:PRACH:SCRamblecode	1125
:ULINK:PRACH:SDElay	1125
:ULINK:PRACH:SUBChannel	1126
:ULINK:PRACH:TOFFset	1126
:ULINK:PRACH:TPA	1127
:ULINK:PRACH:TPM	1127
:ULINK:PRACH:TPOWer	1128
:ULINK:PRACH:TPP	1128
:ULINK:PRACH:TRIGger	1129

:ULINK:PRACH:TRIGGER:POLARITY	1129
:ULINK:PRACH:TRIGGER:SOURCE	1129
:ULINK:PRACH:TTI	1130
:ULINK:PRACH[:SINGLE]:MESSAGE[:STATE]	1130
:ULINK:PRACH[:SINGLE]:NUMBER	1131
:ULINK:PRACH[:SINGLE]:MESSAGE:CPART:CCODE	1131
:ULINK:PRACH[:SINGLE]:MESSAGE:DPART:CCODE	1132
:ULINK:PRACH[:SINGLE]:MESSAGE:TPOWER	1133
:ULINK:PRACH[:SINGLE]:NUMBER	1133
:ULINK:PRACH[:SINGLE]:PREAMBLE:NUMBER	1134
:ULINK:PRACH[:SINGLE]:PREAMBLE:POWER:INITIAL	1134
:ULINK:PRACH[:SINGLE]:PREAMBLE:POWER:MAX	1135
:ULINK:PRACH[:SINGLE]:PREAMBLE:POWER:RSTEP	1135
:ULINK:PRACH[:SINGLE]:PREAMBLE:PPM	1136
:ULINK:PRACH[:SINGLE]:PREAMBLE:SIGNATURE	1136
:ULINK:RMCHANNEL	1137
:ULINK:RPANEL:DPCH:INPUT:ALTPower	1137
:ULINK:RPANEL:DPCH:INPUT:BBGRef	1138
:ULINK:RPANEL:DPCH:INPUT:BGATE	1138
:ULINK:RPANEL:DPCH:INPUT:PTRIGGER1	1138
:ULINK:RPANEL:DPCH:INPUT:PTRIGGER2	1139
:ULINK:RPANEL:DPCH:OUTPUT:DCLock	1139
:ULINK:RPANEL:DPCH:OUTPUT:DOUT	1140
:ULINK:RPANEL:DPCH:OUTPUT:EVENT1	1141
:ULINK:RPANEL:DPCH:OUTPUT:EVENT2	1141
:ULINK:RPANEL:DPCH:OUTPUT:EVENT3	1142
:ULINK:RPANEL:DPCH:OUTPUT:EVENT4	1142
:ULINK:RPANEL:DPCH:OUTPUT:SSYNc	1143
:ULINK:RPANEL:PRACH:INPUT:ALTPower	1143
:ULINK:RPANEL:PRACH:INPUT:BBGRef	1144
:ULINK:RPANEL:PRACH:INPUT:BGATE	1144
:ULINK:RPANEL:PRACH:INPUT:PTRIGGER1	1144
:ULINK:RPANEL:PRACH:INPUT:PTRIGGER2	1145
:ULINK:RPANEL:PRACH:OUTPUT:DCLock	1145
:ULINK:RPANEL:PRACH:OUTPUT:DOUT	1147
:ULINK:RPANEL:PRACH:OUTPUT:EVENT1	1147
:ULINK:RPANEL:PRACH:OUTPUT:EVENT2	1148
:ULINK:RPANEL:PRACH:OUTPUT:EVENT3	1149

Contents

:ULINK:RPANel:PRACH:OUTPut:EVENT4	1149
:ULINK:RPANel:PRACH:OUTPut:SSYNc	1150
:ULINK:SCRamblecode	1151
:ULINK:SDElay	1151
:ULINK:SFNRst:POLarity	1151
:ULINK:SYNC:MODE	1152
:ULINK:SYNC[:SOURce]	1152
:ULINK:TGAP:POFFset	1154
:ULINK:TGAP:PSI[1] 2 3 4 5 6:CFN	1154
:ULINK:TGAP:PSI[1]:CMMethod	1155
:ULINK:TGAP:PSI[1] 2 3 4 5 6:D	1155
:ULINK:TGAP:PSI[1] 2 3 4 5 6:L1	1156
:ULINK:TGAP:PSI[1] 2 3 4 5 6:L2	1156
:ULINK:TGAP:PSI[1] 2 3 4 5 6:PL1	1156
:ULINK:TGAP:PSI[1] 2 3 4 5 6:PL2	1157
:ULINK:TGAP:PSI[1] 2 3 4 5 6:POWer	1157
:ULINK:TGAP:PSI[1] 2 3 4 5 6:PRC	1157
:ULINK:TGAP:PSI[1] 2 3 4 5 6:PS	1158
:ULINK:TGAP:PSI[1] 2 3 4 5 6:SN	1158
:ULINK:TGAP:RPARameter	1158
:ULINK:TGAP:SCFN	1159
:ULINK:TGAP[:STATe]	1159
:ULINK:TGAP:START:TRIGger	1160
:ULINK:TGAP:START:TRIGger:POLarity	1160
:ULINK:TGAP:STOP:TRIGger	1160
:ULINK:TGAP:STOP:TRIGger:POLarity	1160
:ULINK:TOFFset	1161
:ULINK:TSTatus:COMPRessed	1161
:ULINK:TSTatus:RACH	1161
:ULINK:TSTatus:RECeive	1162
:ULINK:TSTatus:SYNC	1162
:ULINK:[TGRoup[1]]:DCH[1] 2 3 3 5 6:BLKSize	1162
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:BPFRame	1163
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:BRATe	1163
:ULINK:[TGRoup[1]]:DCH[1] 2 3 3 5 6:CODE	1163
:ULINK:[TGRoup[1]]:DCH[1] 2 3 3 5 6:CRC	1164
:ULINK:[TGRoup[1]]:DCH[1] 2 3 3 5 6:DATA	1164
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:DATA:BER:ACTual	1165

:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:DATA:BER:ERRor:BIT	1165
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:DATA:BER:TOTal:BIT	1165
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:DATA:BER[:VALue]	1166
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:DATA:BLER:ACTual	1166
:ULINK[:TGRoup[1] 2]:DCH[1] 2 3 4 5 6:DATA:BLER:ERRor:BLOCK	1166
:ULINK[:TGRoup[1] 2]:DCH[1] 2 3 4 5 6:DATA:BLER:TOTal:BLOCK	1167
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:DATA:BLER[:VALue]	1167
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:DATA:EINsert	1168
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:DATA:FIX4	1168
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:NBLock	1169
:ULINK[:TGRoup [1]]:DCH[1] 2 3 4 5 6:PPERcentage	1169
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:RMATch	1169
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6:TTI	1170
:ULINK[:TGRoup[1]]:DCH[1] 2 3 4 5 6[:STATe]	1170
:ULINK[:TGRoup[1]]:RACH[1]:BLKSize	1170
:ULINK[:TGRoup [1]]:RACH[1]:BPFRame	1171
:ULINK[:TGRoup [1]]:RACH[1]:BRATe	1171
:ULINK[:TGRoup[1]]:RACH[1]:CODE	1171
:ULINK[:TGRoup[1]]:RACH[1]:CRC	1171
:ULINK[:TGRoup[1]]:RACH[1]:DATA	1172
:ULINK[:TGRoup[1]]:RACH[1]:DATA:BER:ACTual	1172
:ULINK[:TGRoup[1]]:RACH[1]:DATA:BER:ERRor:BIT	1172
:ULINK[:TGRoup[1]]:RACH[1]:DATA:BER:TOTal:BIT	1173
:ULINK[:TGRoup[1]]:RACH[1]:DATA:BER[:VALue]	1173
:ULINK[:TGRoup[1]]:RACH[1]:DATA:BLER:ACTual	1173
:ULINK[:TGRoup[1]]:RACH[1]:DATA:BLER:ERRor:BLOCK	1174
:ULINK[:TGRoup[1]]:RACH[1]:DATA:BLER:TOTal:BLOCK	1174
:ULINK[:TGRoup[1]]:RACH[1]:DATA:BLER[:VALue]	1174
:ULINK[:TGRoup[1]]:RACH[1]:DATA:EINsert	1175
:ULINK[:TGRoup[1]]:RACH[1]:DATA:FIX4	1175
:ULINK[:TGRoup[1]]:RACH[1]:NBLock	1176
:ULINK[:TGRoup [1]]:RACH[1]:PPERcentage	1176
:ULINK[:TGRoup[1]]:RACH[1]:RMATch	1176
:ULINK[:TGRoup[1]]:RACH[1]:TTI	1177
:ULINK[:TGRoup[1]]:RACH[1][:STATe]	1177
[:STATe]	1177

Contents

Documentation Overview

Installation Guide

- Safety Information
- Getting Started
- Operation Verification
- Regulatory Information

User's Guide

- E4428C Analog Signal Generator Overview
- E4423C Analog Signal Generator Overview
- Basic Operation
- Basic Digital Operation
- AWGN Waveform Generator
- Analog Modulation
- Digital Signal Interface Module
- Bluetooth Signals
- BERT
- CDMA Digital Modulation
- GPS Modulation
- Multitone Waveform Generator
- Custom Digital Modulation
- Real Time TDMA Formats
- W-CDMA Digital Modulation for Component Test
- W-CDMA Uplink Digital Modulation for Receiver Test
- W-CDMA Downlink Digital Modulation for Receiver Test
- Troubleshooting

Programming Guide

- Getting Started with Remote Operation
- Using IO Interfaces
- Programming Examples
- Programming the Status Register System
- Creating and Downloading Waveform Files
- Creating and Downloading User-Data Files

SCPI Reference

Volume 1:

- SCPI Basics
- Basic Function Commands
- System Commands
- Analog Commands
- Component Test Digital Commands

Volume 2:

- Digital Signal Interface Module Commands
- Bit Error Rate Test (BERT) Commands
- Receiver Test Digital Commands

Volume 3:

- Receiver Test Digital Commands (continued)

Compatibility with E44xxB SCPI Commands

- Overview
- E4428C/38C SCPI Commands
- ESG E44xxB Commands
- 8648A/B/C/D Commands
- 8658B, 8657A/B/D/J Programming Codes

Service Guide

- Troubleshooting
- Replaceable Parts
- Assembly Replacement
- Post-Repair Procedures
- Safety and Regulatory

Key and Data Field Reference

Volume 1:

- Symbols, Numerics, A-H

Volume 2:

- Volume 2: I-Z

9 Receiver Test Digital Commands (continued)

This chapter provides a continuation of SCPI descriptions for commands dedicated to digital real-time testing using the E4438C ESG Vector Signal Generator. This chapter contains the following sections:

- “3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])” on page 668
- “Real Time GPS Subsystem–Option 409 ([:SOURCE]:RADio[1]|2|3|4:GPS)” on page 763
- “Real Time MSGPS Subsystem–Option 409 ([:SOURCE]:RADio[1]|2|3|4:MSGPs)” on page 770
- “GSM Subsystem–Option 402 ([:SOURCE]:RADio:GSM)” on page 773
- “HSDPA over W-CDMA Subsystem–Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])” on page 812
- “NADC Subsystem–Option 402 ([:SOURCE]:RADio[:NADC])” on page 874
- “PDC Subsystem–Option 402 ([:SOURCE]:RADio:PDC)” on page 908
- “PHS Subsystem–Option 402 ([:SOURCE]:RADio:PHS)” on page 941
- “TETRA Subsystem–Option 402 ([:SOURCE]:RADio:TETRa)” on page 977
- “Wideband CDMA Base Band Generator Subsystem–Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])” on page 1020

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

The commands in this subsystem support the remote functionality of the Signal Studio for 3GPP W-CDMA HSPA software. For a complete description of terms and HSPA functionality, refer to the software online help. Commands used for configuring the carrier signal and performing general signal generator functions are located in different SCPI command subsystems found within the SCPI Command Reference volumes.

There are two methods to determine the SCPI commands for a setup. One method is to locate each individual command listed in this subsystem and others within the *SCPI Command Reference* volumes. The other method is to use the HSPA software UI. After downloading a UI setup to the ESG, the software lets you export a SCPI file that contains the commands used in the UI setup. Refer to the HSPA software online help for information on this feature.

File Overview

The ESG's memory catalog (signal generator memory) uses several file types, each assigned with a unique syntax to recall the file. This section provides information on using files with SCPI commands.

This subsystem uses the following two command variables to represent two different file types stored in signal generator memory:

"<file name>" Bit file
"<user FIR>" FIR file

For more information on managing and using files, refer to the resources in the following list:

- [“File Name Variables” on page 13](#) for information on the file name syntax
- [Table 1-4 on page 14](#) for a listing of the different file types
- ESG Signal Generator *Programming Guide* for information on downloading bit files
- ESG Signal Generator *User's Guide* for information on creating and editing bit and FIR files using the signal generator

The HSPA software interface downloads user files (bit and FIR file types) to the ESG when **USER** is the software data or filter type selection. You can see these files on the ESG by pressing **Utility > Memory Catalog > Catalog Type** and then selecting the file type, or by using the SCPI commands located in the Memory subsystem. User files are located on the ESG in the following directory path: /USER/<file type directory>/<file name>. Table 9-1 shows the software naming convention for the different files created by the HSPA software.

Table 9-1 HSPA Software Downloaded File Names

Link Direction	Data Source	File Name	ESG File Type
Downlink and Uplink	Filter	<project name>-FIR	FIR
Downlink	BCH	<project name>-BCH	Bit
	PICH	<project name>-PICH	
	DCH	<project name>-DCH	
	DPCH	<project name>-DPCH	
	DCH _x ^a	<project name>-DCH _x ^a	
	Inter-TTI	<project name>-ITTI _x ^b	
	HARQ ACK/NACK Pattern	<project name>-DLCP	
	AMC CQI Pattern	<project name>-DLAPT	
	HS-DSCH	<project name>-DSCH1	
	HS-PDSCH	<project name>-HSPD _x ^b	
	HS-SCCH	<project name>-HSSCC _x ^b	
	E-AGCH Absolute Grant Scope	<project name>-EAGCH_AGS	
	E-AGCH Absolute Grant Value	<project name>-EAGCH_AGV	
	E-RGCH	<project name>-ERGCH	
E-HICH	<project name>-EHICH		

Table 9-1 HSPA Software Downloaded File Names

Link Direction	Data Source	File Name	ESG File Type
Uplink	DPCCH	<project name>-DPCCH	Bit
	FBI	<project name>-FBI	
	TPC	<project name>-TPC	
	DPDCH	<project name>-DPDCH	
	DCHx ^a	<project name>-DCHx ^a	
	ACK Pattern	<project name>-APAT	
	CQI Pattern	<project name>-CPAT	
	EDPCCH Pattern	<project name>-EDPCCH	
	EDPDCH Pattern	<project name>-EDPDCH	
	EDCH Pattern	<project name>-EDCH	
	EDPDCH (alternate) Pattern	<project name>-EDCHA	
	HARQ ACK Pattern	<project name>-UAPT	
	TFC E-TFCI User Pattern	<project name>-UETT	
	Happy Bit Pattern	<project name>-HBIT	
EXT Pattern	<project name>-EPAT		

a. x is the DCH number (1–6).

b. x is the channel number (1–4) for the HSDPA, the HS-PDSCH and the HS-SCCH.

Managing ESG Setting Conflicts and Error Messages

The ESG reports setting conflicts as error messages. When a setting conflict occurs, an error number and a brief message appear at the bottom of the ESG display. You can view the full text of the error message in either of two ways: by using the front panel of the ESG, or by executing SCPI commands.

Front Panel Press **Utility > Error Info**.

SCPI Execute the SCPI error commands described in the “[System Subsystem \(:SYSTEM\)](#)” on page 154.

For more information on Error messages, refer to the signal generator *Programming Guide* for remote viewing or the signal generator *User's Guide* for front panel viewing.

:DLINK:APPLY

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:APPLY  
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:APPLY?
```

This command applies changes to the channel setup and data for active downlink physical and transport channels, immediately starting the channel coding generation process. A progress bar may appear on the ESG display indicating that the new signal parameters are being applied. Signal parameters are also applied when the modulation format is turned on.

Use the query to determine whether or not execution of this command is required. It returns the following responses:

0	Command execution is not required.
1	Command execution is required.

NOTE The apply query response is valid only when downlink HSPA format is active.

The apply function will not work if there is a conflict with range values and coupled parameters. For example, if all the physical channel codes are not orthogonal to each other, the new settings are not applied to the signal when this command is executed. Resolve any conflicts before reapplying the changes. The ESG reports an error when conflicts occur.

:DLINK:AWGN:CN

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:AWGN:CN <val>  
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:AWGN:CN?
```

This command sets the downlink in-band carrier to noise ratio (C/N) value using AWGN.

***RST** 0

Range -30 to 30

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])**:DLINK:AWGN[:STATe]**

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:AWGN [ :STATe ] ON | OFF | 0 | 1
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:AWGN [ :STATe ] ?
```

This command turns the downlink AWGN on or off.

***RST** 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:BBCLock[:SOURCE]

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:BBCLock [ :SOURCE ]
{ INTernal } | EXTernal
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:BBCLock [ :SOURCE ] ?
```

This command selects the downlink baseband generator chip clock source, which is either internal to the signal generator or applied externally.

***RST** INT

Remarks When using an external chip clock source, connect the signal to the DATA CLOCK connector on the front panel of the ESG.

:DLINK:CPICH:CCODE

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:CPICH:CCODE?
```

This query returns the CPICH channelization code, which is always set to zero.

:DLINK:CPICH:POWER

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:CPICH:POWER <val>

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:CPICH:POWER?

This command sets the CPICH power level. The variable <val> is expressed in decibels (dB).

***RST** 3.30000000E+000

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:CPICH[:STATE]

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:CPICH [:STATE] ON | OFF | 1 | 0

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:CPICH [:STATE] ?

This command turns the CPICH on or off.

***RST** 1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:CCODE

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:DPCH:CCODE <val>

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:DPCH:CCODE?

This command sets the downlink DPCH channel code number.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

*RST	10
Range	0–511
Remarks	<p>Setting the command parameter while the signal is active also requires executing the apply command. Refer to “DLINK:APPLY” on page 671.</p> <p>The channel code is coupled with the slot format and all other physical channel codes. If the channel code exceeds the limits of the slot format or if it is not orthogonal with all other physical channel codes, the apply function (downlink apply command) will not work. If any channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.</p>

:DLINK:DPCH:DATA

Supported	E4438C with Option 419
	[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:DPCH:DATA PN9 PN15 FIX4 DCH "<file name>"
	[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:DPCH:DATA?

This command configures the downlink DPCH data pattern.

DCH	This selects the transport channel as the data source. The DCH selection is not available for a DPCH slot format of 16.
"<file name>"	This represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “ File Overview ” on page 668 for more information on files.
*RST	PN9
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “ DLINK:APPLY ” on page 671.

:DLINK:DPCH:DATA:FIX4

Supported	E4438C with Option 419
	[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:DPCH:DATA:FIX4 <val>
	[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:DPCH:DATA:FIX4?

This command sets the downlink DPCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

*RST	0
Range	0–15
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6:BSIZE

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6  
:BSIZE <val>  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :BSIZE?
```

This command sets the block size for the selected downlink DCH.

*RST	20
Range	0–5000
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671. The number of data bits per DCH cannot exceed 200,000. To maintain this data bit limit, the ESG calculates the product of the block size and the number of blocks. If the product of these two parameters exceeds 200,000, the apply function (downlink apply command) will not work.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6:CRC

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :CRC 0 | 8 |  
12 | 16 | 24  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :CRC?
```

This command sets the number of CRC bits for the selected downlink DCH.

*RST	8
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:DPCH:DCH[1]|2|3|4|5|6:CTYPE****Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:DPCH:DCH[1]|2|3|4|5|6:CTYPE
HCONv|TCONv|TURBo|NONE
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:DPCH:DCH[1]|2|3|4|5|6:CTYPE?
```

This command sets the coder type for the selected downlink DCH.

HCONv This choice selects the 1/2 rate convolutional encoder.

TCONv This choice selects the 1/3 rate convolutional encoder.

TURBo This choice selects the turbo coder.

NONE This choice selects no coding.

***RST** HCON

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:DCH[1]|2|3|4|5|6:DATA**Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:DPCH:DCH[1]|2|3|4|5|6:DATA PN9|
PN15|FIX4|"<file name>"
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:DPCH:DCH[1]|2|3|4|5|6:DATA?
```

This command configures the data for the selected downlink DCH.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “File Overview” on page 668 for more information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:FIX4

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA:  
FIX4 <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA:FIX4?
```

This command sets the repeating 4-bit binary data pattern for the selected downlink DCH. The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6:NBLocks

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :  
NBLocks <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :NBLocks?
```

This command sets the number of data blocks for the selected downlink DCH.

***RST** 1

Range 0–512

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

The number of data bits per DCH cannot exceed 200,000. To maintain this data bit limit, the ESG calculates the product of the block size and the number of blocks. If the product of these two parameters exceeds 200,000, the apply function (downlink apply command) will not work.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6:RMAtribute**

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [1] | 2 | 3 | 4 | 5 | 6 :
RMAtribute <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [1] | 2 | 3 | 4 | 5 | 6 :
RMAtribute?
```

This command sets the rate matching attribute for the selected downlink DCH.

***RST** 1

Range 1–256

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6:TTI

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [1] | 2 | 3 | 4 | 5 | 6 :TTI 10 | 20 |
40 | 80
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [1] | 2 | 3 | 4 | 5 | 6 :TTI?
```

This command sets the TTI for the selected downlink DCH.

The choices are expressed in millisecond (ms).

***RST** 10

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6[:STATe]

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [1] | 2 | 3 | 4 | 5 | 6 [ :STATe]
ON | OFF | 1 | 0
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:DCH [1] | 2 | 3 | 4 | 5 | 6 [ :STATe] ?
```

This command turns the selected downlink DCH on or off; DCH1 is always on.

***RST** DCH 1: 1 DCH 2–6: 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

The apply command will not work and the ESG will report an error if you turn on a DCH where lower numbered DCHs are off. For example, turning on DCH5 requires turning on DCH2–4. The reverse is true when turning off the DCHs.

:DLINK:DPCH:POWer

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:POWer <val>  
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:POWer?
```

This command sets the downlink DPCH power level.

***RST** –1.02000000E+001

Range –40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:SFORmat

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:SFORmat <val>  
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :DLINK:DPCH:SFORmat?
```

This command configures the downlink DPCH slot format.

***RST** 0

Range 0–16

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

The slot format is coupled with the channel code, so a change in one value may require a change in the other. If the channel code exceeds the limits of the slot format or if it is not orthogonal with all other physical channel codes, the apply function (downlink apply command) will not work.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:DPCH:SSCOffset**

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:DPCH:SSCOffset <val>

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:DPCH:SSCOffset?

This command sets the downlink DPCH secondary scrambling code offset.

***RST** +0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:TFCI

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:DPCH:TFCI <val>

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:DPCH:TFCI?

This command sets the TFCI 10-bit pattern for the downlink DPCH.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** +0

Range 0–1023

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

Setting the TFCI bits is optional; they describe the type of service in use, for example voice or data.

:DLINK:DPCH:TOFFset

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:DPCH:TOFFset <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:DPCH:TOFFset?
```

This command adjusts the downlink DPCH timing offset.

The variable <val> is expressed in chips.

***RST** +0

Range 0–149

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:TPC:NSTeps

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:DPCH:TPC:NSTeps <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:DPCH:TPC:NSTeps?
```

This command sets the number of steps for the down and up (DUP) or up and down (UDOWn) TPC pattern selections.

***RST** +1

Range 1–80

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:DPCH:TPC:PATtern

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:DPCH:TPC:PATtern UDOWn | DUP | UALL |  
DALL | "<file name>"  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:DPCH:TPC:PATtern?
```

This command configures the downlink DPCH TPC pattern for increasing or decreasing, or increasing and decreasing the UE power level.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])

UDOWn	The TPC pattern repetitively steps up and down.
DUP	The TPC pattern repetitively steps down and up.
UALL	The TPC pattern consecutively steps up.
DALL	The TPC pattern consecutively steps down.
"<file name>"	This variable represents a TPC pattern file stored in signal generator memory. The pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “ File Overview ” on page 668 for more information on files.
*RST	UDOW
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “ :DLINK:APPLY ” on page 671. Each step in a TPC pattern signals an increase or decrease of 1 dB in the UE output power level.

:DLINK:DPCH:TRPosition

Supported E4438C with Option 419

[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :DLINK:DPCH:TRPosition?

This query returns the downlink DPCH transport channel position that is always set to FIX.

:DLINK:DPCH[:STATe]

Supported E4438C with Option 419

[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :DLINK:DPCH [:STATe] ON | OFF | 1 | 0

[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :DLINK:DPCH [:STATe] ?

This command turns the downlink DPCH on or off.

***RST** 1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:EAGCh:AGScope

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:EAGCh:AGScope ALL_0 | ALL_1 |
```

```
"<file name>"
```

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:EAGCh:AGScope?
```

This command sets an absolute scope pattern.

ALL_0, ALL_1 These choices configure an absolute grant scope pattern.

"<file name>" This variable represents an absolute scope pattern value. Create this file either by using the absolute grant scope pattern Data Type Entry window and downloading the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- absolute grant scope of 1, 0 using a 1-bit pattern, 1, 0. In the file, do not use delimiters between subframes; enter subframe bits as a binary string.

When creating a pattern, you can determine the number of active subframes, up to 1,280, which are numbered from 0 to 1,279. A subframe is active when it contains 1 bit.

***RST** ALL_0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:EAGCh:AGValue

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:EAGCh:AGValue
```

```
ALL_0 | ALL_1 | ALL_2 | ALL_3 | ALL_4 | ALL_5 | ALL_6 | ALL_7 | ALL_8 | ALL_9 | ALL_10 | ALL_1
```

```
1 | ALL_12 | ALL_13 | ALL_14 | ALL_15 | ALL_16 | ALL_17 | ALL_18 | ALL_19 | ALL_20 | ALL_21 |
```

```
ALL_22 | ALL_23 | ALL_24 | ALL_25 | ALL_26 | ALL_27 | ALL_28 | ALL_29 | ALL_30 | ALL_31 |
```

```
"<file name>"
```

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:EAGCh:AGValue?
```

This command sets an absolute grant value pattern.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

ALL_1 to ALL_31 These choices configure an absolute grant value pattern.

"<file name>" This variable represents an absolute grant pattern value. Create this file either by using the absolute grant value pattern Data Type Entry window and downloading the file to the ESG or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- absolute grant value of 0– 31 using an 8-bit pattern, 00000000 to 00011111
In the file, do not use delimiters between subframes; enter subframe bits as a binary string.

When creating a pattern, you can determine the number of active subframes, up to 1,280, which are numbered from 0 to 1,279. A subframe is active when it contains 8 bits. If a subframe contains at least 1 bit, but less than 8 bits, the apply function (downlink apply command) will not work.

***RST** ALL_0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 671](#).

:DLINK:EAGCh:CCODE

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:EAGCh:CCODE <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:EAGCh:CCODE?
```

This command sets the downlink E-AGCH channel code number.

***RST** 14

Range 0–127

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 671](#).

The channel code is coupled with the slot format and all other physical channel codes. Set the channel code so it does not exceed the limits of the slot format and ensure that all physical channel codes are orthogonal to each other. If any of the channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

:DLINK:EAGCh:ERNTI

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:EAGCh:ERNTI <val>  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:EAGCh:ERNTI?
```

This command sets E-RNTI (E-DCH Radio Network Temporary Identifier).

***RST** 0

Range 0–255

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:EAGCh:Power

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:EAGCh:POWER <val>  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:EAGCh:POWER?
```

This command sets the power level for the E-AGCH.

***RST** –20.00000000E+000

Range –40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:EAGCh[:STATe]

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:EAGCh [ :STATe ] ON | OFF | 1 | 0  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:EAGCh [ :STATe ] ?
```

This command turns the downlink E-AGCH on or off.

***RST** 1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:EHICH:CCODE**Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:CCODE <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:CCODE?

This command sets the downlink E-HICH channel code number.

***RST** 5**Range** 0–127**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

The channel code is coupled with the slot format and all other physical channel codes. Set the channel code so it does not exceed the limits of the slot format and ensure that all physical channel codes are orthogonal to each other. If any of the channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

:DLINK:EHICH:INDicator**Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:INDicator

ALL_1|ALL_0|ALL_M1|"<file name>"

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:INDicator?

This command sets a HARQ acknowledgement indicator pattern.

ALL_<val> These choices configure an HARQ acknowledgement indicator pattern.

"<file name>" This variable represents an HARQ pattern file stored in signal generator memory. Create this file either by using the HARQ pattern Data Type Entry window and downloading the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

HARQ pattern of 1, 0, –1 using at 2-bit pattern: 01, 00, 10.

In the file, do not use delimiters between subframes; enter the subframe bits as a binary string.

When creating a pattern, you can determine the number of active subframes, from 1 to 1,280. The subframes are numbered 0 to 1,279. A subframe is active when it contains 1 bit.

***RST** ALL_1
Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:EHICH:POWER

Supported E4438C with Option 419
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:POWER <val>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:POWER?

This command sets the power level for the E-HICH.

***RST** -20.00000000E+000
Range -40 to 0
Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:EHICH:SSINDEX

Supported E4438C with Option 419
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:SSINDEX <val>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:SSINDEX?

This command sets the downlink E-HICH signature sequence index number.

***RST** 0
Range 0–39
Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:EHICH:TOFFSET

Supported E4438C with Option 419
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:TOFFSET <val>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:EHICH:TOFFSET?

This command adjusts the downlink E-HICH timing offset (tE-HICH).

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

*RST	–17920
Range	–17920, –10240, 5120, 12800, 20480, 28160, 43520, 51200
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:EHICH[:STATE]

Supported E4438C with Option 419

```
[ :SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : DLINK : EHICH [ : STATE ] ON | OFF | 1 | 0
[ : SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : DLINK : EHICH [ : STATE ] ?
```

This command turns the downlink E-HICH on or off.

*RST	1
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:ERGCh:CCODE

Supported E4438C with Option 419

```
[ :SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : DLINK : ERGCh : CCODE <val>
[ : SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : DLINK : ERGCh : CCODE ?
```

This command sets the downlink E-RGCH channel code number.

*RST	6
Range	0–127
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:ERGCh:POWER

Supported E4438C with Option 419

```
[ :SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : DLINK : ERGCh : POWER <val>
[ : SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : DLINK : ERGCh : POWER ?
```

This command sets the power level for the E-ERGCH.

3GPP W-CDMA HSPA Subsystem—Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

*RST	–20.00000000E+000
Range	–40 to 0
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:ERGCh:RGValue

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:ERGCh:RGValue
ALL_1|ALL_0|ALL_M1|"<file name>"
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:ERGCh:RGValue?
```

This command sets a relative grant pattern.

ALL_<val> These choices configure a relative grant value pattern

"<file name>" This variable represents a relative grant value pattern file stored in signal generator memory. Create this file either by using the relative grant value pattern Data Type Entry window and downloading the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- relative grant value pattern of 1, 0, –1 using at 2-bit pattern: 01, 00, 10. In the file, do not use delimiters between subframes; enter subframe bits as a binary string.

When creating a pattern, you can determine the number of active subframes, from 1 to 1,280. The subframes are numbered 0 to 1,279. A subframe is active when it contains 1 bit.

***RST** ALL_1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:ERGCh:SSINDEX

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:ERGCh:SSINDEX <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:ERGCh:SSINDEX?
```

This command sets the downlink E-RGCH signature sequence index number.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

*RST	0
Range	0–39
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:ERGCh:TOFFset

Supported E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:ERGCh:TOFFset <val>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:ERGCh:TOFFset?
```

This command adjusts the downlink E-RGCH timing offset (tE-RGCH).

The variable <val> is expressed in chips.

*RST	–17920
Range	–17920, –10240, 5120, 12800, 20480, 28160, 43520, 51200
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:ERGCh[:STATe]

Supported E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:ERGCh[:STATe] ON|OFF|1|0
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:ERGCh[:STATe]?
```

This command turns the downlink E-RGCH on or off.

*RST	0
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:FILTer

Supported E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:FILTer RNYQuist|NYQuist|
GAUSSian|RECTangle|IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|
"<user FIR>"
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:FILTer?
```

This command selects the downlink filter type.

IS95	This filter meets the criteria of the IS-95 standard.
IS95_EQ	This filter is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard and is best suited for IS-95 baseband filtering.
IS95_MOD	This filter meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.
IS95_MOD_EQ	This filter is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.
UGGaussian	This is a GSM Gaussian filter with a fixed BbT value of 0.300.
AC4Fm	This is a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.
"<user FIR>"	This variable represents any FIR filter file stored in signal generator memory. Refer to “File Overview” on page 668 for more information on files.
*RST	RNYQ
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671 .

:DLINK:FILTer:ALPHa

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:FILTer:ALPHa <val>
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:FILTer:ALPHa?
```

This command sets the downlink Nyquist or root Nyquist filter alpha value.

***RST** +2.20000000E-001

Range 0-1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 671](#).

Executing this command while a filter other than Nyquist or root Nyquist is selected changes the parameter value, but it is not used by the signal generator until one of the Nyquist filters is selected.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:FILTer:BBT**

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:FILTer:BBT <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:FILTer:BBT?
```

This command sets the downlink Gaussian filter BbT value.

***RST** +5.00000000E-001

Range 0–1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

Executing this command while a filter other than the Gaussian filter is selected changes the parameter value, but it is not used by the signal generator until the Gaussian filter is selected.

:DLINK:FILTer:CHANnel

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:FILTer:CHANnel EVM|ACP
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:FILTer:CHANnel?
```

Execute this command to optimize a downlink filter for minimized EVM or for minimized ACP.

EVM This choice provides the most ideal passband.

ACP This choice improves stopband rejection for the root Nyquist and Nyquist filters.

***RST** EVM

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

To change the filter selection, refer to “[:DLINK:FILTer](#)” on page 690.

:DLINK:HSBurst

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSBurst ON|OFF|1|0
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSBurst?
```

This command sets the handling of the off slot periods for the downlink HSDPA channels.

ON 1	This choice turns off the ESG ALC feature and uses DTX during the off slots.
OFF 0	This choice continuously transmits the HSDPA channels filling the off slots with dummy bits.
*RST	0
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:HSDPa:AMC:CQIMapping:UECategory

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:AMC:CQIMapping:
UECategory <val>
```

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:AMC:CQIMapping:UECategory?
```

This command sets the UE category that determines the CQI mapping table per the 3GPP standards.

***RST** 5

Range 1–12

Remarks To use this command's parameter in a setup, you must also set AMC as the feedback selection. Refer to the “:DLINK:HSDPa:FCONtrol” on page 694 for selecting the feedback type.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:HSDPa:AMC:CPATtern

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:AMC:CPATtern ALL_1 | ALL_2 |
ALL_3 | ALL_4 | ALL_5 | ALL_6 | ALL_7 | ALL_8 | ALL_9 | ALL_10 | ALL_11 | ALL_12 | ALL_13 |
ALL_14 | ALL_15 | ALL_16 | ALL_17 | ALL_18 | ALL_19 | ALL_20 | ALL_21 | ALL_22 | ALL_23 |
ALL_24 | ALL_25 | ALL_26 | ALL_27 | ALL_28 | ALL_29 | ALL_30 | "<file_name>"
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:AMC:CPATtern?
```

This command sets a simulated UE CQI pattern that determines HSDPA1's response including the modulation type (QPSK or 16QAM) and the constellation version for 16QAM per the set UE category.

ALL_1 to ALL_30 These choices configure a simulated UE ACK response with a single CQI value for 1,280 subframes.

"<file name>" This variable represents a CQI pattern file stored in signal generator memory.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])

Create this file either by using the AMC CQI pattern Data Type Entry window and downloading the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- CQI value of 1–30 using an 8-bit pattern, 00000001 to 00011110
- DTX is represented by 11111111

In the file, do not use delimiters between subframes; enter subframe bits as a binary string.

When creating a pattern, you can determine the number of active subframes from 1 to 1,280. The subframes are numbered 0 to 1,279. A subframe is active when it contains 8-bits. If a subframe contains at least 1-bit but less than 8-bits, the apply function (downlink apply command) will not work.

***RST** ALL_21

Remarks To use this command's parameter in a setup, you must also set AMC as the feedback selection. Refer to the “[:DLINK:HSDPa:FCONtrol](#)” on page 694 for selecting the feedback type.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:HSDPa:FCONtrol

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:FCONtrol NONE | HARQ | AMC
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:FCONtrol ?
```

This command sets the HSDPA1 feedback control type.

NONE This choice turns off the feedback control.

HARQ This choice provides UE feedback using the HARQ process. This selection provides the capability of configuring a simulated UE ACK/NACK response, setting the maximum number of HARQ transmissions, and providing up to eight different RV parameters.

AMC This choice provides UE feedback using adaptive modulation coding. This selection provides the capability of configuring a simulated UE CQI response aligned with a UE category input.

***RST** NONE

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:HSDPa:HARQ:APATtern

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:HARQ:APATtern ACK_ALL |  
"<file name>"  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:HARQ:APATtern?
```

This command sets a simulated UE ACK/NACK pattern that determines HSDPA1's HARQ response.

ACK_ALL This choice configures 1,280 subframes for a simulated ACK only response.

"<file name>" This variable represents an ACK pattern file stored in signal generator memory. Create this file either by using the HARQ ACK/NACK pattern Data Type Entry window and download the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- An ACK response is represented by 00.
- A NACK response is represented by 01.
- DTX is represented by 10.

In the file, do not use delimiters between subframes; enter subframe bits as a binary string.

When creating a pattern, you can determine the number of active subframes from 1 to 1,280. The subframes are numbered 0 to 1,279. A subframe is active when it contains 2-bits. If a subframe contains only 1-bit, the apply function (downlink apply command) will not work.

***RST** ACK_ALL

Remarks To use this command's parameter in a setup, you must also set HARQ as the feedback selection. Refer to the “[:DLINK:HSDPa:FCONtrol](#)” on page 694 for selecting the feedback type.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:HSDPa:HARQ:MNHTrans**Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:HSDPa:HARQ:MNHTrans <val>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:HSDPa:HARQ:MNHTrans?
```

This command configures the HSDPA1 maximum number of HARQ transmissions for the HARQ function.

Use the command for UE performance testing or for specifying an arbitrary number of HARQ transmissions. When the software encounters a UE NACK response that is set by the HARQ ACK pattern command (see “[:DLINK:HSDPa:HARQ:APATern](#)” on page 695), the software re-sends the same packet payload until either the maximum number of HARQ transmissions is reached or a simulated ACK response is encountered. Whenever the software re-sends the same packet payload, it also transmits another RV parameter that is configured by the RV sequence command.

***RST** 1**Range** 1–8

Remarks To use this command's parameter in a setup, you must also set HARQ as the feedback selection. Refer to the “[:DLINK:HSDPa:FCONtrol](#)” on page 694 for selecting the feedback type.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:HSDPa:HARQ:RVSequence[1]|2|3|4|5|6|7|8**Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:HSDPa:HARQ:RVSequence [1] | 2 | 3 | 4 |
5 | 6 | 7 | 8 <val>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:HSDPa:HARQ:RVSequence [1] | 2 | 3 | 4 |
5 | 6 | 7 | 8?
```

This command sets the HSDPA1 RV parameter sequence used with the maximum number of HARQ transmission setting. You can set eight different RV parameters for the RV sequence.

During simulated ACK responses, the software uses the first RV parameter. When the software encounters a simulated NACK response, it sends data using the next RV parameter. The software keeps incrementing to the next RV parameter in the sequence until it receives a simulated ACK response. When the software encounters an ACK response, the RV sequence resets to the first RV parameter.

*RST	0
Range	0–7
Remarks	<p>To use this command's parameter in a setup, you must also set HARQ as the feedback selection. Refer to the “:DLINK:HSDPa:FCONtrol” on page 694 for selecting the feedback type.</p> <p>Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.</p>

:DLINK:HSDPa[1] | 2 | 3 | 4:BSINfo

Supported	E4438C with Option 419
	<pre>[:SOURce]:RADio:WCDMa:HSPA[:BBG]:DLINK:HSDPa[1] 2 3 4:BSINfo <val> [:SOURce]:RADio:WCDMa:HSPA[:BBG]:DLINK:HSDPa[1] 2 3 4:BSINfo?</pre>
	<p>This command sets the HS-DSCH block size. HSDPA1 is the only HSDPA channel configuration that supports the HS-DSCH; however, the block size information parameter is also available for HSDPA2–4 for HS-SCCH coding purposes.</p>
*RST	36
Range	0–63
Remarks	<p>Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.</p>

:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDsch:COFFset

Supported	E4438C with Option 419
	<pre>[:SOURce]:RADio:WCDMa:HSPA[:BBG]:DLINK:HSDPa[1] 2 3 4:HSPDsch: COFFset <val> [:SOURce]:RADio:WCDMa:HSPA[:BBG]:DLINK:HSDPa[1] 2 3 4:HSPDsch:COFFset?</pre>
	<p>This command sets the HS-PDSCH code offset. The code offset is used in determining the HS-PDSCH channel code.</p>
*RST	HSDPA1: 4 HSDPA2: 8 HSDPA3: 9 HSDPA4: 10
Range	1–16
Remarks	<p>Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.</p> <p>Set all physical channel codes orthogonal to each other. For any channel codes that fail this criteria, the apply function (downlink apply command) will not work.</p>

3GPP W-CDMA HSPA Subsystem—Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDSch:DATA**

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [ 1 ] | 2 | 3 | 4 :HSPDSch:DATA
PN9 | FIX4 | "<file name>" | DSCH
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [ 1 ] | 2 | 3 | 4 :HSPDSch:DATA?
```

This command configures the HS-PDSCH data type.

DSCH This choice is the HS-DSCH selection that is supported on only HSDPA1. Selecting the DSCH choice for HSDPA2–4 will generate an error.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to [“File Overview” on page 668](#) for more information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 671](#).

:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDSch:DATA:FIX4

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [ 1 ] | 2 | 3 | 4 :HSPDSch:DATA:
FIX4 <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [ 1 ] | 2 | 3 | 4 :HSPDSch:DATA:
FIX4?
```

This command sets the HS-PDSCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 671](#).

:DLINK:HSDPa:HSPDSch:DSCH:DATA

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:DATA  
PN9 | FIX4 | "<file name>"  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:DATA?
```

This command defines the HS-DSCH data type for HSDPA1. The HS-DSCH is not supported on HSDPA2–4.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to [“File Overview” on page 668](#) for more information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 671](#).

:DLINK:HSDPa:HSPDSch:DSCH:DATA:FIX4

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:DATA:  
FIX4 <val>  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:DATA:FIX4?
```

This command defines the HS-DSCH repeating 4-bit binary data pattern for HSDPA1. The HS-DSCH is not supported on HSDPA2–4.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 671](#).

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:HSDPa:HSPDSch:DSCH:IRBSize****Supported** E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:IRBSize <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:IRBSize?
```

This command sets the HS-DSCH IR buffer size per the HARQ process for HSDPA1. The HS-DSCH is not supported on HSDPA2–4.

***RST** 9600**Range** 960–28800

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:HSDPa:HSPDsch:NCODE**Supported** E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa:HSPDsch:NCODE <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa:HSPDsch:NCODE?
```

This command sets number of codes for the HS-PDSCH on HSDPA1. HSDPA2–4 do not support multicodes.

***RST** 1**Range** 1–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

Set all physical channel codes so they are orthogonal to each other. If any of the channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDsch:POWer**Supported** E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [ 1 ] | 2 | 3 | 4 :HSPDsch:
POWer <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [ 1 ] | 2 | 3 | 4 :HSPDsch:POWer?
```

This command sets the HS-PDSCH power level.

The variable <val> is expressed in decibels (dB).

***RST** -1.02000000E+001
Range -40 to 0
Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDsch:SFORmat

Supported E4438C with Option 419
[:SOURCE]:RADIo:WCDMa:HSPA[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDsch:SFORmat
0 | 1
[:SOURCE]:RADIo:WCDMa:HSPA[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDsch:SFORmat?

This command sets the HS-PDSCH slot format.

0 This sets the modulation type to QPSK.
1 This sets the modulation type to 16QAM.

***RST** 1
Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDsch[:STATe]

Supported E4438C with Option 419
[:SOURCE]:RADIo:WCDMa:HSPA[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDsch[:STATe]
ON | OFF | 1 | 0
[:SOURCE]:RADIo:WCDMa:HSPA[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDsch[:STATe]?

This command turns the selected HS-PDSCH on or off.

***RST** HSDPA1: 1 HSDPA2–4: 0
Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

The HS-PDSCH turns on only when the HS-SCCH is on. Turning off the HS-SCCH also turns off the active HS-PDSCH. To turn the HS-SCCH on or off, see “:DLINK:HSDPa[1]|2|3|4[:STATe]” on page 706.

3GPP W-CDMA HSPA Subsystem—Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:HSDPa[1]|2|3|4:HSSCch:CCODE****Supported** E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4 :HSSCch:CCODE <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4 :HSSCch:CCODE?
```

This command sets the HS-SCCH channel code.

***RST** HSDPA1: 4 HSDPA2: 5 HSDPA3: 6 HSDPA4: 7**Range** 1–127**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

Set all physical channel codes so they are orthogonal to each other. If any of the channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

:DLINK:HSDPa[1]|2|3|4:HSSCch:DATA**Supported** E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4 :HSSCch:DATA
PN9 | FIX4 | "<file name>" | STD
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4 :HSSCch:DATA?
```

This command sets the data type for the selected downlink HS-SCCH.

STD This choice configures the bit field as defined by the 3GPP standards.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “[File Overview](#)” on page 668 for more information on files.

***RST** STD**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:HSDPa[1] | 2 | 3 | 4:HSSCch:DATA:FIX4

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:HSDPa [1] | 2 | 3 | 4 :HSSCch:DATA:FIX4 <val>

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:HSDPa [1] | 2 | 3 | 4 :HSSCch:DATA:FIX4?

This command sets the HS-SCCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:HSDPa[1] | 2 | 3 | 4:HSSCch:POWER

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:HSDPa [1] | 2 | 3 | 4 :HSSCch:POWER <val>

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :DLINK:HSDPa [1] | 2 | 3 | 4 :HSSCch:POWER?

This command sets the HS-SCCH power level.

The variable <val> is expressed in decibels (dB).

***RST** -1.02000000E+001

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:HSDPa[1]|2|3|4:ITTI****Supported** E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4 :ITTI <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4 :ITTI?
```

This command sets the static inter-TTI pattern value for the selected HSDPA.

The variable <val> is expressed in subframes (one subframe = 2 ms).

***RST** 8**Range** 1–16

Remarks To use a static pattern, select FIX as the choice for the [:DLINK:HSDPa\[1\]|2|3|4:ITTI:PATTERN](#) command.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:HSDPa[1]|2|3|4:ITTI:PATTERN**Supported** E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4 :ITTI:PATTERN
FIX | "<file name>"
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4 :ITTI:PATTERN?
```

This command selects which method sets the inter-TTI pattern for the selected HSDPA.

FIX This choice enables a static pattern. To configure the pattern, see “[:DLINK:HSDPa\[1\]|2|3|4:ITTI](#)”.

"<file name>" This variable represents an inter-TTI pattern file stored in signal generator memory. Creating and using a file provides the option of having a flexible inter-TTI pattern where you can vary the distance between HS-PDSCH transmissions. To create a file, use one or a combination of the following methods:

- To create a file internal to the software, use the inter-TTI user pattern editor.
- To create a file external to the software, use a text editor.

For more information, see the Signal Studio for 3GPP W-CDMA HSPA software online help.

The file name follows the form <project name>-ITTIx, where 'x' is the HSDPA number from one to four. The inter-TTI pattern must contain at least one bit, or the apply function (downlink apply command) will not work.

***RST** FIX

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:HSDPa:NHPRocess

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:NHPRocess <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa:NHPRocess?
```

This command sets the HS-DSCH number of HARQ processes for HSDPA1. For HSDPA2–4, this parameter is fixed at one and is used only for HS-SCCH coding purposes.

***RST** 4

Range 1–8

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:HSDPa[1] | 2 | 3 | 4:RVParameter

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4:RVParameter <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:HSDPa [1] | 2 | 3 | 4:RVParameter?
```

This command sets the HS-DSCH RV parameter. For HSDPA2–4, which do not support an HS-DSCH, this parameter is used only for HS-SCCH coding purposes.

***RST** 0

Range 0–7

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:HSDPa[1]|2|3|4:UEID****Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:HSDPa[1]|2|3|4:UEID <val>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:HSDPa[1]|2|3|4:UEID?
```

This command sets the UEID.

RST** HSDPA1: 0 HSDPA2: 1 HSDPA3: 2 HSDPA4: 3**Range** 0–65535**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.**:DLINK:HSDPa[1]|2|3|4[:STATE]*Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:HSDPa[1]|2|3|4[:STATE] ON|OFF|
1|0
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:HSDPa[1]|2|3|4[:STATE]?
```

This command turns the selected downlink HSDPA channel on or off.

- | | |
|---------|---|
| ON (1) | <ul style="list-style-type: none"> • Turns on the HS-SCCH for the selected HSDPA. • Enables turning on the HS-PDSCH for the selected HSDPA. |
| OFF (0) | <ul style="list-style-type: none"> • Turns off the HS-SCCH for the selected HSDPA. • Turns off the active HS-PDSCH for the selected HSDPA. |

***RST** HSDPA1: 1 HSDPA2–4: 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

Refer to “:DLINK:HSDPa[1]|2|3|4:HSPDSch[:STATE]” on page 701 for turning the HS-PDSCH on or off.

An HSDPA consists of a HS-SCCH and a HS-PDSCH; the HS-DSCH is supported on only HSDPA1.

:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:CCODE

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :CCODE <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :CCODE?
```

This command sets the channel code for the selected downlink OCNS.

*RST	OCNS1: 2	OCNS2: 3	OCNS3: 4	OCNS4: 5
	OCNS5: 6	OCNS6: 7	OCNS7: 8	OCNS8: 9
	OCNS9: 10	OCNS10: 11	OCNS11: 12	OCNS12: 13
	OCNS13: 14	OCNS14: 15	OCNS15: 16	OCNS16: 17

Range 1–127

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:DATA

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :DATA PN9 | PN15
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :DATA?
```

This command configures the data pattern for the selected downlink OCNS.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:MODulation****Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:MODulation<val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:MODulation?

This command sets the modulation for the selected downlink OCNS.

RST** QPSK**Range** QPSK | QAM16**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.**:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:POWer*Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:POWer <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:POWer?

This command sets the power level for the selected downlink OCNS.

The variable <val> is expressed in units of dB.

***RST** OCNS1: -6 OCNS2: -8 OCNS3: -8 OCNS4: -10
OCNS5: -7 OCNS6: -9 OCNS7-16: -10**Range** -40 to 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.**:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:SF****Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:SF<val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:SF?

This command sets the spreading factor for the selected downlink OCNS.

***RST** 128

Range 16 | 128

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:SSCoffset

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:OCNS [ 1 ] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :SSCoffset <val>
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:OCNS [ 1 ] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :SSCoffset?
```

This command sets the secondary scrambling code offset for the selected downlink OCNS.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:TOFFset

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:OCNS [ 1 ] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :TOFFset <val>
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:OCNS [ 1 ] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :TOFFset?
```

This command adjusts the timing offset for the OCNS.

***RST** OCNS1: 1 OCNS2: 2 OCNS3: 3 OCNS4: 4
 OCNS5: 5 OCNS6: 6 OCNS7: 7 OCNS8: 8
 OCNS9: 9 OCNS10: 10 OCNS11: 11 OCNS12: 12
 OCNS13: 13 OCNS14: 14 OCNS15: 15 OCNS16: 16

Range 0–149

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:OCNS[1|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16[:STATE]****Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:OCNS[1|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16[:STATE] ON|OFF|1|0

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:OCNS[1|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16[:STATE]?

This command turns the selected OCNS on or off.

RST** 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.**:DLINK:PCCPch:BCH:DATA*Supported** E4438C with Option 419[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PCCPch:BCH:DATA PN9|PN15|FIX4|"
"<file name>"

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PCCPch:BCH:DATA?

This command sets the BCH data format that is transmitted on the P-CCPCH.

"
"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “[File Overview](#)” on page 668 for more information on files.***RST** FIX4**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 671.**:DLINK:PCCPch:BCH:DATA:FIX4****Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PCCPch:BCH:DATA:FIX4 <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PCCPch:BCH:DATA:FIX4?

This command sets the BCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

*RST	0
Range	0–15
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:PCCPch:CCODE

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PCCPch:CCODE <val>  
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PCCPch:CCODE?
```

This command sets the P-CCPCH channel code.

*RST	+1
Range	0–255
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671. Set all physical channel codes so they are orthogonal to each other. If any of the channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

:DLINK:PCCPch:POWer

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PCCPch:POWer <val>  
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PCCPch:POWer?
```

This command sets the P-CCPCH power level.

The variable <val> is expressed in decibels (dB).

*RST	–5.30000000E+000
Range	–40 to 0
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:PCCPch[:STATE]****Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PCCPch[:STATE] ON|OFF|1|0
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PCCPch[:STATE]?
```

This command turns the P-CCPCH on or off.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.**:DLINK:PICH:CCODE*Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PICH:CCODE <val>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PICH:CCODE?
```

This command sets the PICH channelization code.

***RST** +3**Range** 0–255**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

Set all physical channel codes so they are orthogonal to each other. If any of the channel codes fail to meet this criteria, the downlink apply command will not work.

:DLINK:PICH:DATA**Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PICH:DATA PN9|PN15|FIX4|
"<file name>"
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:PICH:DATA?
```

This command sets the PICH data type.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “File Overview” on page 668 for more information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:PICH:DATA:FIX4

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PICH:DATA:FIX4 <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PICH:DATA:FIX4?
```

This command sets the PICH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:PICH:POWer

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PICH:POWer <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PICH:POWer?
```

This command sets the PICH power level.

The variable <val> is expressed in decibels (dB).

***RST** -8.300000000E+000

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])**:DLINK:PICH[:STATe]****Supported** E4438C with Option 419

```
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:DLINK:PICH[:STATe] ON|OFF|1|0
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:DLINK:PICH[:STATe]?
```

This command turns the PICH on or off.

RST** 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.**:DLINK:POLarity*Supported** E4438C with Option 419

```
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:DLINK:POLarity NORMal|INVerted|INVert
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:DLINK:POLarity?
```

This command selects the phase polarity of the downlink signal.

NORMal This choice selects normal polarity.**INVerted, INVert** These choices perform the same function, inverting the internal Q signal.***RST** NORM**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. For more information, refer to “:DLINK:APPLY” on page 671.**:DLINK:PSCH:POWer****Supported** E4438C with Option 419

```
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:DLINK:PSCH:POWer <val>
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:DLINK:PSCH:POWer?
```

This command sets the PSCH power level.

The variable <val> is expressed in decibels (dB).

***RST** -8.30000000E+000**Range** -40 to 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.

:DLINK:PSCH[:STATe]

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PSCH [ :STATe ] ON | OFF | 1 | 0  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:PSCH [ :STATe ] ?
```

This command turns the PSCH on or off.

***RST** 1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. For more information, refer to “[:DLINK:APPLY](#)” on [page 671](#).

:DLINK:SCRamblecode

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:SCRamblecode <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:SCRamblecode ?
```

This command sets the downlink scramble code number.

***RST** +0

Range 0–511

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on [page 671](#).

:DLINK:SSCH:POWer

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:SSCH:POWer <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :DLINK:SSCH:POWer ?
```

This command sets the SSCH power level. The variable <val> is expressed in decibels (dB)

***RST** –8.30000000E+000

Range –40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on [page 671](#).

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:DLINK:SSCH[:STATE]****Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:SSCH[:STATE] ON|OFF|1|0
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:SSCH[:STATE]?
```

This command turns the SSCH on or off.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.**:DLINK:TXDiversity*Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:TXDiversity NONE|OANT1|OANT2
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:DLINK:TXDiversity?
```

This command selects the downlink signal transmit diversity mode.

NONE This choice disables the transmit diversity mode.

OANT1 This choice selects the transmit diversity openloop antenna 1 mode.

OANT2 This choice selects the transmit diversity openloop antenna 2 mode.

***RST** NONE**Remarks** To configure both antennas (one and two) requires two ESGs.
Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 671.**:LINK****Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:LINK DOWN|UP
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:LINK?
```

This command sets the uplink or downlink mode.

***RST** UP

:ULINK:APPLY

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:APPLY  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:APPLY?
```

This command applies changes to the channel setup and data for active physical and transport channels, immediately starting the channel coding generation process. A progress bar may appear on the ESG display indicating that the new signal parameters are being applied. Turning on the HSPA modulation format also applies the signal parameters.

The query response determines whether or not there is a need to execute the command. It returns the following responses:

0	Command execution is not required.
1	Command execution is required.

NOTE The query response is only valid while the HSPA format is active.

When there is a setting conflict (ESG reports an error) with the range values or coupled parameters, or both, executing the uplink apply command does not apply the new changes until the conflicts are resolved. After resolving the setting conflicts, execute the command to apply the new settings.

:ULINK:AWGN:CN

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:AWGN:CN <val>  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:AWGN:CN?
```

This command sets the uplink in-band carrier to noise ratio (C/N) value using AWGN.

***RST** 0 dB

Range -30 to 30 dB

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [:ULINK:APPLY](#)”.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURce]:RADio:WCDMa:HSPA[:BBG])**:ULINK:AWGN[:STATe]**

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:AWGN [ :STATe ] ON | OFF | 0 | 1
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:AWGN [ :STATe ] ?
```

This command turns the uplink AWGN on or off.

***RST** 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:BBReference:EXTeRnal:MRATe

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:BBReference:EXTeRnal:MRATe
X1 | X2 | X4
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:BBReference:EXTeRnal:MRATe?
```

This command configures the ESG, so it can accept an external baseband generator clock that is a multiple of the internal 3.84 MHz chip clock.

X1 This sets the ESG to accept an external clock rate identical to the chip clock.

X2 This sets the ESG to accept an external clock rate that is two times the rate of the chip clock.

X4 This sets the ESG to accept an external clock rate that is four times the rate of the chip clock.

***RST** X1

:ULINK:BBReference:EXTeRnal[:SOURce]

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:BBReference [ :SOURce ] { INTernal } |
EXTeRnal
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:BBReference?
```

This command selects the baseband generator reference source for the radio uplink channel.

***RST** INT

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:CRATe

Supported E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:CRATe <val>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:CRATe?
```

This command sets the chip rate (in units of samples).

***RST** 3.840000 Mcps

Range .24000 - 4.224 Mcps

:ULINK:DPCCh:CCODE

Supported E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPCCh:CCODE?
```

This query returns the channelization code for the uplink DPCCH. The slot format determines the channelization code in accordance with the 3GPP standards.

:ULINK:DPCCh:DATA

Supported E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPCCh:DATA PN9|PN15|FIX4|STD|
"<file name>"
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPCCh:DATA?
```

This command configures the uplink DPCCH data pattern.

STD This sets the DPCCH bit fields according to the 3GPP standards.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (uplink apply command) will not work. Refer to [“File Overview” on page 668](#) for more information on files.

***RST** STD

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:ULINK:APPLY” on page 717](#).

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:DPCCh:DATA:FIX4****Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPCCh:DATA:FIX4 <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPCCh:DATA:FIX4?

This command sets the uplink DPCCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

RST** 0**Range** 0–15**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.**:ULINK:DPCCh:FBI:PATtern*Supported** E4438C with Option 419[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPCCh:FBI:PATtern PN9|PN15|FIX|
"<file name>"

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPCCh:FBI:PATtern?

This command configures the uplink DPCCH FBI pattern.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (uplink apply command) will not work. Refer to “File Overview” on page 668 for more information on files.

RST** FIX**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.**:ULINK:DPCCh:FBI:PATtern:FIX*Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPCCh:FBI:PATtern:FIX <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPCCh:FBI:PATtern:FIX?

This command sets the 30-bit FBI pattern for the uplink DPCCH.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

3GPP W-CDMA HSPA Subsystem—Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

*RST	+0
Range	0–1073741823
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:DPCCh:POWer

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPCCh:POWer <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPCCh:POWer?
```

This command sets the uplink DPCCH power level.

The variable <val> is expressed in decibels (dB)

*RST	–2.69000000E+000
Range	–40 to 0
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:DPCCh:SFORmat

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPCCh:SFORmat <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPCCh:SFORmat?
```

This command sets the uplink DPCCH slot format.

*RST	+0
Range	0–5
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717. The slot format determines the settings for other parameters in accordance with 3GPP standards.

3GPP W-CDMA HSPA Subsystem—Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])**:ULINK:DPCCh:TFCI****Supported** E4438C with Option 419

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:DPCCh:TFCI <val>

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:DPCCh:TFCI?

This command sets the uplink DPCCH TFCI 10-bit data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only decimal values.

RST** +0**Range** 0–1023**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.**:ULINK:DPCCh:TPC:NSteps*Supported** E4438C with Option 419

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:DPCCh:TPC:NSteps <val>

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:DPCCh:TPC:NSteps?

This command sets the number of steps for the down and up (DUP) or up and down (UDOWn) TPC pattern selections.

The variable <val> is expressed in decibels (dB).

RST** +1**Range** 1–80**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.**:ULINK:DPCCh:TPC:PATtern*Supported** E4438C with Option 419

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:DPCCh:TPC:PATtern

UDOWn|DUP|UALL|DALL|"<file name>"

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:DPCCh:TPC:PATtern?

This command configures the uplink DPCCH TPC pattern for increasing or decreasing, or increasing and decreasing the BTS power level.

3GPP W-CDMA HSPA Subsystem—Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

UDOWN	The TPC pattern repetitively steps up and down.
DUP	The TPC pattern repetitively steps down and up.
UALL	The TPC pattern consecutively steps up.
DALL	The TPC pattern consecutively steps down.
"<file name>"	This variable represents a power pattern file stored in signal generator memory. The pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “File Overview” on page 668 for more information on files.
*RST	UDOW
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717 . Each step in a TPC pattern signals an increase or decrease of 1 dB in the BTS output power level.

:ULINK:DPCCh[:STATe]

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPCCh [ :STATe ] ON | OFF | 1 | 0
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPCCh [ :STATe ] ?
```

This command turns the uplink DPCCH on or off.

***RST** 1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:ULINK:APPLY” on page 717](#).

:ULINK:DPDCh:CCODE

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:CCODE?
```

This query returns the uplink DPDCH channelization code.

The slot format determines the channelization code in accordance with the 3GPP standards. See [“:ULINK:DPDCh:SFORmat” on page 729](#) for setting the slot format.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:DPDCh:DATA**

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DATA PN9 | PN15 | FIX4 | DCH |
"<file name>"
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DATA?
```

This command configures the uplink DPDCH data pattern.

DCH This choice selects the transport channel as the data source.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (uplink apply command) will not work. Refer to [“File Overview” on page 668](#) for more information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:ULINK:APPLY” on page 717](#).

:ULINK:DPDCh:DATA:FIX4

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DATA:FIX4 <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DATA:FIX4?
```

This command sets the uplink DPDCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:ULINK:APPLY” on page 717](#).

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:BSIZE

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :  
BSIZE <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :BSIZE?
```

This command sets the block size for the selected uplink DCH.

***RST** 20

Range 0–5000

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:ULINK:APPLY](#)” on page 717.

The number of data bits per DCH cannot exceed 200,000. To maintain this data bit limit, the ESG calculates the product of the block size and the number of blocks. If the product of these two parameters exceeds 200,000, the apply function (uplink apply command) will not work.

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:CRC

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :CRC  
0 | 8 | 12 | 16 | 24
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :CRC?
```

This command sets the number of CRC bits for the selected uplink DCH.

***RST** 8

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:ULINK:APPLY](#)” on page 717.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:DPDCh:DCH[1] | 2 | 3 | 4 | 5 | 6:CTYPe****Supported** E4438C with Option 419[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH[1] | 2 | 3 | 4 | 5 | 6:CTYPe
HCONv | TCONv | TURBo | NONE

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH[1] | 2 | 3 | 4 | 5 | 6:CTYPe?

This command selects the encoder type for the selected uplink DCH.

HCONv This choice selects the 1/2 rate convolutional encoder.

TCONv This choice selects the 1/3 rate convolutional encoder.

TURBo This choice selects the turbo coder.

NONE This choice selects no coding.

RST** HCON**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.**:ULINK:DPDCh:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA*Supported** E4438C with Option 419[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA PN9 |
PN15 | FIX4 | "<file name>"

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA?

This command configures the data for the selected uplink DCH.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (uplink apply command) will not work. Refer to “File Overview” on page 668 for more information on files.

***RST** PN9**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:DATA:FIX4

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA  
:FIX4 <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA  
:FIX4?
```

This command sets the repeating 4-bit binary data pattern for the selected uplink DCH.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:ULINK:APPLY” on page 717](#).

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:NBLocks

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :NBLocks  
<val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :NBLocks?
```

This command sets the number of blocks for the selected uplink DCH.

***RST** 1

Range 0–512

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:ULINK:APPLY” on page 717](#).

The number of data bits per DCH cannot exceed 200,000. To maintain this data bit limit, the block size is multiplied by the number of blocks. If the product of these two parameters exceeds 200,000, the uplink apply command will not work.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:DPDCh:DCH[1]|2|3|4|5|6:RMATtribute****Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH[1]|2|3|4|5|6:RMATtribute <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH[1]|2|3|4|5|6:RMATtribute?

This command sets the rate matching attribute for the selected uplink DCH.

RST** 1**Range** 1–256**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. For more information, refer to “:ULINK:APPLY” on page 717.**:ULINK:DPDCh:DCH[1]|2|3|4|5|6:TTI*Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH[1]|2|3|4|5|6:TTI 10|20|40|80

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH[1]|2|3|4|5|6:TTI?

This command sets the TTI for the selected uplink DCH.

The choices are expressed in millisecond (ms).

RST** 10**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. For more information, refer to “:ULINK:APPLY” on page 717.**:ULINK:DPDCh:DCH2|3|4|5|6[:STATe]*Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH2|3|4|5|6[:STATe] ON|OFF|1|0

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:DPDCh:DCH2|3|4|5|6[:STATe]?

This command turns the selected uplink DCH on or off; DCH1 is always on.

***RST** DCH 1: 1 DCH 2– 6: 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

The apply command will not work and the ESG will report an error if you turn on a DCH where lower numbered DCHs are off. For example, turning on DCH5 requires turning on DCH2–4. The reverse is true when turning off the DCHs.

:ULINK:DPDCh:POWer

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:POWer <val>  
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:POWer?
```

This command sets the uplink DPDCH power level.

The variable <val> is expressed in decibels (dB).

***RST** +0.00000000E+00

Range –40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:DPDCh:SFORmat

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:SFORmat <val>  
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :ULINK:DPDCh:SFORmat?
```

This command sets the uplink DPDCH slot format.

***RST** +2

Range 0– 6

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

The slot format determines the settings for other parameters in accordance with the 3GPP standards.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])**:ULink:DPDCh[:STATe]****Supported** E4438C with Option 419

```
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULink:DPDCh[:STATe] ON|OFF|1|0
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULink:DPDCh[:STATe]?
```

This command turns the uplink DPDCH on or off.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULink:APPLY” on page 717.**:ULink:FClock:INTERval*Supported** E4438C with Option 419

```
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULink:FClock:INTERval 10|20|40|80|2560
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULink:FClock:INTERval?
```

This command selects the frame clock interval for the synchronization signal.

The frame clock interval is set in milliseconds (ms).

***RST** 80**Remarks** Ensure that the selected interval is equal to or longer than the longest transport channel TTI period.

This command is applicable only when FClock is the sync source selection. See “:ULink:SYNC[:SOURCE]” on page 755 for selecting the sync source.

:ULink:FClock:POLarity**Supported** E4438C with Option 419

```
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULink:FClock:POLarity POSitive|
NEGative
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULink:FClock:POLarity?
```

This command sets the frame clock polarity.

POSitive This choice sets the clock gate to trigger when the signal is high.**NEGative** This choice sets the clock gate to trigger when the signal is low.***RST** POS**Remarks** This command is applicable only when FClock is the sync source selection. See “:ULink:SYNC[:SOURCE]” on page 755 for selecting the sync source.

:ULINK:FILTer

Supported E4438C with Option 419

```
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:FILTer RNYQuist|NYQuist|  
GAUSSian|RECTangle|IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|  
"<user FIR>"  
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:FILTer?
```

This command selects the uplink filter type.

IS95	This filter meets the criteria of the IS-95 standard.
IS95_EQ	This filter is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard and is best suited for IS-95 baseband filtering.
IS95_MOD	This filter meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.
IS95_MOD_EQ	This filter is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.
UGGaussian	This is a GSM Gaussian filter with a fixed BbT value of 0.300.
AC4Fm	This is a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.
"<user FIR>"	This variable represents any FIR filter file stored in signal generator memory. Refer to “File Overview” on page 668 for more information on files.
*RST	RNYQ
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851 .

:ULINK:FILTer:ALPHa

Supported E4438C with Option 419

```
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:FILTer:ALPHa <val>  
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:FILTer:ALPHa?
```

This command sets the uplink Nyquist or root Nyquist filter alpha value.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])

*RST	+2.20000000E–001
Range	0–1
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Executing this command while a filter other than Nyquist or root Nyquist is selected changes the parameter value, but it is not used by the signal generator until one of the Nyquist filters is selected. Refer to “:ULINK:APPLY” on page 717 .

:ULINK:FILTer:BBT

Supported	E4438C with Option 419
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:FILTer:BBT <val>
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:FILTer:BBT?

This command sets the uplink Gaussian filter BbT value.

*RST	+5.00000000E–001
Range	0–1
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717 . Executing this command while a filter other than the Gaussian filter is selected changes the parameter value, but it is not used by the signal generator until the Gaussian filter is selected.

:ULINK:FILTer:CHANnel

Supported	E4438C with Option 419
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:FILTer:CHANnel EVM ACP
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:FILTer:CHANnel?

This command optimizes an uplink filter for minimized EVM or for minimized ACP.

EVM	This choice provides the most ideal passband.
ACP	This choice improves stopband rejection for the root Nyquist and Nyquist filters.
*RST	EVM
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717 . To change the filter selection, refer to “:ULINK:FILTer” on page 731 .

:ULINK:FOFFset

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:FOFFset <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:FOFFset?
```

This command sets the CFN starting frame within the SFN by setting a frame offset relative to SFN zero.

***RST** 0

Range 0–255

Remarks The command adds delays to the internal frame counter by specifying the starting frame number count. When the frame offset (FOFFset) is set to 0, the frame number starts at the system sync trigger. When the FOFFset is set to 2, the signal generator triggers two frames after the SFN RST. For additional information, refer to 3GPP TS25.402 for SFN and CFN relationship.

:ULINK:HCONfig

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HCONfig 0|1  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HCONfig?
```

This command sets HS-DSCH to be configured.

***RST** 1

:ULINK:HSDPcch:APATtern

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSDPcch:APATtern NONE|ACK_ALL|  
"<file name>"  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSDPcch:APATtern?
```

This command sets the HS-DPCCH ACK/NACK transmission pattern for each of the 1280 subframes that make up the pattern.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])

NONE	This choice sets all subframes to DTX.
"<file name>"	<p>This variable represents an ACK pattern file stored in signal generator memory. The file must contain 2,560-bits of data (2-bits per subframe) or the apply function (uplink apply command) will not work.</p> <ul style="list-style-type: none"> • An ACK response is represented by 00. • A NACK response is represented by 01. • DTX is represented by 10. <p>Enter the 2,560-bits into the file as a binary string.</p> <p>Refer to “File Overview” on page 668 for more information on files.</p>
*RST	ACK_ALL
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717 .

:ULINK:HSDPcch:APOWer

Supported	E4438C with Option 419
	[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSDPcch:APOWer <val> [:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSDPcch:APOWer?
	This command sets the HS-DPCCH ACK part power level.
	The variable <val> is expressed in decibels (dB).
*RST	-2.69000000E+000
Range	-40 to 0
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717 .

:ULINK:HSDPcch:CCODE

Supported	E4438C with Option 419
	[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSDPcch:CCODE?
	This query returns the HS-DPCCH channelization code.

:ULINK:HSDPcch:CPATtern

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSDPcch:CPATtern NONE |
"<file name>"
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSDPcch:CPATtern?
```

This command sets the HS-DPCCH CQI transmission pattern for each of the 1280 subframes that make up the pattern.

NONE This choice sets all subframes to DTX.

"<file name>" This variable represents a bit file stored in signal generator memory. The file must contain 10,240-bits of data (8-bits per subframe) or the apply function (uplink apply command) will not work.

- A CQI response range is one to thirty using 8-bits, 00000001 to 00011110.
- DTX is represented by 11111111.

Enter the 10,240-bits into the file as a binary string.

Refer to [“File Overview” on page 668](#) for more information on files.

***RST** NONE

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:ULINK:APPLY” on page 717](#).

:ULINK:HSDPcch:CPOWer

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSDPcch:CPOWer <val>
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSDPcch:CPOWer?
```

This command sets the HS-DPCCH CQI part power level.

The variable <val> is expressed in decibels (dB).

***RST** -2.69000000E+000

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:ULINK:APPLY” on page 717](#).

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:HSDPcch:NPOWer****Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSDPcch:NPOWer <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSDPcch:NPOWer?

This command sets the HS-DPCCH NACK part power level. The variable <val> is expressed in decibels (dB).

RST** -2.69000000E+000**Range** -40 to 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.**:ULINK:HSDPcch:SFDelay*Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSDPcch:SFDelay <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSDPcch:SFDelay?

This command sets the HS-DPCCH subframe delay. The variable <val> is expressed in units of 256 chips.

RST** 0**Range** 0–150**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.**:ULINK:HSDPcch[:STATe]*Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSDPcch[:STATe] ON|OFF|1|0

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSDPcch[:STATe]?

This command turns the HS-DPCCH on or off.

***RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:EDPCch:DATA

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:EDPCch:DATA  
PN9 | FIX4 | STD | "<file name>"  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:EDPCch:DATA?
```

This command sets the data type for the selected downlink E-DPCCH.

STD This choice configures the bit field as defined by the 3GPP standards.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function will not work.

***RST** STD

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:EDPCch:DATA:FIX4

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:EDPCch:DATA:FIX4 <val>  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:EDPCch:DATA:FIX4?
```

This command sets the data type for E-DPCCH repeating 4-bit binary pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:EDPCch:POWer

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:EDPCch:POWer <val>  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:EDPCch:POWer?
```

This command sets the E-DPCCH power level. The variable <val> is expressed in decibels (dB).

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])

*RST	–2.69000000E+000
Range	–40 to 0 dB
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:HSUPa:EDPCch[:STATe]

Supported	E4438C with Option 419
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:HSUPa:EDPCch [:STATe] ON OFF 1 0
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:HSUPa:EDPCch [:STATe] ?

This command turns the E-DPCCH on or off.

*RST	1
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:EDPDch:DATA

Supported	E4438C with Option 419
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:HSUPa:EDPDch:DATA:
	PN9 FIX4 STD "<file name>"
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:HSUPa:EDPDch:DATA?

This command sets the data type for the selected downlink E-DPDCH.

STD	This choice configures the bit field as defined by the 3GPP standards.
"<file name>"	This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function will not work.
*RST	STD

:ULINK:HSUPa:EDPDch:DATA:FIX4

Supported	E4438C with Option 419
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:HSUPa:EDPDch:DATA:FIX4 <val>
	[:SOURCE] :RADio:WCDMa:HSPA [:BBG] :ULINK:HSUPa:EDPDch:DATA?

This command sets the data type for E-DPDCH repeating 4-bit binary pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

*RST	0
Range	0–15
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:EDPDch:EDCH:DATA

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSUPa:EDPDch:DATA PN9 | FIX4 | STD |
"<file name>"
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSUPa:EDPDch:DATA?
```

This command defines the E-DCH data type.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function will not work.

*RST	PN9
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:EDPDch:EDCH:DATA:FIX4

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSUPa:EDPDch:EDCH:DATA:FIX4 <val>
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSUPa:EDPDch:EDCH:DATA:FIX4?
```

This command sets the E-DPDCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

*RST	0
Range	0–15
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:EDPDch:MCCodes

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:EDPDch:MCCodes
SF256 | SF128 | SF64 | SF32 | SF16 | SF8 | SF4 | SF4SF4 | SF2SF2 | SF4SF4SF2SF2
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:EDPDch:MCCodes?
```

This command sets the maximum channelization codes for E-DPDCH.

SF256	Set the spreading factor to 256 and the number of E-DPDCH to 1
SF128	Set the spreading factor to 128 and the number of E-DPDCH to 1
SF64	Set the spreading factor to 64 and the number of E-DPDCH to 1
SF32	Set the spreading factor to 32 and the number of E-DPDCH to 1
SF16	Set the spreading factor to 16 and the number of E-DPDCH to 1
SF8	Set the spreading factor to 8 and the number of E-DPDCH to 1
SF4	Set the spreading factor to 4 and the number of E-DPDCH to 1
SF4SF4	Set the spreading factor to 4 and the number of E-DPDCH to 2
SF2SF2	Set the spreading factor to 2 and the number of E-DPDCH to 2
SF4SF4SF2SF2	Set the spreading factor to 4 for 2 E-DPDCHs and spreading factor to 2 for 2 E-DPDCHs
*RST	SF4SF4SF2SF2

Remarks The maximum channelization codes are used together with the E-DCH configuration, and PL-non-MAX to automatically calculate the physical channel codes according to TS 25.212 (4.8.4.1).

:ULINK:HSUPa:EDPDch:PLNMax

Supported E4438C with Option 419

```
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:EDPDch:PLNMax <val>
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:EDPDch:PLNMax?
```

This command sets the PL non-max value for the E-DPDCH used in the determination of SF and number of E-DPDCHs as defined in TS 25.212 (4.8.4.1) for compressed mode.

***RST** 0.44

Resolution 0.04

Range 0.44 to 1.0

:ULINK:HSUPa:EDPDch:POWer

Supported E4438C with Option 419

```
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:EDPDch:POWer <val>
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:EDPCch:POWer?
```

This command sets the E-DPDCH power level. The variable <val> is expressed in decibels (dB).

***RST** +0.00000000E+001

:ULINK:HSUPa:EDPDch:SNPHchs

Supported E4438C with Option 419

```
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:EDPDch:SNPHchs
SF256|SF128|SF64|SF32|SF16|SF8|SF4|SF4SF4|SF2SF2|SF4SF4SF2SF2|AUTO
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:EDPCch:SNPHchs?
```

This command sets the SF and number of E-DPDCHs to configure the physical channel manually. To configure the physical channel as defined in TS 25.212 (4.8.4.1), refer to [“:ULINK:HSUPa:EDPDch:MCCodes” on page 740](#).

SF256	Set the spreading factor to 256 and the number of E-DPDCH to 1
SF128	Set the spreading factor to 128 and the number of E-DPDCH to 1
SF64	Set the spreading factor to 64 and the number of E-DPDCH to 1
SF32	Set the spreading factor to 32 and the number of E-DPDCH to 1
SF16	Set the spreading factor to 16 and the number of E-DPDCH to 1
SF8	Set the spreading factor to 8 and the number of E-DPDCH to 1

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

SF4	Set the spreading factor to 4 and the number of E-DPDCH to 1
SF4SF4	Set the spreading factor to 4 and the number of E-DPDCH to 2
SF2SF2	Set the spreading factor to 2 and the number of E-DPDCH to 2
SF4SF4SF2SF2	Set the spreading factor to 4 for 2 E-DPDCHs and spreading factor to 2 for 2 E-DPDCHs
AUTO	Calculate the spreading factor and number of codes automatically from maximum channelization codes, PL non-max, E-TFCI table selection, and E-TFCI index as defined in TS 25.212 (4.8.4.1).
*RST	SF4
Remarks	ULINK:TGAP:PSI[1]:PS can be set ACTIVE only when the :ULINK:HSUPa:EDPDch:SNPHchs is AUTO.

:ULINK:HSUPa:EDPDch[:STATE]

Supported E4438C with Option 419

```
[ :SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : ULINK : HSUPa : EDPDch [ : STATE ]
[ : SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : ULINK : HSUPa : EDPCch [ : STATE ] ?
```

This command turns the E-DPDCH on or off.

***RST** 1

:ULINK:HSUPa:ETABLE

Supported E4438C with Option 419

```
[ : SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : ULINK : HSUPa : EDPDch : ETABLE 0 | 1
[ : SOURCE ] : RADIO : WCDMA : HSPA [ : BBG ] : ULINK : HSUPa : EDPCch : ETABLE ?
```

This command selects the E-TFCI tables as specified in E-TFCI Table Selection, TS 25.321 Annex B.

***RST** 1

:ULINK:HSUPa:ETFCi

Supported E4438C with Option 419
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:ETFCi <val>
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:ETFCi?

This command sets the E-TFC index 7-bit pattern.

***RST** 41
Range 0–127 if E-TFCI Table = 0 and TTI = 2 ms
0–125 if E-TFCI Table = 1 and TTI = 2 ms
0–127 if E-TFCI Table = 0 and TTI = 10 ms
0–120 if E-TFCI Table = 1 and TTI = 10 ms

:ULINK:HSUPa:HARQ:APATtern

Supported E4438C with Option 419
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:HARQ:APATtern
ACK_ALL|EXtErnal|"<file name>"
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:HARQ:APATtern?

This command sets a simulated Node B ACK/NACK pattern that determines HSUPA's HARQ response.

ACK_ALL This choice configures 1,280 subframes (if TTI=2ms) or 1,280 frames (if TTI=10ms) for a simulated ACK only response. For a long transmission, up to 18000 (sub)frames can be configured.

“<file name>” This variable represents an ACK pattern file stored in signal generator memory. Create this file either by using the HARQ ACK/NACK pattern Data Type Entry window and download the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- An ACK response is represented by 0.
- A NACK response is represented by 1.

In the file, do not use delimiters between (sub)frames; enter (sub)frame bits as a binary string. When creating a pattern, you can determine the number of active (sub)frames from 1 to 1,280. The (sub)frames are numbered 0 to 1,279.

External This choice selects specifies an external ACK/NACK pattern.
***RST** ACK_ALL

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:HSUPa:HARQ:APATtern[:EXternal]:DELay****Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:HARQ:APATtern[:EXternal]:DELay <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:HARQ:APATtern[:EXternal]:DELay?

This command sets the amount of time between the head of a transmitted process and the sampling point of the external ACK/NACK signal corresponding with the process.

The variable <val> is expressed in chips with a resolution of 256.

RST** 7680**:ULINK:HSUPa:HARQ:APATtern[:EXternal]:INPut*Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:HARQ:APATtern[:EXternal]:INPut ALTP|BGAT|PTR2

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:HARQ:APATtern[:EXternal]:INPut?

This command sets the amount of time between the head of a transmitted process and the sampling point of the external ACK/NACK signal corresponding with the process.

The variable <val> is expressed in chips with a resolution of 256.

ALTP This choice sets the input port of the external signal to ALT PWR IN.

BGAT This choice sets the input port of the external signal to BURST GATE IN.

PTR2 This choice sets the input port of the external signal to PATT TRIG IN 2.

***RST** BGAT

:ULINK:HSUPa:HARQ:APATtern[:EXTernal]:POLarity

Supported E4438C with Option 419

```
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:HARQ:APATtern[:EXTernal]:  
POLarity POSitive|NEGative  
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:HARQ:APATtern[:EXTernal]:  
POLarity?
```

This command sets the ACK/NACK signal polarity.

POSitive This choice sets the pattern signal to ACK when the external signal is low and NACK when the external signal is high.

NEGative This choice sets the pattern signal to ACK when the external signal is high and NACK when the external signal is low.

***RST** POS

:ULINK:HSUPa:HARQ:MNRTrans

Supported E4438C with Option 419

```
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:HARQ:MNRTrans <val>  
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:HARQ:MNRTrans?
```

This command sets the maximum number of retransmissions.

Range 0–15

***RST** 15

:ULINK:HSUPa:HARQ[:MODE]

Supported E4438C with Option 419

```
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:HARQ[:MODE] NONE |  
IREdundancy|CCOMbining  
[:SOURce]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:HARQ[:MODE] ?
```

This command sets the HARQ mode to use None, Incremental Redundancy, or Chase Combining for retransmission.

Incr Redundancy This choice sends different coded bits instead of the same coded packets, when a NACK is received.

Chase Combining This choice provides UE feedback by sending the same coded packet again upon reception of a NACK signal.

***RST** NONE

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:HSUPa:HARQ:HBIT**

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:HARQ:HBIT
HAPPY|NHAPPY| "<file name>"
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:HARQ:HBIT?
```

This command sets the HSUPA happy bit.

HAPPY This choice sets the happy bit to happy.

NHAPPY This choice sets the happy bit to not happy.

“<file name>” This variable represents a happy bit pattern file stored in signal generator memory. Create this file either by using the Happy Bit Pattern Data Type Entry window and download the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- A not happy response is represented by 0.
- A happy response is represented by 1.

***RST** HAPPY

:ULINK:HSUPa:HPROcess

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:HPROcess [0] | 1 | | 2 | 3 | 4 | 5 | 6 | 7
[ :STATE ] ON | OFF | 1 | 0
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa:HPROcess [0] 1 | | 2 | 3 | 4 | 5 | 6 | 7
[ :STATE ] ?
```

This command turns the uplink HSUPA Hybrid ARQ Process on or off for the selected HARQ process.

1|ON TX the process #n

2|OFF DTX the process #n

***RST** 1

:ULINK:HSUPa:RSN

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :ULINK:HSUPa:RSN 0 | 1 | 2 | 3

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :ULINK:HSUPa:RSN?

This command sets the HSUPA retransmission sequence number (RSN) when HARQ mode is not selected.

***RST** 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:RVIndex

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :ULINK:HSUPa:RVIndex 0 | 1 | 2 | 3

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :ULINK:HSUPa:RVIndex?

This command sets the RV control when the HARQ mode is not selected.

***RST** 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:TFC:EPATtern[:EXternal]:DElay

Supported E4438C with Option 419

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :ULINK:HSUPa:TFC:EPATtern [:EXternal] :
DElay <val>

[:SOURCE] :RADIO:WCDMA:HSPA [:BBG] :ULINK:HSUPa:TFC:EPATtern [:EXternal] :
DElay?

This command sets the amount of time between the head of a transmitted process and the sampling point of the external signal corresponding with the E-TFCI pattern control.

<val> The variable <val> is expressed in chips with a resolution of 256.

***RST** 7680

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURce]:RADio:WCDMa:HSPA[:BBG])

Range	0 to 153344 (for TTI = 10 ms) 0 to 61184 (for TTI = 2 ms)
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:TFC:EPATtern[:EXtErnal]:INPut

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSUPa:TFC:EPATtern [ :EXtErnal ] :
INPut ALTP|BGAT|PTR2
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSUPa:TFC:EPATtern [ :EXtErnal ] :
INPut?
```

This command selects the input port for the external TFC E-TFCI pattern signal.

ALTP	This choice sets the input port of the external signal to ALT PWR IN.
BGAT	This choice sets the input port of the external signal to BURST GATE IN.
PTR2	This choice sets the input port of the external signal to PATT TRIG IN 2.
*RST	BGAT
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:TFC:EPATtern[:EXtErnal]:POLarity

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSUPa:TFC:EPATtern [ :EXtErnal ] :
POLarity POSitive|NEGative
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:HSUPa:TFC:EPATtern [ :EXtErnal ] :
POLarity?
```

This command sets the external E-TFCI pattern control signal polarity.

POSitive	This choice sets the pattern signal to MAIN when the external signal is low and ALT when the external signal is high.
NEGative	This choice sets the pattern signal to MAIN when the external signal is high and ALT when the external signal is low.
*RST	POS
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:TFC:EPATtern

Supported E4438C with Option 419

```
[ :SOURce] :RADio:WCDMa:HSPA [ :BBG] :ULINK:HSUPa:TFC:EPATtern
MAIN|EXTeRnal| "<file name>"
[:SOURce] :RADio:WCDMa:HSPA [ :BBG] :ULINK:HSUPa:TFC:EPATtern?
```

This command sets the MAIN and ALT TFC pattern to be used.

MAIN_ALL This choice configures all subframes for a simulated MAIN only response.

EXT This choice selects an external signal to control the data pattern.

"<file name>" This variable represents a MAIN/ALT pattern file stored in signal generator memory. Create this file either by using the TFC pattern Data Type Entry window and download the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- A MAIN response is represented by 0.
- An ALT response is represented by 1

In the file, do not use delimiters between (sub)frames; enter (sub)frame bits as a binary string.

***RST** MAIN

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:ULINK:APPLY” on page 717](#).

:ULINK:HSUPa:TFC[:ALT]:EDPCch:POWer

Supported E4438C with Option 419

```
[ :SOURce] :RADio:WCDMa:HSPA [ :BBG] :ULINK:HSUPa:TFC [ :ALT] :EDPCch:
POWer <val>
[:SOURce] :RADio:WCDMa:HSPA [ :BBG] :ULINK:HSUPa:TFC [ :ALT] :EDPCch:POWer?
```

This command sets the E-DPCCH power level of the alternate TFC setting.

The variable <val> is expressed in decibels (dB).

***RST** -2.69000000E+000

Range -40 to 0

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:HSUPa:TFC[:ALT]:EDPDch:EDCH:DATA****Supported** E4438C with Option 419[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TFC[:ALT]:EDPDch:EDCH:DATA
PN9|FIX4|"<file name>"

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TFC[:ALT]:EDPDch:EDCH:DATA?

This command defines the alternate E-DCH data type.

EDCH This choice selects E-DCH for data.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function will not work.

RST** PN9**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.**:ULINK:HSUPa:TFC[:ALT]:EDPDch:EDCH:DATA:FIX4*Supported** E4438C with Option 419[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TFC[:ALT]:EDPDch:EDCH:DATA:
FIX4 <val>[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TFC[:ALT]:EDPDch:EDCH:DATA:
FIX4?

This command defines the E-DCH repeating 4-bit binary data pattern when the alternate TFC setting is used.

The variable <val> accepts values in binary, hexadecimal, or decimal format; however, the query returns only binary values.

***RST** 0**Range** 0–15**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:HSUPa:TFC[:ALT]:EDPDch:POWer

Supported E4438C with Option 419

```
[ :SOURce] :RADio:WCDMa:HSPA [ :BBG] :ULINK:HSUPa:TFC [ :ALT] :EDPDch:
POWer <val>
[ :SOURce] :RADio:WCDMa:HSPA [ :BBG] :ULINK:HSUPa:TFC [ :ALT] :EDPDch:POWer?
```

This command sets the E-DPDCH power level of the alternate TFC setting.

The variable <val> is expressed in decibels (dB).

***RST** 0.00000000E+00

Range -40 to 0

:ULINK:HSUPa:TFC[:ALT]EDPDch:SNPHchs

Supported E4438C with Option 419

```
[ :SOURce] :RADio:WCDMa:HSPA [ :BBG] :ULINK:HSUPa:TFC [ :ALT] :EDPDch:SNPHchs
SF256 | SF128 | SF64 | SF32 | SF16 | SF8 | SF4 | SF4SF4 | SF2SF2 | SF4SF4SF2SF2
[ :SOURce] :RADio:WCDMa:HSPA [ :BBG] :ULINK:HSUPa:TFC [ :ALT] :EDPDch:SNPHchs?
```

This command sets the SF and number of E-DPDCHs of the TFC alternate setting.

- SF256 Set the spreading factor to 256 and the number of E-DPDCH to 1
- SF128 Set the spreading factor to 128 and the number of E-DPDCH to 1
- SF64 Set the spreading factor to 64 and the number of E-DPDCH to 1
- SF16 Set the spreading factor to 16 and the number of E-DPDCH to 1
- SF8 Set the spreading factor to 8 and the number of E-DPDCH to 1
- SF4 Set the spreading factor to 4 and the number of E-DPDCH to 1
- SF4SF4 Set the spreading factor to 4 and the number of E-DPDCH to 2
- SF2SF2 Set the spreading factor to 2 and the number of E-DPDCH to 2
- SF4SF4SF2SF2 Set the spreading factor to 4 for 2 E-DPDCHs and the spreading factor to 2 for 2 E-DPDCHs
- *RST** SF4

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:HSUPa:TFC[:ALT]:ETABLE****Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TFC[:ALT]:ETABLE 0|1
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TFC[:ALT]:ETABLE?
```

This command sets the E-TFCI table selection of the TFC alternate setting as shown in the E-TFCI Table Selection, TS 25.321 Annex B.

0 This choice selects Table 0.

1 This choice selects Table 1.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.**:ULINK:HSUPa:TFC[:ALT]:ETFCI*Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TFC[:ALT]:ETFCI <value>
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TFC[:ALT]:ETFCI?
```

This command sets the E-TFC index 7-bit pattern for the TFC alternate setting. The TTI value controls the E-TFCI value as described in range field below. If a value exceeds its range, the value is clipped to the allowed maximum value for the current configuration.

***RST** 41

Range 0-127 if E-TFCI Table = 0
 0-125 if E-TFCI Table = 1 and TTI = 2 ms
 0-120 if E-TFCI Table = 1 and TTI = 10 ms

:ULINK:HSUPa:TTI**Supported** E4438C with Option 419

```
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TTI 2|10
[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:HSUPa:TTI?
```

This command sets the static TTI value for the HSUPA.

***RST** 10

:ULINK:HSUPa[:STATe]

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa : [ :STATe ] ON | OFF | 1 | 0  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:HSUPa : [ :STATe ] ?
```

This command turns the uplink HSUPA state to ON | 1 or OFF | 0.

***RST** 1

:ULINK:NMDPdch

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:NMDPdch 0 | 1  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:NMDPdch?
```

This command sets the Nmax-dpdch (maximum number of simultaneous uplink DPDCH).

***RST** 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:POLarity

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:POLarity NORMAL | INVERTed | INVERT  
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:POLarity?
```

This command selects the phase polarity of the uplink signal.

NORMAL This choice selects normal polarity.

INVERTed, INVERT These choices perform the same function, inverting the internal Q signal.

***RST** NORM

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])**:ULINK:SCRamblecode****Supported** E4438C with Option 419

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:SCRamblecode <val>

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:SCRamblecode?

This command sets the scramble code.

RST** +0**Range** 0–16777215**:ULINK:SDElay*Supported** E4438C with Option 419

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:SDElay <val>

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:SDElay?

This command sets the uplink DPCH delay, measured in slots.

***RST** +0**Range** 0–119**Remarks** Calculate the delay between downlink and uplink DPCH, in slots, using the following formulas. Total Delay = (T0) + (TOFFset) + ((SDElay) * 2560 chips)

- T0 = 1024 chips
- TOFFset is set by “:ULINK:TOFFset” on page 758

Slot Delay = (Total Delay - T0) / 2560

:ULINK:SFNRst:POLarity**Supported** E4438C with Option 419

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:SFNRst:POLarity POSitive|

NEGative

[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:SFNRst:POLarity?

This command sets the polarity of the system frame number reset signal for the uplink synchronization source.

POSitive	This choice sets the signal to trigger when the trigger signal is high.
NEGative	This choice sets the signal to trigger when the trigger signal is low.
*RST	POS
Remarks	This command is applicable only when SFN_RST is the sync source selection. See “:ULINK:SYNC[:SOURce]” on page 755 for selecting the sync source.

:ULINK:SYNC:MODE

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:SYNC:MODE SINGLE | CONTInuous
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:SYNC:MODE?
```

This command selects the uplink frame synchronization triggering mode.

SINGle	The signal generator, once triggered, generates frames based on the reference clock.
CONTInuous	The signal generator continuously aligns the frame timing with the frame sync trigger signal.
*RST	SING

:ULINK:SYNC[:SOURce]

Supported E4438C with Option 419

```
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:SYNC [ :SOURce ] SFN_RST | FCLock
[ :SOURce ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:SYNC [ :SOURce ] ?
```

This command selects the uplink frame synchronization source type.

SFN_RST	The uplink signal triggers on the system frame number reset signal.
FCLock	The uplink signal triggers on the frame clock.
*RST	FCL

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])**:ULINK:TGAP:PSI[1]:CFN****Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:TGAP:PSI[1]:CFN <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:TGAP:PSI[1]:CFN?

This command sets the connection frame number (CFN) for the first radio frame of the first pattern 1.

RST** 0**Range** 0–255**Remarks** In the signal generator, CFN is counted internally, relative to the system sync signal.**:ULINK:TGAP:PSI[1]:D*Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:TGAP:PSI[1]:D <val>

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:TGAP:PSI[1]:D?

This command sets the transmission gap distance. It specifies the number of slots between the starting slots of two consecutive transmission gaps within a transmission gap pattern. A value of 0 indicates that there is only one transmission gap within the transmission gap pattern.

RST** 0**Range** 0, 15–269**:ULINK:TGAP:PSI[1]:L1*Supported** E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:TGAP:PSI[1]:L1 3|4|5|7|10|14

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:TGAP:PSI[1]:L1?

This command specifies the length of the first transmission gap (TGL1). The length is expressed in number of slots.

***RST** +7

:ULINK:TGAP:PSI[1]:L2

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :L2 0|3|4|5|7|10|14  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :L2?
```

This command specifies the length of the second transmission gap (TGL2). When the value is set to 0, TGL2=TGL1.

***RST** 0

:ULINK:TGAP:PSI[1]:PL1

Supported E4438C with Option 419 and Option 400

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :PL1 <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :PL1?
```

This command specifies the duration of the transmission gap pattern length 1 (TGPL1). The pattern length is expressed in number of frames.

***RST** +2

Range 1–144

:ULINK:TGAP:PSI[1]:PRC

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :PRC <val>  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :PRC?
```

This command sets the transmission gap pattern repetition count. The pattern repetition count (PRC) sets the number of transmission gap patterns within the transmission gap pattern sequence.

***RST** 0

Range 0–511

Remarks A value of 0 indicates that the PRC will continue indefinitely.

:ULINK:TGAP:PSI[1]:PS

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :PS ACTIVE|INACTIVE  
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :PS?
```

This command sets the transmission gap pattern status.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

ACTive	This choice sets the compressed mode active.
INACTive	This choice sets the compressed mode inactive.
*RST	INAC

:ULINK:TGAP:PSI[1]:SN

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :SN <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:TGAP:PSI [1] :SN?
```

This command specifies the timeslot number of the first transmission gap within the first radio frame.

*RST +11

Range 0–14

:ULINK:TOFFset

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:TOFFset <val>
[ :SOURCE ] :RADIO:WCDMA:HSPA [ :BBG ] :ULINK:TOFFset?
```

This command sets the uplink DPCH timing offset (delay), measured in chips.

*RST 0

Range –512 to 2560

Remarks The downlink signal timing is provided by the synchronization signal.
Calculate the delay between downlink and uplink DPCH, in chips, using the following formulas:

$$\text{Total Delay} = (T0) + (\text{TOFFset}) + ((\text{SDElay}) * 2560 \text{ chips})$$

- T0 = 1024 chips
- SDElay is set by “:ULINK:SDElay” on page 754

$$\text{Chip Delay} = (\text{Total Delay} - T0) \text{ mod } 2560$$

:ULINK:TPControl:PATtern

Supported E4438C with Option 419

```
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:TPControl:PATtern
"<file name>"|EXTernal
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:TPControl:PATtern?
```

This command sets a user pattern that determines the power control response and controls the power of the user's equipment (UE). The increase/decrease direction for UE power level changes is determined by the transmit power control (TPC) pattern.

"<file name>" This choice specifies a user file. 0: DOWN, 1: UP

EXTernal This choice specifies an external TPC pattern.

***RST** EXTernal

:ULINK:TPControl:PATtern[:EXTernal]:INPut

Supported E4438C with Option 419

```
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:TFC:EPATtern[:EXTernal]:
INPut ALTP|BGAT|PTR2
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:HSUPa:TFC:EPATtern[:EXTernal]:
INPut?
```

This command sets the input port of the external Ack/Nack signal.

ALTP This choice sets the input port of the external signal to ALT PWR IN.

BGAT This choice sets the input port of the external signal to BURST GATE IN.

PTR2 This choice sets the input port of the external signal to PATT TRIG IN 2.

***RST** PTR2

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to "**:ULINK:APPLY**" on page 717.

:ULINK:TPControl:PATtern[:EXTernal]:POLarity

Supported E4438C with Option 419

```
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:TPControl[:EXTernal]:POLarity
POSitive|NEGative
[:SOURCE]:RADio:WCDMa:HSPA[:BBG]:ULINK:TPControl[:EXTernal]:POLarity?
```

This command sets the external TPC signal polarity.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADio:WCDMa:HSPA[:BBG])

POSitive	This choice sets the pattern signal to DOWN when the external signal is low and sets the pattern signal to UP when the external signal is high.
NEGative	This choice sets the pattern signal to DOWN when the external signal is high and sets the pattern signal to UP when the external signal is low.
*RST	POS
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:TPControl:POWer:INITial

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TPControl:POWer:INITial <val>
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TPControl:POWer:INITial?
```

This command sets the initial power of the transmission power control, in dB (relative to Max Power: 0.00 dB).

***RST** +0.00000000E+000

Range 0 to –40 dB

Remarks If the parameter set by this command is changed while the signal is active, the “:ULINK:APPLY” on page 717 must be executed for the change to occur. The value must be larger than or equal to the minimum transmit power. The power difference between the initial power and the maximum power should be a multiple value of the power step. Initial power is relative to the maximum power (amplitude) set on the signal generator.

:ULINK:TPControl:POWer:MAXimum

Supported E4438C with Option 419

```
[ :SOURCE ] :RADio:WCDMa:HSPA [ :BBG ] :ULINK:TPControl:POWer:MAXimum?
```

This query returns the maximum power of the transmit power control, relative to Maximum Power, in dB. The value shown for this parameter will always be 0.00 dB, and is a relative value to the maximum amplitude set for the signal generator.

For example, if the signal generator amplitude is set to –20 dBm, the Minimum Power is set to –40 dB, and the Initial Power is set to –10 dB, then the absolute initial power level will be –30 dBm, which is 10 dBm below the signal generator amplitude, and the absolute minimum power will be –60 dBm, which is 40 dBm below the signal generator amplitude.

***RST** +0.00000000E+000

:ULINK:TPControl:POWer:MINimum

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :ULINK:TPControl:POWer:MINimum <val>  
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :ULINK:TPControl:POWer:MINimum?
```

This command sets the initial power of the transmission power control, in dB (relative to Max Power: 0.00 dB).

The minimum power value must be less than or equal to the value used for initial power. Minimum power is decreased in increments determined by the value set for the power step. The power difference between minimum and maximum power should be a multiple of the power step value.

Minimum power is limited by the amplitude set on the signal generator. The signal generator amplitude must be set to -96 dBm or lower for the minimum power to be set to -40 dB.

***RST** - 4.00000000E+001

Range - 40 to 0 dB

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

:ULINK:TPControl:POWer:STEP

Supported E4438C with Option 419

```
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :ULINK:TPControl:POWer:STEP  
DB0_5 | DB1_0 | DB2_0 | DB3_0  
[ :SOURCE ] :RADIo:WCDMA:HSPA [ :BBG ] :ULINK:TPControl:POWer:STEP?
```

This command sets the power control step size. Initial power can only be increased in steps set by the power step command.

***RST** DB0_5

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 717.

3GPP W-CDMA HSPA Subsystem–Option 419 ([:SOURCE]:RADIO:WCDMA:HSPA[:BBG])

:ULINK:TPControl[:STATE]

Supported E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:TPControl[:STATE] 1|0|ON|OFF

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG]:ULINK:TPControl[:STATE]?

This command enables or disables the transmission power control.

***RST** 0

[:STATE]

Supported E4438C with Option 419

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG][:STATE] ON|OFF|1|0

[:SOURCE]:RADIO:WCDMA:HSPA[:BBG][:STATE]?

This command turns the HSPA functionality on or off.

***RST** 0

Remarks This command only works when there is at least one active physical channel within the selected link.

Real Time GPS Subsystem—Option 409 ([:SOURce]:RADio[1] | 2 | 3 | 4:GPS)

:DATA

Supported E4438C with Option 409

```
[:SOURce]:RADio:GPS:DATA PN9|PN15|FIX4|"<user file>"  
[:SOURce]:RADio:GPS:DATA?
```

This command sets the data type for the selected data mode.

***RST** PN9

Key Entry **PN9** **PN15** **FIX4** **User file**

Remarks This command is effective only when the data mode is RAW or ENCOded. To set the data mode, refer to “:DMODE”.

:DMODE

Supported E4438C with Option 409

```
[:SOURce]:RADio:GPS:DMODE RAW|ENCOded|TLM  
[:SOURce]:RADio:GPS:DMODE?
```

This command sets the data mode.

RAW This choice modulates data onto the C/A (coarse acquisition) code at 50-bits per second. No parity bits are computed by the signal generator. Every 6 seconds, 300-bits from the source data are transmitted.

ENCOded This choice modulates data onto the C/A (coarse acquisition) code at 50-bits per second. The signal generator computes 6 parity bits for every 24 data bits from the selected data source. Every six seconds, 240-bits of the source data are transmitted along with 60 computed parity bits.

TLM This choice transmits a standard default navigation data transmission which includes a telemetry word (TLM), a handover word (HOW), and default navigation data. The signal generator transmits an incrementing time-of-week (TOW) as part of the HOW.

Real Time GPS Subsystem—Option 409 ([:SOURce]:RADio[1] | 2 | 3 | 4:GPS)

*RST	RAW
Key Entry	Data Mode Raw Enc TLM
Remarks	Since the TLM mode transmits default navigation data, there is no data selection for this mode. For selecting the data type when RAW or ENCOded is the selection, refer to “:DATA” on page 763.

:DSHift

Supported	E4438C with Option 409
	<code>[:SOURce]:RADio:GPS:DSHift <val></code> <code>[:SOURce]:RADio:GPS:DSHift?</code>
	This command sets the frequency and chip rate offsets to simulate a doppler shift. The variable <val> is expressed in units of hertz (Hz to kHz).
*RST	+0.00000000E+000
Range	–125kHz to 125kHz
Key Entry	Doppler Shift
Remarks	The lower bound of the doppler shift is limited by the frequency set on the signal generator. For example, if the signal generator frequency is set to 100 kHz, then the lower limit of the doppler shift would be 0.00 Hz. The doppler shift can not extend lower than the limitations of the signal generator

:FILTer

Supported	E4438C with Option 409
	<code>[:SOURce]:RADio:GPS:FILTer RNYQuist NYQuist GAUSSian RECTangle IS95 IS95_EQ IS95_MOD IS95_MOD_EQ AC4Fm UGGaussian "<user FIR>"</code> <code>[:SOURce]:RADio:GPS:FILTer?</code>
	This command sets the pre-modulation filter type.
IS95	This choice selects a filter that meets the criteria of the IS-95 standard.
IS95_EQ	This choice selects a filter which is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard. This filter is only used for IS-95 baseband filtering.

IS95_MOD	This choice selects a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.																		
IS95_MOD_EQ	This choice selects a filter which is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection.																		
AC4Fm	This choice selects a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.																		
UGGaussian	This choice selects a backwards compatible GSM Gaussian filter (Gaussian filter with a fixed BbT value of 0.300) for the ESG E44xxB Option UN3 or UN4.																		
"<user FIR>"	This variable is any filter file that you have stored into memory.																		
*RST	RECT																		
Key Entry	<table border="0" style="width: 100%;"> <tr> <td style="text-align: left;">Root Nyquist</td> <td style="text-align: left;">Nyquist</td> <td style="text-align: left;">Gaussian</td> <td style="text-align: left;">Rectangle</td> <td style="text-align: left;">IS-95</td> <td style="text-align: left;">IS-95 w/EQ</td> </tr> <tr> <td style="text-align: left;">IS-95 Mod</td> <td style="text-align: left;">IS-95 Mod w/EQ</td> <td style="text-align: left;">APC025 C4FM</td> <td style="text-align: left;">UN3/4 GSM Gaussian</td> <td></td> <td></td> </tr> <tr> <td colspan="6">User FIR</td> </tr> </table>	Root Nyquist	Nyquist	Gaussian	Rectangle	IS-95	IS-95 w/EQ	IS-95 Mod	IS-95 Mod w/EQ	APC025 C4FM	UN3/4 GSM Gaussian			User FIR					
Root Nyquist	Nyquist	Gaussian	Rectangle	IS-95	IS-95 w/EQ														
IS-95 Mod	IS-95 Mod w/EQ	APC025 C4FM	UN3/4 GSM Gaussian																
User FIR																			

:FILTer:ALPHA

Supported E4438C with Option 409

```
[:SOURce]:RADio:GPS:FILTer:ALPHA <val>
[:SOURce]:RADio:GPS:FILTer:ALPHA?
```

This command sets the Nyquist or root Nyquist filter’s alpha value.

The filter alpha value can be set to the minimum value (0), maximum value (1), or in between by using fractional numeric values (0.001–0.999).

***RST** +2.20000000E-001

Range 0.000–1.000

Key Entry **Filter Alpha**

Remarks To change the current filter type, refer to “:FILTer” on page 764.

:FILTer:BBT

Supported E4438C with Option 409

```
[ :SOURCE ] :RADio:GPS:FILTer:BBT <val>
```

```
[ :SOURCE ] :RADio:GPS:FILTer:BBT?
```

This command changes the bandwidth-multiplied-by-bit-time (BbT) filter parameters.

The filter BbT value can be set to the minimum value (0), the maximum value (1), or in between by using fractional numeric values (0.001–0.999)

***RST** +5.00000000E-001

Range 0.000–1.000

Key Entry **Filter BbT**

Remarks This command is effective only after choosing a Gaussian filter. It does not have an effect on other types of filters.

To change the current filter type, refer to “[:FILTer](#)” on page 764.

:FILTer:CHANnel

Supported E4438C with Option 409

```
[ :SOURCE ] :RADio:GPS:FILTer:CHANnel EVM | ACP
```

```
[ :SOURCE ] :RADio:GPS:FILTer:CHANnel?
```

This command optimizes the Nyquist and root Nyquist filters to minimize error vector magnitude (EVM) or to minimize adjacent channel power (ACP).

EVM This choice provides the most ideal passband.

ACP This choice improves stopband rejection.

***RST** EVM

Key Entry **Optimize FIR For EVM ACP**

Remarks To change the current filter type, refer to “[:FILTer](#)” on page 764.

:IQPHase

Supported E4438C with Option 409
[:SOURce]:RADio:GPS:IQPHase NORMal|INVerted
[:SOURce]:RADio:GPS:IQPHase?

This command sets the I/Q phase for the GPS signal.

NORMal This choice selects normal phase polarity.

INVerted This choice inverts the internal Q signal.

***RST** NORM

Key Entry **IQ Phase Normal Invert**

:PCODE

Supported E4438C with Option 409
[:SOURce]:RADio:GPS:PCODE <val>
[:SOURce]:RADio:GPS:PCODE?

This command sets the P code power relative to the C/A code power.

***RST** -3.00000000E+000

Range -40 to 0

Key Entry **P Code Pwr**

Remarks This command is normally used when the CAP (C/A+P) ranging mode choice is selected. Refer to “:RCODE” for selecting the ranging mode.

:RCODE

Supported E4438C with Option 409
[:SOURce]:RADio:GPS:RCODE CA|P|CAP
[:SOURce]:RADio:GPS:RCODE?

This command selects the ranging code for the GPS transmission.

CA This choice selects a 1023-bit pseudorandom C/A (coarse acquisition) code that is BPSK modulated onto the L1 (1575.42 MHz) carrier. The C/A code factory set chip rate is 1.023 Mcps using a 10.23 Mcps reference clock.

Real Time GPS Subsystem—Option 409 ([:SOURCE]:RADio[1] | 2 | 3 | 4:GPS)

P	This choice selects the precise (P) code which is a very long pseudorandom sequence that is BPSK modulated onto the L2 (1227.6 MHz) carrier. The P code factory set chip rate is 10.23 Mcps using a 10.23 Mcps reference clock.
CAP	This choice permits both the C/A (coarse acquisition) and P (precise) codes to modulate the L1 (1575.42 MHz) carrier simultaneously by providing the P code on the Q component and the C/A code in quadrature on the I component.
*RST	CA
Key Entry	Ranging Code C/A P C/A+P

:REFClk

Supported	E4438C with Option 409
	<code>[:SOURCE]:RADio:GPS:REFClk INT Ext</code>
	<code>[:SOURCE]:RADio:GPS:REFClk?</code>

This command sets the GPS reference clock to either internal or external.

INT	This selection sets the signal generator to use the internal chip clock.
EXT	This selection sets the signal generator to use an external chip clock which is supplied to the DATA CLOCK INPUT connector.
*RST	INT
Key Entry	GPS Ref Clk

:REFFreq

Supported	E4438C with Option 409
	<code>[:SOURCE]:RADio:GPS:REFFreq <val><unit></code>
	<code>[:SOURCE]:RADio:GPS:REFFreq?</code>

This command sets the GPS reference clock frequency. If an external source is being used, its frequency must match the value set with this command

*RST	+1.02300000E+007
Range	1kCPS–12.5MCPS
Key Entry	GPS Ref (f0)
Remarks	Changing the GPS reference frequency will change the P and C/A code chip rates.

:SATid

Supported E4438C with Option 409

[:SOURCE]:RADio:GPS:SATid <val>

[:SOURCE]:RADio:GPS:SATid?

This command selects the pseudorandom number (PRN) code used for transmission.

Satellite identification numbers 1–32 are used for GPS satellites. Satellite identification numbers 33–37 are reserved for ground transmitter use in the real-world system.

***RST** +1

Range 1–37

Key Entry **Satellite ID**

[:STATE]

Supported E4438C with Option 409

[:SOURCE]:RADio:GPS[:STATE] ON|OFF|1|0

[:SOURCE]:RADio:GPS[:STATE]?

This command enables or disables the real-time GPS signal.

***RST** 0

Key Entry **Real-time GPS Off On**

Real Time MSGPS Subsystem—Option 409 ([:SOURce]:RADio[1] | 2 | 3 | 4:MSGPs)

:IQPHase

Supported E4438C with Option 409

[:SOURce] :RADio:MSGPs:IQPHase NORMal | INVerted

[:SOURce] :RADio:MSGPs:IQPHase?

This command sets the I/Q phase for the MSGPS signal.

NORMal This choice selects normal phase polarity.

INVerted This choice inverts the internal Q signal.

***RST** NORM

Key Entry **IQ Phase Normal Invert**

:PMODE

Supported E4438C with Option 409

[:SOURce] :RADio:MSGPs:PMODE RUN | PAUSE

[:SOURce] :RADio:MSGPs:PMODE?

This command pauses or plays the real-time MSGPS scenario.

***RST** RUN

Key Entry **Pause/Resume**

:REFClk

Supported E4438C with Option 409

```
[ :SOURCE ] :RADio:MSGPs:REFClk INTernal | EXTernal  
[ :SOURCE ] :RADio:MSGPs:REFClk?
```

This command sets the MSGPS reference clock to either internal or external.

INTernal This selection sets the signal generator to use the internal chip clock.

EXTernal This selection sets the signal generator to use an external chip clock which is supplied to the DATA CLOCK INPUT connector.

***RST** INT

Key Entry **GPS Ref Clk**

:REFFreq

Supported E4438C with Option 409

```
[ :SOURCE ] :RADio:MSGPs:REFFreq <val><unit>  
[ :SOURCE ] :RADio:MSGPs:REFFreq?
```

This command sets the MSGPS reference clock frequency. If an external reference clock is being used, its frequency must match the value set with this command

***RST** +1.02300000E+007

Range 1.023Mcps $\pm 10\%$

Key Entry **GPS Ref (f0)**

Remarks Changing the GPS reference frequency will change the C/A code chip rate.

:REStart

Supported E4438C with Option 409

```
[ :SOURCE ] :RADio:MSGPs:REStart
```

This command sets the real-time MSGPS scenario to the beginning.

Key Entry **Restart**

:SCENario

Supported E4438C with Option 409

```
[:SOURCE]:RADIO:MSGPS:SCENario "<file_name>"  
[:SOURCE]:RADIO:MSGPS:SCENario?
```

This command selects the real-time MSGPS scenario to play.

Key Entry **Select Scenario**

:SCENario:SATellites

Supported E4438C with Option 409

```
[:SOURCE]:RADIO:MSGPS:SCENario:SATellites <val>  
[:SOURCE]:RADIO:MSGPS:SCENario:SATellites?
```

This command sets the number of satellites in view to include in the generated MSGPS signal.

Key Entry **Number of Satellites**

:SCENario:STATus

Supported E4438C with Option 409

```
[:SOURCE]:RADIO:MSGPS:SCENario:STATus?
```

This query returns the following information for the currently selected scenario as a comma-separated list:

Scenario date, scenario time, scenario position, scenario length, satellite IDs

Key Entry **Scenario**

[:STATe]

Supported E4438C with Option 409

```
[:SOURCE]:RADIO:MSGPS[:STATe] ON|OFF|1|0  
[:SOURCE]:RADIO:MSGPS[:STATe] ?
```

This command enables or disables the real-time MSGPS signal.

***RST** 0

Key Entry **Real-time MSGPS Off On**

GSM Subsystem–Option 402 ([:SOURce]:RADio:GSM)

:ALPha

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:GSM:ALPha <val>  
[ :SOURce ] :RADio:GSM:ALPha?
```

This command changes the Nyquist or root Nyquist filter’s alpha value.

The filter alpha value can be set to the minimum level (0), the maximum level (1), or in between by using fractional numeric values (0.001–0.999).

***RST** +5.00000000E–001

Range 0.000–1.000

Key Entry **Filter Alpha**

Remarks To change the current filter type, refer to “:FILTer” on page 786.

:BBCLock

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:GSM:BBCLock INT [1] | EXT [1]  
[ :SOURce ] :RADio:GSM:BBCLock?
```

This command toggles the data (bit) clock input to the baseband generator board to either internal or external. This command is independent in each mode and works for both non-burst (continuous) and burst modes. This allows for a matrix of selections between burst/non-burst, internal/external data generation, internal/external data clock, and external bit/symbol data clock.

INT[1] This choice selects the signal generator internal data clock.

EXT[1] This choice selects an external data clock input.

***RST** INT

Key Entry **BBG Data Clock Ext Int**

Remarks A data clock or continuous symbol sync input must be supplied when external mode is used.

This will be ignored if the external reference is set to EXTERNAL. To change the external reference type, refer to “:EREFerence” on page 785.

:BBT

Supported E4438C with Option 402

[:SOURCE] :RADIO:GSM:BBT <val>

[:SOURCE] :RADIO:GSM:BBT?

This command changes the bandwidth-multiplied-by-bit-time (BbT) filter parameter.

The filter BbT value can be set to the maximum level (1) or in between the minimum level (0.100) and maximum level by using fractional numeric values (0.101–0.999).

***RST** +3.00000000E-001

Range 0.100–1.000

Key Entry **Filter BbT**

Remarks This command is effective only after choosing a Gaussian filter. It does not have an effect on other types of filters.

To change the current filter type, refer to “:FILTer” on page 786.

:BRATe

Supported E4438C with Option 402

[:SOURCE] :RADIO:GSM:BRATe <val>

[:SOURCE] :RADIO:GSM:BRATe?

This command sets the bit rate in bits per second (bps–Mbps). The maximum bit rate is dependent on the modulation type and filter as shown in the following tables.

NOTE When using multiframe, limit the symbol rate to no more than 271 ksps. Although higher rates may work, they are not supported. See “:SRATe” on page 804 for data stated as symbol rates.

The IQ digital data stream is shaped by a FIR filter. The filter length and associated latency and frequency response are dependent on the bit rate as shown in the following tables. The signal generator selects a filter length.

For higher bit rates, the FIR filter length may be truncated (if the minimum filter size allows it) which will impact the relative timing of the modulated data, as well as the actual filter response (see the symbol rate command “:SRATe” on page 965). Refer to “:FILTer” on page 786 for information on filter symbol widths.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 789.

When the bit rate is changed, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the bit rate: lower bit rates require more time.

***RST** +2.70833333E+005

Range	Modulation Type	Bit Rate Range		
		<i>16 Symbol Wide Filter</i>	<i>32 Symbol Wide Filter</i>	<i>64 Symbol Wide Filter</i>
BPSK, FSK2, MSK		1bps–50Mbps	1bps–25Mbps	1bps–12.5Mbps
C4FM, OQPSK, FSK4	OQPSKI95, QPSK P4QPPSK, QPSKIS95 GRAYQPSK, QAM4	2bps–50Mbps	2bps–25Mbps	2bps–12.5Mbps
D8PSK, EDGE, FSK8, PSK8		3bps–50Mbps	3bps–25Mbps	3bps–12.5Mbps
FSK16, PSK16, QAM16		4bps–50Mbps	4bps–25Mbps	4bps–12.5Mbps
QAM32		5bps–50Mbps	5bps–25Mbps	5bps–12.5Mbps
QAM64		6bps–50Mbps	6bps–25Mbps	6bps–12.5Mbps
QAM128		7bps–50Mbps	7bps–25Mbps	7bps–12.5Mbps
QAM256		8bps–50Mbps	8bps–25Mbps	8bps–12.5Mbps

Key Entry **Symbol Rate**

:BURSt:PN9

Supported E4438C with Option 402

[:SOURce] :RADio:GSM: BURSt : PN9 NORMal | QUICk
 [:SOURce] :RADio:GSM: BURSt : PN9?

This command controls the software PN9 generation.

NORMal This choice produces a maximum length PN9 sequence.

QUICk This choice produces a truncated PN9 sequence.

***RST** NORM

Key Entry PN9 Mode Normal Quick

GSM Subsystem—Option 402 (:SOURce):RADio:GSM)

Remarks Use Normal mode for bit-error-rate tests where a maximum length PN9 sequence is required.

:BURSt:SHAPe:FALL:DELay

Supported E4438C with Option 402

[:SOURce] :RADio:GSM: BURSt :SHAPe :FALL :DELay <val>

[:SOURce] :RADio:GSM: BURSt :SHAPe :FALL :DELay?

This command sets the burst shape fall delay.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range -11.0625 to 99

Key Entry **Fall Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 789.

Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FDELay” on page 777 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:FALL:TIME

Supported E4438C with Option 402

[:SOURce] :RADio:GSM: BURSt :SHAPe :FALL :TIME <val>

[:SOURce] :RADio:GSM: BURSt :SHAPe :FALL :TIME?

This command sets the burst shape fall time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +1.00000000E+001

Range 0.0625–127.9375

Key Entry	Fall Time
Remarks	<p>The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.</p> <p>To change the modulation type, refer to “:MODulation[:TYPE]” on page 789. Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.</p> <p>“:BURSt:SHAPe:FTIME” on page 778 performs the same function; in compliance with the SCPI standard, both commands are listed.</p> <p>For concept information on burst shaping, refer to the <i>E4428C/38C ESG Signal Generators User’s Guide</i>.</p>

:BURSt:SHAPe:FDElay

Supported	E4438C with Option 402
	<pre>[:SOURCE] :RADIO:GSM:BURSt:SHAPe:FDElay <val> [:SOURCE] :RADIO:GSM:BURSt:SHAPe:FDElay?</pre>
	<p>This command sets the burst shape fall delay.</p> <p>The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.</p>
*RST	+0.00000000E+000
Range	–11.0625 to 99
Key Entry	Fall Delay
Remarks	<p>The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.</p> <p>To change the modulation type, refer to “:MODulation[:TYPE]” on page 789. Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.</p> <p>“:BURSt:SHAPe:FALL:DElay” on page 776 performs the same function; in compliance with the SCPI standard, both commands are listed.</p> <p>For concept information on burst shaping, refer to the <i>E4428C/38C ESG Signal Generators User’s Guide</i>.</p>

:BURSt:SHAPe:FTIME

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:BURSt:SHAPe:FTIME <val>

[:SOURCE] :RADio:GSM:BURSt:SHAPe:FTIME?

This command sets the burst shape fall time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +3.00000000E+000

Range 0.0625–127.9375

Key Entry Fall Time

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 789.

Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FALL:TIME” on page 776 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RDElay

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:BURSt:SHAPe:RDElay <val>

[:SOURCE] :RADio:GSM:BURSt:SHAPe:RDElay?

This command sets the burst shape rise delay.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate. For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

***RST** +0.00000000E+000

Range –8.0625 to 99

Key Entry Rise Delay

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 789. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:RISE:DELay” on page 779 performs the same function; in compliance with the SCPI standard, both commands are listed.

:BURSt:SHAPe:RISE:DELay

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:GSM:BURSt:SHAPe:RISE:DELay <val>  
[ :SOURce ] :RADio:GSM:BURSt:SHAPe:RISE:DELay?
```

This command sets the burst shape rise delay.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate. For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User's Guide*.

***RST** +0.00000000E+000

Range -8.0625 to 99

Key Entry Rise Delay

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 789. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:RISE:DELay” on page 778 performs the same function; in compliance with the SCPI standard, both commands are listed.

:BURSt:SHAPe:RISE:TIME

Supported E4438C with Option 402

[:SOURCE] :RADIo:GSM:BURSt:SHAPe:RISE:TIME <val>

[:SOURCE] :RADIo:GSM:BURSt:SHAPe:RISE:TIME?

This command sets the burst shape rise time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate. For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User's Guide*.

***RST** +3.00000000E+000

Range 0.0625–11.1875

Key Entry Rise Time

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 789.

Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:RTIME” on page 780 performs the same function; in compliance with the SCPI standard, both commands are listed.

:BURSt:SHAPe:RTIME

Supported E4438C with Option 402

[:SOURCE] :RADIo:GSM:BURSt:SHAPe:RTIME <val>

[:SOURCE] :RADIo:GSM:BURSt:SHAPe:RTIME?

This command sets the burst shape rise time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate. For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User's Guide*.

***RST** +3.00000000E+000

Range 0.0625–11.1875

Key Entry Rise Time

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 789. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:RISE:TIME” on page 780 performs the same function; in compliance with the SCPI standard, both commands are listed.

:BURSt:SHAPe[:TYPE]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:BURSt:SHAPe[:TYPE] SINE| "<file name>"
[:SOURCE]:RADIO:GSM:BURSt:SHAPe[:TYPE] ?
```

This command specifies the burst shape as either SINE or a user-defined file ("<file name>").

SINE This choice selects a state that is defined by the burst rise and fall *RST values, as the default burst shape type.

"<file name>" This choice selects a user designated file from signal generator memory (non-volatile).

***RST** SINE

Key Entry **Sine User File**

:BURSt[:STATe]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:BURSt[:STATe] ON|OFF|1|0
[:SOURCE]:RADIO:GSM:BURSt[:STATe] ?
```

This command enables or disables the burst function.

ON (1) This choice enables the transmission of framed data. If all timeslots which are switched on are up traffic channels or custom, you will be bursting the timeslots that are on; there will be no RF carrier during the off timeslots.

If you have switched on any timeslot that you have configured as a down traffic channel, the RF carrier is not switched off between any of the timeslots. The off timeslots are transmitted as a continuous series of ones for the time period of the off timeslots.

OFF (0) This choice enables the transmission of unframed data.

GSM Subsystem—Option 402 ([:SOURCE]:RADio:GSM)

***RST** 0
Key Entry Data Format Pattern Framed

:CHANnel

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:GSM:CHANnel EVM|ACP
[ :SOURCE ] :RADio:GSM:CHANnel?
```

This command optimizes the Nyquist and root Nyquist filters to minimize error vector magnitude (EVM) or to minimize adjacent channel power (ACP).

EVM This choice provides the most ideal passband.

ACP This choice improves stopband rejection.

***RST** ACP

Key Entry **Optimize FIR For Evm ACP**

Remarks To change the current filter type, refer to “:FILTer” on page 786.

:DATA

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:GSM:DATA PN9|PN11|PN15|PN20|PN23|FIX4|"<file name>"|
EXT|P4|P8|P16|P32|P64|PRAM
[ :SOURCE ] :RADio:GSM:DATA?
```

This command sets the data pattern type (pseudo-random number sequence, 4-bit pattern, sequence of 1’s and 0’s, data from an external source, or a user file) for unframed data transmission.

***RST** PN23

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	Ext
	4 1’s & 4 0’s		8 1’s & 8 0’s		16 1’s & 16 0’s		32 1’s & 32 0’s	
	64 1’s & 64 0’s	PRAM File						

Remarks Refer to “File Name Variables” on page 13 for information on the file name syntax.

:DATA:PRAM

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:DATA:PRAM "<file_name>"
```

```
[ :SOURCE ] :RADIo:GSM:DATA:PRAM?
```

This command selects a pattern RAM (PRAM) file as the pattern data type for the GSM (Global System for Mobile communication) format.

"<file_name>" This variable designates the PRAM file in WFM1. Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

Key Entry **PRAM File**

Remarks Selecting this data source forces the burst source to INTERNAL to allow framing control.

The PRAM file must reside in the signal generator’s volatile memory (WFM1) in order to be accessed by this command. For more information on PRAM files, refer to [“:DATA:PRAM:FILE:BLOCK” on page 112](#).

:DATA:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:DATA:FIX4 <val>
```

```
[ :SOURCE ] :RADIo:GSM:DATA:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern for unframed transmission according to the modulation type, symbol rate, filter, and burst shape selected for the GSM modulation format.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:DEFault

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:DEFault
```

This command returns all of the GSM format parameters to their factory default conditions. It does not affect any other signal generator parameters.

GSM Subsystem—Option 402 ([:SOURCE]:RADio:GSM)

Key Entry Restore GSM Factory Default

:DENCode

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:DENCode ON|OFF|1|0

[:SOURCE] :RADio:GSM:DENCode?

This command enables or disables the differential data encoding function. Once this function is enabled, data bits are encoded prior to modulation; each modulated bit is 1 if the data bit is different from the previous one, or 0 if the data bit is the same as the previous one.

***RST** 1

Key Entry **Diff Data Encode Off On**

EDATa:DELaY

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:EDATa:DELaY?

This query returns the amount of delay (in symbols) from the external data input to the beginning of the symbol on the I OUT and Q OUT rear panel connectors and the front panel RF OUTPUT connector.

Remarks When the format is turned off, the delay value is unchanged; the query will return the same delay value if the format is on or off.

:EDCLock

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:EDCLock SYMBol|NORMal

[:SOURCE] :RADio:GSM:EDCLock?

This command sets the external data clock use.

SYMBol This choice specifies that a continuous symbol clock signal must be provided to the SYMBOL SYNC input connector.

NORMal This choice specifies that the DATA CLOCK input connector requires a bit clock. The SYMBOL SYNC input connector requires a (one-shot or continuous) symbol sync signal.

***RST** NORM

Key Entry **Ext Data Clock Normal Symbol**

Remarks Both choices have no effect in internal clock mode. Refer to “:BBCLock” on page 773 to select EXT as the data clock type.

:EREFerence

Supported E4438C with Option 402

[:SOURCE] :RADIo:GSM:EREFerence INT|EXT

[:SOURCE] :RADIo:GSM:EREFerence?

This command selects either an internal or external bit-clock reference for the data generator.

***RST** INT

Key Entry **BBG Ref Ext Int**

Remarks If the EXT choice is selected, the external source’s frequency value must be applied to the BASEBAND GEN REF IN rear panel connector. The external reference and external data clock are not applicable at the same time. If both are selected, then the external reference takes precedence.

:EREFerence:VALue

Supported E4438C with Option 402

[:SOURCE] :RADIo:GSM:EREFerence:VALue <val>

[:SOURCE] :RADIo:GSM:EREFerence:VALue?

This command sets the expected bit-clock reference frequency value for an externally applied reference signal.

The variable <val> is expressed in units of hertz (Hz–MHz).

***RST** +1.30000000E+007

Range 2.5E5–1E8

Key Entry **Ext BBG Ref Freq**

Remarks The value specified by this command is effective only when you are using an external reference applied to the BASEBAND GEN REF IN rear panel connector.

Refer to “:EREFerence” on page 785 to select EXT (external source) as the reference for the bit-clock reference.

:FILTER

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:FILTER RNYQuist|NYQuist|GAUSSian|RECTangle|
IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|"<user FIR>"
[:SOURCE]:RADIO:GSM:FILTER?
```

This command selects the pre-modulation filter type.

- IS95 This choice selects a filter that meets the criteria of the IS-95 standard.
- IS95_EQ This choice selects a filter which is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard. This filter is only used for IS-95 baseband filtering.
- IS95_MOD This choice selects a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.
- IS95_MOD_EQ This choice selects a filter which is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.
- AC4Fm This choice selects a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.
- UGGaussian This choice selects a backwards compatible GSM Gaussian filter (Gaussian filter with a fixed BbT value of 0.300) for the ESG E44xxB Option UN3 or UN4.
- "<user FIR>" This variable is any filter file that you have stored into memory.

***RST** GAUS

Key Entry	Root Nyquist	Nyquist	Gaussian	Rectangle	IS-95	IS-95 w/EQ
	IS-95 Mod	IS-95 Mod w/EQ	APCO 25 C4FM	UN3/4 GSM Gaussian		
	User FIR					

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:IQ:SCALE

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:IQ:SCALE <val>
```

```
[ :SOURCE ] :RADIo:GSM:IQ:SCALE?
```

This command sets the amplitude of the I/Q outputs for better adjacent channel power (ACP); lower scaling values equate to better ACP.

The variable <val> is expressed in units of percent.

***RST** +100

Range 1–200

Key Entry **I/Q Scaling**

Remarks This command has no effect with MSK or FSK modulation.

:MODulation:FSK[:DEVIation]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:MODulation:FSK[:DEVIation] <val>
```

```
[ :SOURCE ] :RADIo:GSM:MODulation:FSK[:DEVIation]?
```

This command sets the symmetric FSK frequency deviation value.

The variable <val> is expressed in units of Hertz and the maximum range value equals the current symbol rate value multiplied by four, limited to 20 MHz.

***RST** +4.00000000E+002

Range 0–2E7

Key Entry **Freq Dev**

Remarks To change the modulation type, refer to “:MODulation[:TYPE]” on page 789.

Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

To set an asymmetric FSK deviation value, refer to the *E4428C/38C ESG Signal Generators User’s Guide* for more information.

:MODulation:MSK[:PHASe]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:GSM:MODulation:MSK[:PHASe] <val>  
[ :SOURCE ] :RADIO:GSM:MODulation:MSK[:PHASe] ?
```

This command sets the MSK phase deviation value. The variable <val> is in units of degrees

***RST** +9.00000000E+001

Range 0–100

Key Entry Phase Dev

:MODulation:UFSK

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:GSM:MODulation:UFSK "<file name>"  
[ :SOURCE ] :RADIO:GSM:MODulation:UFSK?
```

This command selects a user-defined FSK file from the signal generator memory.

Key Entry **User FSK**

Remarks The user-defined FSK file is held in signal generator memory until the command that selects user FSK as the modulation type is sent. See “:MODulation[:TYPE]” on page 789 to change the current modulation type.

See “File Name Variables” on page 13 for information on the file name syntax.

:MODulation:UIQ

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:GSM:MODulation:UIQ "<file name>"  
[ :SOURCE ] :RADIO:GSM:MODulation:UIQ?
```

This command selects a user-defined I/Q file from the signal generator memory.

Key Entry **User I/Q**

Remarks The user-defined I/Q file is held in signal generator memory until the command that selects user I/Q as the modulation type is sent. Refer to “:MODulation[:TYPE]” on page 789 to change the current modulation type.

See “File Name Variables” on page 13 for information on the file name syntax.

:MODulation[:TYPE]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:GSM:MODulation [ :TYPE ] BPSK | QPSK | IS95QPSK |
GRAYQPSK | OQPSK | IS95OQPSK | P4DQPSK | PSK8 | PSK16 | D8PSK | MSK | FSK2 | FSK4 | FSK8 |
FSK16 | C4FM | QAM4 | QAM16 | QAM32 | QAM64 | QAM128 | QAM256 | UIQ | UFSK
[ :SOURce ] :RADio:GSM:MODulation [ :TYPE ] ?
```

This command sets the modulation type for the GSM personality.

***RST** MSK

Key Entry	BPSK	QPSK	IS-95 QPSK	Gray Coded QPSK	OQPSK			
	IS-95 OQPSK	$\pi/4$ DQPSK	8PSK	16PSK	D8PSK	MSK	2-Lvl FSK	
	4-Lvl FSK	8-Lvl FSK	16-Lvl FSK	C4FM	4QAM	16QAM	32QAM	
	64QAM	128QAM	256QAM	User I/Q	User FSK			

:POLarity[:ALL]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:GSM:POLarity [ :ALL ] NORMal | INVerted
[ :SOURce ] :RADio:GSM:POLarity [ :ALL ] ?
```

This command sets the rotation direction of the phase modulation vector.

NORMal This choice selects normal phase polarity.

INVerted This choice inverts the internal Q signal.

***RST** NORM

Key Entry **Phase Polarity Normal Invert**

Remarks This command is useful for lower sideband mixing applications.

:SECondary:RECall

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:SECondary:RECall

This command recalls the secondary frame configuration, overwriting the current state.

Key Entry **Recall Secondary Frame State**

Remarks To save a secondary frame state, refer to “:SECondary:SAVE” on page 790.

A secondary frame is not active until the secondary state is enabled. To activate a secondary frame, refer to “:SECondary[:STATE]” on page 791.

:SECondary:SAVE

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:SECondary:SAVE

This command saves the current frame configuration as the secondary frame with the filename GSM_SECONDARY_FRAME.

Key Entry **Save Secondary Frame State**

Remarks To recall the secondary frame state (saved in non-volatile signal generator memory), refer to “:SECondary:RECall” on page 790.

:SECondary:TRIGger[:SOURCE]

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:SECondary:TRIGger [:SOURCE] KEY | EXT | BUS
[:SOURCE] :RADio:GSM:SECondary:TRIGger [:SOURCE] ?

This command selects the type of triggering for the secondary frame.

KEY This choice enables triggering by pressing the front panel **Trigger** hardkey.

EXT This choice enables triggering using an externally applied signal at the PATT TRIG IN rear panel connector or the PATT TRIG IN 2 pin on the rear panel AUX I/O connector. To select the appropriate connector, refer to “:TRIGger[:SOURCE]:EXTernal[:SOURCE]” on page 810.

BUS This choice enables GPIB triggering using the *TRG or GET command or LAN and RS-232 triggering using the *TRG command.

Key Entry **Trigger Key Ext Bus**

:SECondary[:STATe]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SECondary[:STATe] ON|OFF|1|0
[:SOURCE]:RADIO:GSM:SECondary[:STATe] ?
```

This command enables or disables the ability to switch to the secondary frame.

***RST** 0

Key Entry **Secondary Frame Off On**

Remarks A frame must already be saved as the secondary frame in order to turn the secondary state function on. To save a frame as the secondary frame, refer to [“:SECondary:SAVE” on page 790](#).

:SLOT0|[1]|2|3|4|5|6|7:ACCess:ENCRyption

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:ENCRyption
PN9|PN15|FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:ENCRyption?
```

This command creates and configures an access encrypted data field.

***RST** PN9

Key Entry **PN9 PN15 FIX4 User File Ext 4 1's & 4 0's 8 1's & 8 0's**
16 1's & 16 0's 32 1's & 32 0's 64 1's & 64 0's

Remarks See [“File Name Variables” on page 13](#) for information on the file name syntax.

:SLOT0|[1]|2|3|4|5|6|7:ACCess:ENCRyption:FIX4

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:ENCRyption:FIX4 <val>
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:ENCRyption:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected access timeslot encryption field.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT0|[1]|2|3|4|5|6|7:ACCess:ETAIl

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:ETAIl <bit_pattern>
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:ETAIl?
```

This command specifies the extended tail bits (8 bits) field for the selected access timeslot.

***RST** #H3A

Range #H00–#HFF

Key Entry ET

:SLOT0|[1]|2|3|4|5|6|7:ACCess:SSEQuence

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:SSEQuence <bit_pattern>
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:SSEQuence?
```

This command specifies the synchronization sequence bits (41 bits) for the selected access timeslot.

***RST** #H096FF335478

Range #H0–#H1FFFFFFFF

Key Entry SS

:SLOT0|[1]|2|3|4|5|6|7:ACCess:CUSTom

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:CUSTom PN9|PN15|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:CUSTom?
```

This command configures the data field for the selected custom timeslot.

***RST** PN9

Key Entry **PN9** **PN15** **FIX4** **User File** **Ext** **4 1's & 4 0's** **8 1's & 8 0's**
16 1's & 16 0's **32 1's & 32 0's** **64 1's & 64 0's**

Remarks See “File Name Variables” on page 13 for information on the file name syntax.

:SLOT0|[1]|2|3|4|5|6|7:CUSTom:FIX4

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:CUSTom:FIX4 <val>
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:CUSTom:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected custom timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT0|[1]|2|3|4|5|6|7:DUMMy:TSEQuence

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:DUMMy:TSEQuence TSC0|
TSC1|TSC2|TSC3|TSC4|TSC5|TSC6|TSC7|<bit_pattern>
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:DUMMy:TSEQuence?
```

This command changes the 26-bit dummy training sequence (TS) for the selected dummy timeslot.

***RST** #H0000000

Range <bit_pattern>: #H0–#H3FFFFFF

Key Entry **TSC0 TSC1 TSC2 TSC3 TSC4 TSC5 TSC6 TSC7**
Custom TS

Remarks When normal preset is selected, the preset hexadecimal value for TS reflects the GSM protocol, however you may use this command to enter a new value.

:SLOT0|[1]|2|3|4|5|6|7:MULTIslot

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:MULTIslot ON|OFF|1|0
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:MULTIslot?
```

This command turns bursting (ramping) on or off between the selected timeslot and the next higher numbered adjacent timeslot.

ON (1) This choice turns ramping off between timeslots.

OFF (0) This choice turns ramping on between timeslots.

***RST** 0

Key Entry **Multislot Off On**

SLOT0|[1]|2|3|4|5|6|7:NORMa1:ENCRyption

Supported E4438C with Option 402

```
[:SOURCE]:RADio:GSM:SLOT0|[1]|2|3|4|5|6|7:NORMa1:ENCRyption
PN9|PN15|FIX4|"<filename>"|EXT|P4|P8|P16|P32|P64|TCHFS|TCHHS|CS1|CS4|
DMCS1|UMCS1|BCH1|BCH2
[:SOURCE]:RADio:GSM:SLOT0|[1]|2|3|4|5|6|7:NORMa1:ENCRyption?
```

This command creates and configures an encrypted data field for a normal timeslot.

- PN9 This choice uses a standard PN9 bit pattern. In the case of TDMA bursted data, a PN9 repeats continuously, running from one timeslot to the matching timeslot in the next frame.
- PN15 This choice uses a standard PN15 bit pattern. In the case of TDMA bursted data, a PN15 repeats continuously, running from one timeslot to the matching timeslot in the next frame.
- FIX4 This choice uses a fixed 4-bit pattern. The selected 4-bit pattern will be repeated as necessary to fill the selected data to set the desired pattern.
- User File This choice selects a user-supplied file to be used as the bit pattern. In the case of TDMA bursted data, enough bits must be supplied to fill the desired number of timeslots (left over bit are ignored). User files contain 8 data bits per byte.
- EXT This choice uses an external user signal as the modulating data stream. Serial data is supplied via the front panel DATA BNC connector.
- P4 This choice selects a data pattern with 4 1's followed by 4 0's. The selected pattern will be repeated as necessary to fill the selected data area.
- P8 This choice selects a data pattern with 8 1's followed by 8 0's. The selected pattern will be repeated as necessary to fill the selected data area.
- P16 This choice selects a data pattern with 16 1's followed by 16 0's. The selected pattern will be repeated as necessary to fill the selected data area.
- P32 This choice selects a data pattern with 32 1's followed by 32 0's. The selected pattern will be repeated as necessary to fill the selected data area.
- P64 This choice selects a data pattern with 64 1's followed by 64 0's. The selected pattern will be repeated as necessary to fill the selected data area.
- TCHFS This choice selects traffic channel with full rate speech (TCH/FS). This channel would be represented by a 26 frame multiframe with an SACCH and IDLE frame.

TCHHS	This choice selects traffic channel with half rate speech (TCH/HS). This is when a complex coding scheme is used that can allow two mobile stations to share the same timeslot. On an ESG this is represented by having one timeslot with a normal burst and user definable training sequence and the same timeslot on an alternate frame using a dummy burst. This represents the situation where TCH/HS is being used in one timeslot and the other timeslot is not being used.
CS-1	This choice selects the CS-1 channel, a packet data traffic channel with block type 1 as per 3GPP standard GSM 05.03.
CS4	This choice selects the CS-4 channel, a packet data traffic channel with block type 4 as per 3GPP standard GSM 05.03.
DMCS1	This choice selects the downlink MCS-1 channel, a packet data traffic channel with block type 5 as per 3GPP standard GSM 05.03.
UMCS1	This choice selects the uplink MCS-1 channel, a packet data traffic channel with block type 5 as per 3GPP standard GSM 05.03.
BCH1	This choice selects a non-combined broadcast channel. BCH1 can only be set in timeslot zero and can be the only multiframe type in a frame. This means that BCH1 will conflict with the following parameters: TCH/FS, TCH/HS, CS-1, CS-4, DMCS-1 and UMCS-1.
BCH2	This choice selects a combined broadcast channel. BCH2 can only be set in timeslot zero and can be the only multiframe type in a frame. This means that BCH2 will conflict with the following parameters: TCH/FS, TCH/HS, CS-1, CS-4, DMCS-1, and UMCS-1.
*RST	PN9
Range	BCH1: 0–65535 BCH2: 0–65535
Key Entry	PN9 PN15 FIX4 User File Ext 4 1's & 4 0's 8 1's & 8 0's 16 1's & 16 0's 32 1's & 32 0's 64 1's & 64 0's TCH/FS TCH/HS CS-1 CS-4 Downlink MCS-1 Uplink MCS-1
Remarks	See “File Name Variables” on page 13 for information on the file name syntax.

:SLOT0:NORMAL:ENCRyption:BCH1:BCC**Supported** E4438C with Option 416

[:SOURCE]:RADIO:GSM:SLOT0:NORMAL:ENCRyption:BCH1:BCC <val>

[:SOURCE]:RADIO:GSM:SLOT0:NORMAL:ENCRyption:BCH1:BCC?

This command sets the broadcast control code (BCC) which is used to indicate what training sequence is being used by the basestation in the forward channels. This code will allow the mobile station to decode the other channels in the broadcast channel.

RST** 0**Range** 0–7**:SLOT0:NORMAL:ENCRyption:BCH1:CELLid*Supported** E4438C with Option 416

[:SOURCE]:RADIO:GSM:SLOT0:NORMAL:ENCRyption:BCH1:CELLid <val>

[:SOURCE]:RADIO:GSM:SLOT0:NORMAL:ENCRyption:BCH1:CELLid?

This command sets the cell identification. This will identify a cell within a location area.

RST** 0**Range** 0–65535**:SLOT0:NORMAL:ENCRyption:BCH1:LAC*Supported** E4438C with Option 416

[:SOURCE]:RADIO:GSM:SLOT0:NORMAL:ENCRyption:BCH1:LAC <val>

[:SOURCE]:RADIO:GSM:SLOT0:NORMAL:ENCRyption:BCH1:LAC?

This command sets the location area code (LAC). The location area code provides 16 bits to allow the administrator to define a location.

***RST** 0**Range** 0–65535

:SLOT0:NORMAL:ENCRyption:BCH1:MCC

Supported E4438C with Option 416

[:SOURCE] :RADIo:GSM:SLOT0:NORMAl:ENCRyption:BCH1:MCC <val>

[:SOURCE] :RADIo:GSM:SLOT0:NORMAl:ENCRyption:BCH1:MCC?

This command sets the mobile country code (MCC). The mobile country code is a 12 bit number used to represent the country where the basestation is located.

***RST** 0

Range 0–4095

:SLOT0:NORMAL:ENCRyption:BCH1:MNC

Supported E4438C with Option 416

[:SOURCE] :RADIo:GSM:SLOT0:NORMAl:ENCRyption:BCH1:MNC <val>

[:SOURCE] :RADIo:GSM:SLOT0:NORMAl:ENCRyption:BCH1:MNC?

This command sets the mobile network code (MNC). The mobile network code is the individual number a network will be assigned.

***RST** 0

Range 0–255

Remarks Federal regulation mandates that a 3-digit MNC will be used. For the ESG implementation the upper four bits are set to 1111.

:SLOT0:NORMAL:ENCRyption:BCH1:PLMN

Supported E4438C with Option 416

[:SOURCE] :RADIo:GSM:SLOT0:NORMAl:ENCRyption:BCH1:PLMN <val>

[:SOURCE] :RADIo:GSM:SLOT0:NORMAl:ENCRyption:BCH1:PLMN?

This command is used to set the Public Land Mobile Network (PLMN) which is used to indicate the country the phone is in. PLMN is also referred to as the National Country Code (NCC).

***RST** 0

Range 0–7

:SLOT0|[1]|2|3|4|5|6|7:NORMAL:ENCRyption:CS1:DATA

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:CS1:DATA  
PN9 | PN15  
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:CS1:DATA?
```

This command sets the bit pattern for the CS1 packet data traffic channel.

***RST** PN9

Key Entry **PN9 PN15**

:SLOT0|[1]|2|3|4|5|6|7:NORMAL:ENCRyption:CS4:DATA

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo [1] | 2 | 3 | 4 :GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:CS4  
:DATA PN9 | PN15  
[ :SOURCE ] :RADIo [1] | 2 | 3 | 4 :GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:CS4  
:DATA?
```

This command selects the encryption field data, if the selected timeslot uses the packet data block type 4 coding scheme.

***RST** PN9

Key Entry **PN9 PN15**

Remarks Refer to “[SLOT0|\[1\]|2|3|4|5|6|7:NORMAL:ENCRyption](#)” on page 794 for selecting the coding scheme.

:SLOT0|[1]|2|3|4|5|6|7:NORMAL:ENCRyption:DLINK:MCS1:DATA

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:DLINK:MCS1:  
DATA PN9 | PN15  
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:DLINK:MCS1:  
DATA?
```

This command sets the bit pattern for the downlink MCS1 packet data traffic channel.

***RST** PN9

Key Entry **PN9 PN15**

:SLOT0|[1]|2|3|4|5|6|7:NORMAL:ENCRyption:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:FIX4 <val>  
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected normal timeslot encryption field.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT0|[1]|2|3|4|5|6|7:NORMAL:ENCRyption:TCH:FS:DATA

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:TCH:FS:DATA  
PN9 | PN15  
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:TCH:FS:DATA?
```

This command sets the bit pattern for the TCH/FS channel.

***RST** PN9

Key Entry **PN9 PN15**

:SLOT0|[1]|2|3|4|5|6|7:NORMAL:ENCRyption:ULINK:MCS1:DATA

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:ULINK:MCS1:  
DATA PN9 | PN15  
[ :SOURCE ] :RADIo:GSM:SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:ULINK:MCS1:  
DATA?
```

This command sets the bit pattern for the uplink MCS1 packet data traffic channel.

***RST** PN9

Key Entry **PN9 PN15**

:SLOT0|[1]|2|3|4|5|6|7:NORMAL:STeal

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:NORMAL:STeal <val>
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:NORMAL:STeal?
```

This command specifies the normal stealing bits for the selected timeslot. The single bit defines the value for both 1-bit fields.

***RST** #H0

Range #H0–#H1

Key Entry **S**

:SLOT0|[1]|2|3|4|5|6|7:NORMAL:TSEQuence

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:NORMAL:TSEQuence
TSC0|TSC1|TSC2|TSC3|TSC4|TSC5|TSC6|TSC7|<bit_pattern>
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:NORMAL:TSEQuence?
```

This command changes the 26-bit training sequence (TS) for a normal timeslot. The preset hexadecimal value (when normal preset is selected) for TS reflects the GSM protocol, however you can enter a new value by using this command. The hexadecimal values for the 8 training sequence codes are listed below:

***RST** #H0000000

Range <bit_pattern>: #H0–#H3FFFFFF

Key Entry **TSC0 TSC1 TSC2 TSC3 TSC4 TSC5 TSC6 TSC7**

Custom TS

Remarks The preset hexadecimal value (when normal preset is selected) for TS reflects the GSM protocol, however you can enter a new value by using this command.

:SLOT0|[1]|2|3|4|5|6|7:POWer

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:POWer MAIN|DELTA
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:POWer?
```

This command defines the RF output power level for the selected timeslot.

MAIN This choice specifies RF output as the main power level.

DELTA This choice specifies RF output as the alternative power level.

***RST** MAIN

Key Entry **Timeslot Ampl Main Delta**

:SLOT0|[1]|2|3|4|5|6|7:STATe

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:STATe ON|OFF|1|0
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:STATe?
```

This command enables or disables the operating state of the selected timeslot.

***RST** Timeslot 0: 1 Timeslot 1–7: 0

Key Entry **Timeslot Off On**

:SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRyption

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRyption PN9|PN11|PN15|
PN20|PN23|FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRyption?
```

This command creates and configures an encrypted data field for a synchronization timeslot.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's				
	64 1's & 64 0's							

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRyption:FIX4

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRyption:FIX4 <val>
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRyption:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected synchronization timeslot encryption field.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT0|[1]|2|3|4|5|6|7:SYNC:TSEQUence

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:SYNC:TSEQUence <bit_pattern>
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7:SYNC:TSEQUence?
```

This command customizes the training sequence (TS) for the selected synchronization timeslot. The preset hexadecimal value (when normal preset is selected) for TS reflects the GSM protocol, however you can enter a new value by using this command.

***RST** #HB962040F2D45761B

Range #H0–#HFFFFFFFFFFFFFFFF

Key Entry **TS**

:SLOT0|[1]|2|3|4|5|6|7[:TYPE]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7[:TYPE] CUSTom|NORMAl|
FCORrection|SYNC|DUMMy|ACCess|NORMAL_ALL
[:SOURCE]:RADIO:GSM:SLOT0|[1]|2|3|4|5|6|7[:TYPE]?
```

This command sets the timeslot type for the selected timeslot.

***RST** NORMAL

Key Entry **Custom Normal FCorr Sync Dummy Access Normal All**

:SOUT

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SOUT FRAME|SLOT|ALL
[:SOURCE]:RADIO:GSM:SOUT?
```

This command sets the synchronization location (within the pattern of data) and the type of output at the EVENT 1 rear panel connector.

FRAME This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a framed data pattern.

SLOT This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a selected timeslot.

ALL This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for all active timeslots.

***RST** FRAME

Key Entry	Begin Frame	Begin Timeslot #	All Timeslots
------------------	--------------------	-------------------------	----------------------

:SOUT:OFFSet

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:GSM:SOUT:OFFSet <val>
[:SOURCE]:RADIO:GSM:SOUT:OFFSet?
```

This command sets the offset value for the location of the output synchronization signal on the EVENT1 rear panel connector relative to the beginning of the framed data pattern or timeslot.

The variable <val> is expressed as a number of bits.

***RST** +0

Range -155 to 155

Key Entry **Sync Out Offset**

Remarks Negative values move the synchronization output signal earlier; positive values move it later.

To change the output of the EVENT1 rear panel connector to SLOT, refer to [“:SOUT” on page 803](#).

:SOUT:SLOT

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:SOUT:SLOT <val>

[:SOURCE] :RADio:GSM:SOUT:SLOT?

This command selects the timeslot that will trigger a 1-bit output signal at the EVENT 1 rear panel connector.

***RST** +0

Range 0–7

Key Entry **Begin Timeslot #**

Remarks To change the output of the EVENT1 rear panel connector to SLOT, refer to “:SOUT” on page 803.

:SRATe

Supported E4438C with Option 402

[:SOURCE] :RADio:GSM:SRATe <val>

[:SOURCE] :RADio:GSM:SRATE?

This command sets the transmission symbol rate. Symbol rate is the bit rate divided by the bits per symbol. A change in the symbol rate affects the bit rate. Refer to “:BRATe” on page 774 for information on bit rate.

The variable <val> is expressed in units of symbols per second (sps–MSPS) and the maximum symbol rate depends on the filter. Refer to “:FILTer” on page 786 for minimum filter symbol width.

NOTE When using multiframe, limit the symbol rate to no more than 271 kSPS. Although higher rates may work, they are not supported.

The filter may have to be truncated down to 32 or 16 symbols wide to achieve the highest symbol rate. The signal generator’s internal filters are not truncated below their minimum filter length and user-defined FIR filters are not truncated. If the filter cannot be truncated then the symbol rate is limited to the maximum rate of the narrowest filter size possible.

The relative timing of the modulated data, as well as the actual filter response is affected when the filter is truncated.

When the symbol rate changes, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the symbol rate: lower symbol rates require more time.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 789.

***RST** +2.70833333E+006

Range	Modulation Type	Symbol Rate Range		
		<i>16 Symbol Wide Filter</i>	<i>32 Symbol Wide Filter</i>	<i>64 Symbol Wide Filter</i>
	BPSK, FSK2, MSK	1sps–50Mspss	1sps–25Mspss	1sps–12.5Mspss
	C4FM, OQPSK, FSK4	2sps–25Mspss	2sps–12.5Mspss	2sps–6.25Mspss
	OQPSKI95, QPSK			
	P4QPPSK, QPSKIS95			
	GRAYQPSK, QAM4			
	D8PSK, EDGE, FSK8, PSK8	3sps–16.666666666 Mspss	3sps–8.333333333 Mspss	3sps–4.166666666Mspss
	FSK16, PSK16, QAM16	4sps–12.5Mspss	4sps–6.25Mspss	4sps–3.125Mspss
	QAM32	5sps–10Mspss	5sps–5Mspss	5sps–2.5Mspss
	QAM64	6sps–8.333333333 Mspss	6sps–4.166666666 Mspss	6sps–2.083333333 Mspss
	QAM128	7sps–7.142857142 Mspss	7sps–3.571428572 Mspss	7sps–1.785714285 Mspss
	QAM256	8sps–6.25Mspss	8sps–3.125 Mspss	8sps–1.5625 Mspss

NOTE Using I/Q skew will half the minimum number of symbols for the selected filter.

Key Entry **Symbol Rate**

:TRIGger:EXtErnal:DELay

Supported E4438C with Option 416

[:SOURce] :RADio:GSM:TRIGger:EXtErnal:DELay <val>

[:SOURce] :RADio:GSM:TRIGger:EXtErnal:DELay?

This command sets the trigger delay for synchronizing the ESG. The variable <val> is expressed in number of symbols.

***RST** +0

Range 0–1048575

:TRIGger:TYPE

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:TRIGger:TYPE CONTInuous | SINGle | GATE
[ :SOURCE ] :RADIo:GSM:TRIGger:TYPE?
```

This command sets the trigger type.

CONTInuous The framed data sequence repeats continuously; the sequence restarts every time the previous playback is completed. To customize continuous triggering, refer to “[:TRIGger:TYPE:CONTInuous\[:TYPE\]](#)” on page 806.

SINGle The framed data sequence plays once for every trigger received.

GATE An external trigger signal interrupts the playback while the gating signal is in the inactive state. Playback resumes when the external control signal returns to the active state. The active state can be set to high or low.

***RST** CONT

Key Entry **Continuous** **Single** **Gated**

:TRIGger:TYPE:CONTInuous[:TYPE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:GSM:TRIGger:TYPE:CONTInuous [ :TYPE ] FREE | TRIGger | RESet
[ :SOURCE ] :RADIo:GSM:TRIGger:TYPE:CONTInuous [ :TYPE ] ?
```

This commands selects the waveform’s response to a trigger signal while using the continuous trigger mode. See “[:TRIGger:TYPE](#)” on page 806 for more information on triggering modes.

The following list describes the waveform’s response to each of the command choices:

FREE Turning the ARB format on immediately triggers the waveform. The waveform repeats until the format is turned off or another trigger or waveform is selected.

TRIGger The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously until you turn the format off, select another trigger, or choose another waveform file.

RESet The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously. Subsequent triggers reset the waveform to the beginning. For a waveform sequence, this means to the beginning of the first segment in the sequence.

***RST** FREE

Key Entry **Free Run** **Trigger & Run** **Reset & Run**

:TRIGger:TYPE:GATE:ACTive

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:GSM:TRIGger:TYPE:GATE:ACTive LOW|HIGH  
[ :SOURCE ] :RADIO:GSM:TRIGger:TYPE:GATE:ACTive?
```

This command selects the active state (gate polarity) of the gate while using the gating trigger mode.

The LOW and HIGH selections correspond to the low and high states of an external trigger signal. For example, when you select HIGH, the active state occurs during the high of the trigger signal. When the active state occurs, the ESG stops the waveform playback at the last played sample point, then restarts the playback at the next sample point when the inactive state occurs. For more information on triggering and to select gating as the trigger mode, see “:TRIGger:TYPE” on page 806.

The following list describes the signal generator’s gating behavior for the external trigger signal polarity selections:

LOW	The waveform playback stops when the trigger signal goes low (active state) and restarts when the trigger signal goes high (inactive state).
HIGH	The waveform playback stops when the trigger signal goes high (active state) and restarts when the trigger signal goes low (inactive state).
*RST	HIGH

Key Entry Gate Active Low High

:TRIGger[:SOURCE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:GSM:TRIGger [ :SOURCE ] KEY|EXT|BUS  
[ :SOURCE ] :RADIO:GSM:TRIGger [ :SOURCE ] ?
```

This command sets the trigger source.

For more information on triggering, see “:TRIGger:TYPE” on page 806. The following list describes the command choices:

KEY	This choice enables manual triggering by pressing the front-panel Trigger hardkey.
EXT	An externally applied signal triggers the waveform. This is the only choice that works with gating. The following conditions affect an external trigger: <ul style="list-style-type: none">The input connector selected for the trigger signal. You have a choice between the rear-panel PATTERN TRIG IN connector or the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector. To make the connector selection, see “:TRIGger[:SOURCE]:EXTernal[:SOURCE]” on page 810.

GSM Subsystem—Option 402 ([:SOURCE]:RADio:GSM)

For more information on the connectors and on connecting the cables, see the *E4428C/38C ESG Signal Generators User's Guide*.

- The trigger signal polarity:
 - gating mode, see “:TRIGger:TYPE:GATE:ACTive” on page 807
 - continuous and single modes, see “:TRIGger[:SOURCE]:EXTernal:SLOPe” on page 809
- The time delay between when the ESG receives a trigger and when the waveform responds to the trigger. There are two parts to setting the delay:
 - setting the amount of delay, see “:TRIGger[:SOURCE]:EXTernal:DELay” on page 808
 - turning the delay on, see “:TRIGger[:SOURCE]:EXTernal:DELay:STATe” on page 809

BUS This choice enables triggering over the GPIB or LAN using the *TRG or GET commands or the AUXILIARY INTERFACE (RS-232) using the *TRG command.

***RST** KEY

Key Entry **Trigger Key** **Ext** **Bus**

:TRIGger[:SOURCE]:EXTernal:DELay

Supported E4438C with Option 402

This command sets the number of bits to delay the signal generator's response to an external trigger.

The bit delay is a delay between when the ESG receives the trigger and when it responds to the trigger. The delay uses the clocks of the bit-clock to time the delay. After the ESG receives the trigger and the set number of delay bits (clocks) occurs, the ESG transmits the data pattern.

The delay occurs after you enable the state. See “:TRIGger[:SOURCE]:EXTernal:DELay:STATe” on page 809. You can set the number of bits either before or after enabling the state.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURCE]” on page 807.

***RST** +0

Range 0–1048575

Key Entry **Ext Delay Bits**

:TRIGger[:SOURCE]:EXTErnal:DELay:FINE

Supported E4438C with Option 416

```
[ :SOURCE ] :RADio:GSM:TRIGger [ :SOURCE ] :EXTErnal:DELay:FINE <val>  
[ :SOURCE ] :RADio:GSM:TRIGger [ :SOURCE ] :EXTErnal:DELay:FINE?
```

This command sets the fine trigger delay for synchronizing the ESG.

The fine delay value is added to the coarse delay setting (see “:TRIGger[:SOURCE]:EXTErnal:DELay” on page 808).

The variable <val> is expressed as a fraction of one symbol.

***RST** +0.00000000E+000

Range 0–1

:TRIGger[:SOURCE]:EXTErnal:DELay:STATe

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:GSM:TRIGger [ :SOURCE ] :EXTErnal:DELay:STATe ON|OFF|1|0  
[ :SOURCE ] :RADio:GSM:TRIGger [ :SOURCE ] :EXTErnal:DELay:STATe?
```

This command enables or disables the operating state of the external trigger delay function.

For setting the delay time, see “:TRIGger[:SOURCE]:EXTErnal:DELay” on page 808, and for more information on configuring an external source, see “:TRIGger[:SOURCE]” on page 807.

***RST** 0

Key Entry Ext Delay Off On

:TRIGger[:SOURCE]:EXTErnal:SLOPe

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:GSM:TRIGger [ :SOURCE ] :EXTErnal:SLOPe POSitive|NEGative  
[ :SOURCE ] :RADio:GSM:TRIGger [ :SOURCE ] :EXTErnal:SLOPe?
```

This command sets the polarity for an external trigger signal while using the continuous, single triggering mode. To set the polarity for gating, see “:TRIGger:TYPE:GATE:ACTive” on page 807.

The POSitive and NEGative selections correspond to the high (positive) and low (negative) states of the external trigger signal. For example, when you select POSitive, the waveform responds (plays) during the high state of the trigger signal. When the ESG receives multiple trigger occurrences when only one is required, the signal generator uses the first trigger and ignores the rest.

Receiver Test Digital Commands (continued)
GSM Subsystem—Option 402 ([:SOURCE]:RADio:GSM)

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURCE]” on page 807.

***RST** NEG
Key Entry **Ext Polarity Neg Pos**

:TRIGger[:SOURCE]:EXTernal[:SOURCE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:GSM:TRIGger [ :SOURCE ] :EXTernal [ :SOURCE ] EPT1 |  
EPT2 | EPTRIGGER1 | EPTRIGGER2  
[ :SOURCE ] :RADio:GSM:TRIGger [ :SOURCE ] :EXTernal [ :SOURCE ] ?
```

This command selects which PATTERN TRIG IN connection the ESG uses to accept an externally applied trigger signal when external is the trigger source selection.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURCE]” on page 807. For more information on the rear-panel connectors, see the *E4428C/38C ESG Signal Generators User’s Guide*.

The following list describes the command choices:

EPT1	This choice is synonymous with EPTRIGGER1 and selects the PATTERN TRIG IN rear-panel connector.
EPT2	This choice is synonymous with EPTRIGGER2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector.
EPTRIGGER1	This choice is synonymous with EPT1 and selects the PATTERN TRIG IN rear-panel connector.
EPTRIGGER2	This choice is synonymous with EPT2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector.
*RST	EPT1
Key Entry	Patt Trig In 1 Patt Trig In 2

[:STATe]

Supported E4438C with Option 402

[:SOURce] :RADio:GSM [:STATe] ON|OFF|1|0

[:SOURce] :RADio:GSM [:STATe] ?

This command enables or disables the GSM modulation format.

***RST** 0

Key Entry **GSM Off On**

Remarks Although the GSM modulation is enabled with this command, the RF carrier is not modulated unless you also activate the front panel **Mod On/Off** hardkey.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])

The commands in this subsystem support the remote functionality of the Signal Studio for HSDPA over W-CDMA software. For a complete description of terms and HSDPA functionality, refer to the software online help. Commands used for configuring the carrier signal and performing general signal generator functions are located in different SCPI command subsystems found within the SCPI Command Reference volumes.

There are two methods to determine the SCPI commands for a setup. One method is to locate each individual command listed in this subsystem and others within the *SCPI Command Reference* volumes. The other method is to use the HSDPA software UI. After downloading a UI setup to the ESG, the software lets you export a SCPI file that contains the commands used in the UI setup. Refer to the HSDPA software online help for information on this feature.

File Overview

The ESG's memory catalog (signal generator memory) uses several file types, each assigned with a unique syntax to recall the file. This section provides information on using files with SCPI commands.

This subsystem uses the following two command variables to represent two different file types stored in signal generator memory:

"<file name>" Bit file

"<user FIR>" FIR file

For more information on managing and using files, refer to the resources in the following list:

- [“File Name Variables” on page 13](#) for information on the file name syntax
- [Table 1-4 on page 14](#) for a listing of the different file types
- *E4428C/38C ESG Signal Generators Programming Guide* for information on downloading bit files
- *E4428C/38C ESG Signal Generators User's Guide* for information on creating and editing bit and FIR files using the signal generator

NOTE To create or edit HSDPA files with the ESG, use the table editors located in the Real Time W-CDMA modulation format. Access the bit table editor through the Data field and then select **User File** as the data source. Access the FIR filter table editor through the Filter field and then select **Define User FIR** as the filter type.

HSDPA over W-CDMA Subsystem—Option 418 [:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]

The HSDPA software interface downloads user files (bit and FIR file types) to the ESG when **USER** is the software data or filter type selection. You can see these files on the ESG by pressing **Utility > Memory Catalog > Catalog Type** and then selecting the file type, or by using the SCPI commands located in the Memory subsystem. User files are located on the ESG in the following directory path: /USER/<file type directory>/<file name>. Table 9-2 shows the software naming convention for the different files created by the HSDPA software.

Table 9-2 HSDPA Software Downloaded File Names

Link Direction	Data Source	File Name	ESG File Type
Downlink and Uplink	Filter	<project name>–FIR	FIR
Downlink	BCH	<project name>–BCH	Bit
	PICH	<project name>–PICH	
	DPCH	<project name>–DPCH	
	DCH _x ^a	<project name>–DCH _x ^a	
	Inter-TTI	<project name>–ITTI _x ^b	
	HARQ ACK/NACK Pattern	<project name>–DLCPT	
	AMC CQI Pattern	<project name>–DLAPT	
	HS-DSCH	<project name>–DSCH1	
	HS-PDSCH	<project name>–HSPD _x ^b	
	HS-SCCH	<project name>–HSSCC _x ^b	
Uplink	DPCCH	<project name>–DPCCH	
	FBI	<project name>–FBI	
	TPC	<project name>–TPC	
	DPDCH	<project name>–DPDCH	
	DCH _x ^a	<project name>–DCH _x ^a	
	ACK Pattern	<project name>–APAT	
	CQI Pattern	<project name>–CPAT	

a. x is the DCH number (1–6).

b. x is the channel number (1–4) for the HSDPA, the HS-PDSCH and the HS-SCCH.

Managing ESG Setting Conflicts and Error Messages

The ESG reports setting conflicts as error messages. When a setting conflict occurs, an error number and a brief message appear at the bottom of the ESG display. You can view the full text of the error message in either of two ways: by using the front panel of the ESG, or by executing SCPI commands.

Front Panel Press **Utility > Error Info**.

SCPI Execute the SCPI error commands described in the “[System Subsystem \(:SYSTem\)](#)” on page 154.

For more information on Error messages, refer to the *E4428C/38C ESG Signal Generators Programming Guide* for remote viewing or the *E4428C/38C ESG Signal Generators User’s Guide* for front panel viewing.

:DLINK:APPLY

Supported E4438C with Option 418

```
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:APPLY
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:APPLY?
```

This command applies changes to the channel setup and data for active downlink physical and transport channels, immediately starting the channel coding generation process. A progress bar may appear on the ESG display indicating that the new signal parameters are being applied. Signal parameters are also applied when the HSDPA modulation format is turned on.

Use the query to determine whether or not execution of this command is required. It returns the following responses:

```
0                        Command execution is not required.
1                        Command execution is required.
```

NOTE The apply query response is valid only when downlink HSDPA format is active.

The apply function will not work if there is a conflict with range values and coupled parameters. For example, if all the physical channel codes are not orthogonal to each other, the new settings are not applied to the signal when this command is executed. Resolve any conflicts before reapplying the changes. The ESG reports an error when conflicts occur.

:DLINK:AWGN:CN

Supported E4438C with Option 418

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:AWGN:CN <val>  
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:AWGN:CN?
```

This command sets the downlink in-band carrier to noise ratio (C/N) value using AWGN.

***RST** 0

Range -30 to 30

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:AWGN[:STATe]

Supported E4438C with Option 418

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:AWGN [ :STATe ] ON | OFF | 0 | 1  
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:AWGN [ :STATe ] ?
```

This command turns the downlink AWGN on or off.

***RST** 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:BBClock[:SOURce]

Supported E4438C with Option 418

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:BBClock [ :SOURce ] INT | EXT  
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:BBClock [ :SOURce ] ?
```

This command selects the downlink baseband generator chip clock source, which is either internal to the signal generator or applied externally.

***RST** INT

Remarks When using an external chip clock source, connect the signal to the DATA CLOCK connector on the front panel of the ESG.

:DLINK:CPICH:CCODE**Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:CPICH:CCODE?

This query returns the CPICH channelization code, which is always set to zero.

:DLINK:CPICH:POWER**Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:CPICH:POWER <val>

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:CPICH:POWER?

This command sets the CPICH power level. The variable <val> is expressed in decibels (dB).

RST** 3.30000000E+000**Range** -40 to 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:CPICH[:STATe]*Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:CPICH[:STATe] ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:CPICH[:STATe] ?

This command turns the CPICH on or off.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:DPCH:CCODE*Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:DPCH:CCODE <val>

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:DPCH:CCODE?

This command sets the downlink DPCH channel code number.

***RST** 10**Range** 0–511

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURce]:RADio:WCDMa:HSDPa[:BBG])

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

The channel code is coupled with the slot format and all other physical channel codes. Set the channel code to not exceed limits of the slot format and ensure that all physical channel codes are orthogonal to each other. If any channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

:DLINK:DPCH:DATA

Supported E4438C with Option 418

```
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:DPCH:DATA PN9|PN15|FIX4|DCH|
"<file name>"
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:DPCH:DATA?
```

This command configures the downlink DPCH data pattern.

DCH This selects the transport channel as the data source. The DCH selection is not available for a DPCH slot format of 16.

"<file name>" This represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “File Overview” on page 812 for more information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:DPCH:DATA:FIX4

Supported E4438C with Option 418

```
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:DPCH:DATA:FIX4 <val>
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:DPCH:DATA:FIX4?
```

This command sets the downlink DPCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:DLINK:DPCH:DCH[1]|2|3|4|5|6:BSIZE****Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:DPCH:DCH[1]|2|3|4|5|6

:BSIZE <val>

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:DPCH:DCH[1]|2|3|4|5|6:BSIZE?

This command sets the block size for the selected downlink DCH.

***RST** 20**Range** 0–5000**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

The number of data bits per DCH cannot exceed 200,000. To maintain this data bit limit, the ESG calculates the product of the block size and the number of blocks. If the product of these two parameters exceeds 200,000, the apply function (downlink apply command) will not work.

:DLINK:DPCH:DCH[1]|2|3|4|5|6:CTYPE**Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:DPCH:DCH[1]|2|3|4|5|6

:CTYPE HCONv|TCONv|TURBo|NONE

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:DPCH:DCH[1]|2|3|4|5|6:CTYPE?

This command sets the coder type for the selected downlink DCH.

HCONv This choice selects the 1/2 rate convolutional encoder.**TCONv** This choice selects the 1/3 rate convolutional encoder.**TURBo** This choice selects the turbo coder.**NONE** This choice selects no coding.***RST** HCON**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6 :CRC

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :CRC 0 | 8 |  
12 | 16 | 24  
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :CRC?
```

This command sets the number of CRC bits for the selected downlink DCH.

***RST** 8

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[DLINK:APPLY](#)” on page 814.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA PN9 |  
PN15 | FIX4 | "<file name>"  
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA?
```

This command configures the data for the selected downlink DCH.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “[File Overview](#)” on page 812 for more information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[DLINK:APPLY](#)” on page 814.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:FIX4

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA:  
FIX4 <val>  
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA:FIX4?
```

This command sets the repeating 4-bit binary data pattern for the selected downlink DCH.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6:NBLocks

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :
NBLocks <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :NBLocks?
```

This command sets the number of data blocks for the selected downlink DCH.

***RST** 1

Range 0–512

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

The number of data bits per DCH cannot exceed 200,000. To maintain this data bit limit, the ESG calculates the product of the block size and the number of blocks. If the product of these two parameters exceeds 200,000, the apply function (downlink apply command) will not work.

:DLINK:DPCH:DCH[1] | 2 | 3 | 4 | 5 | 6:RMATtribute

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :
RMATtribute <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :
RMATtribute?
```

This command sets the rate matching attribute for the selected downlink DCH.

***RST** 1

Range 1–256

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:DPCH:DCH[1]|2|3|4|5|6:TTI

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :TTI 10 | 20 |  
40 | 80
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :TTI?
```

This command sets the TTI for the selected downlink DCH.

The choices are expressed in millisecond (ms).

***RST** 10

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:DPCH:DCH2|3|4|5|6[:STATE]

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH2 | 3 | 4 | 5 | 6 [ :STATE ] ON |  
OFF | 1 | 0
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:DCH2 | 3 | 4 | 5 | 6 [ :STATE ] ?
```

This command turns the selected downlink DCH on or off; DCH1 is always on.

***RST** DCH 1: 1 DCH 2–6: 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

The apply command will not work and the ESG will report an error if you turn on a DCH where lower numbered DCHs are off. For example, turning on DCH5 requires turning on DCH2–4. The reverse is true when turning off the DCHs.

:DLINK:DPCH:POWer

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:POWER <val>  
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:POWER?
```

This command sets the downlink DPCH power level.

***RST** -1.02000000E+001

Range -40 to 0

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:DPCH:SFORmat

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:SFORmat <val>
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:SFORmat?
```

This command configures the downlink DPCH slot format.

***RST** 0

Range 0–16

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

The slot format is coupled with the channel code, so a change in one value may require a change in the other. If the channel code exceeds the limits of the slot format or if it is not orthogonal with all other physical channel codes, the apply function (downlink apply command) will not work.

:DLINK:DPCH:SSCOffset

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:SSCOffset <val>
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:DPCH:SSCOffset?
```

This command sets the downlink DPCH secondary scrambling code offset.

***RST** +0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:DPCH:TFCI

Supported E4438C with Option 418

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:DPCH:TFCI <val>  
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:DPCH:TFCI?
```

This command sets the TFCI 10-bit pattern for the downlink DPCH.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** +0

Range 0–1023

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

Setting the TFCI bits is optional; they describe the type of service in use, for example voice or data.

:DLINK:DPCH:TOFFset

Supported E4438C with Option 418

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:DPCH:TOFFset <val>  
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:DPCH:TOFFset?
```

This command adjusts the downlink DPCH timing offset.

The variable <val> is expressed in chips.

***RST** +0

Range 0–149

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

:DLINK:DPCH:TPC:NSTeps

Supported E4438C with Option 418

```
[ :SOURce] :RADio:WCDMa:HSDPa [:BBG] :DLINK:DPCH:TPC:NSTeps <val>
[:SOURce] :RADio:WCDMa:HSDPa [:BBG] :DLINK:DPCH:TPC:NSTeps?
```

This command sets the number of steps for the down and up (DUP) or up and down (UDOWn) TPC pattern selections.

***RST** +1

Range 1–80

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

:DLINK:DPCH:TPC:PATtern

Supported E4438C with Option 418

```
[ :SOURce] :RADio:WCDMa:HSDPa [:BBG] :DLINK:DPCH:TPC:PATtern UDOWn|DUP|UALL|
DALL| "<file name>"
[:SOURce] :RADio:WCDMa:HSDPa [:BBG] :DLINK:DPCH:TPC:PATtern?
```

This command configures the downlink DPCH TPC pattern for increasing or decreasing, or increasing and decreasing the UE power level.

UDOWn The TPC pattern repetitively steps up and down.

DUP The TPC pattern repetitively steps down and up.

UALL The TPC pattern consecutively steps up.

DALL The TPC pattern consecutively steps down.

"<file name>" This variable represents a TPC pattern file stored in signal generator memory. The pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “[File Overview](#)” on page 812 for more information on files.

***RST** UDOW

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

Each step in a TPC pattern signals an increase or decrease of 1 dB in the UE output power level.

HSDPA over W-CDMA Subsystem—Option 418 [:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]**:DLINK:DPCH:TRPosition****Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:DPCH:TRPosition?

This query returns the downlink DPCH transport channel position that is always set to FIX.

:DLINK:DPCH[:STATe]**Supported** E4438C with Option 418[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:DPCH[:STATe] ON|OFF|1|0
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:DPCH[:STATe] ?

This command turns the downlink DPCH on or off.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:FILTer*Supported** E4438C with Option 418[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:FILTer RNYQuist|NYQuist|
GAUSSian|RECTangle|IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|
"<user FIR>"
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:FILTer?

This command selects the downlink filter type.

IS95 This filter meets the criteria of the IS-95 standard.

IS95_EQ This filter is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard and is best suited for IS-95 baseband filtering.

IS95_MOD This filter meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.

IS95_MOD_EQ This filter is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.

UGGaussian This is a GSM Gaussian filter with a fixed BbT value of 0.300.

AC4Fm This is a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])

"<user FIR>" This variable represents any FIR filter file stored in signal generator memory. Refer to [“File Overview” on page 812](#) for more information on files.

***RST** RNYQ

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 814](#).

:DLINK:FILTer:ALPHa

Supported E4438C with Option 418

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:FILTer:ALPHa <val>
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:FILTer:ALPHa?
```

This command sets the downlink Nyquist or root Nyquist filter alpha value.

***RST** +2.20000000E-001

Range 0–1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 814](#).

Executing this command while a filter other than Nyquist or root Nyquist is selected changes the parameter value, but it is not used by the signal generator until one of the Nyquist filters is selected.

:DLINK:FILTer:BBT

Supported E4438C with Option 418

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:FILTer:BBT <val>
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:FILTer:BBT?
```

This command sets the downlink Gaussian filter BbT value.

***RST** +5.00000000E-001

Range 0–1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 814](#).

Executing this command while a filter other than the Gaussian filter is selected changes the parameter value, but it is not used by the signal generator until the Gaussian filter is selected.

:DLINK:FILTer:CHANnel

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:FILTer:CHANnel EVM|ACP  
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:FILTer:CHANnel?
```

Execute this command to optimize a downlink filter for minimized EVM or for minimized ACP.

EVM This choice provides the most ideal passband

ACP This choice improves stopband rejection for the root Nyquist and Nyquist filters.

***RST** EVM

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

To change the filter selection, refer to “[:DLINK:FILTer](#)” on page 825.

:DLINK:HSBurst

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSBurst ON|OFF|1|0  
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSBurst?
```

This command sets the handling of the off slot periods for the downlink HSDPA channels.

ON|1 This choice turns off the ESG ALC feature and uses DTX during the off slots.

OFF|0 This choice continuously transmits the HSDPA channels filling the off slots with dummy bits.

***RST** 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])**:DLINK:HSDPa:AMC:CQIMapping:UECategory****Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa:AMC:CQIMapping:UECategory <val>

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa:AMC:CQIMapping:UECategory?

This command sets the UE category that determines the CQI mapping table per the 3GPP standards.

***RST** 5**Range** 1–12

Remarks To use this command's parameter in a setup, you must also set AMC as the feedback selection. Refer to the “:DLINK:HSDPa:FCONtrol” on page 829 for selecting the feedback type.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:HSDPa:AMC:CPATtern**Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa:AMC:CPATtern ALL_1|ALL_2|ALL_3|ALL_4|ALL_5|ALL_6|ALL_7|ALL_8|ALL_9|ALL_10|ALL_11|ALL_12|ALL_13|ALL_14|ALL_15|ALL_16|ALL_17|ALL_18|ALL_19|ALL_20|ALL_21|ALL_22|ALL_23|ALL_24|ALL_25|ALL_26|ALL_27|ALL_28|ALL_29|ALL_30|"<file_name>"

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa:AMC:CPATtern?

This command sets a simulated UE CQI pattern that determines HSDPA1's response including the modulation type (QPSK or 16QAM) and the constellation version for 16QAM per the set UE category.

ALL_<val> These choices configure a simulated UE ACK response with a single CQI value for 1,280 subframes.

"<file name>" This variable represents a CQI pattern file stored in signal generator memory. Create this file either by using the AMC CQI pattern Data Type Entry window and downloading the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- CQI value of 1–30 using an 8-bit pattern, 00000001 to 00011110
- DTX is represented by 11111111

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])

In the file, do not use delimiters between subframes; enter subframe bits as a binary string.

When creating a pattern, you can determine the number of active subframes from 1 to 1,280. The subframes are numbered 0 to 1,279. A subframe is active when it contains 8-bits. If a subframe contains at least 1-bit but less than 8-bits, the apply function (downlink apply command) will not work.

***RST**

ALL_21

Remarks

To use this command's parameter in a setup, you must also set AMC as the feedback selection. Refer to the “:DLINK:HSDPA:FCONTROL” for selecting the feedback type.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:HSDPA:FCONTROL

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA:FCONTROL NONE | HARQ | AMC
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA:FCONTROL ?
```

This command sets the HSDPA1 feedback control type.

NONE This choice turns off the feedback control.

HARQ This choice provides UE feedback using the HARQ process. This selection provides the capability of configuring a simulated UE ACK/NACK response, setting the maximum number of HARQ transmissions, and providing up to eight different RV parameters.

AMC This choice provides UE feedback using adaptive modulation coding. This selection provides the capability of configuring a simulated UE CQI response aligned with a UE category input.

***RST**

NONE

Remarks

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814

:DLINK:HSDPa:HARQ:APATtern**Supported** E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa:HARQ:APATtern ACK_ALL |
"<file name>"
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa:HARQ:APATtern?
```

This command sets a simulated UE ACK/NACK pattern that determines HSDPA1's HARQ response.

ACK_ALL This choice configures 1,280 subframes for a simulated ACK only response.

"<file name>" This variable represents an ACK pattern file stored in signal generator memory. Create this file either by using the HARQ ACK/NACK pattern Data Type Entry window and download the file to the ESG, or by using the ESG Real Time W-CDMA table editor to create a bit file with the following bit patterns:

- An ACK response is represented by 00.
- A NACK response is represented by 01.
- DTX is represented by 10.

In the file, do not use delimiters between subframes; enter subframe bits as a binary string.

When creating a pattern, you can determine the number of active subframes from 1 to 1,280. The subframes are numbered 0 to 1,279. A subframe is active when it contains 2-bits. If a subframe contains only 1-bit, the apply function (downlink apply command) will not work.

***RST** ACK_ALL

Remarks To use this command's parameter in a setup, you must also set HARQ as the feedback selection. Refer to the “[:DLINK:HSDPa:FCONtrol](#)” for selecting the feedback type.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

:DLINK:HSDPa:HARQ:MNHTrans**Supported** E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa:HARQ:MNHTrans <val>
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa:HARQ:MNHTrans?
```

This command configures the HSDPA1 maximum number of HARQ transmissions for the HARQ function.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURce]:RADio:WCDMa:HSDPa[:BBG])

Use the command for UE performance testing or for specifying an arbitrary number of HARQ transmissions. When the software encounters a UE NACK response that is set by the HARQ ACK pattern command (see “:DLINK:HSDPa:HARQ:APATtern”), the software re-sends the same packet payload until either the maximum number of HARQ transmissions is reached or a simulated ACK response is encountered. Whenever the software re-sends the same packet payload, it also transmits another RV parameter that is configured by the RV sequence command.

***RST** 1

Range 1–8

Remarks To use this command's parameter in a setup, you must also set HARQ as the feedback selection. Refer to the “:DLINK:HSDPa:FCONtrol” on page 829 for selecting the feedback type.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:HSDPa:HARQ:RVSequence[1]|2|3|4|5|6|7|8

Supported E4438C with Option 418

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:HSDPa:HARQ:RVSequence [1] | 2 | 3 | 4 |
5 | 6 | 7 | 8 <val>
```

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:HSDPa:HARQ:RVSequence [1] | 2 | 3 | 4 |
5 | 6 | 7 | 8?
```

This command sets the HSDPA1 RV parameter sequence used with the maximum number of HARQ transmission setting. You can set eight different RV parameters for the RV sequence.

During simulated ACK responses, the software uses the first RV parameter. When the software encounters a simulated NACK response, it sends data using the next RV parameter. The software keeps incrementing to the next RV parameter in the sequence until it receives a simulated ACK response. When the software encounters an ACK response, the RV sequence resets to the first RV parameter.

***RST** 0

Range 0–7

Remarks To use this command's parameter in a setup, you must also set HARQ as the feedback selection. Refer to the “:DLINK:HSDPa:FCONtrol” on page 829 for selecting the feedback type.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])**:DLINK:HSDPa[1] | 2 | 3 | 4:BSInfo****Supported** E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:BSInfo <val>
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:BSInfo?
```

This command sets the HS-DSCH block size. HSDPA1 is the only HSDPA channel configuration that supports the HS-DSCH, however the block size information parameter is also available for HSDPA2–4 for HS-SCCH coding purposes.

RST** 36**Range** 0–63**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDSch:COFFset*Supported** E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDSch:
COFFset <val>
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDSch:COFFset?
```

This command sets the HS-PDSCH code offset. The code offset is used in determining the HS-PDSCH channel code.

***RST** HSDPA1: 4 HSDPA2: 8 HSDPA3: 9 HSDPA4: 10**Range** 1–15**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

Set all physical channel codes orthogonal to each other. For any channel codes that fail this criteria, the apply function (downlink apply command) will not work.

:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDSch:DATA**Supported** E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDSch:DATA PN9 |
FIX4 | "<file name>" | DSCH
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1] | 2 | 3 | 4:HSPDSch:DATA?
```

This command configures the HS-PDSCH data type.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])

DSCH	This choice is the HS-DSCH selection that is supported on only HSDPA1. Selecting the DSCH choice for HSDPA2–4 will generate an error.
"<file name>"	This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “ File Overview ” on page 812 for more information on files.
*RST	PN9
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “ DLINK:APPLY ” on page 814.

:DLINK:HSDPA[1] | 2 | 3 | 4:HSPDSch:DATA:FIX4

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA [ 1 ] | 2 | 3 | 4 :HSPDSch:DATA:
FIX4 <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA [ 1 ] | 2 | 3 | 4 :HSPDSch:DATA:
FIX4?
```

This command sets the HS-PDSCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[DLINK:APPLY](#)” on page 814.

:DLINK:HSDPA:HSPDSch:DSCH:DATA

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA:HSPDSch:DSCH:DATA PN9 |
FIX4 | "<file name>"
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA:HSPDSch:DSCH:DATA?
```

This command defines the HS-DSCH data type for HSDPA1. The HS-DSCH is not supported on HSDPA2–4.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “[File Overview](#)” on page 812 for more

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])

information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

:DLINK:HSDPa:HSPDSch:DSCH:DATA:FIX4

Supported E4438C with Option 418

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:DATA:
FIX4 <val>
```

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:DATA:FIX4?
```

This command defines the HS-DSCH repeating 4-bit binary data pattern for HSDPA1. The HS-DSCH is not supported on HSDPA2–4.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

:DLINK:HSDPa:HSPDSch:DSCH:IRBSize

Supported E4438C with Option 418

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:IRBSize <val>
```

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :DLINK:HSDPa:HSPDSch:DSCH:IRBSize?
```

This command sets the HS-DSCH IR buffer size per the HARQ process for HSDPA1. The HS-DSCH is not supported on HSDPA2–4.

***RST** 9600

Range 960–28800

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

:DLINK:HSDPA:HSPDSch:NCODE

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA:HSPDSch:NCODE <val>  
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA:HSPDSch:NCODE?
```

This command sets number of codes for the HS-PDSCH on HSDPA1. HSDPA2–4 do not support multicodes.

***RST** 1

Range 1–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

Set all physical channel codes so they are orthogonal to each other. If any of the channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

:DLINK:HSDPA[1] | 2 | 3 | 4:HSPDSch:POWER

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA [ 1 ] | 2 | 3 | 4 :HSPDSch:  
POWER <val>  
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:HSDPA [ 1 ] | 2 | 3 | 4 :HSPDSch:POWER?
```

This command sets the HS-PDSCH power level.

The variable <val> is expressed in decibels (dB).

***RST** –1.02000000E+001

Range –40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])**:DLINK:HSDPa[1]|2|3|4:HSPDsch:SFORmat****Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1]|2|3|4:HSPDsch:SFORmat 0|1

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1]|2|3|4:HSPDsch:SFORmat?

This command sets the HS-PDSCH slot format.

0 This sets the modulation type to QPSK.

1 This sets the modulation type to 16QAM.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:HSDPa[1]|2|3|4:HSPDsch[:STATe]*Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1]|2|3|4:HSPDsch[:STATe] ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1]|2|3|4:HSPDsch[:STATe]?

This command turns the selected HS-PDSCH on or off.

***RST** HSDPA1: 1 HSDPA2–4: 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

The HS-SCCH must be on for the HS-PDSCH to turn on. Turning off the HS-SCCH also turns off the active HS-PDSCH. See “:DLINK:HSDPa[1]|2|3|4[:STATe]” on page 841 for turning the HS-SCCH on or off.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:DLINK:HSDPA[1] | 2 | 3 | 4:HSSCch:CCODE****Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1] | 2 | 3 | 4:HSSCch:CCODE <val>

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1] | 2 | 3 | 4:HSSCch:CCODE?

This command sets the HS-SCCH channel code.

***RST** HSDPA1: 4 HSDPA2: 5 HSDPA3: 6 HSDPA4: 7**Range** 1–127**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

Set all physical channel codes so they are orthogonal to each other. If any of the channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

:DLINK:HSDPA[1] | 2 | 3 | 4:HSSCch:DATA**Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1] | 2 | 3 | 4:HSSCch:DATA PN9 | FIX4 | "<file name>" | STD

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1] | 2 | 3 | 4:HSSCch:DATA?

This command sets the data type for the selected downlink HS-SCCH.

STD This choice configures the bit field as defined by the 3GPP standards."<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “[File Overview](#)” on page 812 for more information on files.***RST** STD**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])**:DLINK:HSDPa[1]|2|3|4:HSSCch:DATA:FIX4****Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1]|2|3|4:HSSCch:DATA:FIX4 <val>

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1]|2|3|4:HSSCch:DATA:FIX4?

This command sets the HS-SCCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

RST** 0**Range** 0–15**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:HSDPa[1]|2|3|4:HSSCch:POWer*Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1]|2|3|4:HSSCch:POWer <val>

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:HSDPa[1]|2|3|4:HSSCch:POWer?

This command sets the HS-SCCH power level.

The variable <val> is expressed in decibels (dB).

***RST** -1.02000000E+001**Range** -40 to 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:DLINK:HSDPA[1]|2|3|4:ITTI****Supported** E4438C with Option 418

```
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1]|2|3|4:ITTI <val>
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1]|2|3|4:ITTI?
```

This command sets the static inter-TTI pattern value for the selected HSDPA.

The variable <val> is expressed in subframes (one subframe = 2 ms).

***RST** 8**Range** 1–16

Remarks To use a static pattern, select FIX as the choice for the [:DLINK:HSDPA\[1\]|2|3|4:ITTI:PATTERN](#) command.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:DLINK:APPLY](#)” on page 814.

:DLINK:HSDPA[1]|2|3|4:ITTI:PATTERN**Supported** E4438C with Option 418

```
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1]|2|3|4:ITTI:
PATTERN FIX|"<file name>"
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1]|2|3|4:ITTI:PATTERN?
```

This command selects which method sets the inter-TTI pattern for the selected HSDPA.

FIX This choice enables a static pattern. To configure the pattern, see “[:DLINK:HSDPA\[1\]|2|3|4:ITTI](#)”.

"<file name>" This variable represents an inter-TTI pattern file stored in signal generator memory. Creating and using a file provides the option of having a flexible inter-TTI pattern where you can vary the distance between HS-PDSCH transmissions. To create a file, use one or a combination of the following methods:

- To create a file internal to the software, use the inter-TTI user pattern editor.
- To create a file external to the software, use a text editor.

For more information, see the Signal Studio for HSDPA over W-CDMA software online help.

The file name follows the form <project name>–ITTIx, where 'x' is the HSDPA number from one to four. The inter-TTI pattern must contain at least one bit, or the apply function (downlink apply command) will not work.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])***RST** FIX**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:HSDPA:NHPRocess****Supported** E4438C with Option 418[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA:NHPRocess <val>
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA:NHPRocess?

This command sets the HS-DSCH number of HARQ processes for HSDPA1. For HSDPA2–4, this parameter is fixed at one and is used only for HS-SCCH coding purposes.

RST** 4**Range** 1–8**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:HSDPA[1] | 2 | 3 | 4:RVParameter*Supported** E4438C with Option 418[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1] | 2 | 3 | 4:RVParameter <val>
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1] | 2 | 3 | 4:RVParameter?

This command sets the HS-DSCH RV parameter. For HSDPA2–4, which do not support an HS-DSCH, this parameter is used only for HS-SCCH coding purposes.

***RST** 0**Range** 0–7**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:DLINK:HSDPA[1]|2|3|4:UEID****Supported** E4438C with Option 418

```
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1]|2|3|4:UEID <val>
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1]|2|3|4:UEID?
```

This command sets the UEID.

RST** HSDPA1: 0 HSDPA2: 1 HSDPA3: 2 HSDPA4: 3**Range** 0–65535**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:HSDPA[1]|2|3|4[:STATe]*Supported** E4438C with Option 418

```
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1]|2|3|4[:STATe] ON|OFF|
1|0
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:HSDPA[1]|2|3|4[:STATe]?
```

This command turns the selected downlink HSDPA channel on or off.

ON (1)	<ul style="list-style-type: none"> • Turns on the HS-SCCH for the selected HSDPA. • Enables turning on the HS-PDSCH for the selected HSDPA.
--------	---

OFF (0)	<ul style="list-style-type: none"> • Turns off the HS-SCCH for the selected HSDPA. • Turns off the active HS-PDSCH for the selected HSDPA.
---------	--

***RST** HSDPA1: 1 HSDPA2–4: 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

Refer to “:DLINK:HSDPA[1]|2|3|4:HSPDSch[:STATe]” on page 836 for turning the HS-PDSCH on or off.

An HSDPA consists of a HS-SCCH and a HS-PDSCH, however the HS-DSCH is supported on only HSDPA1.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURce]:RADio:WCDMa:HSDPa[:BBG])**:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:CCODE****Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:CCODE <val>

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:CCODE?

This command sets the channel code for the selected downlink OCNS.

*RST	OCNS1: 2	OCNS2: 3	OCNS3: 4	OCNS4: 5
	OCNS5: 6	OCNS6: 7	OCNS7: 8	OCNS8: 9
	OCNS9: 10	OCNS10: 11	OCNS11: 12	OCNS12: 13
	OCNS13: 14	OCNS14: 15	OCNS15: 16	OCNS16: 17

Range 1–127**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:DATA****Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:DATA PN9 | PN15

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:DATA?

This command configures the data pattern for the selected downlink OCNS.

***RST** PN9**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:POWer

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :POWer <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :POWer?
```

This command sets the power level for the selected downlink OCNS.

The variable <val> is expressed in units of dB.

*RST	OCNS1: -6	OCNS2: -8	OCNS3: -8	OCNS4: -10
	OCNS5: -7	OCNS6: -9	OCNS7-16: -10	

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:SSCOffset

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :SSCOffset <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 |
12 | 13 | 14 | 15 | 16 :SSCOffset?
```

This command sets the secondary scrambling code offset for the selected downlink OCNS.

***RST** 0

Range 0-15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:TOFFset****Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:TOFFset <val>

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:TOFFset?

This command adjusts the timing offset for the OCNS.

*RST	OCNS1: 1	OCNS2: 2	OCNS3: 3	OCNS4: 4
	OCNS5: 5	OCNS6: 6	OCNS7: 7	OCNS8: 8
	OCNS9: 9	OCNS10: 10	OCNS11: 11	OCNS12: 12
	OCNS13: 13	OCNS14: 14	OCNS15: 15	OCNS16: 16

Range 0–149**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16[:STATE]****Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16[:STATE] ON|OFF|1|0

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16[:STATE]?

This command turns the selected OCNS on or off.

RST** 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:PCCPch:BCH:DATA*Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:PCCPch:BCH:DATA PN9|PN15|FIX4|<file name>"

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:DLINK:PCCPch:BCH:DATA?

This command sets the BCH data format that is transmitted on the P-CCPCH.

HSDPA over W-CDMA Subsystem—Option 418 [:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “File Overview” on page 812 for more information on files.

***RST** FIX4

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:PCCPch:BCH:DATA:FIX4

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:PCCPch:BCH:DATA:FIX4 <val>
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:PCCPch:BCH:DATA:FIX4?
```

This command sets the BCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:PCCPch:CCODE

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:PCCPch:CCODE <val>
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:PCCPch:CCODE?
```

This command sets the P-CCPCH channel code.

***RST** +1

Range 0–255

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

Set all physical channel codes so they are orthogonal to each other. If any of the channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

:DLINK:PCCPch:POWer**Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PCCPch:POWer <val>

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PCCPch:POWer?

This command sets the P-CCPCH power level.

The variable <val> is expressed in decibels (dB).

RST** -5.30000000E+000**Range** -40 to 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:PCCPch[:STATe]*Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PCCPch[:STATe] ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PCCPch[:STATe]?

This command turns the P-CCPCH on or off.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:PICH:CCODE*Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PICH:CCODE <val>

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PICH:CCODE?

This command sets the PICH channelization code.

***RST** +3**Range** 0–255**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

Set all physical channel codes so they are orthogonal to each other. If any of the channel codes fail to meet this criteria, the apply function (downlink apply command) will not work.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:DLINK:PICH:DATA**

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:PICH:DATA PN9 | PN15 | FIX4 |
"<file name>"
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:PICH:DATA?
```

This command sets the PICH data type.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to [“File Overview” on page 812](#) for more information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 814](#).

:DLINK:PICH:DATA:FIX4

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:PICH:DATA:FIX4 <val>
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :DLINK:PICH:DATA:FIX4?
```

This command sets the PICH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0

Range 0–15

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to [“:DLINK:APPLY” on page 814](#).

:DLINK:PICH:POWer**Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PICH:POWer <val>

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PICH:POWer?

This command sets the PICH power level.

The variable <val> is expressed in decibels (dB).

RST** -8.300000000E+000**Range** -40 to 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:PICH[:STATe]*Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PICH[:STATe] ON|OFF|1|0

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:PICH[:STATe] ?

This command turns the PICH on or off.

RST** 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:POLarity*Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:POLarity NORMal|INVerted|INVert

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:POLarity?

This command selects the phase polarity of the downlink signal.

NORMal This choice selects normal polarity.**INVerted, INVert** These choices perform the same function, inverting the internal Q signal.***RST** NORM**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. For more information, refer to “:DLINK:APPLY” on page 814.

:DLINK:PSCH:POWer

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:PSCH:POWer <val>  
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:PSCH:POWer?
```

This command sets the PSCH power level.

The variable <val> is expressed in decibels (dB).

***RST** -8.30000000E+000

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:PSCH[:STATe]

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:PSCH [ :STATe ] ON | OFF | 1 | 0  
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:PSCH [ :STATe ] ?
```

This command turns the PSCH on or off.

***RST** 1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. For more information, refer to “:DLINK:APPLY” on page 814.

:DLINK:SCRamblecode

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:SCRamblecode <val>  
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :DLINK:SCRamblecode?
```

This command sets the downlink scramble code number.

***RST** +0

Range 0–511

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

:DLINK:SSCH:POWer**Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:SSCH:POWer <val>

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:SSCH:POWer?

This command sets the SSCH power level. The variable <val> is expressed in decibels (dB)

RST** -8.3000000E+000**Range** -40 to 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:SSCH[:STATe]*Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:SSCH[:STATe] ON|OFF|1|0

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:SSCH[:STATe]?

This command turns the SSCH on or off.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.**:DLINK:TXDiversity*Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:TXDiversity NONE|OANT1|OANT2

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:DLINK:TXDiversity?

This command selects the downlink signal transmit diversity mode.

NONE This choice disables the transmit diversity mode.

OANT1 This choice selects the transmit diversity openloop antenna 1 mode.

OANT2 This choice selects the transmit diversity openloop antenna 2 mode.

***RST** NONE**Remarks** To configure both antennas (one and two) requires two ESGs.

Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:DLINK:APPLY” on page 814.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:LINK****Supported** E4438C with Option 418

```
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:LINK DOWN|UP
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:LINK?
```

This command sets the uplink or downlink mode.

RST** DOWN**:ULINK:APPLY*Supported** E4438C with Option 418

```
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:APPLY
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:APPLY?
```

This command applies changes to the channel setup and data for active physical and transport channels, immediately starting the channel coding generation process. A progress bar may appear on the ESG display indicating that the new signal parameters are being applied. Turning on the HSDPA modulation format also applies the signal parameters.

The query response determines whether or not there is a need to execute the command. It returns the following responses:

```
0          Command execution is not required.
1          Command execution is required.
```

NOTE The query response is only valid while the HSDPA format is active.

When there is a setting conflict (ESG reports an error) with the range values or coupled parameters, or both, executing the uplink apply command does not apply the new changes until the conflicts are resolved. After resolving the setting conflicts, execute the command to apply the new settings.

:ULINK:AWGN:CN**Supported** E4438C with Option 418

```
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:AWGN:CN <val>
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:AWGN:CN?
```

This command sets the uplink in-band carrier to noise ratio (C/N) value using AWGN.

***RST** 0**Range** -30 to 30

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to **:ULINK:APPLY**”.

:ULINK:AWGN[:STATe]

Supported E4438C with Option 418

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:AWGN [ :STATe ] ON | OFF | 0 | 1
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:AWGN [ :STATe ] ?
```

This command turns the uplink AWGN on or off.

***RST** 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to **“:ULINK:APPLY” on page 851**.

:ULINK:BBReference:EXTeRnal:MRATe

Supported E4438C with Option 418

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:BBReference:EXTeRnal:MRATe X1 |
X2 | X4
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:BBReference:EXTeRnal:MRATe ?
```

This command configures the ESG, so it can accept an external baseband generator clock that is a multiple of the internal 3.84 MHz chip clock.

X1 This sets the ESG to accept an external clock rate identical to the chip clock.

X2 This sets the ESG to accept an external clock rate that is two times the rate of the chip clock.

X4 This sets the ESG to accept an external clock rate that is four times the rate of the chip clock.

***RST** X1

:ULINK:BBReference[:SOURce]

Supported E4438C with Option 418

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:BBReference [ :SOURce ] INT [1] |
EXT [1]
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:BBReference [ :SOURce ] ?
```

This command selects the baseband generator reference source for the radio uplink channel.

***RST** INT

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:ULINK:DPCCh:CCODE**

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:DPCCh:CCODE?
```

This query returns the channelization code for the uplink DPCCH.

The slot format determines the channelization code in accordance with the 3GPP standards. See “:ULINK:DPCCh:SFORmat” on page 856 for setting the slot format.

:ULINK:DPCCh:DATA

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:DPCCh:DATA PN9 | PN15 | FIX4 |
"<file name>" | STD
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:DPCCh:DATA?
```

This command configures the uplink DPCCH data pattern.

STD This sets the DPCCH bit fields according to the 3GPP standards.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (uplink apply command) will not work. Refer to “File Overview” on page 812 for more information on files.

***RST** STD

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:DPCCh:DATA:FIX4**Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:DATA:FIX4 <val>

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:DATA:FIX4?

This command sets the uplink DPCCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

RST** 0**Range** 0–15**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.**:ULINK:DPCCh:FBI:PATtern*Supported** E4438C with Option 418[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:FBI:PATtern PN9|PN15|FIX|
"<file name>"

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:FBI:PATtern?

This command configures the uplink DPCCH FBI pattern.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (uplink apply command) will not work. Refer to “File Overview” on page 812 for more information on files.

***RST** FIX**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

HSDPA over W-CDMA Subsystem—Option 418 [:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]**:ULINK:DPCCh:FBI:PATtern:FIX****Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:FBI:PATtern:FIX <val>

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:FBI:PATtern:FIX?

This command sets the 30-bit FBI pattern for the uplink DPCCH.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

RST** +0**Range** 0–1073741823**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.**:ULINK:DPCCh:POWer*Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:POWer <val>

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:POWer?

This command sets the uplink DPCCH power level.

The variable <val> is expressed in decibels (dB)

***RST** –2.69000000E+000**Range** –40 to 0**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:DPCCh:SFORmat**Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:SFORmat <val>

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:SFORmat?

This command sets the uplink DPCCH slot format.

***RST** +0**Range** 0–5**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

The slot format determines the settings for other parameters in accordance with 3GPP standards.

:ULINK:DPCCh[:STATe]**Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh[:STATe] ON|OFF|1|0

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh[:STATe]?

This command turns the uplink DPCCH on or off.

RST** 1**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.**:ULINK:DPCCh:TFCI*Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:TFCI <val>

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:TFCI?

This command sets the uplink DPCCH TFCI 10-bit data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only decimal values.

***RST** +0**Range** 0–1023**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

HSDPA over W-CDMA Subsystem—Option 418 [:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]**:ULINK:DPCCh:TPC:NSTeps****Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:TPC:NSTeps <val>

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:TPC:NSTeps?

This command sets the number of steps for the down and up (DUP) or up and down (UDOWn) TPC pattern selections.

The variable <val> is expressed in decibels (dB).

***RST** +1**Range** 1–80

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:DPCCh:TPC:PATtern**Supported** E4438C with Option 418

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:TPC:PATtern

UDOWn|DUP|UALL|DALL|"<file name>"

[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:DPCCh:TPC:PATtern?

This command configures the uplink DPCCH TPC pattern for increasing or decreasing, or increasing and decreasing the BTS power level.

UDOWn The TPC pattern repetitively steps up and down.

DUP The TPC pattern repetitively steps down and up.

UALL The TPC pattern consecutively steps up.

DALL The TPC pattern consecutively steps down.

"<file name>" This variable represents a power pattern file stored in signal generator memory. The pattern must contain at least one bit or the apply function (downlink apply command) will not work. Refer to “File Overview” on page 812 for more information on files.

***RST** UDOW

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

Each step in a TPC pattern signals an increase or decrease of 1 dB in the BTS output power level.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])**:ULINK:DPDCh:CCODE****Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:DPDCh:CCODE?

This query returns the uplink DPDCH channelization code.

The slot format determines the channelization code in accordance with the 3GPP standards. See “:ULINK:DPDCh:SFORmat” on page 863 for setting the slot format.

:ULINK:DPDCh:DATA**Supported** E4438C with Option 418[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:DPDCh:DATA PN9|PN15|FIX4|DCH|"
"<file name>"

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:DPDCh:DATA?

This command configures the uplink DPDCH data pattern.

DCH This choice selects the transport channel as the data source."
"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (uplink apply command) will not work. Refer to “File Overview” on page 812 for more information on files.***RST** PN9**Remarks** Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.**:ULINK:DPDCh:DATA:FIX4****Supported** E4438C with Option 418

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:DPDCh:DATA:FIX4 <val>

[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:DPDCh:DATA:FIX4?

This command sets the uplink DPDCH repeating 4-bit binary data pattern.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0**Range** 0–15

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:BSIZE

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [1] | 2 | 3 | 4 | 5 | 6 :
BSIZE <val>
```

```
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [1] | 2 | 3 | 4 | 5 | 6 :BSIZE?
```

This command sets the block size for the selected uplink DCH.

***RST** 20

Range 0–5000

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

The number of data bits per DCH cannot exceed 200,000. To maintain this data bit limit, the ESG calculates the product of the block size and the number of blocks. If the product of these two parameters exceeds 200,000, the apply function (uplink apply command) will not work.

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:CRC

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [1] | 2 | 3 | 4 | 5 | 6 :
CRC 0 | 8 | 12 | 16 | 24
```

```
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [1] | 2 | 3 | 4 | 5 | 6 :CRC?
```

This command sets the number of CRC bits for the selected uplink DCH.

***RST** 8

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:CTYPE

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [1] | 2 | 3 | 4 | 5 | 6 :
CTYPE HCONv | TCONv | TURBo | NONE
```

```
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [1] | 2 | 3 | 4 | 5 | 6 :CTYPE?
```

This command selects the encoder type for the selected uplink DCH.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])

HCONv	This choice selects the 1/2 rate convolutional encoder.
TCONv	This choice selects the 1/3 rate convolutional encoder.
TURBo	This choice selects the turbo coder.
NONE	This choice selects no coding.
*RST	HCON
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:DATA

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA PN9 |
PN15 | FIX4 | "<file name>"
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA?
```

This command configures the data for the selected uplink DCH.

"<file name>" This variable represents a data pattern file stored in signal generator memory. The data pattern must contain at least one bit or the apply function (uplink apply command) will not work. Refer to “File Overview” on page 812 for more information on files.

***RST** PN9

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:DATA:FIX4

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA :
FIX4 <val>
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :DATA :
FIX4?
```

This command sets the repeating 4-bit binary data pattern for the selected uplink DCH.

The variable <val> accepts values in binary, hexadecimal, or decimal format, however the query returns only binary values.

***RST** 0

Range 0–15

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURce]:RADio:WCDMa:HSDPa[:BBG])

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:DPDCh:DCH[1] | 2 | 3 | 4 | 5 | 6:NBLocks

Supported E4438C with Option 418

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :
NBLocks <val>
```

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :NBLocks?
```

This command sets the number of blocks for the selected uplink DCH.

***RST** 1

Range 0–512

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

The number of data bits per DCH cannot exceed 200,000. To maintain this data bit limit, the block size is multiplied by the number of blocks. If the product of these two parameters exceeds 200,000, the apply function (uplink apply command) will not work.

:ULINK:DPDCh:DCH[1] | 2 | 3 | 4 | 5 | 6:RMATtribute

Supported E4438C with Option 418

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :
RMATtribute <val>
```

```
[ :SOURce ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:DPDCh:DCH [ 1 ] | 2 | 3 | 4 | 5 | 6 :
RMATtribute?
```

This command sets the rate matching attribute for the selected uplink DCH.

***RST** 1

Range 1–256

Remarks Setting the command parameter while the signal is active also requires executing the apply command. For more information, refer to “:ULINK:APPLY” on page 851.

:ULINK:DPDCh:DCH[1]|2|3|4|5|6:TTI**Supported** E4438C with Option 418

```
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:DPDCh:DCH[1]|2|3|4|5|6:
TTI 10|20|40|80
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:DPDCh:DCH[1]|2|3|4|5|6:TTI?
```

This command sets the TTI for the selected uplink DCH.

The choices are expressed in millisecond (ms).

***RST** 10

Remarks Setting the command parameter while the signal is active also requires executing the apply command. For more information, refer to “:ULINK:APPLY” on page 851.

:ULINK:DPDCh:DCH2|3|4|5|6[:STATe]**Supported** E4438C with Option 418

```
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:DPDCh:
DCH2|3|4|5|6[:STATe] ON|OFF|1|0
[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:DPDCh:DCH2|3|4|5|6[:STATe]?
```

This command turns the selected uplink DCH on or off; DCH1 is always on.

***RST** *DCH 1: 1 DCH 2–6: 0*

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

The apply command will not work and the ESG will report an error if you turn on a DCH where lower numbered DCHs are off. For example, turning on DCH5 requires turning on DCH2–4. The reverse is true when turning off the DCHs.

:ULINK:DPDCh:POWer

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:DPDCh:POWer <val>  
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:DPDCh:POWer?
```

This command sets the uplink DPDCH power level.

The variable <val> is expressed in decibels (dB).

***RST** +0.00000000E+000

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:DPDCh:SFORmat

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:DPDCh:SFORmat <val>  
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:DPDCh:SFORmat?
```

This command sets the uplink DPDCH slot format.

***RST** +2

Range 0– 6

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

The slot format determines the settings for other parameters in accordance with the 3GPP standards.

:ULINK:DPDCh[:STATe]

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:DPDCh [ :STATe ] ON | OFF | 1 | 0  
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:DPDCh [ :STATe ] ?
```

This command turns the uplink DPDCH on or off.

***RST** 1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])**:ULINK:FCLock:INTerval**

Supported E4438C with Option 418

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:FCLock:INTerval 10|20|40|80|2560
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:FCLock:INTerval?
```

This command selects the frame clock interval for the synchronization signal.

The frame clock interval is set in milliseconds (ms).

***RST** 80

Remarks Ensure that the selected interval is equal to or longer than the longest transport channel TTI period.

This command is applicable only when FCLock is the sync source selection. See “:ULINK:SYNC[:SOURCE]” on page 872 for selecting the sync source.

:ULINK:FCLock:POLarity

Supported E4438C with Option 418

```
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:FCLock:POLarity POSitive|
NEGative
[ :SOURCE ] :RADio:WCDMa:HSDPa [ :BBG ] :ULINK:FCLock:POLarity?
```

This command sets the frame clock polarity.

POSitive This choice sets the clock gate to trigger when the signal is high.

NEGative This choice sets the clock gate to trigger when the signal is low.

***RST** POS

Remarks This command is applicable only when FCLock is the sync source selection. See “:ULINK:SYNC[:SOURCE]” on page 872 for selecting the sync source.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:ULINK:FILTer**

Supported E4438C with Option 418

```
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:FILTer RNYQuist|NYQuist|
GAUSSian|RECTangle|IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|
"<user FIR>"
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:FILTer?
```

This command selects the uplink filter type.

IS95	This filter meets the criteria of the IS-95 standard.
IS95_EQ	This filter is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard and is best suited for IS-95 baseband filtering.
IS95_MOD	This filter meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.
IS95_MOD_EQ	This filter is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.
UGGaussian	This is a GSM Gaussian filter with a fixed BbT value of 0.300.
AC4Fm	This is a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.
"<user FIR>"	This variable represents any FIR filter file stored in signal generator memory. Refer to “File Overview” on page 812 for more information on files.
*RST	RNYQ
Remarks	Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851 .

:ULINK:FILTer:ALPHa

Supported E4438C with Option 418

```
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:FILTer:ALPHa <val>
[:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]:ULINK:FILTer:ALPHa?
```

This command sets the uplink Nyquist or root Nyquist filter alpha value.

***RST** +2.20000000E-001

Range 0–1

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Executing this command while a filter other than Nyquist or root Nyquist is selected changes the parameter value, but it is not used by the signal generator until one of the Nyquist filters is selected. Refer to “:ULINK:APPLY” on page 851.

:ULINK:FILTer:BBT

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:FILTer:BBT <val>
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:FILTer:BBT?
```

This command sets the uplink Gaussian filter BbT value.

***RST** +5.00000000E-001

Range 0–1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

Executing this command while a filter other than the Gaussian filter is selected changes the parameter value, but it is not used by the signal generator until the Gaussian filter is selected.

:ULINK:FILTer:CHANnel

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:FILTer:CHANnel EVM|ACP
[ :SOURCE ] :RADIo:WCDMA:HSDPA [ :BBG ] :ULINK:FILTer:CHANnel?
```

This command optimizes an uplink filter for minimized EVM or for minimized ACP.

EVM This choice provides the most ideal passband.

ACP This choice improves stopband rejection for the root Nyquist and Nyquist filters.

***RST** EVM

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

To change the filter selection, refer to “:ULINK:FILTer” on page 865.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])**:ULINK:FOFFset**

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:FOFFset <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:FOFFset?
```

This command sets the CFN starting frame within the SFN by setting a frame offset relative to SFN zero.

***RST** 0

Range 0–255

Remarks The command adds delays to the internal frame counter by specifying the starting frame number count. When the frame offset (FOFFset) is set to 0, the frame number starts at the system sync trigger. When the FOFFset is set to 2, the signal generator triggers two frames after the SFN RST. For additional information, refer to 3GPP TS25.402 for SFN and CFN relationship.

:ULINK:HSDPcch:APATtern

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:HSDPcch:APATtern NONE | ACK_ALL |
"<file name>"
```

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] :ULINK:HSDPcch:APATtern?
```

This command sets the HS-DPCCH ACK/NACK transmission pattern for each of the 1280 subframes that make up the pattern.

NONE This choice sets all subframes to DTX.

"<file name>" This variable represents an ACK pattern file stored in signal generator memory. The file must contain 2,560-bits of data (2-bits per subframe) or the apply function (uplink apply command) will not work.

- An ACK response is represented by 00.
- A NACK response is represented by 01.
- DTX is represented by 10.

Enter the 2,560-bits into the file as a binary string.

Refer to [“File Overview” on page 812](#) for more information on files.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])

***RST** ACK_ALL

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:HSDPcch:APOWer

Supported E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:HSDPcch:APOWer <val>
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:HSDPcch:APOWer?
```

This command sets the HS-DPCCH ACK part power level.

The variable <val> is expressed in decibels (dB).

***RST** -2.69000000E+000

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:HSDPcch:CCODE

Supported E4438C with Option 418

```
[:SOURCE]RADio:WCDMa:HSDPa[:BBG]:ULINK:HSDPcch:CCODE?
```

This query returns the HS-DPCCH channelization code.

:ULINK:HSDPcch:CPATtern

Supported E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:HSDPcch:CPATtern NONE |
"<file name>"
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:HSDPcch:CPATtern?
```

This command sets the HS-DPCCH CQI transmission pattern for each of the 1280 subframes that make up the pattern.

NONE This choice sets all subframes to DTX.

"<file name>" This variable represents a bit file stored in signal generator memory. The file must contain 10,240-bits of data (8-bits per subframe) or the apply function (uplink apply command) will not work.

- A CQI response range is one to thirty using 8-bits, 00000001 to 00011110.

HSDPA over W-CDMA Subsystem—Option 418 [:SOURCE]:RADIO:WCDMA:HSDPA[:BBG]

- DTX is represented by 11111111.

Enter the 10,240-bits into the file as a binary string.

Refer to “[File Overview](#)” on page 812 for more information on files.

***RST** NONE

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:ULINK:APPLY](#)” on page 851.

:ULINK:HSDPcch:CPOWer

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:HSDPcch:CPOWer <val>
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:HSDPcch:CPOWer?
```

This command sets the HS-DPCCH CQI part power level.

The variable <val> is expressed in decibels (dB).

***RST** -2.69000000E+000

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:ULINK:APPLY](#)” on page 851.

:ULINK:HSDPcch:NPOWer

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:HSDPcch:NPOWer <val>
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:HSDPcch:NPOWer?
```

This command sets the HS-DPCCH NACK part power level. The variable <val> is expressed in decibels (dB).

***RST** -2.69000000E+000

Range -40 to 0

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “[:ULINK:APPLY](#)” on page 851.

:ULINK:HSDPcch:SFDelay

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIo:WCDMA:HSDPa [ :BBG ] :ULINK:HSDPcch:SFDelay <val>
```

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURce]:RADio:WCDMa:HSDPa[:BBG])

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:HSDPcch:SFDeLay?

This command sets the HS-DPCCH subframe delay. The variable <val> is expressed in units of 256 chips.

***RST** 0**Range** 0–150

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:HSDPcch[:STATe]**Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:HSDPcch[:STATe] ON|OFF|1|0

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:HSDPcch[:STATe]?

This command turns the HS-DPCCH on or off.

***RST** 1

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:POLarity**Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:POLarity NORMAl|INVerted|INVert

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:POLarity?

This command selects the phase polarity of the uplink signal.

NORMAl This choice selects normal polarity.

INVerted, INVert These choices perform the same function, inverting the internal Q signal.

***RST** NORM

Remarks Setting the command parameter while the signal is active also requires executing the apply command. Refer to “:ULINK:APPLY” on page 851.

:ULINK:SCRamblecode**Supported** E4438C with Option 418

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:SCRamblecode <val>

[:SOURce]:RADio:WCDMa:HSDPa[:BBG]:ULINK:SCRamblecode?

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])

This command sets the scramble code.

***RST** +0
Range 0–16777215

:ULINK:SDElay

Supported E4438C with Option 418

[:SOURCE] :RADIO:WCDMA:HSDPA [:BBG] :ULINK:SDElay <val>
 [:SOURCE] :RADIO:WCDMA:HSDPA [:BBG] :ULINK:SDElay?

This command sets the uplink DPCH delay, measured in slots.

***RST** +0
Range 0–119
Remarks Calculate the delay between downlink and uplink DPCH, in slots, using the following formulas. Total Delay = (T0) + (TOFFset) + ((SDElay) * 2560 chips)

- T0 = 1024 chips
- TOFFset is set by “:ULINK:TOFFset” on page 872

Slot Delay = (Total Delay – T0) / 2560

:ULINK:SFNRst:POLarity

Supported E4438C with Option 418

[:SOURCE] :RADIO:WCDMA:HSDPA [:BBG] :ULINK:SFNRst:POLarity POSitive|
 NEGative
 [:SOURCE] :RADIO:WCDMA:HSDPA [:BBG] :ULINK:SFNRst:POLarity?

This command sets the polarity of the system frame number reset signal for the uplink synchronization source.

POSitive This choice sets the signal to trigger when the trigger signal is high.

NEGative This choice sets the signal to trigger when the trigger signal is low.

***RST** POS

Remarks This command is applicable only when SFN_RST is the sync source selection. See “:ULINK:SYNC[:SOURCE]” on page 872 for selecting the sync source.

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADio:WCDMa:HSDPa[:BBG])**:ULINK:SYNC:MODE****Supported** E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:SYNC:MODE SINGLE|CONTInuous
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:SYNC:MODE?
```

This command selects the uplink frame synchronization triggering mode.

SINGLE The signal generator, once triggered, generates frames based on the reference clock.

CONTInuous The signal generator continuously aligns the frame timing with the frame sync trigger signal.

***RST** SING

:ULINK:SYNC[:SOURCE]**Supported** E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:SYNC[:SOURCE] SFN_RST|FCLock
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:SYNC[:SOURCE]?
```

This command selects the uplink frame synchronization source type.

SFN_RST The uplink signal triggers on the system frame number reset signal.

FCLock The uplink signal triggers on the frame clock.

***RST** FCL

:ULINK:TOFFset**Supported** E4438C with Option 418

```
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:TOFFset <val>
[:SOURCE]:RADio:WCDMa:HSDPa[:BBG]:ULINK:TOFFset?
```

This command sets the uplink DPCH timing offset (delay), measured in chips.

***RST** +0

Range -512 to 2560

HSDPA over W-CDMA Subsystem—Option 418 ([:SOURCE]:RADIO:WCDMA:HSDPA[:BBG])

- Remarks** The downlink signal timing is provided by the synchronization signal.
- Calculate the delay between downlink and uplink DPCH, in chips, using the following formulas:
- Total Delay = (T0) + (TOFFset) + ((SDElay) * 2560 chips)
- T0 = 1024 chips
 - SDElay is set by “:ULINK:SDElay” on page 871
- Chip Delay = (Total Delay - T0) mod 2560

[:STATe]

Supported E4438C with Option 418

```
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] [ :STATe ] ON | OFF | 1 | 0
[ :SOURCE ] :RADIO:WCDMA:HSDPA [ :BBG ] [ :STATe ] ?
```

This command turns the HSDPA functionality on or off.

***RST** 0

Remarks This command only works when there is at least one active physical channel within the selected link.

NADC Subsystem—Option 402 ([:SOURce]:RADio[:NADC])

:ALPha

Supported E4438C with Option 402

```
[ :SOURce ] :RADio [ :NADC ] :ALPha <val>  
[ :SOURce ] :RADio [ :NADC ] :ALPha?
```

This command changes the Nyquist or root Nyquist filter's alpha value.

The filter alpha value can be set to a minimum level (0), a maximum level (1), or in between by using fractional numeric values (0.001–0.999).

***RST** +3.50000000E–001

Range 0.000–1.000

Key Entry **Filter Alpha**

Remarks This command is effective only after choosing a root Nyquist or Nyquist filter; it does not effect other types of filters. To change the current filter type, refer to [“:FILTer” on page 887](#).

:BBCLock

Supported E4438C with Option 402

```
[ :SOURce ] :RADio [ :NADC ] :BBCLock INT [1] | EXT [1]  
[ :SOURce ] :RADio [ :NADC ] :BBCLock?
```

This command toggles the data (bit) clock input to the baseband generator board to either internal or external. This command is independent in each mode and works for both non-burst (continuous) and burst modes. This allows for a matrix of selections between burst/non-burst, internal/external data generation, internal/external data clock, and external bit/symbol data clock.

INT[1] This choice selects the signal generator internal data clock.

EXT[1] This choice selects an external data clock input.

***RST** INT

Key Entry **BBG Data Clock Ext Int**

Remarks A data clock or continuous symbol sync input must be supplied when external mode is used.

:BBT

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:BBT <val>  
[:SOURCE]:RADio[:NADC]:BBT?
```

This command changes the bandwidth-multiplied-by-bit-time (BbT) filter parameter.

The filter BbT value can be set to the maximum level (1) or in between the minimum level (0.100) and maximum level by using fractional numeric values (0.101–0.999).

***RST** +5.00000000E–001

Range 0.100–1.000

Key Entry Filter BbT

Remarks This command is effective only after choosing a Gaussian filter. It does not have an effect on other types of filters. To change the current filter type, refer to [“:FILTer” on page 887](#).

:BRATe

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:BRATe <val>  
[:SOURCE]:RADio[:NADC]:BRATe?
```

This command sets the bit rate in bits per second (bps–Mbps). The maximum bit rate is dependent on the modulation type and filter as shown in the following tables

The IQ digital data stream is shaped by a FIR filter. The filter length and associated latency and frequency response are dependent on the bit rate as shown in the following tables. The signal generator selects a filter length.

For higher bit rates, the FIR filter length may be truncated (if the minimum filter size allows it) which will impact the relative timing of the modulated data, as well as the actual filter response (see the symbol rate command [“:SRATe” on page 965](#)). Refer to [“:FILTer” on page 887](#) for information on filter symbol widths.

To change the modulation type, refer to [“:MODulation\[:TYPE\]” on page 890](#).

When the bit rate is changed, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the bit rate: lower bit rates require more time.

Receiver Test Digital Commands (continued)
NADC Subsystem—Option 402 ([:SOURCE]:RADio[:NADC])

***RST** +4.86000000E+004

Range	Modulation Type	Bit Rate Range		
		16 Symbol Wide Filter	32 Symbol Wide Filter	64 Symbol Wide Filter
	BPSK, FSK2, MSK	1bps–50Mbps	1bps–25Mbps	1bps–12.5Mbps
	C4FM, OQPSK, FSK4	2bps–50Mbps	2bps–25Mbps	2bps–12.5Mbps
	OQPSKI95, QPSK			
	P4QPPSK, QPSKIS95			
	GRAYQPSK, QAM4			
	D8PSK, EDGE, FSK8, PSK8	3bps–50Mbps	3bps–25Mbps	3bps–12.5Mbps
	FSK16, PSK16, QAM16	4bps–50Mbps	4bps–25Mbps	4bps–12.5Mbps
	QAM32	5bps–50Mbps	5bps–25Mbps	5bps–12.5Mbps
	QAM64	6bps–50Mbps	6bps–25Mbps	6bps–12.5Mbps
	QAM128	7bps–50Mbps	7bps–25Mbps	7bps–12.5Mbps
	QAM256	8bps–50Mbps	8bps–25Mbps	8bps–12.5Mbps

Key Entry **Symbol Rate**

:BURSt:PN9

Supported E4438C with Option 402

[:SOURCE] :RADio [:NADC] :BURSt :PN9 NORMal | QUICk
 [:SOURCE] :RADio [:NADC] :BURSt :PN9?

This command controls the software PN9 generation.

NORMal This choice produces a maximum length PN9 sequence.

QUICk This choice produces a truncated PN9 sequence.

***RST** NORM

Key Entry **PN9 Mode Normal Quick**

Remarks Use Normal mode for bit-error-rate tests where a maximum length PN9 sequence is required.

:BURSt:SHAPe[:TYPE]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:BURSt:SHAPe[:TYPE] SINE | "<file name>"
[:SOURCE]:RADIO[:NADC]:BURSt:SHAPe[:TYPE] ?
```

This command specifies the burst shape as either SINE or a user-defined file ("*<file name>*").

SINE This choice selects a state that is defined by the burst rise and fall *RST values, as the default burst shape type.

"*<file name>*" This choice selects a user designated file from signal generator memory (non-volatile).

***RST** SINE

Key Entry **Sine User File**

:BURSt:SHAPe:FALL:DElay

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:BURSt:SHAPe:FALL:DElay <val>
[:SOURCE]:RADIO[:NADC]:BURSt:SHAPe:FALL:DElay?
```

This command sets the burst shape fall delay.

The variable *<val>* is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range -22.3750 to 99

Key Entry **Fall Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 890. Refer to “:SRate” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FDElay” on page 878 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:FALL:TIME

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :BURSt :SHAPe :FALL :TIME <val>  
[ :SOURCE ] :RADio [ :NADC ] :BURSt :SHAPe :FALL :TIME?
```

This command sets the burst shape fall time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +5.00000000E+000

Range 0.1250–255.8750

Key Entry **Fall Time**

Remarks The setting enabled by this command is not affected by signal

generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 890.
Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FTIME” on page 879 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:FDElay

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :BURSt :SHAPe :FDElay <val>  
[ :SOURCE ] :RADio [ :NADC ] :BURSt :SHAPe :FDElay?
```

This command sets the burst shape fall delay.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range –22.3750 to 99

Key Entry **Fall Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 890. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FALL:DELay” on page 877 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:FTIME

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:BURSt:SHAPe:FTIME <val>  
[:SOURCE]:RADIO[:NADC]:BURSt:SHAPe:FTIME?
```

This command sets the burst shape fall time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range 0.1250–255.8750

Key Entry **Fall Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 890. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FALL:TIME” on page 878 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RDELaY

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :BURSt :SHAPe :RDELaY <val>  
[ :SOURCE ] :RADio [ :NADC ] :BURSt :SHAPe :RDELaY?
```

This command sets the burst shape rise delay.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range -17.3750 to 99

Key Entry **Rise Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 890. Refer to “:SRATE” on page 965 for minimum and maximum symbol rate values.

“:BURSt:SHAPe:RISE:DELaY” on page 880 performs the same function; in compliance with the SCPI standard, both commands are listed.

Refer to the *E4428C/38C ESG Signal Generators User’s Guide* for more information.

:BURSt:SHAPe:RISE:DELaY

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :BURSt :SHAPe :RISE :DELaY <val>  
[ :SOURCE ] :RADio [ :NADC ] :BURSt :SHAPe :RISE :DELaY?
```

This command sets the burst shape rise delay.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range -17.3750 to 99

Key Entry **Rise Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 890. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPE:RDElay” on page 880 performs the same function; in compliance with the SCPI standard, both commands are listed.

Refer to the *E4428C/38C ESG Signal Generators User’s Guide* for more information.

:BURSt:SHAPE:RISE:TIME

Supported E4438C with Option 402

```
[:SOURce]:RADio[:NADC]:BURSt:SHAPE:RISE:TIME <val>  
[:SOURce]:RADio[:NADC]:BURSt:SHAPE:RISE:TIME?
```

This command sets the burst shape rise time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +5.00000000E+000

Range 0.1250–22.5000

Key Entry Rise Time

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 890. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPE:RTIME” on page 882 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPE:RTIME

Supported E4438C with Option 402

```
[ :SOURce ] :RADio [ :NADC ] :BURSt :SHAPE :RTIME <val>  
[ :SOURce ] :RADio [ :NADC ] :BURSt :SHAPE :RTIME ?
```

This command sets the burst shape rise time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +5.00000000E+000

Range 0.1250–22.5000

Key Entry **Rise Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 890. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPE:RISE:TIME” on page 881 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt[:STATe]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio [ :NADC ] :BURSt [ :STATe ] ON | OFF | 1 | 0  
[ :SOURce ] :RADio [ :NADC ] :BURSt [ :STATe ] ?
```

This command enables or disables the burst function.

ON (1) This choice enables the transmission of framed data. If all timeslots which are switched on are up traffic channels or custom, you will be bursting the timeslots that are on; there will be no RF carrier during the off timeslots.

If you have switched on any timeslot that you have configured as a down traffic channel, the RF carrier is not switched off between any of the timeslots. The off timeslots are transmitted as a continuous series of ones for the time period of the off timeslots.

OFF (0) This choice enables the transmission of unframed data.

***RST** 0
Key Entry **Data Format Pattern Framed**

:BURSt:SHAPE[:TYPE]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:BURSt:SHAPE[:TYPE] SINE | "<file name>"
[:SOURCE]:RADIO[:NADC]:BURSt:SHAPE[:TYPE] ?
```

This command specifies the burst shape as either SINE or a user-defined file ("<file name>").

SINE This choice selects a state that is defined by the burst rise and fall *RST values, as the default burst shape type.

"<file name>" This choice selects a user designated file from signal generator memory (non-volatile).

***RST** SINE

Key Entry **Sine User File**

:CHANnel

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:CHANnel EVM|ACP
[:SOURCE]:RADIO[:NADC]:CHANnel ?
```

This command optimizes the Nyquist and root Nyquist filters to minimize error vector magnitude (EVM) or to minimize adjacent channel power (ACP).

EVM This choice provides the most ideal passband.

ACP This choice improves stopband rejection.

***RST** ACP

Key Entry **Optimize FIR For EVM ACP**

Remarks To change the current filter type, refer to “:FILTer” on page 887.

:DATA

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:DATA PN9|PN11|PN15|PN20|PN23|FIX4|"<file_name>"|
EXT|P4|P8|P16|P32|P64|PRAM
[:SOURCE]:RADio[:NADC]:DATA?
```

This command sets a pseudo-random number sequence, 4-bit pattern, sequence of 1's and 0's, data from an external source, or a user file as the data pattern for unframed transmission.

***RST** PN23

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	Ext
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's	PRAM File		

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:DATA:PRAM

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:DATA:PRAM "<file_name>"
[:SOURCE]:RADio[:NADC]:DATA:PRAM?
```

This command selects a pattern RAM (PRAM) file as the pattern data type for the NADC (North American Digital Cellular) format.

"<file_name>" This variable designates the PRAM file in WFM1. Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

Key Entry **PRAM File**

Remarks Selecting this data source forces the burst source to INTERNAL to allow framing control. The PRAM file must reside in the signal generator's volatile memory (WFM1) in order to be accessed by this command. For more information refer to [“:DATA:PRAM:FILE:BLOCK” on page 112](#)

:DATA:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO [ :NADC ] :DATA :FIX4 <val>  
[ :SOURCE ] :RADIO [ :NADC ] :DATA :FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern for unframed transmission according to the modulation type, symbol rate, filter, and burst shape selected for the NADC (North American Digital Cellular) modulation format.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:DEFault

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO [ :NADC ] :DEFault
```

This command returns all of the NADC (North American Digital Cellular) modulation format parameters to factory settings. It does not affect any other signal generator parameters.

Key Entry **Restore NADC Factory Default**

:EDATa:DELay

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO [ :NADC ] :EDATa :DELay?
```

This query returns the amount of delay (in symbols) from the external data input to the beginning of the symbol on the I OUT and Q OUT rear panel connectors and the front panel RF OUTPUT connector.

Remarks When the format is turned off, the delay value is unchanged; the query will return the same delay value if the format is on or off.

:EDCLock

Supported E4438C with Option 402

[:SOURCE] :RADio [:NADC] :EDCLock SYMBOL | NORMAl

[:SOURCE] :RADio [:NADC] :EDCLock?

This command sets the external data clock use.

SYMBOL This choice specifies that a continuous symbol clock signal must be provided to the SYMBOL SYNC input connector.

NORMAl This choice specifies that the DATA CLOCK input connector requires a bit clock. The SYMBOL SYNC input connector requires a (one-shot or continuous) symbol sync signal.

***RST** NORM

Key Entry Ext Data Clock Normal Symbol

Remarks Both choices have no effect in internal clock mode. Refer to “:BBCLock” on page 874 to select EXT as the data clock type.

:EREFerence

Supported E4438C with Option 402

[:SOURCE] :RADio [:NADC] :EREFerence INT | EXT

[:SOURCE] :RADio [:NADC] :EREFerence?

This command selects either an internal or external bit-clock reference for the data generator.

***RST** INT

Key Entry BBG Ref Ext Int

Remarks If the EXT choice is selected, the external source’s frequency value must be applied to the BASEBAND GEN REF IN rear panel connector. The external reference and external data clock are not applicable at the same time. If both are selected, then the external reference takes precedence.

Refer to, “:EREFerence:VALue” on page 887 to enter the external reference frequency setting.

:EREFerence:VALue

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:EREFerence:VALue <val>
[:SOURCE]:RADIO[:NADC]:EREFerence:VALue?
```

This command sets the expected bit-clock reference frequency value for an externally applied reference signal.

The variable <val> is expressed in units of hertz (Hz–MHz).

***RST** +1.30000000E+007

Range 2.5E5–1E8

Key Entry **Ext BBG Ref Freq**

Remarks The value specified by this command is effective only when you are using an external reference applied to the BASEBAND GEN REF IN rear panel connector.

Refer to “:EREFerence” on page 886 to select EXT (external source) as the reference for the bit-clock.

:FILTer

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:FILTer RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|
IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|"<user FIR>"
[:SOURCE]:RADIO[:NADC]:FILTer?
```

This command selects the pre-modulation filter type.

IS95 This choice selects a filter that meets the criteria of the IS-95 standard.

IS95_EQ This choice selects a filter which is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard. This filter is only used for IS-95 baseband filtering.

IS95_MOD This choice selects a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.

IS95_MOD_EQ This choice selects a filter which is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.

AC4Fm This choice selects a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.

NADC Subsystem—Option 402 ([:SOURce]:RADio[:NADC])

UGGaussian	This choice selects a backwards compatible GSM Gaussian filter (Gaussian filter with a fixed BbT value of 0.300) for the ESG E44xxB Option UN3 or UN4.
"<user FIR>"	This variable is any filter file that you have stored into memory.
*RST	RNYQ
Key Entry	Root Nyquist Nyquist Gaussian Rectangle IS-95 IS-95 w/EQ IS-95 Mod IS-95 Mod w/EQ APCO 25 C4FM UN3/4 GSM Gaussian User FIR
Remarks	Refer to “File Name Variables” on page 13 for information on the file name syntax.

:FRATe

Supported	E4438C with Option 402
	[:SOURce] :RADio [:NADC] :FRATe FULL HALF
	[:SOURce] :RADio [:NADC] :FRATe?

This command toggles between a full- or half-rate traffic channel.

FULL	Selects two equally spaced timeslots of the frame. Since there are six timeslots per frame, timeslots 1, 2, and 3 are paired with timeslots 4, 5, and 6, respectively.
HALF	Selects one timeslot of the frame (6 individual timeslots per frame).
*RST	FULL
Key Entry	Rate Full Half

:IQ:SCALE

Supported	E4438C with Option 402
	[:SOURce] :RADio [:NADC] :IQ:SCALE <val>
	[:SOURce] :RADio [:NADC] :IQ:SCALE?

This command sets the amplitude of the I/Q outputs for better adjacent channel power (ACP); lower scaling values equate to better ACP.

The variable <val> is expressed in units of percent.

*RST	+100
Range	1–200
Key Entry	I/Q Scaling
Remarks	This command has no effect with MSK or FSK modulation.

:MODulation:FSK[:DEVIation]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :MODulation:FSK [ :DEVIation ] <val>  
[ :SOURCE ] :RADio [ :NADC ] :MODulation:FSK [ :DEVIation ] ?
```

This command sets the symmetric FSK frequency deviation value. The variable <val> is expressed in units of Hertz and the maximum range value equals the current symbol rate value multiplied by four, limited to 20 MHz

***RST** +4.00000000E+002

Range 0–2E7

Key Entry **Freq Dev**

Remarks To change the modulation type, refer to “:MODulation[:TYPE]” on page 890.

Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.

To set an asymmetric FSK deviation value, refer to the *E4428C/38C ESG Signal Generators User’s Guide for more information*.

:MODulation:MSK[:PHASe]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :MODulation:MSK [ :PHASe ] <val>  
[ :SOURCE ] :RADio [ :NADC ] :MODulation:MSK [ :PHASe ] ?
```

This command sets the MSK phase deviation value. The variable <val> is expressed in units of degrees.

***RST** +9.00000000E+001

Range 0–100

Key Entry **Phase Dev**

:MODulation:UFSK

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :MODulation:UFSK "<file name>"  
[ :SOURCE ] :RADio [ :NADC ] :MODulation:UFSK ?
```

This command selects a user-defined FSK file from the signal generator memory.

Receiver Test Digital Commands (continued)
NADC Subsystem—Option 402 ([:SOURCE]:RADIO[:NADC])

Key Entry **User FSK**

Remarks The user-defined FSK file is held in signal generator memory until the command that selects user FSK as the modulation type is sent. Refer to “:MODulation[:TYPE]” on page 890 to change the current modulation type.

Refer to “File Name Variables” on page 13 for information on the file name syntax.

:MODulation:UIQ

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:MODulation:UIQ "<file name>"
[:SOURCE]:RADIO[:NADC]:MODulation:UIQ?
```

This command selects a user-defined I/Q file from the signal generator memory.

Key Entry **User I/Q**

Remarks The user-defined I/Q file is held in signal generator memory until the command that selects user I/Q as the modulation type is sent. Refer to “:MODulation[:TYPE]” on page 890 to change the current modulation type.

Refer to “File Name Variables” on page 13 for information on the file name syntax.

:MODulation[:TYPE]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|GRAYQPSK|
OQPSK|IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|FSK8|FSK16|C4FM|
QAM4|QAM16|QAM32|QAM64|QAM128|QAM256|UIQ|UFSK
[:SOURCE]:RADIO[:NADC]:MODulation[:TYPE]?
```

This command sets the modulation type for the NADC personality.

***RST** P4DQPSK

Key Entry	BPSK	QPSK	IS-95 QPSK	Gray Coded QPSK	OQPSK			
	IS-95 OQPSK	$\pi/4$ DQPSK	8PSK	16PSK	D8PSK	MSK	2-Lvl FSK	
	4-Lvl FSK	8-Lvl FSK	16-Lvl FSK	C4FM	4QAM	16QAM	32QAM	
	64QAM	128QAM	256QAM	User I/Q	User FSK			

:REPeat

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:REPeat SINGLE|CONTInuous  
[:SOURCE]:RADio[:NADC]:REPeat?
```

This command sets the rotation direction of the phase modulation vector.

SINGLE This choice outputs one occurrence of the selected frame.

CONTInuous This choice outputs a continuous stream of the selected frame.

***RST** SING

Key Entry **Frame Repeat Single Cont**

:POLarity[:ALL]

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:POLarity[:ALL] NORMal|INVerted  
[:SOURCE]:RADio[:NADC]:POLarity[:ALL]?
```

This command sets the rotation direction of the phase modulation vector.

NORMal This choice selects normal phase polarity.

INVerted This choice inverts the internal Q signal.

***RST** NORM

Key Entry **Polarity Normal Invert**

:SECOndary:RECall

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:SECOndary:RECall
```

This command recalls the secondary frame configuration, overwriting the current state.

Key Entry **Recall Secondary Frame State**

Remarks To save a secondary frame state, refer to “[:SECOndary:SAVE]” on page 892.

A secondary frame is not active until the secondary state is enabled. To activate a secondary frame, refer to “[:SECOndary[:STATe]]” on page 892.

:SECondary:SAVE

Supported E4438C with Option 402

[:SOURce] :RADio [:NADC] :SECondary :SAVE

This command saves the current frame configuration as the secondary frame with the filename NADC_SECONDARY_FRAME.

Key Entry **Save Secondary Frame State**

Remarks To recall the secondary frame (saved in non-volatile signal generator memory), refer to “:SECondary:RECall” on page 891.

:SECondary:TRIGger[:SOURce]

Supported E4438C with Option 402

[:SOURce] :RADio [:NADC] :SECondary :TRIGger [:SOURce] KEY | EXT | BUS
[:SOURce] :RADio [:NADC] :SECondary :TRIGger [:SOURce] ?

This command selects the type of triggering for the secondary frame.

KEY This choice enables triggering by pressing the front panel **Trigger** hardkey.

EXT This choice enables triggering using an externally applied signal at the PATT TRIG IN rear panel connector or the PATT TRIG IN 2 pin on the rear panel AUX I/O connector. To select the appropriate connector, refer to “:TRIGger[:SOURce]:EXTernal[:SOURce]” on page 906.

BUS This choice enables GPIB triggering using the *TRG or GET command or LAN and RS-232 triggering using the *TRG command.

Key Entry **Trigger Key Ext Bus**

:SECondary[:STATe]

Supported E4438C with Option 402

[:SOURce] :RADio [:NADC] :SECondary [:STATe] ON | OFF | 1 | 0
[:SOURce] :RADio [:NADC] :SECondary [:STATe] ?

This command enables or disables the ability to switch to the secondary frame.

***RST** 0

Key Entry **Secondary Frame Off On**

Remarks A frame must already be saved as the secondary frame in order to turn the secondary state function on.

 To save a frame as the secondary frame, refer to “:SECOndary:SAVE” on page 892.

:SLOT[1] | 2 | 3 | 4 | 5 | 6:DCUStom

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:SLOT[1] | 2 | 3 | 4 | 5 | 6:DCUStom
PN9 | PN11 | PN15 | PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURCE]:RADIO[:NADC]:SLOT[1] | 2 | 3 | 4 | 5 | 6:DCUStom?
```

This command configures the data field for the selected downlink custom timeslot.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's			

Remarks Refer to “File Name Variables” on page 13 for information on the file name syntax.

:SLOT[1] | 2 | 3 | 4 | 5 | 6:DCUStom:FIX4

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:SLOT[1] | 2 | 3 | 4 | 5 | 6:DCUStom:FIX4 <val>
[:SOURCE]:RADIO[:NADC]:SLOT[1] | 2 | 3 | 4 | 5 | 6:DCUStom:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink custom timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT[1]|2|3|4|5|6:DTCHannel:CDLocator

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 :DTCHannel :  
CDLocator <bit_pattern>  
[ :SOURCE ] :RADIO [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 :DTCHannel :CDLocator?
```

This command changes the 11-bit coded digital control channel locator (CDL) field.

***RST** #H000

Range #H0–#H7FF

Key Entry **CDL**

Remarks The preset hexadecimal value (when normal preset is selected) for CDL reflects the NADC protocol; however, you can enter a new value by using this command.

:SLOT[1]|2|3|4|5|6:DTCHannel:CDVCCode

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 :DTCHannel :  
CDVCCode <bit_pattern>  
[ :SOURCE ] :RADIO [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 :DTCHannel :CDVCCode?
```

This command changes the 12-bit coded digital verification color code (CDVCC).

***RST** #H000

Range #H0–#HFFF

Key Entry **CDVCC**

Remarks The preset hexadecimal value (when normal preset is selected) for CDVCC reflects the NADC protocol; however, you can enter a new value by using this command.

:SLOT[1]|2|3|4|5|6:DTCHannel:SACChannel

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 :DTCHannel :  
SACChannel <bit_pattern>  
[ :SOURCE ] :RADIO [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 :DTCHannel :SACChannel?
```

This command changes the 15-bit slow associated control channel.

***RST** #H000

Range	#H0–#HFFF
Key Entry	SACCH
Remarks	The preset hexadecimal value (when normal preset is selected) for SACCH reflects the value specified by the standard.

:SLOT[1]|2|3|4|5|6:DTCHannel:SWORd

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:DTCHannel:SWORd <bit_pattern>
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:DTCHannel:SWORd?
```

This command sets the 28-bit synchronization word as the active function. This is used for slot synchronization, equalizer training, and timeslot identification.

*RST	#HA91DE4A
Range	#H0–#HFFFFFFF
Key Entry	SYNC

:SLOT[1]|2|3|4|5|6:DTCHannel[:DATA]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:DTCHannel[:DATA] PN9|
PN11|PN15|PN20|PN23|FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:DTCHannel[:DATA]?
```

This command sets a pseudo-random number sequence, 4-bit pattern, sequence of 1's and 0's, data from an external source, or a user file as the data pattern for the selected downlink traffic channel timeslot during framed transmission.

*RST	PN9
Key Entry	PN9 PN11 PN15 PN20 PN23 FIX4 User File EXT
	4 1's & 4 0's 8 1's & 8 0's 16 1's & 16 0's 32 1's & 32 0's
	64 1's & 64 0's

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:SLOT[1]|2|3|4|5|6:DTCHannel[:DATA]FIX4

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:DTCHannel[:DATA]:FIX4 <val>  
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:DTCHannel[:DATA]:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink traffic channel timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT[1]|2|3|4|5|6:POWER

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:POWER MAIN|DELTA  
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:POWER?
```

This command toggles the RF output power level function for the selected timeslot.

MAIN This choice specifies RF output as the main power level.

DELTA This choice specifies RF output as the alternative power level.

***RST** MAIN

Key Entry **Timeslot Ampl Main Delta**

:SLOT[1]|2|3|4|5|6:STATE

Supported E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:STATE ON|OFF|1|0  
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:STATE?
```

This command enables or disables the operating state of the selected timeslot.

***RST** Timeslot 1: 1 Timeslots 2–6: 0

Key Entry **Timeslot Off On**

:SLOT[1]|2|3|4|5|6:UCUStom

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:UCUStom PN9|PN11|PN15|
PN20|PN23|FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:UCUStom?
```

This command configures the data field for the selected uplink custom timeslot.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's				
	64 1's & 64 0's							

Remarks Refer to “[File Name Variables](#)” on page 13 for information on the file name syntax.

:SLOT[1]|2|3|4|5|6:UCUStom:FIX4

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:UCUStom:FIX4 <val>
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:UCUStom:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected uplink custom timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT[1]|2|3|4|5|6:UTCHannel:CDVCcode

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:
CDVCcode <bit_pattern>
[:SOURCE]:RADIO[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:CDVCcode?
```

This command changes the 12-bit coded digital verification color code (CDVCC).

***RST** #H000

Range #H0–#HFFF

NADC Subsystem—Option 402 ([:SOURCE]:RADio[:NADC])**Key Entry** **CDVCC**

Remarks The preset hexadecimal value (when normal preset is selected) for CDVCC reflects the NADC protocol, however you can enter a new value by using this command.

:SLOT[1]|2|3|4|5|6:UTCHannel:SACChannel**Supported** E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:SACChannel
<bit_pattern>
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:SACChannel?
```

This command changes the 15-bit slow associated control channel.

***RST** #H000**Range** #H0–#HFFF**Key Entry** **SACCH**

Remarks The preset hexadecimal value (when normal preset is selected) for SACCH reflects the value specified by the standard.

:SLOT[1]|2|3|4|5|6:UTCHannel:SWORd**Supported** E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:SWORd <bit_pattern>
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:SWORd?
```

This command sets the 28-bit synchronization word as the active function. This is used for slot synchronization, equalizer training, and timeslot identification.

RST** #HA91DE4A**Range** #H0–#HFFFFFFF**Key Entry** **SYNC*:SLOT[1]|2|3|4|5|6:UTCHannel[:DATA]****Supported** E4438C with Option 402

```
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel[:DATA] PN9|PN15|
FIX4|<file name>|EXT|P4|P8|P16|P32|P64
[:SOURCE]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel[:DATA]?
```


This command sets a pseudo-random number sequence, 4-bit pattern, sequence of 1's and 0's, data from an external source, or a user file as the data pattern for the selected uplink traffic channel timeslot during framed transmission.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's			

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:SLOT[1] | 2 | 3 | 4 | 5 | 6:UTCHannel[:DATA]:FIX4

Supported E4438C with Option 402

```
[ :SOURce ] :RADio [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 :UTCHannel [ :DATA ] :FIX4 <val>
[ :SOURce ] :RADio [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 :UTCHannel [ :DATA ] :FIX4 ?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected uplink traffic channel timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT[1] | 2 | 3 | 4 | 5 | 6[:TYPE]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 [ :TYPE ] UCUSom | DCUSom | UTCH |
UTCH_ALL | DTCH | DTCH_ALL
[ :SOURce ] :RADio [ :NADC ] :SLOT [ 1 ] | 2 | 3 | 4 | 5 | 6 [ :TYPE ] ?
```

This command sets the timeslot type for the selected timeslot.

***RST** Timeslot 1: UTCH Timeslots 2–6: UCUS

Key Entry	Up Custom	Down Custom	Up TCH	Up TCH All	Down TCH
	Down TCH All				

:SOUT

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:SOUT FRAME|SLOT|ALL
[:SOURCE]:RADIO[:NADC]:SOUT?
```

This command sets the synchronization location (within the pattern of data) and the type of output at the EVENT 1 rear panel connector.

FRAME This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a framed data pattern.

SLOT This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a selected timeslot.

ALL This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for all active timeslots.

***RST** FRAME

Key Entry	Begin Frame	Begin Timeslot #	All Timeslots
------------------	--------------------	-------------------------	----------------------

:SOUT:OFFSet

Supported E4438C with Option 402

```
[:SOURCE]:RADIO[:NADC]:SOUT:OFFSet <val>
[:SOURCE]:RADIO[:NADC]:SOUT:OFFSet?
```

This command sets the offset value for the location of the output synchronization signal on the EVENT1 rear panel connector relative to the beginning of the framed data pattern or timeslot.

The variable <val> is expressed as a number of bits.

***RST** +0

Range -323 to 323

Key Entry **Sync Out Offset**

Remarks Negative values move the synchronization output signal earlier; positive values move it later.

To change the output of the EVENT1 rear panel connector to SLOT, refer to [“:SOUT” on page 900](#).

:SOUT: SLOT

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO [ :NADC ] :SOUT :SLOT <val>
```

```
[ :SOURCE ] :RADIO [ :NADC ] :SOUT :SLOT?
```

This command selects the timeslot that will trigger a 1-bit output signal at the EVENT 1 rear panel connector.

***RST** +1

Range 1–3

Key Entry **Begin Timeslot #**

Remarks To change the output of the EVENT1 rear panel connector to SLOT, refer to “:SOUT” on page 900.

:SRATe

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO [ :NADC ] :SRATe <val>
```

```
[ :SOURCE ] :RADIO [ :NADC ] :SRATe?
```

This command sets the transmission symbol rate. Symbol rate is the bit rate divided by the bits per symbol. A change in the symbol rate affects the bit rate. Refer to “:BRATe” on page 774 for information on bit rate.

The variable <val> is expressed in units of symbols per second (sps–Mps) and the maximum symbol rate depends on the filter. Refer to “:FILTer” on page 887 for minimum filter symbol width.

The filter may have to be truncated down to 32 or 16 symbols wide to achieve the highest symbol rate. The signal generator’s internal filters are not truncated below their minimum filter length and user-defined FIR filters are not truncated. If the filter cannot be truncated then the symbol rate is limited to the maximum rate of the narrowest filter size possible.

The relative timing of the modulated data, as well as the actual filter response is affected when the filter is truncated.

When the symbol rate changes, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the symbol rate: lower symbol rates require more time.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 890.

***RST** +2.43000000E+004

Receiver Test Digital Commands (continued)
NADC Subsystem—Option 402 ([:SOURce]:RADio[:NADC])

Range	Modulation Type	Symbol Rate Range		
		<i>16 Symbol Wide Filter</i>	<i>32 Symbol Wide Filter</i>	<i>64 Symbol Wide Filter</i>
	BPSK, FSK2, MSK	1sps–50Msps	1sps–25Msps	1sps–12.5Msps
	C4FM, OQPSK, FSK4	2sps–25Msps	2sps–12.5Msps	2sps–6.25Msps
	OQPSKI95, QPSK			
	P4QPPSK, QPSKIS95			
	GRAYQPSK, QAM4			
	D8PSK, EDGE, FSK8, PSK8	3sps–16.666666666 Msps	3sps–8.333333333 Msps	3sps–4.166666666Msps
	FSK16, PSK16, QAM16	4sps–12.5Msps	4sps–6.25Msps	4sps–3.125Msps
	QAM32	5sps–10Msps	5sps–5Msps	5sps–2.5Msps
	QAM64	6sps–8.333333333 Msps	6sps–4.166666666 Msps	6sps–2.083333333 Msps
	QAM128	7sps–7.142857142 Msps	7sps–3.571428572 Msps	7sps–1.785714285 Msps
	QAM256	8sps–6.25Msps	8sps–3.125 Msps	8sps–1.5625 Msps

NOTE Using I/Q skew will half the minimum number of symbols for the selected filter.

Key Entry **Symbol Rate**

:TRIGger:TYPE

Supported E4438C with Option 402

[:SOURce] :RADio [:NADC] :TRIGger:TYPE CONTInuous | SINGle | GATE
 [:SOURce] :RADio [:NADC] :TRIGger:TYPE?

This command sets the trigger type.

CONTInuous	The framed data sequence repeats continuously; the sequence restarts every time the previous playback is completed. To customize continuous triggering, refer to “:TRIGger:TYPE:CONTInuous[:TYPE]” on page 903.		
SINGle	The framed data sequence plays once for every trigger received.		
GATE	An external trigger signal interrupts the playback while the gating signal is in the inactive state. Playback resumes when the external control signal returns to the active state. The active state can be set to high or low.		
*RST	CONT		
Key Entry	Continuous	Single	Gated

:TRIGger:TYPE:CONTInuous[:TYPE]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio [ :NADC ] :TRIGger :TYPE :CONTInuous [ :TYPE ] FREE | TRIGger | RESet
[ :SOURce ] :RADio [ :NADC ] :TRIGger :TYPE :CONTInuous [ :TYPE ] ?
```

This commands selects the waveform’s response to a trigger signal while using the continuous trigger mode.

For more information on triggering and to select the continuous trigger mode, see “:TRIGger:TYPE” on page 902.

The following list describes the waveform’s response to each of the command choices:

FREE	Turning the ARB format on immediately triggers the waveform. The waveform repeats until you turn the format off, select another trigger, or choose another waveform file.		
TRIGger	The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously until you turn the format off, select another trigger, or choose another waveform file.		
RESet	The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously. Subsequent triggers reset the waveform to the beginning. For a waveform sequence, this means to the beginning of the first segment in the sequence.		
*RST	FREE		
Key Entry	Free Run	Trigger & Run	Reset & Run

:TRIGger:TYPE:GATE:ACTive

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :TRIGger :TYPE:GATE:ACTive LOW|HIGH  
[ :SOURCE ] :RADio [ :NADC ] :TRIGger :TYPE:GATE:ACTive?
```

This command selects the active state (gate polarity) of the gate while using the gating trigger mode.

The LOW and HIGH selections correspond to the low and high states of an external trigger signal. For example, when you select HIGH, the active state occurs during the high of the trigger signal. When the active state occurs, the ESG stops the waveform playback at the last played sample point, then restarts the playback at the next sample point when the inactive state occurs. For more information on triggering and to select gating as the trigger mode, see “:TRIGger:TYPE” on page 902.

The following list describes the signal generator’s external trigger signal gating behavior for the polarity selections:

LOW	The waveform playback stops when the trigger signal goes low (active state) and restarts when the trigger signal goes high (inactive state).
HIGH	The waveform playback stops when the trigger signal goes high (active state) and restarts when the trigger signal goes low (inactive state).
*RST	HIGH
Key Entry	Gate Active Low High

:TRIGger[:SOURCE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :TRIGger [ :SOURCE ] KEY|EXT|BUS  
[ :SOURCE ] :RADio [ :NADC ] :TRIGger [ :SOURCE ] ?
```

This command sets the trigger source.

For more information on triggering, see “:TRIGger:TYPE” on page 902. The following list describes the command choices:

KEY	This choice enables manual triggering by pressing the front-panel Trigger hardkey.
EXT	An externally applied signal triggers the waveform. This is the only choice that works with gating. The following conditions affect an external trigger: <ul style="list-style-type: none">• The input connector selected for the trigger signal. You have a choice between the rear-panel PATTERN TRIG IN connector or the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector. To make the connector selection, see “:TRIGger[:SOURCE]:EXTernal[:SOURCE]” on page 906.

For more information on the connectors and on connecting the cables, see the *E4428C/38C ESG Signal Generators User's Guide*.

- The trigger signal polarity:
 - gating mode, see “[:TRIGger:TYPE:GATE:ACTive” on page 904
 - continuous and single modes, see “[:TRIGger[:SOURce]:EXTernal:SLOPe” on page 906
- The time delay between when the ESG receives a trigger and when the waveform responds to the trigger. There are two parts to setting the delay:
 - setting the amount of delay, see “[:TRIGger[:SOURce]:EXTernal:DELay” on page 905
 - turning the delay on, see “[:TRIGger[:SOURce]:EXTernal:DELay:STATe” on page 906

BUS This choice enables triggering over the GPIB or LAN using the *TRG or GET commands or the AUXILIARY INTERFACE (RS-232) using the *TRG command.

***RST** KEY

Key Entry	Trigger Key	Ext	Bus
------------------	--------------------	------------	------------

[:TRIGger[:SOURce]:EXTernal:DELay

Supported E4438C with Option 402

```
[:SOURce]:RADio[:NADC]:TRIGger[:SOURce]:EXTernal:DELay <val>
[:SOURce]:RADio[:NADC]:TRIGger[:SOURce]:EXTernal:DELay?
```

This command sets the number of bits to delay the ESG's response to an external trigger.

The bit delay is a delay between when the ESG receives the trigger and when it responds to the trigger. The delay uses the clocks of the bit-clock to time the delay. After the ESG receives the trigger and the set number of delay bits (clocks) occurs, the ESG transmits the data pattern.

The delay occurs after you enable the state. See “[:TRIGger[:SOURce]:EXTernal:DELay:STATe” on page 906. You can set the number of bits either before or after enabling the state.

For more information on configuring an external trigger source and to select external as the trigger source, see “[:TRIGger[:SOURce]” on page 904.

***RST** +0

Range 0–1048575

Key Entry Ext Delay Bits

:TRIGger[:SOURCE]:EXternal:DELay:STATe

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :TRIGger [ :SOURCE ] :EXternal :DELay :STATe ON | OFF | 1 | 0  
[ :SOURCE ] :RADio [ :NADC ] :TRIGger [ :SOURCE ] :EXternal :DELay :STATe ?
```

This command enables or disables the operating state of the external trigger delay function.

For setting the delay time, see “:TRIGger[:SOURCE]:EXternal:DELay” on page 905, and for more information on configuring an external source, see “:TRIGger[:SOURCE]” on page 904.

***RST** 0

Key Entry Ext Delay Off On

:TRIGger[:SOURCE]:EXternal:SLOPe

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :TRIGger [ :SOURCE ] :EXternal :SLOPe POSitive | NEGative  
[ :SOURCE ] :RADio [ :NADC ] :TRIGger [ :SOURCE ] :EXternal :SLOPe ?
```

This command sets the polarity for an external trigger signal while using the continuous, single triggering mode. To set the polarity for gating, see “:TRIGger:TYPE:GATE:ACTive” on page 904.

The POSitive and NEGative selections correspond to the high (positive) and low (negative) states of the external trigger signal. For example, when you select POSitive, the waveform responds (plays) during the high state of the trigger signal. When the ESG receives multiple trigger occurrences when only one is required, the signal generator uses the first trigger and ignores the rest.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURCE]” on page 904.

***RST** POS

Key Entry Ext Polarity Neg Pos

:TRIGger[:SOURCE]:EXternal[:SOURCE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio [ :NADC ] :TRIGger [ :SOURCE ] :EXternal [ :SOURCE ] EPT1 | EJPT2 |  
EPTRIGGER1 | EPTRIGGER2  
[ :SOURCE ] :RADio [ :NADC ] :TRIGger [ :SOURCE ] :EXternal [ :SOURCE ] ?
```

This command selects which PATTERN TRIG IN connection the ESG uses to accept an externally applied trigger signal when external is the trigger source selection.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURce]” on page 904. For more information on the rear-panel connectors, see the *E4428C/38C ESG Signal Generators User’s Guide*.

The following list describes the command choices:

EPT1	This choice is synonymous with EPTRIGGER1 and selects the PATTERN TRIG IN rear-panel connector.
EPT2	This choice is synonymous with EPTRIGGER2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector.
EPTRIGGER1	This choice is synonymous with EPT1 and selects the PATTERN TRIG IN rear-panel connector.
EPTRIGGER2	This choice is synonymous with EPT2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector.
*RST	EPT1
Key Entry	Patt Trig In 1 Patt Trig In 2

[:STATe]

Supported E4438C with Option 402

[:SOURce] :RADio [:NADC] [:STATe] ON | OFF | 1 | 0
 [:SOURce] :RADio [:NADC] [:STATe] ?

This command enables or disables the NADC modulation format.

***RST** OFF

Key Entry **NADC Off On**

Remarks Although the NADC modulation is enabled with this command, the RF carrier is not modulated unless you also activate the front panel **Mod On/Off** hardkey.

PDC Subsystem–Option 402 ([:SOURce]:RADio:PDC)

:ALPha

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:ALPha <val>  
[ :SOURce ] :RADio:PDC:ALPha?
```

This command changes the Nyquist or root Nyquist filter’s alpha value.

The filter alpha value can be set to a minimum level (0), a maximum level (1), or in between by using fractional numeric values (0.001–0.999).

***RST** +5.00000000E–001

Range 0.000–1.000

Key Entry **Filter Alpha**

Remarks To change the current filter type, refer to “:FILTer” on page 920.

:BBCLock

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:BBCLock INT [1] | EXT [1]  
[ :SOURce ] :RADio:PDC:BBCLock?
```

This command toggles the data (bit) clock input to the baseband generator board to either internal or external. This command is independent in each mode and works for both non-burst (continuous) and burst modes. This allows for a matrix of selections between burst/non-burst, internal/external data generation, internal/external data clock, and external bit/symbol data clock.

INT[1] This choice selects the signal generator internal data clock.

EXT[1] This choice selects an external data clock input.

***RST** INT

Key Entry **Ext Data Clock Ext Int**

Remarks A data clock or continuous symbol sync input must be supplied when external mode is used.

:BBT

Supported E4438C with Option 402

[:SOURCE] :RADio:PDC:BBT <val>

[:SOURCE] :RADio:PDC:BBT?

This command changes the bandwidth-multiplied-by-bit-time (BbT) filter parameter.

The filter BbT value can be set to the maximum level (1) or in between the minimum level (0.100) and maximum level by using fractional numeric values (0.101–0.999).

***RST** +5.00000000E–001

Range 0.100–1.000

Key Entry **Filter BbT**

Remarks This command is effective only after choosing a Gaussian filter. It does not have an effect on other types of filters.

To change the current filter type, refer to “:FILTer” on page 920.

:BRATe

Supported E4438C with Option 402

[:SOURCE] :RADio:PDC:BRATe <val>

[:SOURCE] :RADio:PDC:BRATe?

This command sets the bit rate in bits per second (bps–Mbps). The maximum bit rate is dependent on the modulation type and filter as shown in the following tables

The IQ digital data stream is shaped by a FIR filter. The filter length and associated latency and frequency response are dependent on the bit rate as shown in the following tables. The signal generator selects a filter length.

For higher bit rates, the FIR filter length may be truncated (if the minimum filter size allows it) which will impact the relative timing of the modulated data, as well as the actual filter response (see the symbol rate command “:SRATe” on page 965). Refer to “:FILTer” on page 920 for information on filter symbol widths.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 923.

When the bit rate is changed, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the bit rate: lower bit rates require more time.

Receiver Test Digital Commands (continued)
PDC Subsystem–Option 402 ([:SOURce]:RADio:PDC)

***RST** +4.20000000E+004

Range	Modulation Type	Bit Rate Range		
		16 Symbol Wide Filter	32 Symbol Wide Filter	64 Symbol Wide Filter
	BPSK, FSK2, MSK	1bps–50Mbps	1bps–25Mbps	1bps–12.5Mbps
	C4FM, OQPSK, FSK4	2bps–50Mbps	2bps–25Mbps	2bps–12.5Mbps
	OQPSKI95, QPSK			
	P4QPPSK, QPSKIS95			
	GRAYQPSK, QAM4			
	D8PSK, EDGE, FSK8, PSK8	3bps–50Mbps	3bps–25Mbps	3bps–12.5Mbps
	FSK16, PSK16, QAM16	4bps–50Mbps	4bps–25Mbps	4bps–12.5Mbps
	QAM32	5bps–50Mbps	5bps–25Mbps	5bps–12.5Mbps
	QAM64	6bps–50Mbps	6bps–25Mbps	6bps–12.5Mbps
	QAM128	7bps–50Mbps	7bps–25Mbps	7bps–12.5Mbps
	QAM256	8bps–50Mbps	8bps–25Mbps	8bps–12.5Mbps

Key Entry **Symbol Rate**

:BURSt:PN9

Supported E4438C with Option 402

[:SOURce] :RADio:PDC: BURSt : PN9 NORMAl | QUICk
 [:SOURce] :RADio:PDC: BURSt : PN9?

This command controls the software PN9 generation.

NORMAl This choice produces a maximum length PN9 sequence.

QUICk This choice produces a truncated PN9 sequence.

***RST** NORM

Key Entry **PN9 Mode Normal Quick**

Remarks Use Normal mode for bit-error-rate tests where a maximum length PN9 sequence is required.

:BURSt:SHAPe:FALL:DELay

Supported E4438C with Option 402

[:SOURce] :RADio:PDC:BURSt:SHAPe:FALL:DELay <val>

[:SOURce] :RADio:PDC:BURSt:SHAPe:FALL:DELay?

This command sets the period of time that the start of the burst fall is delayed.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range -22.3750 to 99

Key Entry **Fall Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 923. Refer to “:SRATe” on page 965 for a list of minimum and maximum symbol rate values.

“:BURSt:SHAPe:FDELay” on page 912 performs the same function. In compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:FALL:TIME

Supported E4438C with Option 402

[:SOURce] :RADio:PDC:BURSt:SHAPe:FALL:TIME <val>

[:SOURce] :RADio:PDC:BURSt:SHAPe:FALL:TIME?

This command sets the period of time where the burst decreases from full power to minimum power.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +1.00000000E+001

Range 0.1250–255.8750

Key Entry Fall Time

PDC Subsystem—Option 402 ([:SOURce]:RADio:PDC)

Remarks	<p>The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.</p> <p>To change the modulation type, refer to “:MODulation[:TYPE]” on page 923. Refer to “:SRATE” on page 965 for a list of minimum and maximum symbol rate values.</p> <p>“:BURSt:SHAPe:FTIME” on page 913 performs the same function. In compliance with the SCPI standard, both commands are listed.</p> <p>For concept information on burst shaping, refer to the <i>E4428C/38C ESG Signal Generators User’s Guide</i>.</p>
----------------	--

:BURSt:SHAPe:FDElay

Supported E4438C with Option 402

[:SOURce] :RADio:PDC:BURSt:SHAPe:FDElay <val>

[:SOURce] :RADio:PDC:BURSt:SHAPe:FDElay?

This command sets the period of time that the start of the burst fall is delayed.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range –22.3750 to 99

Key Entry **Fall Delay**

Remarks	<p>The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.</p> <p>To change the modulation type, refer to “:MODulation[:TYPE]” on page 923. Refer to “:SRATE” on page 965 for a list of minimum and maximum symbol rate values.</p> <p>“:BURSt:SHAPe:FALL:DElay” on page 911 performs the same function. In compliance with the SCPI standard, both commands are listed.</p> <p>For concept information on burst shaping, refer to the <i>E4428C/38C ESG Signal Generators User’s Guide</i>.</p>
----------------	---

:BURSt:SHAPe:FTIME

Supported E4438C with Option 402

[:SOURce] :RADio:PDC:BURSt:SHAPe:FTIME <val>

[:SOURce] :RADio:PDC:BURSt:SHAPe:FTIME?

This command sets the period of time where the burst decreases from full power to minimum power.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range 0.1250–255.8750

Key Entry **Fall Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 923. Refer to “:SRATE” on page 965 for a list of minimum and maximum symbol rate values.

“:BURSt:SHAPe:FALL:TIME” on page 911 performs the same function. In compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RDELay

Supported E4438C with Option 402

[:SOURce] :RADio:PDC:BURSt:SHAPe:RDELay <val>

[:SOURce] :RADio:PDC:BURSt:SHAPe:RDELay?

This command sets the period of time that the start of the burst rise is delayed.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range –18.3750 to 99

Key Entry **Rise Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 923. Refer to “:SRATe” on page 965 for a list of minimum and maximum symbol rate values.

“:BURSt:SHAPe:RISE:DELay” on page 914 performs the same function. In compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RISE:DELay

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:BURSt:SHAPe:RISE:DELay <val>  
[ :SOURce ] :RADio:PDC:BURSt:SHAPe:RISE:DELay?
```

This command sets the period of time that the start of the burst rise is delayed.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range –18.3750 to 99

Key Entry **Rise Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 923. Refer to “:SRATe” on page 965 for a list of minimum and maximum symbol rate values.

“:BURSt:SHAPe:RDELay” on page 913 performs the same function. In compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RISE:TIME

Supported E4438C with Option 402

[:SOURce] :RADio:PDC:BURSt:SHAPe:RISE:TIME <val>

[:SOURce] :RADio:PDC:BURSt:SHAPe:RISE:TIME?

This command sets the period of time where the burst increases from a minimum power to full power.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +1.00000000E+001

Range 0.1250–22.5000

Key Entry **Rise Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 923. Refer to “:SRATe” on page 965 for a list of minimum and maximum symbol rate values.

“:BURSt:SHAPe:RTIME” on page 915 performs the same function. In compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RTIME

Supported E4438C with Option 402

[:SOURce] :RADio:PDC:BURSt:SHAPe:RTIME <val>

[:SOURce] :RADio:PDC:BURSt:SHAPe:RTIME?

This command sets the period of time where the burst increases from a minimum power to full power.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +1.00000000E+001

Range 0.1250–22.5000

Key Entry **Rise Time**

PDC Subsystem—Option 402 ([:SOURce]:RADio:PDC)

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 923. Refer to “:SRATE” on page 965 for a list of minimum and maximum symbol rate values.

“:BURSt:SHAPe:RISE:TIME” on page 915 performs the same function. In compliance with the SCPI standard, both commands are listed.

Refer to the *E4428C/38C ESG Signal Generators User’s Guide* for concept information.

:BURSt:SHAPe[:TYPE]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:BURSt:SHAPe[:TYPE] SINE | "<file name>"
[ :SOURce ] :RADio:PDC:BURSt:SHAPe[:TYPE] ?
```

This command specifies the burst shape as either SINE or a user-defined file ("<file name>").

SINE This choice selects a state that is defined by the burst rise and fall *RST values, as the default burst shape type.

"<file name>" This choice selects a user designated file from signal generator memory.

***RST** SINE

Key Entry **Sine** **User File**

:BURSt[:STATe]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:BURSt[:STATe] ON | OFF | 1 | 0
[ :SOURce ] :RADio:PDC:BURSt[:STATe] ?
```

This command enables or disables the burst function.

ON (1) This choice enables the transmission of framed data. If all timeslots which are switched on are up traffic channels or custom, you will be bursting the timeslots that are on; there will be no RF carrier during the off timeslots.

If you have switched on any timeslot that you have configured as a down traffic channel, the RF carrier is not switched off between any of the timeslots. The off timeslots are transmitted as a continuous series of ones for the time period of the off timeslots.

OFF (0) This choice enables the transmission of unframed data.
***RST** 0
Key Entry **Data Format Pattern Framed**

:CHANnel

Supported E4438C with Option 402
[:SOURCE]:RADio:PDC:CHANnel EVM|ACP
[:SOURCE]:RADio:PDC:CHANnel?

This command optimizes the Nyquist and root Nyquist filters to minimize error vector magnitude (EVM) or to minimize adjacent channel power (ACP).

EVM This choice provides the most ideal passband.
ACP This choice improves stopband rejection.
***RST** EVM

Key Entry **Optimize FIR For EVM ACP**

Remarks To change the current filter type, refer to “[:FILTer](#)” on page 920.

:DATA

Supported E4438C with Option 402
[:SOURCE]:RADio:PDC:DATA PN9|PN11|PN15|PN20|PN23|FIX4|"<file name>"|
EXT|P4|P8|P16|P32|P64|PRAM
[:SOURCE]:RADio:PDC:DATA?

This command sets the data pattern type (pseudo-random number sequence, 4-bit pattern, sequence of 1’s and 0’s, data from an external source, or a user file) for unframed data transmission.

***RST** PN23
Key Entry **PN9 PN11 PN15 PN20 PN23 FIX4 User File Ext**
4 1’s & 4 0’s 8 1’s & 8 0’s 16 1’s & 16 0’s 32 1’s & 32 0’s
64 1’s & 64 0’s PRAM File

Remarks Refer to “[File Name Variables](#)” on page 13 for information on the file name syntax.

:DATA:PRAM

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:PDC:DATA:PRAM "<file_name>"
```

```
[ :SOURCE ] :RADIO:PDC:DATA:PRAM?
```

This command selects a pattern RAM (PRAM) file as the pattern data type for the PDC (Personal Digital Cellular) format.

"<file_name>" This variable designates the PRAM file in WFM1. Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

Key Entry **PRAM File**

Remarks Selecting this data source forces the burst source to INTERNAL to allow framing control.

The PRAM file must reside in the ESG’s volatile memory (WFM1) in order to be accessed by this command. See [“:DATA:PRAM:FILE:BLOCK” on page 112](#).

:DATA:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:PDC:DATA:FIX4 <val>
```

```
[ :SOURCE ] :RADIO:PDC:DATA:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern for unframed transmission according to the protocols (modulation type, symbol rate, filter, and burst shape) selected for the PDC format.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:DEFault

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:PDC:DEFault
```

This command returns all of the PDC modulation format parameters to factory settings. It does not affect any other signal generator parameters.

Key Entry **Restore PDC Factory Default**

:EDATa:DELay

Supported E4438C with Option 402

`[:SOURce]:RADio:PDC:EDATa:DELay?`

This query returns the amount of delay (in symbols) from the external data input to the beginning of the symbol on the I OUT and Q OUT rear panel connectors and the front panel RF OUTPUT connector.

Remarks When the format is turned off, the delay value is unchanged; the query will return the same delay value if the format is on or off.

:EDCLock

Supported E4438C with Option 402

`[:SOURce]:RADio:PDC:EDCLock SYMBOL|NORMal`
`[:SOURce]:RADio:PDC:EDCLock?`

This command sets the external data clock use.

SYMBOL This choice specifies that a continuous symbol clock signal must be provided to the SYMBOL SYNC input connector.

NORMal This choice specifies that the DATA CLOCK input connector requires a bit clock. The SYMBOL SYNC input connector requires a (one-shot or continuous) symbol sync signal.

***RST** NORM

Key Entry **Ext Data Clock Normal Symbol**

Remarks Both choices have no effect in internal clock mode. Refer to “:BBCLock” on [page 908](#) to select EXT as the data clock type.

:EREFerence

Supported E4438C with Option 402

`[:SOURce]:RADio:PDC:EREFerence INT|EXT`
`[:SOURce]:RADio:PDC:EREFerence?`

This command selects either an internal or external bit-clock reference for the data generator.

***RST** INT

Key Entry **BBG Ref Ext Int**

PDC Subsystem—Option 402 ([:SOURCE]:RADIO:PDC)

Remarks If the EXT choice is selected, the external source's frequency value must be applied to the BASEBAND GEN REF IN rear panel connector. The external reference and external data clock are not applicable at the same time. If both are selected, then the external reference takes precedence.

Refer to, “:EREFerence:VALue” on page 920 to enter the external reference frequency setting.

:EREFerence:VALue

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:PDC:EREFerence:VALue <val>
[ :SOURCE ] :RADIo:PDC:EREFerence:VALue?
```

This command sets the expected bit-clock reference frequency value for an externally applied reference signal.

The variable <val> is expressed in units of hertz (Hz–MHz).

***RST** +1.30000000E+007

Range 2.5E5–1E8

Key Entry **Ext BBG Ref Freq**

Remarks The value specified by this command is effective only when you are using an external reference applied to the BASEBAND GEN REF IN rear panel connector.

Refer to “:EREFerence” on page 919 to select EXT (external source) as the reference for the bit-clock.

:FILTer

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIo:PDC:FILTer RNYQuist|NYQuist|GAUSSian|RECTangle|
IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|"<user FIR>"
[ :SOURCE ] :RADIo:PDC:FILTer?
```

This command selects the pre-modulation filter type.

IS95 This choice selects a filter that meets the criteria of the IS-95 standard.

IS95_EQ This choice selects a filter which is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard. This filter is only used for IS-95 baseband filtering.

IS95_MOD This choice selects a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the

	filter specified in the IS-95 standard.
IS95_MOD_EQ	This choice selects a filter which is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.
AC4Fm	Selects a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.
UGGaussian	This choice selects a backwards compatible GSM Gaussian filter (Gaussian filter with a fixed BbT value of 0.300) for the ESG E44xxB Option UN3 or UN4.
"<user FIR>"	This variable is any filter file that you have stored into memory.
*RST	RYNQ
Key Entry	Root Nyquist Nyquist Gaussian Rectangle IS-95 IS-95 w/EQ IS-95 Mod IS-95 Mod w/EQ APCO 25 C4FM UN3/4 GSM Gaussian User FIR
Remarks	Refer to “File Name Variables” on page 13 for information on the file name syntax.

:FRATe

Supported E4438C with Option 402
[:SOURCE]:RADio:PDC:FRATe FULL|HALF
[:SOURCE]:RADio:PDC:FRATe?

This command toggles between a full- or half-rate traffic channel.

FULL Selects two equally spaced timeslots of the frame. Since there are six timeslots per frame, timeslots 1, 2, and 3 are paired with timeslots 4, 5, and 6, respectively.

HALF Selects one timeslot of the frame (6 individual timeslots per frame).

***RST** **FULL**

Key Entry **Rate Full Half**

:IQ:SCALE

Supported E4438C with Option 402
[:SOURCE]:RADio:PDC:IQ:SCALE <val>
[:SOURCE]:RADio:PDC:IQ:SCALE?

This command sets the amplitude of the I/Q outputs for better adjacent channel power (ACP); lower scaling values equate to better ACP.

Receiver Test Digital Commands (continued)
PDC Subsystem—Option 402 ([:SOURce]:RADio:PDC)

The variable <val> is expressed in units of percent.

*RST	+100
Range	1–200
Key Entry	I/Q Scaling
Remarks	This command has no effect with MSK or FSK modulation.

:MODulation:FSK[:DEVIation]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:MODulation:FSK[:DEVIation] <val>  
[ :SOURce ] :RADio:PDC:MODulation:FSK[:DEVIation] ?
```

This command sets the symmetric FSK frequency deviation value.

The variable <val> is expressed in units of Hertz and the maximum range value equals the current symbol rate value multiplied by four, limited to 20 MHz.

*RST	+4.00000000E+002
Range	0–2E7
Key Entry	Freq Dev
Remarks	To change the modulation type, refer to “:MODulation[:TYPE]” on page 923.

Refer to “:SRATe” on page 965 for minimum and maximum symbol rate values.
To set an asymmetric FSK deviation value, refer to the *E4428C/38C ESG Signal Generators User’s Guide* for more information.

:MODulation:MSK[:PHASe]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:MODulation:MSK[:PHASe] <val>  
[ :SOURce ] :RADio:PDC:MODulation:MSK[:PHASe] ?
```

This command sets the MSK phase deviation value.

The variable <val> is expressed in units of degrees.

*RST	+9.00000000E+001
Range	0–100
Key Entry	Phase Dev

:MODulation:UFSK

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:MODulation:UFSK "<file name>"
```

```
[ :SOURCE ] :RADio:PDC:MODulation:UFSK?
```

This command selects a user-defined FSK file from the signal generator memory.

Key Entry **User FSK**

Remarks The user-defined FSK file is held in signal generator memory until the command that selects user FSK as the modulation type is sent. Refer to [“:MODulation\[:TYPE\]” on page 923](#) to change the current modulation type.

Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:MODulation:UIQ

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:MODulation:UIQ "<file name>"
```

```
[ :SOURCE ] :RADio:PDC:MODulation:UIQ?
```

This command selects a user-defined I/Q file from the signal generator memory.

Key Entry **User I/Q**

Remarks The user-defined I/Q file is held in signal generator memory until the command that selects user I/Q as the modulation type is sent. Refer to [“:MODulation\[:TYPE\]” on page 923](#) to change the current modulation type.

Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:MODulation[:TYPE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|  
GRAYQPSK|OQPSK|IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|  
FSK2|FSK4|FSK8|FSK16|C4FM|QAM4|QAM16|QAM32|QAM64|QAM128|QAM256|UIQ|UFSK  
[ :SOURCE ] :RADio:PDC:MODulation[:TYPE] ?
```

This command sets the modulation type for the PDC personality.

PDC Subsystem—Option 402 ([:SOURCE]:RADio:PDC)

*RST	P4DQPSK							
Key Entry	BPSK	QPSK	IS-95 QPSK	Gray Coded QPSK		OQPSK		
	IS-95 OQPSK	$\pi/4$ DQPSK	8PSK	16PSK	D8PSK	MSK	2-Lvl FSK	
	4-Lvl FSK	8-Lvl FSK	16-Lvl FSK	C4FM	4QAM	16QAM	32QAM	
	64QAM	128QAM	256QAM	User I/Q	User FSK			

:POLarity[:ALL]

Supported E4438C with Option 402

[:SOURCE] :RADio:PDC:POLarity[:ALL] NORMal | INVerted

[:SOURCE] :RADio:PDC:POLarity[:ALL] ?

This command sets the rotation direction for of the phase modulation vector.

NORMal This choice selects normal phase polarity.

INVerted This choice inverts the internal Q signal.

***RST** NORM

Key Entry **Phase Polarity Normal Invert**

:SECondary:RECall

Supported E4438C with Option 402

[:SOURCE] :RADio:PDC:SECondary:RECall

This command recalls the secondary frame configuration, overwriting the current state.

Key Entry **Recall Secondary Frame State**

Remarks To save a secondary frame state, refer to “:SECondary:SAVE” on page 924.

A secondary frame is not active until the secondary state is enabled. To activate a secondary frame, refer to “:SECondary[:STATE]” on page 925.

:SECondary:SAVE

Supported E4438C with Option 402

[:SOURCE] :RADio:PDC:SECondary:SAVE

This command saves the current frame configuration as the secondary frame with the filename PDC_SECONDARY_FRAME.

Key Entry **Save Secondary Frame State**

Remarks To recall the secondary frame (saved in non-volatile signal generator memory), refer to “:SECOndary:SAVE” on page 924.

:SECOndary:TRIGger[:SOURce]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:SECOndary:TRIGger [ :SOURce ] KEY | EXT | BUS
[ :SOURce ] :RADio:PDC:SECOndary:TRIGger [ :SOURce ] ?
```

This command selects the type of triggering for the secondary frame.

KEY This choice enables triggering by pressing the front panel **Trigger** hardkey.

EXT This choice enables triggering using an externally applied signal at the PATT TRIG IN rear panel connector or the PATT TRIG IN 2 pin on the rear panel AUX I/O connector. To select the appropriate connector, refer to “:TRIGger[:SOURce]:EXTErnal[:SOURce]” on page 940.

BUS This choice enables GPIB triggering using the *TRG or GET command or LAN and RS-232 triggering using the *TRG command.

Key Entry **Trigger Key Ext Bus**

:SECOndary[:STATe]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:SECOndary [ :STATe ] ON | OFF | 1 | 0
[ :SOURce ] :RADio:PDC:SECOndary [ :STATe ] ?
```

This command enables or disables the ability to switch to the secondary frame.

***RST** 0

Key Entry **Secondary Frame Off On**

Remarks A frame must already be saved as the secondary frame in order to turn the secondary state function on.

To save a frame as the secondary frame, refer to “:SECOndary[:STATe]” on page 925.

:SLOT0|[1]|2|3|4|5:DCUStom

Supported E4438C with Option 402

```
[ :SOURce] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DCUStom PN9 | PN11 | PN15 |
PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURce] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DCUStom?
```

This command configures the data field for the selected downlink custom timeslot.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's			

Remarks Refer to “File Name Variables” on page 13 for information on the file name syntax.

:SLOT0|[1]|2|3|4|5:DCUSTom:FIX4

Supported E4438C with Option 402

```
[ :SOURce] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DCUSTom:FIX4 <val>
[:SOURce] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DCUSTom:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink custom timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type. To change the data type, refer to “:SLOT0|[1]|2|3|4|5:DCUStom” on page 926.

:SLOT0|[1]|2|3|4|5:DTCHannel:CCODE

Supported E4438C with Option 402

```
[ :SOURce] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel:CCODE <bit_pattern>
[:SOURce] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel:CCODE?
```

This command changes the 8-bit color code (CC). The preset hexadecimal value (when normal preset is selected) for CC reflects the PDC protocol, however you can enter a new value using this command.

***RST** #H00

Range #H00–#HFF

Key Entry CC

:SLOT0|[1]|2|3|4|5:DTCHannel:SACChannel

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel:SACChannel <bit_pattern>  
[ :SOURce ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel:SACChannel?
```

This command changes the 15-bit slow associated control channel (SACCH). The preset hexadecimal value (when normal preset is selected) for SACCH reflects the PDC protocol, however you can enter a new value by executing this command.

***RST** #H00000

Range #H0–#HFFFFFF

Key Entry SACCH

:SLOT0|[1]|2|3|4|5:DTCHannel:SWORd

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel:SWORd <bit_pattern>  
[ :SOURce ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel:SWORd?
```

This command sets the 20-bit synchronization word as the active function. This is used for the control and traffic physical channels.

***RST** #H87A4B

Range #H0–#HFFFFFF

Key Entry SW

:SLOT0|[1]|2|3|4|5:DTCHannel[:TCHannel]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel[:TCHannel] PN9 |  
PN11 | PN15 | PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64  
[ :SOURce ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel[:TCHannel] ?
```

This command configures the data field for the selected downlink traffic channel field.

PDC Subsystem—Option 402 ([:SOURce]:RADio:PDC)

***RST** PN9

Key Entry PN9 PN11 PN15 PN20 PN23 FIX4 User File EXT
 4 1's & 4 0's 8 1's & 8 0's 16 1's & 16 0's 32 1's & 32 0's
 64 1's & 64 0's

Remarks See “File Name Variables” on page 13 for information on the file name syntax.

:SLOT0|[1]|2|3|4|5:DTCHannel[:TCHannel]:FIX4

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel [ :TCHannel ] :FIX4 <val>
[ :SOURce ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :DTCHannel [ :TCHannel ] :FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink traffic channel timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry FIX4

Remarks FIX4 must already be defined as the data type.

:SLOT0|[1]|2|3|4:POWer

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:DLINK:SLOT0 | [1] | 2 | 3 | 4 :POWer MAIN|DELTA
[ :SOURce ] :RADio:PDC:DLINK:SLOT0 | [1] | 2 | 3 | 4 :POWer?
```

This command toggles the RF output power level function for the selected timeslot.

MAIN This choice specifies RF output as the main power level.

DELTA This choice specifies RF output as the alternative power level.

***RST** MAIN

Key Entry Timeslot Ampl Main Delta

:SLOT0|[1]|2|3|4|5:STATE

Supported E4438C with Option 402

```
[:SOURce]:RADio:PDC:SLOT0 [1] | 2 | 3 | 4 | 5:STATE ON|OFF|1|0
[:SOURce]:RADio:PDC:SLOT0 [1] | 2 | 3 | 4 | 5:STATE?
```

This command enables or disables the operating state of the selected timeslot.

***RST** Timeslot 0: 1 Timeslots 1–5: 0

Key Entry Timeslot Off On

:SLOT0|[1]|2|3|4|5:UCUStom

Supported E4438C with Option 402

```
[:SOURce]:RADio:PDC:SLOT0 [1] | 2 | 3 | 4 | 5:UCUStom PN9|PN11|PN15 |
PN20|PN23|FIX4 | "<file name>" |EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio:PDC:SLOT0 [1] | 2 | 3 | 4 | 5:UCUStom?
```

This command configures the data field for the selected uplink custom timeslot.

***RST** PN9

Key Entry **PN9 PN11 PN15 PN20 PN23 FIX4 User File EXT**
4 1's & 4 0's 8 1's & 8 0's 16 1's & 16 0's 32 1's & 32 0's
64 1's & 64 0's

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:SLOT0|[1]|2|3|4|5:UCUStom:FIX4

Supported E4438C with Option 402

```
[:SOURce]:RADio:PDC:SLOT0 [1] | 2 | 3 | 4 | 5:UCUStom:FIX4 <val>
[:SOURce]:RADio:PDC:SLOT0 [1] | 2 | 3 | 4 | 5:UCUStom:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected uplink custom timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

PDC Subsystem—Option 402 ([:SOURCE]:RADio:PDC)**:SLOT0|[1]|2|3|4|5:UTCHannel:CCODE****Supported** E4438C with Option 402

```
[:SOURCE]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel:CCODE <bit_pattern>
[:SOURCE]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel:CCODE?
```

This command changes the 8-bit color code (CC). The preset hexadecimal value (when normal preset is selected) for CC reflects the PDC protocol, however you can enter a new value using this command.

RST** #H00**Range** #H00–#HFF**Key Entry** **CC*:SLOT0|[1]|2|3|4|5:UTCHannel:SACChannel****Supported** E4438C with Option 402

```
[:SOURCE]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel:SACChannel <bit_pattern>
[:SOURCE]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel:SACChannel?
```

This command changes the 15-bit slow associated control channel (SACCH). The preset hexadecimal value (when normal preset is selected) for SACCH reflects the PDC protocol, however you can enter a new value by executing this command.

RST** #H0000**Range** #H0–#H7FFF**Key Entry** **SACCH*:SLOT0|[1]|2|3|4|5:UTCHannel:SWORd****Supported** E4438C with Option 402

```
[:SOURCE]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel:SWORd <bit_pattern>
[:SOURCE]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel:SWORd?
```

This command sets the 20-bit synchronization word as the active function. This is used for the control and traffic physical channels.

***RST** #H785B4**Range** #H0–#HFFFFFF**Key Entry** **SW**

:SLOT0|[1]|2|3|4|5:UTCHannel[:TCHannel]

Supported E4438C with Option 402

```
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel[:TCHannel] PN9|
PN11|PN15|PN20|PN23|FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel[:TCHannel]?
```

This command sets a pseudo-random number sequence, 4-bit pattern, sequence of 1's and 0's, data from an external source, or a user file as the data pattern type for the uplink traffic channel field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's			

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:SLOT0|[1]|2|3|4|5:UTCHannel[:TCHannel]:FIX4

Supported E4438C with Option 402

```
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel[:TCHannel]:FIX4 <val>
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel[:TCHannel]:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected uplink traffic channel timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT0|[1]|2|3|4|5:UVOX:CCODE

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :UVOX:CCODE <bit_pattern>  
[ :SOURCE ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :UVOX:CCODE?
```

This command changes the 8-bit color code (CC). The preset hexadecimal value (when normal preset is selected) for CC reflects the PDC protocol, however you can enter a new value using this command.

***RST** #H00

Range #H00–#HFF

Key Entry **CC**

:SLOT0|[1]|2|3|4|5:UVOX:SACChannel

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :UVOX:SACChannel <bit_pattern>  
[ :SOURCE ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :UVOX:SACChannel?
```

This command changes the 15-bit slow associated control channel (SACCH). The preset hexadecimal value (when normal preset is selected) for SACCH reflects the PDC protocol, however you can enter a new value by executing this command.

***RST** #H0000

Range #H0–#H7FFF

Key Entry **SACCH**

:SLOT0|[1]|2|3|4|5:UVOX:SWORD

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :UVOX:SWORD <bit_pattern>  
[ :SOURCE ] :RADio:PDC:SLOT0 | [1] | 2 | 3 | 4 | 5 :UVOX:SWORD?
```

This command changes the synchronization word, which is used for slot synchronization, equalizer training, and timeslot identification.

***RST** UTCH & UVOX: 785B4 DTCH: 87A4B

Range #H0–#HFFFFFF

Key Entry **SW**

Remarks The *RST hexadecimal value reflects the value specified by the indicated standard.

:SLOT0|[1]|2|3|4|5[:TYPE]

Supported E4438C with Option 402

```
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5[:TYPE] UCUSom|DCUSom|
UTCH|UTCH_ALL|UVOX|DTCH|DTCH_ALL
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5[:TYPE]?
```

This command sets the timeslot type for the selected timeslot.

***RST** UTCH

Key Entry	Up Custom	Down Custom	Up TCH	UP TCH All	Up VOX
	Down TCH	Down TCH All			

:SOUT

Supported E4438C with Option 402

```
[:SOURce]:RADio:PDC:SOUT FRAME|SLOT|ALL
[:SOURce]:RADio:PDC:SOUT?
```

This command sets the synchronization location (within the pattern of data) and the type of output at the EVENT 1 rear panel connector.

FRAME This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a framed data pattern.

SLOT This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a selected timeslot.

ALL This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for all active timeslots.

***RST** FRAME

Key Entry	Begin Frame	Begin Timeslot #	All Timeslots
------------------	--------------------	-------------------------	----------------------

:SOUT:OFFSet

Supported E4438C with Option 402

```
[:SOURce]:RADio:PDC:SOUT:OFFSet <val>
[:SOURce]:RADio:PDC:SOUT:OFFSet?
```

This command sets the offset value for the location of the output synchronization signal on the EVENT1 rear panel connector relative to the beginning of the framed data pattern or timeslot.

The variable <val> is expressed as a number bits.

***RST** +0

Receiver Test Digital Commands (continued)
PDC Subsystem—Option 402 ([:SOURce]:RADio:PDC)

Range	–279 to 279
Key Entry	Sync Out Offset
Remarks	Negative values move the synchronization output signal earlier; positive values move it later. To change the output of the EVENT1 rear panel connector to SLOT, refer to “:SOUT” on page 933.

:SOUT:SLOT

Supported	E4438C with Option 402
	[:SOURce] :RADio:PDC:SOUT:SLOT <val>
	[:SOURce] :RADio:PDC:SOUT:SLOT?

This command selects the timeslot that will trigger a 1-bit signal at the EVENT 1 rear panel connector.

*RST	+0
Range	0–5
Key Entry	Begin Timeslot #
Remarks	To change the output of the EVENT1 rear panel connector to SLOT, refer to “:SOUT” on page 933.

:SRATe

Supported	E4438C with Option 402
	[:SOURce] :RADio:PDC:SRATe <val>
	[:SOURce] :RADio:PDC:SRATe?

This command sets the transmission symbol rate. Symbol rate is the bit rate divided by the bits per symbol. A change in the symbol rate affects the bit rate. Refer to “:BRATe” on page 774 for information on bit rate.

The variable <val> is expressed in units of symbols per second (sps–MSPS) and the maximum symbol rate depends on the filter. Refer to “:FILTer” on page 920 for minimum filter symbol width.

The filter may have to be truncated down to 32 or 16 symbols wide to achieve the highest symbol rate. The signal generator’s internal filters are not truncated below their minimum filter length and user-defined FIR filters are not truncated. If the filter cannot be truncated then the symbol rate is limited to the maximum rate of the narrowest filter size possible.

The relative timing of the modulated data, as well as the actual filter response is affected when the filter is truncated.

When the symbol rate changes, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the symbol rate: lower symbol rates require more time.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 923.

***RST** +2.1000000E+004

Range	Modulation Type	Symbol Rate Range		
		<i>16 Symbol Wide Filter</i>	<i>32 Symbol Wide Filter</i>	<i>64 Symbol Wide Filter</i>
	BPSK, FSK2, MSK	1sps–50Msps	1sps–25Msps	1sps–12.5Msps
	C4FM, OQPSK, FSK4	2sps–25Msps	2sps–12.5Msps	2sps–6.25Msps
	OQPSKI95, QPSK			
	P4QPPSK, QPSKIS95			
	GRAYQPSK, QAM4			
	D8PSK, EDGE, FSK8, PSK8	3sps–16.666666666 Msps	3sps–8.333333333 Msps	3sps–4.166666666Msps
	FSK16, PSK16, QAM16	4sps–12.5Msps	4sps–6.25Msps	4sps–3.125Msps
	QAM32	5sps–10Msps	5sps–5Msps	5sps–2.5Msps
	QAM64	6sps–8.333333333 Msps	6sps–4.166666666 Msps	6sps–2.083333333 Msps
	QAM128	7sps–7.142857142 Msps	7sps–3.571428572 Msps	7sps–1.785714285 Msps
	QAM256	8sps–6.25Msps	8sps–3.125 Msps	8sps–1.5625 Msps

NOTE Using I/Q skew will half the minimum number of symbols for the selected filter.

Key Entry **Symbol Rate**

:TRIGger:TYPE

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:TRIGger:TYPE CONTInuous | SINGle | GATE
[ :SOURCE ] :RADio:PDC:TRIGger:TYPE?
```

This command sets the trigger type.

CONTInuous The framed data sequence repeats continuously; the sequence restarts every time the previous playback is completed. To customize continuous triggering, refer to “[:TRIGger:TYPE:CONTInuous\[:TYPE\]](#)” on page 936.

SINGle The framed data sequence plays once for every trigger received.

GATE An external trigger signal interrupts the playback while the gating signal is in the inactive state. Playback resumes when the external control signal returns to the active state. The active state can be set to high or low.

***RST** CONT

Key Entry	Continuous	Single	Gated
------------------	-------------------	---------------	--------------

:TRIGger:TYPE:CONTInuous[:TYPE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:TRIGger:TYPE:CONTInuous [ :TYPE ] FREE | TRIGger | RESet
[ :SOURCE ] :RADio:PDC:TRIGger:TYPE:CONTInuous [ :TYPE ] ?
```

This commands selects the waveform’s response to a trigger signal while using the continuous trigger mode.

For more information on triggering and to select the continuous trigger mode, see “[:TRIGger:TYPE](#)” on page 936.

The following list describes the waveform’s response to each of the command choices:

FREE Turning the ARB format on immediately triggers the waveform. The waveform repeats until you turn the format off, select another trigger, or choose another waveform file.

TRIGger The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously until you turn the format off, select another trigger, or choose another waveform file.

RESet The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously. Subsequent triggers reset the waveform to the beginning. For a waveform sequence, this means to the beginning of the first segment in the sequence.

*RST	FREE		
Key Entry	Free Run	Trigger & Run	Reset & Run

:TRIGger:TYPE:GATE:ACTive

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:TRIGger:TYPE:GATE:ACTive LOW|HIGH
[ :SOURCE ] :RADio:PDC:TRIGger:TYPE:GATE:ACTive?
```

This command selects the active state (gate polarity) of the gate while using the gating trigger mode.

The LOW and HIGH selections correspond to the low and high states of an external trigger signal. For example, when you select HIGH, the active state occurs during the high of the trigger signal. When the active state occurs, the ESG stops the waveform playback at the last played sample point, then restarts the playback at the next sample point when the inactive state occurs. For more information on triggering and to select gating as the trigger mode, see “:TRIGger:TYPE” on page 936.

The following list describes the ESG’s gating behavior for the polarity selections:

- | | |
|------|--|
| LOW | The waveform playback stops when the trigger signal goes low (active state) and restarts when the trigger signal goes high (inactive state). |
| HIGH | The waveform playback stops when the trigger signal goes high (active state) and restarts when the trigger signal goes low (inactive state). |

***RST** HIGH

Key Entry Gate Active Low High

:TRIGger[:SOURCE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PDC:TRIGger [ :SOURCE ] KEY|EXT|BUS
[ :SOURCE ] :RADio:PDC:TRIGger [ :SOURCE ] ?
```

This command sets the trigger source.

For more information on triggering, see “:TRIGger:TYPE” on page 936. The following list describes the command choices:

- | | |
|-----|---|
| KEY | This choice enables manual triggering by pressing the front-panel Trigger hardkey. |
|-----|---|

- EXT** An externally applied signal triggers the waveform. This is the only choice that works with gating. The following conditions affect an external trigger:
- The input connector selected for the trigger signal. You have a choice between the rear-panel PATTERN TRIG IN connector or the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector. To make the connector selection, see “[:TRIGger[:SOURce]:EXTErnal[:SOURce]]” on page 940.
 For more information on the connectors and on connecting the cables, see the *E4428C/38C ESG Signal Generators User’s Guide*.
 - The trigger signal polarity:
 - gating mode, see “[:TRIGger:TYPE:GATE:ACTive]” on page 937
 - continuous and single modes, see “[:TRIGger[:SOURce]:EXTErnal:SLOPe]” on page 939
 - The time delay between when the ESG receives a trigger and when the waveform responds to the trigger. There are two parts to setting the delay:
 - setting the amount of delay, see “[:TRIGger[:SOURce]:EXTErnal:DELay]” on page 938
 - turning the delay on, see “[:TRIGger[:SOURce]:EXTErnal:DELay:STATe]” on page 939
- BUS** This choice enables triggering over the GPIB or LAN using the *TRG or GET commands or the AUXILIARY INTERFACE (RS-232) using the *TRG command.

***RST** KEY

Key Entry	Trigger Key	Ext	Bus
-----------	-------------	-----	-----

:TRIGger[:SOURce]:EXTErnal:DELay

Supported E4438C with Option 402

```
[:SOURce]:RADio:PDC:TRIGger[:SOURce]:EXTErnal:DELay <val>
[:SOURce]:RADio:PDC:TRIGger[:SOURce]:EXTErnal:DELay?
```

This command sets the number of bits to delay the ESG’s response to an external trigger.

The bit delay is a delay between when the ESG receives the trigger and when it responds to the trigger. The delay uses the clocks of the bit-clock to time the delay. After the ESG receives the trigger and the set number of delay bits (clocks) occurs, the ESG transmits the data pattern.

The delay occurs after you enable the state. See “[:TRIGger[:SOURce]:EXTErnal:DELay:STATe]” on page 939. You can set the number of bits either before or after enabling the state.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURce]” on page 937.

***RST** +0
Range 0–1048575
Key Entry **Ext Delay Bits**

:TRIGger[:SOURce]:EXTErnal:DELAy:STATe

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:TRIGger [ :SOURce ] :EXTErnal:DELAy:STATe ON|OFF|1|0  
[ :SOURce ] :RADio:PDC:TRIGger [ :SOURce ] :EXTErnal:DELAy:STATe?
```

This command enables or disables the operating state of the external trigger delay function.

For setting the delay time, see “:TRIGger[:SOURce]:EXTErnal:DELAy” on page 938, and for more information on configuring an external source, see “:TRIGger[:SOURce]” on page 937.

***RST** 0
Key Entry **Ext Delay Off On**

:TRIGger[:SOURce]:EXTErnal:SLOPe

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PDC:TRIGger [ :SOURce ] :EXTErnal:SLOPe POSitive|NEGative  
[ :SOURce ] :RADio:PDC:TRIGger [ :SOURce ] :EXTErnal:SLOPe?
```

This command sets the polarity for an external trigger signal while using the continuous, single triggering mode. To set the polarity for gating, see “:TRIGger:TYPE:GATE:ACTive” on page 937.

The POSitive and NEGative selections correspond to the high (positive) and low (negative) states of the external trigger signal. For example, when you select POSitive, the waveform responds (plays) during the high state of the trigger signal. When the ESG receives multiple trigger occurrences when only one is required, the signal generator uses the first trigger and ignores the rest.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURce]” on page 937.

***RST** NEG
Key Entry **Ext Polarity Neg Pos**

:TRIGger[:SOURCE]:EXTernal[:SOURCE]

Supported E4438C with Option 402

```
[:SOURCE]:RADio:PDC:TRIGger[:SOURCE]:EXTernal[:SOURCE] EPT1|EPT2|
EPTRIGGER1|EPTRIGGER2
[:SOURCE]:RADio:PDC:TRIGger[:SOURCE]:EXTernal[:SOURCE]?
```

This command selects which PATTERN TRIG IN connection the ESG uses to accept an externally applied trigger signal when external is the trigger source selection.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURCE]” on page 937. For more information on the rear-panel connectors, see the *E4428C/38C ESG Signal Generators User’s Guide*.

The following list describes the command choices:

- EPT1 This choice is synonymous with EPTRIGGER1 and selects the PATTERN TRIG IN rear-panel connector.
 - EPT2 This choice is synonymous with EPTRIGGER2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector.
 - EPTRIGGER1 This choice is synonymous with EPT1 and selects the PATTERN TRIG IN rear-panel connector.
 - EPTRIGGER2 This choice is synonymous with EPT2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector.
 - *RST** EPT1
- Key Entry** **Patt Trig In 1** **Patt Trig In 2**

[:STATe]

Supported E4438C with Option 402

```
[:SOURCE]:RADio:PDC[:STATe] ON|OFF|1|0[:SOURCE]:RADio:PDC[:STATe]?
```

This command enables or disables the PDC modulation format.

***RST** OFF

Key Entry **PDC Off On**

Remarks Although the PDC modulation is enabled with this command, the RF carrier is not modulated unless you also activate the front panel **Mod On/Off** hardkey.

PHS Subsystem–Option 402 ([:SOURce]:RADio:PHS)

:ALPha

Supported E4438C with Option 402

[:SOURce]:RADio:PHS:ALPha <val>

[:SOURce]:RADio:PHS:ALPha?

This command changes the Nyquist or root Nyquist filter’s alpha value.

The filter alpha value can be set to the minimum level (0), the maximum level (1), or in between by using fractional numeric values (0.001–0.999).

***RST** +5.00000000E–001

Range 0.000–1.000

Key Entry **Filter Alpha**

Remarks To change the current filter type, refer to “:FILTer” on page 959.

:BBCLock

Supported E4438C with Option 402

[:SOURce]:RADio:PHS:BBCLock INT[1] |EXT[1]

[:SOURce]:RADio:PHS:BBCLock?

This command toggles the data (bit) clock input to the baseband generator board to either internal or external. This command is independent in each mode and works for both non-burst (continuous) and burst modes. This allows for a matrix of selections between burst/non-burst, internal/external data generation, internal/external data clock, and external bit/symbol data clock.

INT[1] This choice selects the signal generator internal data clock.

EXT[1] This choice selects an external data clock input.

***RST** INT

Key Entry **BBG Data Clock Ext Int**

Remarks A data clock or continuous symbol sync input must be supplied when external mode is used.

:BBT

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:BBT <val>  
[ :SOURCE ] :RADio:PHS:BBT?
```

This command changes the bandwidth-multiplied-by-bit-time (BbT) filter parameter.

The filter BbT value can be set to the maximum level (1) or in between the minimum level (0.100) and maximum level by using fractional numeric values (0.101–0.999).

***RST** +5.00000000E–001

Range 0.100–1.000

Key Entry **Filter BbT**

Remarks This command is effective only after choosing a Gaussian filter. It does not have an effect on other types of filters.

To change the current filter type, refer to “:FILTer” on page 959.

:BRATe

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:BRATe <val>  
[ :SOURCE ] :RADio:PHS:BRATe?
```

This command sets the bit rate in bits per second (bps–Mbps). The maximum bit rate is dependent on the modulation type and filter as shown in the following tables

The IQ digital data stream is shaped by a FIR filter. The filter length and associated latency and frequency response are dependent on the bit rate as shown in the following tables. The signal generator selects a filter length.

For higher bit rates, the FIR filter length may be truncated (if the minimum filter size allows it) which will impact the relative timing of the modulated data, as well as the actual filter response (see the symbol rate command “:SRATe” on page 965). Refer to “:FILTer” on page 959 for information on filter symbol widths.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 962.

When the bit rate is changed, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the bit rate: lower bit rates require more time.

***RST** +3.8400000E+005

Range	Modulation Type	Bit Rate Range		
		16 Symbol Wide Filter	32 Symbol Wide Filter	64 Symbol Wide Filter
	BPSK, FSK2, MSK	1bps–50Mbps	1bps–25Mbps	1bps–12.5Mbps
	C4FM, OQPSK, FSK4	2bps–50Mbps	2bps–25Mbps	2bps–12.5Mbps
	OQPSKI95, QPSK			
	P4QPPSK, QPSKIS95			
	GRAYQPSK, QAM4			
	D8PSK, EDGE, FSK8, PSK8	3bps–50Mbps	3bps–25Mbps	3bps–12.5Mbps
	FSK16, PSK16, QAM16	4bps–50Mbps	4bps–25Mbps	4bps–12.5Mbps
	QAM32	5bps–50Mbps	5bps–25Mbps	5bps–12.5Mbps
	QAM64	6bps–50Mbps	6bps–25Mbps	6bps–12.5Mbps
	QAM128	7bps–50Mbps	7bps–25Mbps	7bps–12.5Mbps
	QAM256	8bps–50Mbps	8bps–25Mbps	8bps–12.5Mbps

Key Entry **Symbol Rate**

:BURSt:PN9

Supported E4438C with Option 402

[:SOURCE] :RADio:PHS: BURSt:PN9 NORMal | QUICk
 [:SOURCE] :RADio:PHS: BURSt:PN9?

This command controls the software PN9 generation.

NORMal This choice produces a maximum length PN9 sequence.

QUICk This choice produces a truncated PN9 sequence.

***RST** NORM

Key Entry **PN9 Mode Normal Quick**

Remarks Use Normal mode for bit-error-rate tests where a maximum length PN9 sequence is required.

:BURSt:SCRamble:SEED

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:BURSt:SCRamble:SEED <16-bit val>  
[ :SOURce ] :RADio:PHS:BURSt:SCRamble:SEED?
```

This command select a 16-bit scramble seed value for scrambling.

***RST** #H3FF

Range #H0–#H3FF

Key Entry **Scramble Seed**

Remarks Although values may be set using this command, it does not active that scramble function.

To enable the scrambling function, refer to “:BURSt:SCRamble[:STATe]” on [page 944](#).

:BURSt:SCRamble[:STATe]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:BURSt:SCRamble [ :STATe ] ON | OFF | 1 | 0  
[ :SOURce ] :RADio:PHS:BURSt:SCRamble [ :STATe ] ?
```

This command enables or disables the operating state of the scramble function.

ON (1) This choice scrambles data on the related fields, using the seed setting.

OFF (0) This choice disables the scramble function.

***RST** 0

Key Entry **Scramble Off On**

Remarks To set the seed setting, refer to “:BURSt:SCRamble:SEED” on [page 944](#).

:BURSt:SHAPe:FALL:DELay

Supported E4438C with Option 402

[:SOURce] :RADio:PHS: BURSt :SHAPe :FALL :DELay <val>

[:SOURce] :RADio:PHS: BURSt :SHAPe :FALL :DELay?

This command sets the burst shape fall delay.

The variable <val> is expressed in bits.

***RST** +0.00000000E+000

Range -22.1250 to 99

Key Entry **Fall Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 962. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FDELay” on page 946 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:FALL:TIME

Supported E4438C with Option 402

[:SOURce] :RADio:PHS: BURSt :SHAPe :FALL :TIME <val>

[:SOURce] :RADio:PHS: BURSt :SHAPe :FALL :TIME?

This command sets the burst shape fall time.

The variable <val> is expressed in bits.

***RST** +4.00000000E+001

Range 0.1250–255.8750

Key Entry **Fall Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 962. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FTIME” on page 947 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:FDElay

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:BURSt:SHAPe:FDElay <val>  
[ :SOURce ] :RADio:PHS:BURSt:SHAPe:FDElay?
```

This command sets the burst shape fall delay.

The variable <val> is expressed in bits.

***RST** +0.00000000E+000

Range –22.1250 to 99

Key Entry **Fall Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 962. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FALL:DElay” on page 945 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:FTIME

Supported E4438C with Option 402

[:SOURce] :RADio:PHS: BURSt:SHAPe:FTIME <val>

[:SOURce] :RADio:PHS: BURSt:SHAPe:FTIME?

This command sets the burst shape fall time.

The variable <val> is expressed in bits.

***RST** +4.00000000E+001

Range 0.1250–255.8750

Key Entry **Fall Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 962. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FALL:TIME” on page 945 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RDELay

Supported E4438C with Option 402

[:SOURce] :RADio:PHS: BURSt:SHAPe:RDELay <val>

[:SOURce] :RADio:PHS: BURSt:SHAPe:RDELay?

This command sets the burst shape rise delay.

The variable <val> is expressed in bits.

***RST** +0.00000000E+000

Range –18.1250 to 99

Key Entry **Rise Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 962. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:RISE:DELay” on page 948 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RISE:DELay

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:BURSt:SHAPe:RISE:DELay <val>  
[ :SOURce ] :RADio:PHS:BURSt:SHAPe:RISE:DELay?
```

This command sets the burst shape rise delay.

The variable <val> is expressed in bits.

***RST** +0.00000000E+000

Range –18.1250 to 99

Key Entry **Rise Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 962. Refer to “:SRATE” on page 965 for minimum and maximum symbol rate values.

“:BURSt:SHAPe:RDELay” on page 947 performs the same function; in compliance with the SCPI standard, both commands are listed.

See the *E4428C/38C ESG Signal Generators User’s Guide* for concept information.

:BURSt:SHAPe:RISE:TIME

Supported E4438C with Option 402

[:SOURce] :RADio:PHS:BURSt:SHAPe:RISE:TIME <val>

[:SOURce] :RADio:PHS:BURSt:SHAPe:RISE:TIME?

This command sets the burst shape rise time. The variable <val> is expressed in bits.

***RST** +4.00000000E+001

Range 0.1250–22.500

Key Entry **Rise Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to [“:MODulation\[:TYPE\]” on page 962](#). Refer to [“:SRATe” on page 965](#) for a list of the minimum and maximum symbol rate values. The command [“:BURSt:SHAPe:RTIME” on page 949](#) performs the same function. See the *E4428C/38C ESG Signal Generators User’s Guide* for more information.

:BURSt:SHAPe:RTIME

Supported E4438C with Option 402

[:SOURce] :RADio:PHS:BURSt:SHAPe:RTIME <val>

[:SOURce] :RADio:PHS:BURSt:SHAPe:RTIME?

This command sets the burst shape rise time. The variable <val> is expressed in bits.

***RST** +4.00000000E+001

Range 0.1250–22.500

Key Entry **Rise Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to [“:MODulation\[:TYPE\]” on page 962](#). Refer to [“:SRATe” on page 965](#) for a list of the minimum and maximum symbol rate values.

[“:BURSt:SHAPe:RISE:TIME” on page 949](#) performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal*

Generators User's Guide.

:BURSt:SHAPe[:TYPE]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:BURSt:SHAPe[:TYPE] SINE| "<file name>"  
[ :SOURce ] :RADio:PHS:BURSt:SHAPe[:TYPE] ?
```

This command specifies the burst shape as either SINE or a user-defined file ("<file name>").

SINE This choice selects a state that is defined by the burst rise and fall *RST values, as the default burst shape type.

"<file name>" This choice selects a user designated file from signal generator memory (non-volatile).

***RST** SINE

Key Entry **Sine User File**

:BURSt[:STATe]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:BURSt[:STATe] ON|OFF|1|0  
[ :SOURce ] :RADio:PHS:BURSt[:STATe] ?
```

This command enables or disables the burst function.

ON (1) This choice enables the transmission of framed data. If all timeslots which are switched on are up traffic channels or custom, you will be bursting the timeslots that are on; there will be no RF carrier during the off timeslots.

If you have switched on any timeslot that you have configured as a down traffic channel, the RF carrier is not switched off between any of the timeslots. The off timeslots are transmitted as a continuous series of ones for the time period of the off timeslots.

OFF (0) This choice enables the transmission of unframed data.

***RST** 0

Key Entry **Data Format Pattern Framed**

:CHANnel

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:CHANnel EVM|ACP
[ :SOURCE ] :RADio:PHS:CHANnel?
```

This command optimizes the Nyquist and root Nyquist filters to minimize error vector magnitude (EVM) or to minimize adjacent channel power (ACP).

EVM This choice provides the most ideal passband.

ACP This choice improves stopband rejection.

***RST** EVM

Key Entry **Optimize FIR For EVM ACP**

Remarks To change the current filter type, refer to [“:FILTer” on page 959](#).

:DATA

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:DATA PN9|PN11|PN15|PN20|PN23|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64|PRAM
[ :SOURCE ] :RADio:PHS:DATA?
```

This command sets the data pattern type (pseudo-random number sequence, 4-bit pattern, sequence of 1's and 0's, data from an external source, or a user file) for unframed data transmission.

***RST** PN23

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	Ext
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's	PRAM File		

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:DATA:PRAM

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:DATA:PRAM "<file_name>"
```

```
[ :SOURCE ] :RADio:PHS:DATA:PRAM?
```

This command selects a pattern RAM (PRAM) file as the pattern data type for the PHS (Personal Handy-phone System) format.

"<file_name>" This variable designates the PRAM file in WFM1. Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

Key Entry **PRAM File**

Remarks Selecting this data source forces the burst source to INTERNAL to allow framing control.

The PRAM file must reside in the signal generator’s volatile memory (WFM1) in order to be accessed by this command. For more information on PRAM files, refer to [“:DATA:PRAM:FILE:BLOCK” on page 112](#).

:DATA:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:DATA:FIX4 <val>
```

```
[ :SOURCE ] :RADio:PHS:DATA:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern for unframed transmission according to the protocols (modulation type, symbol rate, filter, and burst shape) selected for the PHS format.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:DEfault

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:DEfault
```

This command returns all of the PHS modulation format parameters to factory settings. It does not affect any other signal generator parameters.

Key Entry **Restore PHS Factory Default**

:DLINK:SLOT[1] | 2 | 3 | 4:CUSTom

Supported E4438C with Option 402

```
[:SOURce]:RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:CUSTom PN9 | PN11 | PN15 |
PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURce]:RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:CUSTom?
```

This command configures the data field for the selected downlink custom timeslot.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's				
	64 1's & 64 0's							

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:DLINK:SLOT[1] | 2 | 3 | 4:CUSTom:FIX4

Supported E4438C with Option 402

```
[:SOURce]:RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:CUSTom:FIX4 <val>
[:SOURce]:RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:CUSTom:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink custom timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:DLINK:SLOT[1] | 2 | 3 | 4:POWer

Supported E4438C with Option 402

```
[:SOURce]:RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:POWer MAIN | DELTA
[:SOURce]:RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:POWer?
```

This command toggles the RF output power level function for the selected timeslot.

MAIN This choice specifies RF output as the main power level.

Receiver Test Digital Commands (continued)
PHS Subsystem—Option 402 ([:SOURCE]:RADio:PHS)

DELTA This choice specifies RF output as the alternative power level.
*RST MAIN
Key Entry Timeslot Ampl Main Delta

:DLINK:SLOT[1] | 2 | 3 | 4:SCHannel:CSID

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :SCHannel:CSID <bit_pattern>  
[ :SOURCE ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :SCHannel:CSID?
```

This command changes the 42-bit cell station identification code (CSID) field of the selected downlink timeslot. The preset hexadecimal value (when normal preset is selected) for CSID reflects the PHS protocol, however you can enter a new value with this command.

*RST #H20200020001
Range #H0–#H3FFFFFFFFF
Key Entry CSID

:DLINK:SLOT[1] | 2 | 3 | 4:SCHannel:IDLE

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :SCHannel:IDLE <bit_pattern>  
[ :SOURCE ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :SCHannel:IDLE?
```

This command changes the 34-bit idle (IDLE) field of the selected downlink timeslot. The preset hexadecimal value (when normal preset is selected) for IDLE reflects the PHS protocol, however you can enter a new value with this command.

*RST #H000000000
Range #H0–#H3FFFFFFFFF
Key Entry IDLE

:DLINK:SLOT[1] | 2 | 3 | 4:SCHannel:PSID

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :SCHannel:PSID <bit_pattern>  
[ :SOURCE ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :SCHannel:PSID?
```

This command changes the 28-bit personal station identification code (PSID) field in the synchronization channel of the selected downlink timeslot. The normal preset hexadecimal value for PSID reflects the PHS protocol, however you can enter a new value with this command.

***RST** #H0000001
Range #H0–#H3FFFFFFF
Key Entry **PSID**

:DLINK:SLOT[1] | 2 | 3 | 4:SCHannel:UWORD

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :SCHannel:UWORD <bit_pattern>  
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :SCHannel:UWORD?
```

This command changes the unique word (UW) field of the selected downlink timeslot. The preset hexadecimal value (when normal preset is selected) for UW reflects the PHS protocol, however you can enter a new value with this command.

***RST** #H50EF2993
Range #H0–#HFFFFFFF
Key Entry **UW**

:DLINK:SLOT[1] | 2 | 3 | 4:STATe

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :STATe ON|OFF|1|0  
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :STATe?
```

This command enables or disables the operating state of the selected downlink timeslot.

***RST** Timeslot 1: 1 *Timeslots 2–4: 0*
Key Entry **Timeslot Off On**

:DLINK:SLOT[1] | 2 | 3 | 4:TCHannel:SACChannel

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :TCHannel:SACChannel  
<bit_pattern>  
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 :TCHannel:SACChannel?
```

This command changes the 15-bit slow associated control channel of the selected downlink timeslot. The preset hexadecimal value (when normal preset is selected) for SACCH reflects the value specified by the standard.

***RST** #H8000
Range #H0–#HFFFF

Key Entry SA

:DLINK:SLOT[1] | 2 | 3 | 4:TCHannel:UWORD

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:TCHannel:UWORD <bit_pattern>
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:TCHannel:UWORD?
```

This command changes the unique word (UW) field of the selected downlink timeslot. The preset hexadecimal value (when normal preset is selected) for UW reflects the PHS protocol, however you can enter a new value with this command.

***RST** #H3D4C

Range #H0–#HFFFF

Key Entry UW

:DLINK:SLOT[1] | 2 | 3 | 4:TCHannel[:TCHannel]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:TCHannel
[:TCHannel] PN9 | PN11 | PN15 | PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 |
P64
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:TCHannel [:TCHannel] ?
```

This command customizes the selected downlink traffic channel timeslot.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's			

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:DLINK:SLOT[1] | 2 | 3 | 4:TCHannel[:TCHannel]:FIX4

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:TCHannel [:TCHannel] :FIX4 <val>
[ :SOURce ] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4:TCHannel [:TCHannel] :FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink traffic channel timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type. To change the data type, refer to “**:DLINK:SLOT[1]|2|3|4:TCHannel[:TCHannel]**” on page 956.

:DLINK:SLOT[1]|2|3|4[:TYPE]

Supported E4438C with Option 402

[:SOURCE] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 [:TYPE] CUSTom | TCH | TCH_ALL | SYNC
 [:SOURCE] :RADio:PHS:DLINK:SLOT [1] | 2 | 3 | 4 [:TYPE] ?

This command sets the downlink timeslot type for the selected timeslot.

***RST** Timeslot 1: TCH Timeslots 2–4: CUST

Key Entry **Custom TCH TCH All SYNC**

:EDATa:DElay

Supported E4438C with Option 402

[:SOURCE] :RADio:PHS:EDATa:DElay?

This query returns the amount of delay (in symbols) from the external data input to the beginning of the symbol on the I OUT and Q OUT rear panel connectors and the front panel RF OUTPUT connector.

Remarks When the format is turned off, the delay value is unchanged; the query will return the same delay value if the format is on or off.

:EDCLock

Supported E4438C with Option 402

[:SOURCE] :RADio:PHS:EDCLock SYMBol | NORMal
 [:SOURCE] :RADio:PHS:EDCLock?

This command sets the external data clock use.

SYMBol This choice specifies that a continuous symbol clock signal must be provided to the SYMBOL SYNC input connector.

NORMal This choice specifies that the DATA CLOCK input connector requires a bit clock. The SYMBOL SYNC input connector requires a (one-shot or continuous) symbol sync signal.

Receiver Test Digital Commands (continued)
PHS Subsystem—Option 402 ([:SOURce]:RADio:PHS)

*RST	NORM
Key Entry	Ext Data Clock Normal Symbol
Remarks	Both choices have no effect in internal clock mode. Refer to “:BBCLock” on page 941 to select EXT as the data clock type.

:EREFerence

Supported	E4438C with Option 402
	<code>[:SOURce]:RADio:PHS:EREFerence INT EXT</code>
	<code>[:SOURce]:RADio:PHS:EREFerence?</code>

This command selects either an internal or external bit-clock reference for the data generator.

*RST	INT
Key Entry	BBG Ref Ext Int
Remarks	If the EXT choice is selected, the external source’s frequency value must be applied to the BASEBAND GEN REF IN rear panel connector. The external reference and external data clock are not applicable at the same time. If both are selected, then the external reference takes precedence. Refer to, “:EREFerence:VALue” on page 958 to enter the external reference frequency setting.

:EREFerence:VALue

Supported	E4438C with Option 402
	<code>[:SOURce]:RADio:PHS:EREFerence:VALue <val></code>
	<code>[:SOURce]:RADio:PHS:EREFerence:VALue?</code>

This command sets the expected bit-clock reference frequency value for an externally applied reference signal.

The variable <val> is expressed in units of hertz (Hz–MHz).

*RST	+1.30000000E+007
Range	2.5E5–1E8

Key Entry **Ext BBG Ref Freq**

Remarks The value specified by this command is effective only when you are using an external reference applied to the BASEBAND GEN REF IN rear panel connector.

Refer to “[EREFerence](#)” on page 958 to select EXT (external source) as the reference for the bit-clock.

:FILTer

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:PHS:FILTer RNYQuist|NYQuist|GAUSSian|RECTangle|
IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|"<user FIR>"
[:SOURCE]:RADIO:PHS:FILTer?
```

This command selects the pre-modulation filter type.

- IS95 This choice selects a filter that meets the criteria of the IS-95 standard.
- IS95_EQ This choice selects a filter which is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard. This filter is only used for IS-95 baseband filtering.
- IS95_MOD This choice selects a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.
- IS95_MOD_EQ This choice selects a filter which is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.
- AC4Fm This choice selects a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.
- UGGaussian This choice selects a backwards compatible GSM Gaussian filter (Gaussian filter with a fixed BbT value of 0.300) for the ESG E44xxB Option UN3 or UN4.
- "<user FIR>" This variable is any filter file that you have stored into memory.

***RST** RNYQ

Key Entry	Root Nyquist	Nyquist	Gaussian	Rectangle	IS-95	IS-95 w/EQ
	IS-95 Mod	IS-95 Mod w/EQ	APCO 25 C4FM	UN3/4 GSM Gaussian		
	User FIR					

Remarks Refer to “[File Name Variables](#)” on page 13 for information on the file name syntax.

:IQ:SCALe

Supported E4438C with Option 402

[:SOURce] :RADio:PHS:IQ:SCALe <val>

[:SOURce] :RADio:PHS:IQ:SCALe?

This command sets the amplitude of the I/Q outputs for better adjacent channel power (ACP); lower scaling values equate to better ACP.

The variable <val> is expressed in units of percent.

***RST** +100

Range 1–200

Key Entry I/Q Scaling

Remarks This command has no effect with MSK or FSK modulation.

:MODulation:FSK[:DEVIation]

Supported E4438C with Option 402

[:SOURce] :RADio:PHS:MODulation:FSK[:DEVIation] <val>

[:SOURce] :RADio:PHS:MODulation:FSK[:DEVIation]?

This command sets the symmetric FSK frequency deviation value.

The variable <val> is expressed in units of Hertz and the maximum range value equals the current symbol rate value multiplied by four, limited to 20 MHz.

***RST** +4.00000000E+002

Range 0–2E7

Key Entry Freq Dev

Remarks To change the modulation type, refer to “:MODulation[:TYPE]” on page 962.

Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

To set an asymmetric FSK deviation value, refer to the *E4428C/38C ESG Signal Generators User’s Guide* for more information.

:MODulation:MSK[:PHASe]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:MODulation:MSK[:PHASe] <val>
```

```
[ :SOURce ] :RADio:PHS:MODulation:MSK[:PHASe] ?
```

This command sets the MSK phase deviation value. The variable <val> is in units of degrees.

***RST** +9.00000000E+001

Range 0–100

Key Entry **Phase Dev**

:MODulation:UFSK

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:MODulation:UFSK "<file name>"
```

```
[ :SOURce ] :RADio:PHS:MODulation:UFSK?
```

This command selects a user-defined FSK file from the signal generator memory.

Key Entry **User FSK**

Remarks The user-defined FSK file is held in signal generator memory until the command that selects user FSK as the modulation type is sent. Refer to [“:MODulation\[:TYPE\]” on page 962](#) to change the current modulation type.

Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:MODulation:UIQ

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:MODulation:UIQ "<file name>"
```

```
[ :SOURce ] :RADio:PHS:MODulation:UIQ?
```

This command selects a user-defined I/Q file from the signal generator memory.

Key Entry **User I/Q**

Remarks The user-defined I/Q file is held in signal generator memory until the command that selects user I/Q as the modulation type is sent. Refer to [“:MODulation\[:TYPE\]” on page 962](#) to change the current modulation type.

Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:MODulation[:TYPE]

Supported E4438C with Option 402

```
[:SOURCE]:RADio:PHS:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|
GRAYQPSK|OQPSK|IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|
FSK8|FSK16|C4FM|QAM4|QAM16|QAM32|QAM64|QAM128|QAM256|UIQ|UFSK
[:SOURCE]:RADio:PHS:MODulation[:TYPE] ?
```

This command sets the modulation type for the PHS personality.

***RST** P4DQPSK

Key Entry	BPSK	QPSK	IS-95 QPSK	Gray Coded QPSK	OQPSK			
	IS-95 OQPSK	$\pi/4$ DQPSK	8PSK	16PSK	D8PSK	MSK	2-Lvl FSK	
	4-Lvl FSK	8-Lvl FSK	16-Lvl FSK	C4FM	4QAM	16QAM	32QAM	
	64QAM	128QAM	256QAM	User I/Q	User FSK			

:POLarity[:ALL]

Supported E4438C with Option 402

```
[:SOURCE]:RADio:PHS:POLarity[:ALL] NORMal|INVerted
[:SOURCE]:RADio:PHS:POLarity[:ALL] ?
```

This command sets the rotation direction of the phase modulation vector.

NORMal This choice selects normal phase polarity.

INVerted This choice inverts the internal Q signal.

***RST** NORM

Key Entry **Phase Polarity Normal Invert**

:SECondary:RECall

Supported E4438C with Option 402

```
[:SOURCE]:RADio:PHS:SECondary:RECall
```

This command recalls the secondary frame configuration, overwriting the current state.

Key Entry **Recall Secondary Frame State**

Remarks To save a secondary frame state, refer to “:SECondary:SAVE” on page 963.

A secondary frame is not active until the secondary state is enabled. To activate a secondary frame, refer to “:SECondary[:STATE]” on page 963.

:SECondary:SAVE

Supported E4438C with Option 402

`[:SOURCE]:RADio:PHS:SECondary:SAVE`

This command saves the current frame configuration as the secondary frame with the filename `PHS_SECONDARY_FRAME`.

Key Entry **Save Secondary Frame State**

Remarks To recall the secondary frame (saved in non-volatile signal generator memory), refer to “[:SECondary:RECall](#)” on page 962.

:SECondary:TRIGger[:SOURCE]

Supported E4438C with Option 402

`[:SOURCE]:RADio:PHS:SECondary:TRIGger[:SOURCE] KEY|EXT|BUS`
`[:SOURCE]:RADio:PHS:SECondary:TRIGger[:SOURCE]?`

This command selects the type of triggering for the secondary frame.

KEY This choice enables triggering by pressing the front panel **Trigger** hardkey.

EXT This choice enables triggering using an externally applied signal at the PATT TRIG IN rear panel connector or the PATT TRIG IN 2 pin on the rear panel AUX I/O connector. To select the appropriate connector, refer to “[:TRIGger\[:SOURCE\]:EXTernal\[:SOURCE\]](#)” on page 969.

BUS This choice enables GPIB triggering using the *TRG or GET command or LAN and RS-232 triggering using the *TRG command.

Key Entry **Trigger Key Ext Bus**

:SECondary[:STATE]

Supported E4438C with Option 402

`[:SOURCE]:RADio:PHS:SECondary[:STATE] ON|OFF|1|0`
`[:SOURCE]:RADio:PHS:SECondary[:STATE]?`

This command enables or disables the ability to switch to the secondary frame.

***RST** 0

Key Entry **Secondary Frame Off On**

Receiver Test Digital Commands (continued)
PHS Subsystem—Option 402 ([:SOURce]:RADio:PHS)

Remarks A frame must already be saved as the secondary frame in order to turn the secondary state function on.
To save a frame as the secondary frame, refer to “:SECOndary:SAVE” on page 963.

:SOUT

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:SOUT FRAME | SLOT | ALL  
[ :SOURce ] :RADio:PHS:SOUT?
```

This command sets the synchronization location (within the pattern of data) and the type of output at the EVENT 1 rear panel connector.

FRAME This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a framed data pattern.

SLOT This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a selected timeslot.

ALL This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for all active timeslots.

***RST** FRAME

Choices FRAME SLOT ALL

:SOUT:OFFSet

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:SOUT:OFFSet <val>  
[ :SOURce ] :RADio:PHS:SOUT:OFFSet?
```

This command sets the offset value for the location of the output synchronization signal on the EVENT1 rear panel connector relative to the beginning of the framed data pattern or timeslot.

The variable <val> is expressed as a number of bits.

***RST** +0

Range -239 to 239

Key Entry **Sync Out Offset**

Remarks Negative values move the synchronization output signal earlier; positive values move it later.

To change the output of the EVENT1 rear panel connector to SLOT, refer to “:SOUT” on page 964.

:SOUT:SLOT

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:SOUT:SLOT <val>  
[ :SOURce ] :RADio:PHS:SOUT:SLOT?
```

This command selects the timeslot that will trigger a 1-bit output signal at the EVENT 1 rear panel connector.

***RST** +0

Range 1–4

Key Entry **Begin Timeslot #**

Remarks To change the output of the EVENT1 rear panel connector to SLOT, refer to “:SOUT” on page 964.

:SRATe

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:SRATe <val>  
[ :SOURce ] :RADio:PHS:SRATe?
```

This command sets the transmission symbol rate. Symbol rate is the bit rate divided by the bits per symbol. A change in the symbol rate affects the bit rate. Refer to “:BRATe” on page 875 for information on bit rate.

The variable <val> is expressed in units of symbols per second (sps–Mps) and the maximum symbol rate depends on the filter. Refer to “:FILTer” on page 959 for minimum filter symbol width.

The filter may have to be truncated down to 32 or 16 symbols wide to achieve the highest symbol rate. The signal generator’s internal filters are not truncated below their minimum filter length and user-defined FIR filters are not truncated. If the filter cannot be truncated then the symbol rate is limited to the maximum rate of the narrowest filter size possible.

The relative timing of the modulated data, as well as the actual filter response is affected when the filter is truncated.

When the symbol rate changes, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the symbol rate: lower symbol rates require more time.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 962.

Receiver Test Digital Commands (continued)
PHS Subsystem–Option 402 ([:SOURce]:RADio:PHS)

*RST +1.92000000E+004

Range	Modulation Type	Symbol Rate Range		
		16 Symbol Wide Filter	32 Symbol Wide Filter	64 Symbol Wide Filter
	BPSK, FSK2, MSK	1sps–50Msps	1sps–25Msps	1sps–12.5Msps
	C4FM, OQPSK, FSK4	2sps–25Msps	2sps–12.5Msps	2sps–6.25Msps
	OQPSKI95, QPSK			
	P4QPPSK, QPSKI95			
	GRAYQPSK, QAM4			
	D8PSK, EDGE, FSK8, PSK8	3sps–16.6666666666 Msps	3sps–8.3333333333 Msps	3sps–4.1666666666 Msps
	FSK16, PSK16, QAM16	4sps–12.5Msps	4sps–6.25Msps	4sps–3.125Msps
	QAM32	5sps–10Msps	5sps–5Msps	5sps–2.5Msps
	QAM64	6sps–8.3333333333 Msps	6sps–4.1666666666 Msps	6sps–2.0833333333 Msps
	QAM128	7sps–7.142857142 Msps	7sps–3.571428572 Msps	7sps–1.785714285 Msps
	QAM256	8sps–6.25Msps	8sps–3.125 Msps	8sps–1.5625 Msps

NOTE Using I/Q skew will half the minimum number of symbols for the selected filter.

Key Entry **Symbol Rate**

:TRIGger:TYPE

Supported E4438C with Option 402

[:SOURce] :RADio:PHS:TRIGger:TYPE CONTInuous | SINGle | GATE
 [:SOURce] :RADio:PHS:TRIGger:TYPE?

This command sets the trigger type.

CONTInuous The framed data sequence repeats continuously; the sequence restarts every time the previous playback is completed. To customize continuous triggering, refer to “:TRIGger:TYPE:CONTInuous[:TYPE]” on page 967.

SINGle The framed data sequence plays once for every trigger received.

GATE An external trigger signal interrupts the playback while the gating signal is in the inactive state. Playback resumes when the external control signal returns to the active state. The active state can be set to high or low.

***RST** **CONT**

Key Entry **Continuous** **Single** **Gated**

:TRIGger:TYPE:CONTInuous[:TYPE]

Supported E4438C with Option 402

[:SOURce] :RADio:PHS:TRIGger:TYPE:CONTInuous[:TYPE] FREE | TRIGger | RESet
 [:SOURce] :RADio:PHS:TRIGger:TYPE:CONTInuous[:TYPE] ?

This commands selects the waveform’s response to a trigger signal while using the continuous trigger mode.

For more information on triggering and to select the continuous trigger mode, see “:TRIGger:TYPE” on page 966.

The following list describes the waveform’s response to each of the command choices:

FREE Turning the ARB format on immediately triggers the waveform. The waveform repeats until you turn the format off, select another trigger, or choose another waveform file.

TRIGger The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously until you turn the format off, select another trigger, or choose another waveform file.

RESet The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously. Subsequent triggers reset the waveform to the beginning. For a waveform sequence, this means to the beginning of the first segment in the sequence.

***RST** **FREE**

Key Entry **Free Run** **Trigger & Run** **Reset & Run**

:TRIGger:TYPE:GATE:ACTive

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:TRIGger:TYPE:GATE:ACTive LOW|HIGH  
[ :SOURCE ] :RADio:PHS:TRIGger:TYPE:GATE:ACTive?
```

This command selects the active state (gate polarity) of the gate while using the gating trigger mode.

The LOW and HIGH selections correspond to the low and high states of an external trigger signal. For example, when you select HIGH, the active state occurs during the high of the trigger signal. When the active state occurs, the ESG stops the waveform playback at the last played sample point, then restarts the playback at the next sample point when the inactive state occurs. For more information on triggering and to select gating as the trigger mode, see “:TRIGger:TYPE” on page 966.

The following list describes the ESG’s gating behavior for the polarity selections:

LOW The waveform playback stops when the trigger signal goes low (active state) and restarts when the trigger signal goes high (inactive state).

HIGH The waveform playback stops when the trigger signal goes high (active state) and restarts when the trigger signal goes low (inactive state).

*RST HIGH

Key Entry Gate Active Low High

:TRIGger[:SOURCE]:EXTErnal:DELAy

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:TRIGger[:SOURCE]:EXTErnal:DELAy <val>  
[ :SOURCE ] :RADio:PHS:TRIGger[:SOURCE]:EXTErnal:DELAy?
```

This command sets the number of bits to delay the ESG’s response to an external trigger.

The bit delay is a delay between when the ESG receives the trigger and when it responds to the trigger. The delay uses the clocks of the bit-clock to time the delay. After the ESG receives the trigger and the set number of delay bits (clocks) occurs, the ESG transmits the data pattern.

The delay occurs after you enable the state. See “:TRIGger[:SOURCE]:EXTErnal:DELAy:STATE” on page 969. You can set the number of bits either before or after enabling the state.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURCE]” on page 970.

*RST +0

Range 0–1048575

Key Entry Ext Delay Bits

:TRIGger[:SOURce]:EXTErnal:DELAy:STATe

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:TRIGger [ :SOURce ] :EXTErnal:DELAy:STATe ON|OFF|1|0  
[ :SOURce ] :RADio:PHS:TRIGger [ :SOURce ] :EXTErnal:DELAy:STATe?
```

This command enables or disables the operating state of the external trigger delay function.

For setting the delay time, see “:TRIGger[:SOURce]:EXTErnal:DELAy” on page 968, and for more information on configuring an external source, see “:TRIGger[:SOURce]” on page 970.

***RST** 0

Key Entry Ext Delay Off On

:TRIGger[:SOURce]:EXTErnal:SLOPe

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:TRIGger [ :SOURce ] :EXTErnal:SLOPe POSitive|NEGative  
[ :SOURce ] :RADio:PHS:TRIGger [ :SOURce ] :EXTErnal:SLOPe?
```

This command sets the polarity for an external trigger signal while using the continuous, single triggering mode. To set the polarity for gating, see “:TRIGger:TYPE:GATE:ACTive” on page 968.

The POSitive and NEGative selections correspond to the high (positive) and low (negative) states of the external trigger signal. For example, when you select POSitive, the waveform responds (plays) during the high state of the trigger signal. When the ESG receives multiple trigger occurrences when only one is required, the signal generator uses the first trigger and ignores the rest.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURce]” on page 970.

***RST** NEG

Key Entry Ext Polarity Neg Pos

:TRIGger[:SOURce]:EXTErnal[:SOURce]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:TRIGger [ :SOURce ] :EXTErnal [ :SOURce ] EPT1 |  
EPT2 | EPTRIGGER1 | EPTRIGGER2  
[ :SOURce ] :RADio:PHS:TRIGger [ :SOURce ] :EXTErnal [ :SOURce ] ?
```

This command selects which PATTERN TRIG IN connection the ESG uses to accept an externally applied trigger signal when external is the trigger source selection.

For more information on configuring an external trigger source and to select external as the trigger source, see “:TRIGger[:SOURce]” on page 970. For more information on the rear-panel connectors, see the *E4428C/38C ESG Signal Generators User’s Guide*.

The following list describes the command choices:

EPT1	This choice is synonymous with EPTRIGGER1 and selects the PATTERN TRIG IN rear-panel connector.
EPT2	This choice is synonymous with EPTRIGGER2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector.
EPTRIGGER1	This choice is synonymous with EPT1 and selects the PATTERN TRIG IN rear-panel connector.
EPTRIGGER2	This choice is synonymous with EPT2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector.
*RST	EPT1
Key Entry	Patt Trig In 1 Patt Trig In 2

:TRIGger[:SOURce]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:TRIGger [ :SOURce ] KEY | EXT | BUS  
[ :SOURce ] :RADio:PHS:TRIGger [ :SOURce ] ?
```

This command sets the trigger source.

For more information on triggering, see “:TRIGger:TYPE” on page 966. The following list describes the command choices:

KEY	This choice enables manual triggering by pressing the front-panel Trigger hardkey.
EXT	An externally applied signal triggers the waveform. This is the only choice that works with gating. The following conditions affect an external trigger: <ul style="list-style-type: none">• The input connector selected for the trigger signal. You have a choice between the rear-panel PATTERN TRIG IN connector or the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector. To make the connector selection, see “:TRIGger[:SOURce]:EXTernal[:SOURce]” on page 969.

For more information on the connectors and on connecting the cables, see the *E4428C/38C ESG Signal Generators User’s Guide*.

- The trigger signal polarity:
 - gating mode, see “:TRIGger:TYPE:GATE:ACTive” on page 968
 - continuous and single modes, see “:TRIGger[:SOURce]:EXTernal[:SOURce]” on page 969
- The time delay between when the ESG receives a trigger and when the waveform responds to the trigger. There are two parts to setting the delay:
 - setting the amount of delay, see “:TRIGger[:SOURce]:EXTernal:DELay” on page 968
 - turning the delay on, see “:TRIGger[:SOURce]:EXTernal:DELay:STATe” on page 969

BUS This choice enables triggering over the GPIB or LAN using the *TRG or GET commands or the AUXILIARY INTERFACE (RS-232) using the *TRG command.

***RST** KEY

Key Entry	Trigger Key	Ext	Bus
------------------	--------------------	------------	------------

:ULINK:SLOT[1] | 2 | 3 | 4:CUSTom

Supported E4438C with Option 402

```
[:SOURce]:RADio:PHS:ULINK:SLOT[1] | 2 | 3 | 4:CUSTom PN9 | PN11 | PN15 |
PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURce]:RADio:PHS:ULINK:SLOT[1] | 2 | 3 | 4:CUSTom?
```

This command configures the data field for the selected uplink custom timeslot.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's		8 1's & 8 0's		16 1's & 16 0's		32 1's & 32 0's	
	64 1's & 64 0's							

Remarks Refer to “File Name Variables” on page 13 for information on the file name syntax.

:ULINK:SLOT[1]|2|3|4:CUSTom:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :CUSTom:FIX4 <val>  
[ :SOURCE ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :CUSTom:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected uplink custom timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:ULINK:SLOT[1]|2|3|4:POWer

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :POWer MAIN|DELTA  
[ :SOURCE ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :POWer?
```

This command toggles the RF output power level function for the selected timeslot.

MAIN This choice specifies RF output as the main power level.

DELTA This choice specifies RF output as the alternative power level.

***RST** MAIN

Key Entry **Timeslot Ampl Main Delta**

:ULINK:SLOT[1]|2|3|4:SCHannel:CSID

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :SCHannel:CSID <bit_pattern>  
[ :SOURCE ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :SCHannel:CSID?
```

This command changes the 42-bit cell station identification code (CSID) field of the selected uplink timeslot. The preset hexadecimal value (when normal preset is selected) for CSID reflects the PHS protocol, however you can enter a new value with this command.

***RST** #H20200020001

Range #H0–#H3FFFFFFFFF

Key Entry **CSID**

:ULINK:SLOT[1] | 2 | 3 | 4:SCHannel:IDLE

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :SCHannel:IDLE <bit_pattern>  
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :SCHannel:IDLE?
```

This command changes the 34-bit idle (IDLE) field of the selected uplink timeslot. The preset hexadecimal value (when normal preset is selected) for IDLE reflects the PHS protocol, however you can enter a new value with this command.

***RST** #H00000000

Range #H0–#H3FFFFFFFF

Key Entry **IDLE**

:ULINK:SLOT[1] | 2 | 3 | 4:SCHannel:PSID

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :SCHannel:PSID <bit_pattern>  
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :SCHannel:PSID?
```

This command changes the 28-bit personal station identification code (PSID) field in the synchronization channel of the selected uplink timeslot. The preset (normal) hexadecimal value for PSID reflects the PHS protocol, however you can enter a new value with this command.

***RST** #H0000001

Range #H0–#H3FFFFFFFF

Key Entry **PSID**

:ULINK:SLOT[1] | 2 | 3 | 4:SCHannel:UWORD

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :SCHannel:UWORD <bit_pattern>  
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :SCHannel:UWORD?
```

This command changes the unique word (UW) field of the selected uplink timeslot. The preset hexadecimal value (when normal preset is selected) for UW reflects the PHS protocol, however you can enter a new value with this command.

***RST** #H050EF2993

Range #H0–#H0FFFFFFFF

Key Entry **UW**

:ULINK:SLOT[1] | 2 | 3 | 4:STATe

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :STATe ON | OFF | 1 | 0  
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :STATe?
```

This command enables or disables the operating state of the selected uplink timeslot.

***RST** Timeslot 1: 1 Timeslots 2–4: 0

Key Entry Timeslot Off On

:ULINK:SLOT[1] | 2 | 3 | 4:TCHannel:SACChannel

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :TCHannel:SACChannel  
<bit_pattern>  
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :TCHannel:SACChannel?
```

This command changes the 15-bit slow associated control channel of the selected uplink timeslot. The preset hexadecimal value (when normal preset is selected) for SACCH reflects the value specified by the standard.

***RST** #H8000

Range #H0–#HFFFF

Key Entry SA

:ULINK:SLOT[1] | 2 | 3 | 4:TCHannel:UWORD

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :TCHannel:UWORD <bit_pattern>  
[ :SOURce ] :RADio:PHS:ULINK:SLOT [1] | 2 | 3 | 4 :TCHannel:UWORD?
```

This command changes the unique word (UW) field of the selected uplink timeslot. The preset hexadecimal value (when normal preset is selected) for UW reflects the PHS protocol, however you can enter a new value with this command.

***RST** #H3D4C

Range #H0–#HFFFF

Key Entry UW

:ULINK:SLOT[1] | 2 | 3 | 4:TCHannel[:TCHannel]

Supported E4438C with Option 402

```
[:SOURce]:RADio:PHS:ULINK:SLOT[1] | 2 | 3 | 4:TCHannel
[:TCHannel] PN9|PN11|PN15|PN20|PN23|FIX4| "<file name>" |EXT|P4|P8|P16|P32|
P64
[:SOURce]:RADio:PHS:ULINK:SLOT[1] | 2 | 3 | 4:TCHannel[:TCHannel] ?
```

This command selects the data pattern for the selected uplink traffic channel timeslot.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's			

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:ULINK:SLOT[1] | 2 | 3 | 4:TCHannel[:TCHannel:FIX4]

Supported E4438C with Option 402

```
[:SOURce]:RADio:PHS:ULINK:SLOT[1] | 2 | 3 | 4:TCHannel[:TCHannel]:FIX4 <val>
[:SOURce]:RADio:PHS:ULINK:SLOT[1] | 2 | 3 | 4:TCHannel[:TCHannel]:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected uplink traffic channel timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:ULINK:SLOT[1] | 2 | 3 | 4[:TYPE]

Supported E4438C with Option 402

```
[:SOURce]:RADio:PHS:ULINK:SLOT[1] | 2 | 3 | 4[:TYPE] CUSTom|TCH|TCH_ALL|SYNC
[:SOURce]:RADio:PHS:ULINK:SLOT[1] | 2 | 3 | 4[:TYPE] ?
```

This command sets the uplink timeslot type for the selected uplink timeslot.

***RST** Timeslot 1: TCH Timeslots 2–4: CUST

Key Entry **Timeslot Type**

PHS Subsystem—Option 402 ([:SOURce]:RADio:PHS)

[:STATe]

Supported E4438C with Option 402

[:SOURce] :RADio:PHS [:STATe] ON|OFF|1|0

[:SOURce] :RADio:PHS [:STATe] ?

This command enables or disables the PHS modulation format.

***RST** 0

Key Entry **PHS Off On**

Remarks Although the PHS modulation is enabled with this command, the RF carrier is not modulated unless you also activate the front panel **Mod On/Off** hardkey.

TETRA Subsystem—Option 402 ([:SOURce]:RADio:TETRa)

:ALPha

Supported E4438C with Option 402

[:SOURce]:RADio:TETRa:ALPha <val>

[:SOURce]:RADio:TETRa:ALPha?

This command changes the Nyquist or root Nyquist filter's alpha value.

The filter alpha value can be set to a minimum level (0), a maximum level (1), or in between by using fractional numeric values (0.001–0.999).

***RST** +3.50000000E-001

Range 0.000–1.000

Key Entry **Filter Alpha**

Remarks To change the current filter type, refer to “:FILTer” on page 991.

:BBCLock

Supported E4438C with Option 402

[:SOURce]:RADio:TETRa:BBCLock INT [1] | EXT [1]

[:SOURce]:RADio:TETRa:BBCLock?

This command toggles the data (bit) clock input to the baseband generator board to either internal or external. This command is independent in each mode and works for both non-burst (continuous) and burst modes. This allows for a matrix of selections between burst/non-burst, internal/external data generation, internal/external data clock, and external bit/symbol data clock.

INT[1] This choice selects the signal generator internal data clock.

EXT[1] This choice selects an external data clock input.

***RST** INT

Key Entry **BBG Data Clock Ext Int**

Remarks A data clock or continuous symbol sync input must be supplied when external mode is used.

TETRA Subsystem—Option 402 ([:SOURCE]:RADIO:TETRA)**:BBT**

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:TETRA:BBT <val>
```

```
[ :SOURCE ] :RADIO:TETRA:BBT?
```

This command changes the bandwidth-multiplied-by-bit-time (BbT) filter parameter.

The filter BbT value can be set to the maximum level (1) or in between the minimum level (0.100) and maximum level by using fractional numeric values (0.101–0.999).

***RST** +5.00000000E–001

Range 0.100–1.000

Key Entry Filter BbT

Remarks This command is effective only after choosing a Gaussian filter. It does not have an effect on other types of filters.

To change the current filter type, refer to “:FILTER” on page 991.

:BRATe

Supported E4438C with Option 402

```
[ :SOURCE ] :RADIO:TETRA:BRATe <val>
```

```
[ :SOURCE ] :RADIO:TETRA:BRATe?
```

This command sets the bit rate in bits per second (bps–Mbps). The maximum bit rate is dependent on the modulation type and filter as shown in the following tables

The IQ digital data stream is shaped by a FIR filter. The filter length and associated latency and frequency response are dependent on the bit rate as shown in the following tables. The signal generator selects a filter length.

For higher bit rates, the FIR filter length may be truncated (if the minimum filter size allows it) which will impact the relative timing of the modulated data, as well as the actual filter response (see the symbol rate command “:SRATe” on page 965). Refer to “:FILTER” on page 991 for information on filter symbol widths. To change the modulation type, refer to “:MODulation[:TYPE]” on page 994.

When the bit rate is changed, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the bit rate: lower bit rates require more time.

***RST** +3.60000000E+004

Range	Modulation Type	Bit Rate Range		
		<i>16 Symbol Wide Filter</i>	<i>32 Symbol Wide Filter</i>	<i>64 Symbol Wide Filter</i>
	BPSK, FSK2, MSK	1bps–50Mbps	1bps–25Mbps	1bps–12.5Mbps
	C4FM, OQPSK, FSK4	2bps–50Mbps	2bps–25Mbps	2bps–12.5Mbps
	OQPSKI95, QPSK			
	P4QPPSK, QPSKIS95			
	GRAYQPSK, QAM4			
	D8PSK, EDGE, FSK8, PSK8	3bps–50Mbps	3bps–25Mbps	3bps–12.5Mbps
	FSK16, PSK16, QAM16	4bps–50Mbps	4bps–25Mbps	4bps–12.5Mbps
	QAM32	5bps–50Mbps	5bps–25Mbps	5bps–12.5Mbps
	QAM64	6bps–50Mbps	6bps–25Mbps	6bps–12.5Mbps
	QAM128	7bps–50Mbps	7bps–25Mbps	7bps–12.5Mbps
	QAM256	8bps–50Mbps	8bps–25Mbps	8bps–12.5Mbps

Key Entry **Symbol Rate**

:BURSt:PN9

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa: BURSt :PN9 NORMal | QUICk
 [:SOURCE] :RADio:TETRa: BURSt :PN9?

This command controls the software PN9 generation.

NORMal This choice produces a maximum length PN9 sequence.

QUICk This choice produces a truncated PN9 sequence.

*RST NORM

Key Entry **PN9 Mode Normal Quick**

Remarks Use Normal mode for bit-error-rate tests where a maximum length PN9 sequence is required.

TETRA Subsystem—Option 402 ([:SOURCE]:RADIO:TETRA)**:BURSt:SCRamble:SEED**

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:BURSt:SCRamble:SEED <32-bit val>
```

```
[:SOURCE]:RADIO:TETRA:BURSt:SCRamble:SEED?
```

This command sets the 32-bit scramble seed value.

***RST** #HFFFFFFF

Range #H0–#HFFFFFFF

Key Entry **Scramble Seed**

Remarks Although values may be set using this command, it does not active that scramble function.

Refer to “[:BURSt:SCRamble\[:STATe\]](#)” on page 980 to enable the scrambling function.

:BURSt:SCRamble[:STATe]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:BURSt:SCRamble[:STATe] ON|OFF|1|0
```

```
[:SOURCE]:RADIO:TETRA:BURSt:SCRamble[:STATe]?
```

This command enables or disables the scramble function.

ON (1) This choice scrambles data on the related fields, using the seed setting.

OFF (0) This choice disables the scramble function.

***RST** 0

Key Entry **Scramble Off On**

Remarks To set the seed value, refer to “[:BURSt:SCRamble:SEED](#)” on page 980.

:BURSt:SHAPE:FALL:DELAy

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:BURSt:SHAPE:FALL:DELAy <val>
```

```
[:SOURCE]:RADIO:TETRA:BURSt:SHAPE:FALL:DELAy?
```

This command sets the burst shape fall delay.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

*RST	+0.00000000E+000
Range	–22.3750 to 99
Key Entry	Fall Delay
Remarks	<p>The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.</p> <p>To change the modulation type, refer to “:MODulation[:TYPE]” on page 994. Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.</p> <p>“:BURSt:SHAPe:FDELay” on page 982 performs the same function; in compliance with the SCPI standard, both commands are listed.</p> <p>For concept information on burst shaping, refer to the <i>E4428C/38C ESG Signal Generators User’s Guide</i>.</p>

:BURSt:SHAPe:FALL:TIME

Supported	E4438C with Option 402
	[:SOURCE]:RADio:TETRa:BURSt:SHAPe:FALL:TIME <val> [:SOURCE]:RADio:TETRa:BURSt:SHAPe:FALL:TIME?
	This command sets the burst shape fall time.
	The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.
*RST	+8.00000000E+000
Range	0.1250–50
Key Entry	Fall Time
Remarks	<p>The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.</p> <p>To change the modulation type, refer to “:MODulation[:TYPE]” on page 994. Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.</p> <p>“:BURSt:SHAPe:FTIME” on page 982 performs the same function; in compliance with the SCPI standard, both commands are listed.</p> <p>For concept information on burst shaping, refer to the <i>E4428C/38C ESG Signal Generators User’s Guide</i>.</p>

TETRA Subsystem—Option 402 ([:SOURCE]:RADio:TETRa)**:BURSt:SHAPe:FDELaY**

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa:BURSt:SHAPe:FDELaY <val>

[:SOURCE] :RADio:TETRa:BURSt:SHAPe:FDELaY?

This command sets the burst shape fall delay.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range -22.3750 to 99

Key Entry **Fall Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 994.

Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FALL:DELaY” on page 980 performs the same

function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:FTIME

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa:BURSt:SHAPe:FTIME <val>

[:SOURCE] :RADio:TETRa:BURSt:SHAPe:FTIME?

This command sets the burst shape fall time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +8.00000000E+000

Range 0.1250–50

Key Entry **Fall Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 994. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:FALL:TIME” on page 981 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RDELay

Supported E4438C with Option 402

[:SOURce] :RADio:TETRa: BURSt :SHAPe: RDELay <val>

[:SOURce] :RADio:TETRa: BURSt :SHAPe: RDELay?

This command sets the burst shape rise delay. The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +0.00000000E+000

Range –14.3750 to 99

Key Entry **Rise Delay**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 994. Refer to “:SRATE” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:RISE:DELay” on page 984 performs the same function; in compliance with the SCPI standard, both commands are listed.

See the *E4428C/38C ESG Signal Generators User’s Guide* for concept information.

:BURSt:SHAPe:RISE:DELay**Supported** E4438C with Option 402

[:SOURCE]:RADio:TETRa:BURSt:SHAPe:RISE:DELay <val>

[:SOURCE]:RADio:TETRa:BURSt:SHAPe:RISE:DELay?

This command sets the burst shape rise delay.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

RST** +0.00000000E+000**Range** -14.3750 to 99**Key Entry** **Rise Delay*Remarks** The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 994.

Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:RDELay” on page 983 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.**:BURSt:SHAPe:RISE:TIME****Supported** E4438C with Option 402

[:SOURCE]:RADio:TETRa:BURSt:SHAPe:RISE:TIME <val>

[:SOURCE]:RADio:TETRa:BURSt:SHAPe:RISE:TIME?

This command sets the burst shape rise time.

The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +8.00000000E+000**Range** 0.1250–22.5000**Key Entry** **Rise Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 994. Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:RTIME” on page 985 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

:BURSt:SHAPe:RTIME

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa: BURSt :SHAPe:RTIME <val>
 [:SOURCE] :RADio:TETRa: BURSt :SHAPe:RTIME?

This command sets the burst shape rise time. The variable <val> is expressed in bits. The minimum and maximum values depend upon modulation type and symbol rate.

***RST** +8.00000000E+000

Range 0.1250–22.5000

Key Entry **Rise Time**

Remarks The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 994. Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.

“:BURSt:SHAPe:RISE:TIME” on page 984 performs the same function; in compliance with the SCPI standard, both commands are listed.

For concept information on burst shaping, refer to the *E4428C/38C ESG Signal Generators User’s Guide*.

TETRA Subsystem—Option 402 ([:SOURCE]:RADIO:TETRA)**:BURSt:SHAPE[:TYPE]**

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:BURSt:SHAPE[:TYPE] SINE | "<file name>"
[:SOURCE]:RADIO:TETRA:BURSt:SHAPE[:TYPE] ?
```

This command specifies the burst shape as either SINE or a user-defined file ("<file name>").

SINE This choice selects a state that is defined by the burst rise and fall *RST values as the default burst shape type.

"<file name>" This choice selects a user designated file from signal generator memory (non-volatile).

***RST** SINE

Key Entry **Sine User File**

:BURSt[:STATe]

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:BURSt[:STATe] ON | OFF | 1 | 0
[:SOURCE]:RADIO:TETRA:BURSt[:STATe] ?
```

This command enables or disables the burst function.

ON (1) This choice enables the transmission of framed data. If all timeslots which are switched on are up traffic channels or custom, you will be bursting the timeslots that are on; there will be no RF carrier during the off timeslots.

If you have switched on any timeslot that you have configured as a down traffic channel, the RF carrier is not switched off between any of the timeslots. The off timeslots are transmitted as a continuous series of ones for the time period of the off timeslots.

OFF (0) This choice enables the transmission of unframed data.

***RST** 0

Key Entry **Data Format Pattern Framed**

:CHANnel

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:CHANnel EVM|ACP
[:SOURCE]:RADio:TETRa:CHANnel?
```

This command optimizes the Nyquist and root Nyquist filters to minimize error vector magnitude (EVM) or to minimize adjacent channel power (ACP).

EVM This choice provides the most ideal passband.

ACP This choice improves stopband rejection.

***RST** EVM

Key Entry **Optimize FIR For EVM ACP**

Remarks To change the current filter type, refer to “:FILTer” on page 991.

:DATA

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:DATA PN9|PN11|PN15|PN20|PN23|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64|PRAM
[:SOURCE]:RADio:TETRa:DATA?
```

This command sets the data pattern for unframed transmission.

***RST** PN23

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	Ext
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's	PRAM File		

Remarks Refer to “File Name Variables” on page 13 for information on the file name syntax.

TETRA Subsystem—Option 402 ([:SOURCE]:RADio:TETRa)**:DATA:PRAM**

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:DATA:PRAM "<file_name>"
```

```
[ :SOURCE ] :RADio:TETRa:DATA:PRAM?
```

This command selects a pattern RAM (PRAM) file as the pattern data type for the TETRA (Trans-European Trunked Radio) format.

"<file_name>" This variable designates the PRAM file in WFM1. Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

Key Entry **PRAM File**

Remarks Selecting this data source forces the burst source to INTERNAL to allow framing control.

The PRAM file must reside in the signal generator’s volatile memory (WFM1) in order to be accessed by this command. For more information on PRAM files, refer to [“:DATA:PRAM:FILE:BLOCK” on page 112](#).

:DATA:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:DATA:FIX4 <val>
```

```
[ :SOURCE ] :RADio:TETRa:DATA:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern for unframed transmission according to the modulation type, symbol rate, filter, and burst shape selected for the TETRA modulation format.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type. To change the data type, refer to [“:DATA” on page 987](#).

:DEFault

Supported E4438C with Option 402

[:SOURCE] :RADIO:TETRA:DEFault

This command returns all of the TETRA modulation format parameters to factory settings. It does not affect any other signal generator parameters.

Key Entry Restore TETRA Factory Default

:EDATa:DELay

Supported E4438C with Option 402

[:SOURCE] :RADIO:TETRA:EDATa:DELay?

This query returns the amount of delay (in symbols) from the external data input to the beginning of the symbol on the I OUT and Q OUT rear panel connectors and the front panel RF OUTPUT connector.

Remarks When the format is turned off, the delay value is unchanged; the query will return the same delay value if the format is on or off.

:EDCLock

Supported E4438C with Option 402

[:SOURCE] :RADIO:TETRA:EDCLock SYMBOL | NORMal

[:SOURCE] :RADIO:TETRA:EDCLock?

This command sets the external data clock use.

SYMBOL This choice specifies that a continuous symbol clock signal must be provided to the SYMBOL SYNC input connector.

NORMal This choice specifies that the DATA CLOCK input connector requires a bit clock. The SYMBOL SYNC input connector requires a (one-shot or continuous) symbol sync signal.

***RST** NORM

Key Entry Ext Data Clock Normal Symbol

Remarks Both choices have no effect in internal clock mode. Refer to “:BBCLock” on [page 977](#) to select EXT as the data clock type.

TETRA Subsystem—Option 402 ([:SOURce]:RADio:TETRa)**:EREFerence****Supported** E4438C with Option 402

[:SOURce]:RADio:TETRa:EREFerence INT|EXT

[:SOURce]:RADio:TETRa:EREFerence?

This command selects either an internal or external bit-clock reference for the data generator.

RST** INT**Key Entry** **BBG Ref Ext Int*Remarks** If the EXT choice is selected, the external source's frequency value

must be applied to the BASEBAND GEN REF IN rear panel connector. The external reference and external data clock are not applicable at the same time. If both are selected, then the external reference takes precedence.

Refer to, “:EREFerence:VALue” on page 990 to enter the external reference frequency setting.

:EREFerence:VALue**Supported** E4438C with Option 402

[:SOURce]:RADio:TETRa:EREFerence:VALue <val>

[:SOURce]:RADio:TETRa:EREFerence:VALue?

This command sets the expected bit-clock reference frequency value for an externally applied reference signal.

The variable <val> is expressed in units of hertz (Hz–MHz).

RST** +1.30000000E+007**Range** 2.5E5–1E8**Key Entry** **Ext BBG Ref Freq*Remarks** The value specified by this command is effective only when you are using an external reference applied to the BASEBAND GEN REF IN rear panel connector.

Refer to “:EREFerence” on page 990 to select EXT (external source) as the reference for the bit-clock.

:FILTer

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:FILTer RNYQuist|NYQuist|GAUSSian|RECTangle|
IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|"<user FIR>"
[:SOURCE]:RADio:TETRa:FILTer?
```

This command selects the pre-modulation filter type.

IS95	This choice selects a filter that meets the criteria of the IS-95 standard.
IS95_EQ	This choice selects a filter which is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard. This filter is only used for IS-95 baseband filtering.
IS95_MOD	This choice selects a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.
IS95_MOD_EQ	This choice selects a filter which is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.
AC4Fm	This choice selects a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.
UGGaussian	This choice selects a backwards compatible GSM Gaussian filter (Gaussian filter with a fixed BbT value of 0.300) for the ESG E44xxB Option UN3 or UN4.
"<user FIR>"	This variable is any filter file that you have stored into memory.

***RST** RNYQ

Key Entry	Root Nyquist	Nyquist	Gaussian	Rectangle	IS-95	IS-95 w/EQ
	IS-95 Mod	IS-95 Mod w/EQ	APCO 25 C4FM	UN3/4 GSM Gaussian		
	User FIR					

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

TETRA Subsystem—Option 402 ([:SOURCE]:RADio:TETRa)**:IQ:SCALe**

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa:IQ:SCALe <val>

[:SOURCE] :RADio:TETRa:IQ:SCALe?

This command sets the amplitude of the I/Q outputs for better adjacent channel power (ACP); lower scaling values equate to better ACP.

The variable <val> is expressed in units of percent.

***RST** +65

Range 1–200

Key Entry **I/Q Scaling**

Remarks This command has no effect with MSK or FSK modulation.

:MODulation:FSK[:DEVIation]

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa:MODulation:FSK[:DEVIation] <val>

[:SOURCE] :RADio:TETRa:MODulation:FSK[:DEVIation]?

This command sets the symmetric FSK frequency deviation value.

The variable <val> is expressed in units of Hertz and the maximum range value equals the current symbol rate value multiplied by four, limited to 20 MHz.

***RST** +4.00000000E+002

Range 0–2E7

Key Entry **Freq Dev**

Remarks To change the modulation type, refer to “:MODulation[:TYPE]” on page 994.

Refer to “:SRATe” on page 965 for a list of the minimum and maximum symbol rate values.

To set an asymmetric FSK deviation value, refer to the *E4428C/38C ESG Signal Generators User’s Guide* for more information.

:MODulation:MSK[:PHASe]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:MODulation:MSK[:PHASe] <val>  
[ :SOURCE ] :RADio:TETRa:MODulation:MSK[:PHASe] ?
```

This command sets the MSK phase deviation value.

The variable <val> is expressed in units of degrees.

***RST** +9.00000000E+001

Range 0–100

Key Entry **Phase Dev**

:MODulation:UFSK

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:MODulation:UFSK "<file name>"  
[ :SOURCE ] :RADio:TETRa:MODulation:UFSK ?
```

This command selects a user-defined FSK file from the signal generator memory.

Key Entry **User FSK**

Remarks The user-defined FSK file is held in signal generator memory until the command that selects user FSK as the modulation type is sent. Refer to [“:MODulation\[:TYPE\]” on page 994](#) to change the current modulation type.

Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:MODulation:UIQ

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:MODulation:UIQ "<file name>"  
[ :SOURCE ] :RADio:TETRa:MODulation:UIQ ?
```

This command selects a user-defined I/Q file from the signal generator memory.

Key Entry **User I/Q**

TETRA Subsystem—Option 402 ([:SOURce]:RADio:TETRa)

Remarks The user-defined I/Q file is held in signal generator memory until the command that selects user I/Q as the modulation type is sent. Refer to “:MODulation[:TYPE]” on page 994 to change the current modulation type.

Refer to “File Name Variables” on page 13 for information on the file name syntax.

:MODulation[:TYPE]

Supported E4438C with Option 402

```
[:SOURce]:RADio:TETRa:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|
GRAYQPSK|OQPSK|IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|
FSK8|FSK16|C4FM|QAM4|QAM16|QAM32|QAM64|QAM128|QAM256|UIQ|UFSK
[:SOURce]:RADio:TETRa:MODulation[:TYPE]?
```

This command sets the modulation type for the TETRA personality.

***RST** P4DQPSK

Key Entry	BPSK	QPSK	IS-95 QPSK	Gray Coded QPSK	OQPSK			
	IS-95 OQPSK	$\pi/4$ DQPSK	8PSK	16PSK	D8PSK	MSK	2-Lvl FSK	
	4-Lvl FSK	8-Lvl FSK	16-Lvl FSK	C4FM	4QAM	16QAM	32QAM	
	64QAM	128QAM	256QAM	User I/Q	User FSK			

:POLarity[:ALL]

Supported E4438C with Option 402

```
[:SOURce]:RADio:TETRa:POLarity[:ALL] NORMal|INVerted
[:SOURce]:RADio:TETRa:POLarity[:ALL]?
```

This command sets the rotation direction of the phase modulation vector.

NORMal This choice selects normal phase polarity.

INVerted This choice inverts the internal Q signal.

***RST** NORM

Key Entry **Phase Polarity Normal Invert**

:SECondary:RECall

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa:SECondary:RECall

This command recalls the secondary frame configuration, overwriting the current state.

Key Entry **Recall Secondary Frame State**

Remarks To save a secondary frame state, refer to “:SECondary:SAVE” on page 995.

A secondary frame is not active until the secondary state is enabled. To activate a secondary frame, refer to “:SECondary[:STATe]” on page 996.

:SECondary:SAVE

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa:SECondary:SAVE

This command saves the current frame configuration as the secondary frame with the file name TETRa_SECONDARY_FRAME.

Key Entry **Save Secondary Frame State**

Remarks To recall the secondary frame (saved in non-volatile signal generator memory), refer to “:SECondary:RECall” on page 995.

:SECondary:TRIGger[:SOURCE]

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa:SECondary:TRIGger [:SOURCE] KEY | EXT | BUS
 [:SOURCE] :RADio:TETRa:SECondary:TRIGger [:SOURCE] ?

This command selects the type of triggering for the secondary frame.

KEY This choice enables triggering by pressing the front panel **Trigger** hardkey.

EXT This choice enables triggering using an externally applied signal at the PATT TRIG IN rear panel connector or the PATT TRIG IN 2 pin on the rear panel AUX I/O connector. To select the appropriate connector, refer to “:TRIGger[:SOURCE]:EXTernal[:SOURCE]” on page 1018.

BUS This choice enables GPIB triggering using the *TRG or GET command or LAN and RS-232 triggering using the *TRG command.

Key Entry **Trigger Key Ext Bus**

TETRA Subsystem—Option 402 ([:SOURCE]:RADio:TETRa)**:SECondary[:STATe]****Supported** E4438C with Option 402

[:SOURCE]:RADio:TETRa:SECondary[:STATe] ON|OFF|1|0

[:SOURCE]:RADio:TETRa:SECondary[:STATe] ?

This command enables or disables the ability to switch to the secondary frame.

RST** 0**Key Entry** **Secondary Frame Off On*Remarks** A frame must already be saved as the secondary frame in order to turn the secondary state function on.To save a frame as the secondary frame, refer to “[:SECondary:SAVE]” on [page 995](#).**:SLOT[1]|2|3|4:DCCustom****Supported** E4438C with Option 402

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DCCustom PN9|PN11|PN15|

PN20|PN23|FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DCCustom?

This command configures the downlink continuous custom timeslot data field.

RST** PN9**Key Entry** **PN9 PN11 PN15 PN20 PN23 FIX4 User File EXT*4 1's & 4 0's 8 1's & 8 0's 16 1's & 16 0's 32 1's & 32 0's****64 1's & 64 0's****Remarks** Refer to “[File Name Variables](#)” on [page 13](#) for information on the file name syntax.**:SLOT[1]|2|3|4:DCCustom:FIX4****Supported** E4438C with Option 402

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DCCustom:FIX4 <val>

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DCCustom:FIX4?

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink continuous custom timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15
Key Entry **FIX4**
Remarks FIX4 must already be defined as the data type.

:DCNormal:B1

Supported E4438C with Option 402
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DCNormal:B1 <val>
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DCNormal:B1?

This command sets the first 14 broadcast bits for the selected downlink continuous normal timeslot.

***RST** #H0000
Range #H0–#H3FFF
Key Entry **B1**

:DCNormal:B2

Supported E4438C with Option 402
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DCNormal:B2 <val>
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DCNormal:B2?

This command sets the last 16 broadcast bits for the selected downlink continuous normal timeslot.

***RST** #H0000
Range #H0–#HFFFF
Key Entry **B2**

:SLOT[1] | 2 | 3 | 4:DCNormal:TSEquence

Supported E4438C with Option 402
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DCNormal:
TSEquence <val>
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DCNormal:TSEquence?

This command sets the normal training sequence bits (30-bit mid-amble) for the selected downlink continuous normal timeslot.

***RST** #H343A74
Range #H0–#H3FFFFFF
Key Entry **TS**

TETRA Subsystem—Option 402 (:SOURce):RADio:TETRa)

Remarks When 1E90DE is selected, the data fields are scrambled as separate logical channels.

:SLOT[1] | 2 | 3 | 4:DCNormal[:DATA]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:DCNormal [ :DATA ] PN9 | PN11 |
PN15 | PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:DCNormal [ :DATA ] ?
```

This command configures the selected downlink continuous normal timeslot data field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's			

Remarks Refer to “[File Name Variables](#)” on page 13 for information on the file name syntax.

:SLOT[1] | 2 | 3 | 4:DCNormal[:DATA]:FIX4

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:DCNormal [ :DATA ] :FIX4 <val>
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:DCNormal [ :DATA ] :FIX4 ?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink continuous normal timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT[1]|2|3|4:DCSync:B

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DCSync:B <val>  
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DCSync:B?
```

This command sets the broadcast bits for the selected downlink continuous synchronization timeslot.

***RST** #H00000000

Range #H0–#H3FFFFFFF

Key Entry **B**

:SLOT[1]|2|3|4:DCSync:FCOR

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DCSync:FCOR <val>  
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DCSync:FCOR?
```

This command sets the frequency correction bits for the selected downlink continuous synchronization timeslot.

***RST** #HFF0000000000000000FF

Range #H0–#HFFFFFFFFFFFFFFFFFFFF

Key Entry **FCOR**

:SLOT[1]|2|3|4:DCSync:SSB

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DCSync:SSB <val>  
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DCSync:SSB?
```

This command sets the synchronization block bits for the selected downlink synchronization continuous timeslot.

***RST** #H00000000000000000000000000000000

Range #H0–#HFFFFFFFFFFFFFFFFFFFFFFFF

Key Entry **SSB**

TETRA Subsystem—Option 402 ([:SOURCE]:RADIO:TETRA)**:SLOT[1]|2|3|4:DCSync:STS****Supported** E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync:STS <val>
[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync:STS?
```

This command sets the synchronization training sequence for the selected downlink continuous synchronization timeslot.

RST** #H30673A7067**Range** #H0–#H3FFFFFFFF**Key Entry** **STS*:SLOT[1]|2|3|4:DCSync[:DATA]****Supported** E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync[:DATA] PN9|PN11|
PN15|PN20|PN23FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync[:DATA]?
```

This command configures the selected downlink continuous synchronization timeslot data field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's		8 1's & 8 0's		16 1's & 16 0's		32 1's & 32 0's	
	64 1's & 64 0's							

Remarks Refer to “[File Name Variables](#)” on page 13 for information on the file name syntax.

:SLOT[1]|2|3|4:DCSync[:DATA]:FIX4**Supported** E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync[:DATA]:FIX4 <val>
[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync[:DATA]:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink continuous synchronization timeslot.

***RST** #B0000**Range** #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

:SLOT[1] | 2 | 3 | 4:DDCustom

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:DDCustom PN9 | PN11 | PN15 |
PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:DDCustom?
```

This command configures the downlink discontinuous custom timeslot data field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's		8 1's & 8 0's		16 1's & 16 0's		32 1's & 32 0's	
			64 1's & 64 0's					

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:SLOT[1] | 2 | 3 | 4:DDCustom:FIX4

Supported E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:DDCustom:FIX4 <val>
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:DDCustom:FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink discontinuous custom timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

TETRA Subsystem—Option 402 ([:SOURCE]:RADIO:TETRA)**:SLOT[1]|2|3|4:DDNormal:B1****Supported** E4438C with Option 402

[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:B1 <val>

[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:B1?

This command sets the first 14 broadcast bits for the selected downlink discontinuous normal timeslot.

RST** #H0000**Range** #H0–#H3FFF**Key Entry** **B1*:SLOT[1]|2|3|4:DDNormal:B2****Supported** E4438C with Option 402

[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:B2 <val>

[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:B2?

This command sets the last 16 broadcast bits for the selected downlink continuous normal timeslot.

RST** #H0000**Range** #H0–#HFFFF**Key Entry** **B2*:SLOT[1]|2|3|4:DDNormal:TSEquence****Supported** E4438C with Option 402

[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:TSEquence <val>

[:SOURCE]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:TSEquence?

This command specifies the normal training sequence bits (30-bit mid-amble) for the selected downlink discontinuous normal timeslot.

RST** #H343A74**Range** #H0–#H3FFFFFFF**Key Entry** **TS*Remarks** When 1E90DE is selected, the data fields are scrambled as separate logical channels.

:SLOT[1] | 2 | 3 | 4:DDNormal[:DATA]

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DDNormal[:DATA] PN9 | PN11 |
PN15 | PN20 | PN23 FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DDNormal[:DATA] ?
```

This command configures the selected downlink discontinuous normal timeslot data field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's			

Remarks Refer to “[File Name Variables](#)” on page 13 for information on the file name syntax.

:SLOT[1] | 2 | 3 | 4:DDNormal[:DATA]:FIX4

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DDNormal[:DATA]:FIX4 <val>
[:SOURCE]:RADio:TETRa:SLOT[1] | 2 | 3 | 4:DDNormal[:DATA]:FIX4 ?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink discontinuous normal timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

Remarks FIX4 must already be defined as the data type.

TETRA Subsystem—Option 402 ([:SOURCE]:RADio:TETRa)**:SLOT[1]|2|3|4:DDSync:B****Supported** E4438C with Option 402

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DDSync:B <val>

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DDSync:B?

This command sets the broadcast bits for the selected downlink discontinuous synchronization timeslot.

RST** #H00000000**Range** #H0–#H3FFFFFFF**Key Entry** **B*:SLOT[1]|2|3|4:DDSync:FCOR****Supported** E4438C with Option 402

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DDSync:FCOR <val>

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DDSync:FCOR?

This command sets the frequency correction bits for the selected downlink discontinuous synchronization timeslot.

RST** #HFF0000000000000000FF**Range** #H0–#HFFFFFFFFFFFFFFFFFFFF**Key Entry** **FCOR*:SLOT[1]|2|3|4:DDSync:SSB****Supported** E4438C with Option 402

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DDSync:SSB <val>

[:SOURCE]:RADio:TETRa:SLOT[1]|2|3|4:DDSync:SSB?

This command sets the synchronization block bits for the selected downlink synchronization discontinuous timeslot.

***RST** #H000000000000000000000000**Range** #H0–#HFFFFFFFFFFFFFFFFFFFFFFFF**Key Entry** **SSB**

:SLOT[1]|2|3|4:DDSync:STS

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DDSync:STS <val>
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DDSync:STS?
```

This command sets the synchronization training sequence for the selected downlink discontinuous synchronization timeslot.

***RST** #H30673A7067

Range #H0–#H3FFFFFFFFF

Key Entry STS

:SLOT[1]|2|3|4:DDSync[:DATA]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DDSync [:DATA] PN9 | PN11 |
PN15 | PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DDSync [:DATA] ?
```

This command configures the selected downlink discontinuous synchronization timeslot data field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's		8 1's & 8 0's		16 1's & 16 0's		32 1's & 32 0's	
	64 1's & 64 0's							

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:SLOT[1]|2|3|4:DDSync[:DATA]:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DDSync [:DATA] :FIX4 <val>
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :DDSync [:DATA] :FIX4?
```

This command sets the binary, 4-bit repeating sequence data pattern that is used in the selected downlink discontinuous synchronization timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry FIX4

TETRA Subsystem—Option 402 ([:SOURce]:RADio:TETRa)

Remarks FIX4 must already be defined as the data type. To change the data type, refer to “:SLOT[1]|2|3|4:DCNormal[:DATA]” on page 998.

:SLOT[1]|2|3|4:POWer

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :POWer MAIN|DELTA
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :POWer?
```

This command toggles the RF output power level function for the selected timeslot.

MAIN This choice specifies RF output as the main power level.

DELTA This choice specifies RF output as the alternative power level.

***RST** MAIN

Key Entry Timeslot Ampl Main Delta

:SLOT[1]|2|3|4:STATe

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :STATe ON|OFF|1|0
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :STATe?
```

This command enables or disables the selected timeslot.

***RST** Timeslot 1: 1 Timeslot 2-4:

Key Entry Timeslot Off On

Remarks Continuous timeslots cannot be disabled.

:SLOT[1]|2|3|4:UC1:TSEQuence

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :UC1:TSEQuence <val>
[ :SOURce ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :UC1:TSEQuence?
```

This command specifies the extended training sequence bits (30-bit mid-amble) for the selected uplink control 1 timeslot.

***RST** #H2743A743

Range #H0–#H3FFFFFFF

Key Entry TS

:SLOT[1] | 2 | 3 | 4:UC1[:DATA]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:UC1 [:DATA] PN9 | PN11 | PN15 |
PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURCE] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:UC1 [:DATA] ?
```

This command configures the selected uplink control 1 data field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	32 1's & 32 0's	64 1's & 64 0's			

Remarks Refer to [“File Name Variables” on page 13](#) for information on the file name syntax.

:SLOT[1] | 2 | 3 | 4:UC1[:DATA]:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:UC1 [:DATA] :FIX4 <val>
[:SOURCE] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:UC1 [:DATA] :FIX4 ?
```

This command configures the uplink control 1 data field FIX4 value for the selected timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

:SLOT[1] | 2 | 3 | 4:UC2:TSEquence

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:UC2:TSEquence <val>
[:SOURCE] :RADio:TETRa:SLOT [1] | 2 | 3 | 4:UC2:TSEquence ?
```

This command specifies the extended training sequence bits (30-bit mid-amble) for the selected uplink control 2 timeslot.

***RST** #H2743A743

Range #H0–#H3FFFFFF

Key Entry **TS**

TETRA Subsystem—Option 402 ([:SOURCE]:RADIO:TETRA)**:SLOT[1] | 2 | 3 | 4:UC2[:DATA]****Supported** E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:UC2[:DATA] PN9 | PN11 | PN15 |
PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:UC2[:DATA] ?
```

This command configures the selected uplink control 2 data field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	16 1's & 16 0's	16 1's & 16 0's	16 1's & 16 0's	32 1's & 32 0's	32 1's & 32 0's
	64 1's & 64 0's							

Remarks Refer to “File Name Variables” on page 13 for information on the file name syntax.

:SLOT[1] | 2 | 3 | 4:UC2[:DATA]:FIX4**Supported** E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:UC2[:DATA]:FIX4 <val>
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:UC2[:DATA]:FIX4?
```

This command configures the uplink control 2 data field FIX4 value for the selected timeslot.

RST** #B0000**Range** #B0000–#B1111 or 0–15**Key Entry** **FIX4*:SLOT[1] | 2 | 3 | 4:UCStom****Supported** E4438C with Option 402

```
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:UCStom PN9 | PN11 | PN15 |
PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURCE]:RADIO:TETRA:SLOT[1] | 2 | 3 | 4:UCStom?
```

This command configures the uplink custom data field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's	8 1's & 8 0's	16 1's & 16 0's	16 1's & 16 0's	16 1's & 16 0's	16 1's & 16 0's	32 1's & 32 0's	32 1's & 32 0's
	64 1's & 64 0's							

Remarks See “File Name Variables” on page 13 for information on the file name syntax.

:SLOT[1] | 2 | 3 | 4:UCUStom:FIX4

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:SLOT [1] | 2 | 3 | 4:UCUStom:FIX4 <val>
[:SOURCE]:RADio:TETRa:SLOT [1] | 2 | 3 | 4:UCUStom:FIX4?
```

This command configures the uplink custom data field to FIX4 (4-bit repeating sequence data pattern).

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

:SLOT[1] | 2 | 3 | 4:UNORmal:TSEquence

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:SLOT [1] | 2 | 3 | 4:UNORmal:TSEquence <val>
[:SOURCE]:RADio:TETRa:SLOT [1] | 2 | 3 | 4:UNORmal:TSEquence?
```

This command specifies the extended training sequence bits (22-bit mid-amble) for the selected uplink normal timeslot.

***RST** #H343A74

Range #H0–#H3FFFFFF

Key Entry **TS**

Remarks When 1E90DE is selected, data fields are scrambled as separate logical channels.

:SLOT[1] | 2 | 3 | 4:UNORmal[:DATA]

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:SLOT [1] | 2 | 3 | 4:UNORmal[:DATA] PN9 | PN11 |
PN15 | PN20 | PN23 | FIX4 | "<file name>" | EXT | P4 | P8 | P16 | P32 | P64
[:SOURCE]:RADio:TETRa:SLOT [1] | 2 | 3 | 4:UNORmal[:DATA] ?
```

This command configures the selected uplink normal data field.

***RST** PN9

Key Entry	PN9	PN11	PN15	PN20	PN23	FIX4	User File	EXT
	4 1's & 4 0's		8 1's & 8 0's		16 1's & 16 0's		32 1's & 32 0's	
			64 1's & 64 0's					

TETRA Subsystem—Option 402 ([:SOURCE]:RADio:TETRa)

Remarks Refer to “File Name Variables” on page 13 for information on the file name syntax.

:SLOT[1]|2|3|4:UNORmal[:DATA]:FIX4

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :UNORmal [ :DATA ] :FIX4 <val>
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 :UNORmal [ :DATA ] :FIX4?
```

This command configures the uplink normal data field FIX4 value for the selected timeslot.

***RST** #B0000

Range #B0000–#B1111 or 0–15

Key Entry **FIX4**

:SLOT[1]|2|3|4[:TYPE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 [ :TYPE ] UCUSTom|UC1|UC2|
UNORmal|DDNormal|DDSync|DCNormal|DCSync|DCCustom|DDCustom
[ :SOURCE ] :RADio:TETRa:SLOT [1] | 2 | 3 | 4 [ :TYPE ] ?
```

This command sets the timeslot type for the selected timeslot.

***RST** *Timeslot 1:* UCUS *Timeslot 2-4:* UNOR

Key Entry **Up Custom** **Up Control 1** **Up Control 2** **Up Normal** **Dn Normal Disc**
Dn Sync Disc **Dn Normal Cont** **Dn Sync Cont** **Dn Custom Cont**
Dn Custom Disc

Remarks When downlink is selected and the frame is uplink, the following mapping is made to convert the uplink protocols to downlink; an error will be generated.

From	To (Continuous Downlink)	To (Discontinuous Downlink)
UC1	DCCustom	DDCustom
UC2	DCCustom	DDCustom
UCUSTom	DCCustom	DDCustom
UNORmal	DCNormal	DDNormal

When uplink is selected and the frame is downlink, the following mapping is made to convert the downlink protocols to uplink; an error will be generated.

From	To
DCCustom/ DDCustom	UCUSTom
DCNormal/ DDNormal	UNORmal
DCSync/ DDSync	UCUSTom

When continuous downlink protocols are selected, all timeslots must be on, and they cannot be turned off. Any attempts to do so will generate an error.

:SOUT

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:SOUT FRAME|SLOT|ALL
[:SOURCE]:RADio:TETRa:SOUT?
```

This command sets the synchronization location (within the pattern of data) and the type of output at the EVENT 1 rear panel connector.

FRAME This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a framed data pattern.

SLOT This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for a selected timeslot.

ALL This choice outputs a 1-bit signal, synchronized to the bit selected by the synchronization output offset command, for all active timeslots.

***RST** FRAME

Key Entry **Begin Frame** **Begin Timeslot #** **All Timeslots**

Remarks See “:SOUT:OFFSet” on page 1011 to change the synchronization output offset.

:SOUT:OFFSet

Supported E4438C with Option 402

```
[:SOURCE]:RADio:TETRa:SOUT:OFFSet <val>
[:SOURCE]:RADio:TETRa:SOUT:OFFSet?
```

This command sets the offset value for the location of the output synchronization signal on the EVENT1 rear panel connector relative to the beginning of the framed data pattern or timeslot.

The variable <val> is expressed as a number of bits.

TETRA Subsystem—Option 402 ([:SOURCE]:RADio:TETRa)

*RST	+0
Range	–509 to 509
Key Entry	Sync Out Offset
Remarks	Negative values move the synchronization output signal earlier; positive values move it later. To change the output of the EVENT1 rear panel connector to SLOT, refer to “:SOUT” on page 1011.

:SOUT:SLOT

Supported	E4438C with Option 402
	[:SOURCE] :RADio:TETRa:SOUT:SLOT <val> [:SOURCE] :RADio:TETRa:SOUT:SLOT?
	This command selects the timeslot that will trigger a 1-bit output signal at the EVENT 1 rear panel connector.
*RST	+1
Range	1–4
Key Entry	Begin Timeslot #
Remarks	SLOT must be selected as the output signal type for the EVENT 1 rear panel connector. To change the output of the EVENT1 rear panel connector to SLOT, refer to “:SOUT” on page 1011.

:SRATe

Supported	E4438C with Option 001/601 or 002/602
	[:SOURCE] :RADio:TETRa:SRATe <val> [:SOURCE] :RADio:TETRa:SRATe?
	This command sets the transmission symbol rate. Symbol rate is the bit rate divided by the bits per symbol. A change in the symbol rate affects the bit rate. Refer to “:BRATe” on page 978 for information on bit rate.
	The variable <val> is expressed in units of symbols per second (sps–MSPS) and the maximum symbol rate depends on the filter. Refer to “:FILTer” on page 991 for minimum filter symbol width.
	The filter may have to be truncated down to 32 or 16 symbols wide to achieve the highest symbol rate. The signal generator’s internal filters are not truncated below their minimum filter length and user-defined FIR filters are not truncated. If the filter cannot be truncated then the symbol rate is

limited to the maximum rate of the narrowest filter size possible.

The relative timing of the modulated data, as well as the actual filter response is affected when the filter is truncated.

When the symbol rate changes, the ESG reconfigures the baseband generator. The time required to reconfigure the baseband generator is inversely proportional to the symbol rate: lower symbol rates require more time.

To change the modulation type, refer to “:MODulation[:TYPE]” on page 994.

*RST +1.80000000E+004

Range	Modulation Type	Symbol Rate Range		
		<i>16 Symbol Wide Filter</i>	<i>32 Symbol Wide Filter</i>	<i>64 Symbol Wide Filter</i>
	BPSK, FSK2, MSK	1sps–50Msps	1sps–25Msps	1sps–12.5Msps
	C4FM, OQPSK, FSK4	2sps–25Msps	2sps–12.5Msps	2sps–6.25Msps
	OQPSKI95, QPSK			
	P4QPPSK, QPSKIS95			
	GRAYQPSK, QAM4			
	D8PSK, EDGE, FSK8, PSK8	3sps–16.666666666 Msps	3sps–8.333333333 Msps	3sps–4.166666666Msps
	FSK16, PSK16, QAM16	4sps–12.5Msps	4sps–6.25Msps	4sps–3.125Msps
	QAM32	5sps–10Msps	5sps–5Msps	5sps–2.5Msps
	QAM64	6sps–8.333333333 Msps	6sps–4.166666666 Msps	6sps–2.083333333 Msps
	QAM128	7sps–7.142857142 Msps	7sps–3.571428572 Msps	7sps–1.785714285 Msps
	QAM256	8sps–6.25Msps	8sps–3.125 Msps	8sps–1.5625 Msps

NOTE Using I/Q skew will half the minimum number of symbols for the selected filter.

Key Entry **Symbol Rate**

TETRA Subsystem—Option 402 ([:SOURce]:RADio:TETRa)**:TRIGger:TYPE**

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:TETRa:TRIGger:TYPE CONTInuous | SINGle | GATE
[ :SOURce ] :RADio:TETRa:TRIGger:TYPE?
```

This command sets the trigger type.

CONTInuous The framed data sequence repeats continuously; the sequence restarts every time the previous playback is completed. To customize continuous triggering, refer to [“:TRIGger:TYPE:CONTInuous\[:TYPE\]” on page 1014](#).

SINGle The framed data sequence plays once for every trigger received.

GATE An external trigger signal interrupts the playback while the gating signal is in the inactive state. Playback resumes when the external control signal returns to the active state. The active state can be set to high or low.

***RST** CONT

Key Entry **Continuous** **Single** **Gated**

:TRIGger:TYPE:CONTInuous[:TYPE]

Supported E4438C with Option 402

```
[ :SOURce ] :RADio:TETRa:TRIGger:TYPE:CONTInuous [ :TYPE ] FREE |
TRIGger | RESet
[ :SOURce ] :RADio:TETRa:TRIGger:TYPE:CONTInuous [ :TYPE ] ?
```

This commands selects the waveform’s response to a trigger signal while using the continuous trigger mode.

For more information on triggering and to select the continuous trigger mode, see [“:TRIGger:TYPE” on page 1014](#).

The following list describes the waveform’s response to each of the command choices:

FREE Turning the ARB format on immediately triggers the waveform. The waveform repeats until you turn the format off, select another trigger, or choose another waveform file.

TRIGger The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously until you turn the format off, select another trigger, or choose another waveform file.

RESet The waveform waits for a trigger before play begins. When the waveform receives the trigger, it plays continuously. Subsequent triggers reset the waveform to the beginning. For a waveform sequence, this means to the beginning of the first segment in the sequence.

***RST** FREE

Key Entry **Free Run Trigger & Run Reset & Run**

:TRIGger:TYPE:GATE:ACTive

Supported E4438C with Option 402

[:SOURce] :RADio:TETRa:TRIGger:TYPE:GATE:ACTive LOW|HIGH
 [:SOURce] :RADio:TETRa:TRIGger:TYPE:GATE:ACTive?

This command selects the active state (gate polarity) of the gate while using the gating trigger mode.

The LOW and HIGH selections correspond to the low and high states of an external trigger signal. For example, when you select HIGH, the active state occurs during the high of the trigger signal. When the active state occurs, the ESG stops the waveform playback at the last played sample point, then restarts the playback at the next sample point when the inactive state occurs. For more information on triggering and to select gating as the trigger mode, see “:TRIGger:TYPE” on page 1014.

The following list describes the ESG’s gating behavior for the polarity selections:

LOW The waveform playback stops when the trigger signal goes low (active state) and restarts when the trigger signal goes high (inactive state).

HIGH The waveform playback stops when the trigger signal goes high (active state) and restarts when the trigger signal goes low (inactive state).

***RST** HIGH

Key Entry **Gate Active Low High**

TETRA Subsystem—Option 402 (:SOURce):RADio:TETRa)**:TRIGger[:SOURce]**

Supported E4438C with Option 402

[:SOURce] :RADio:TETRa:TRIGger [:SOURce] KEY | EXT | BUS

[:SOURce] :RADio:TETRa:TRIGger [:SOURce] ?

This command sets the trigger source.

For more information on triggering, see “:TRIGger:TYPE” on page 1014. The following list describes the command choices:

KEY This choice enables manual triggering by pressing the front-panel **Trigger** hardkey.

EXT An externally applied signal triggers the waveform. This is the only choice that works with gating. The following conditions affect an external trigger:

- The input connector selected for the trigger signal. You have a choice between the rear-panel PATTERN TRIG IN connector or the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector. To make the connector selection, see “:TRIGger[:SOURce]:EXTErnal[:SOURce]” on page 1018.

For more information on the connectors and on connecting the cables, see the *E4428C/38C ESG Signal Generators User’s Guide*.

- The trigger signal polarity:
 - gating mode, see “:TRIGger:TYPE:GATE:ACTive” on page 1015
 - continuous and single modes, see “:TRIGger[:SOURce]:EXTErnal:SLOPe” on page 1018
- The time delay between when the ESG receives a trigger and when the waveform responds to the trigger. There are two parts to setting the delay:
 - setting the amount of delay, see “:TRIGger[:SOURce]:EXTErnal:DELay” on page 1017
 - turning the delay on, see “:TRIGger[:SOURce]:EXTErnal:DELay:STATe” on page 1017

BUS This choice enables triggering over the GPIB or LAN using the *TRG or GET commands or the AUXILIARY INTERFACE (RS-232) using the *TRG command.

***RST** KEY

Key Entry **Trigger Key** **Ext** **Bus**

:TRIGger[:SOURCE]:EXtErnal:DELay

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:TRIGger [ :SOURCE ] :EXtErnal:DELay <val>  
[ :SOURCE ] :RADio:TETRa:TRIGger [ :SOURCE ] :EXtErnal:DELay?
```

This command sets the number of bits to delay the ESG’s response to an external trigger.

The bit delay is a delay between when the ESG receives the trigger and when it responds to the trigger. The delay uses the clocks of the bit-clock to time the delay. After the ESG receives the trigger and the set number of delay bits (clocks) occurs, the ESG transmits the data pattern.

The delay occurs after you enable the state. See “[:TRIGger\[:SOURCE\]:EXtErnal:DELay:STATe](#)” on [page 1017](#). You can set the number of bits either before or after enabling the state.

For more information on configuring an external trigger source and to select external as the trigger source, see “[:TRIGger\[:SOURCE\]](#)” on [page 1016](#).

***RST** +0
Range 0–1048575
Key Entry **Ext Delay Bits**

:TRIGger[:SOURCE]:EXtErnal:DELay:STATe

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:TRIGger [ :SOURCE ] :EXtErnal:DELay:STATe  
ON|OFF|1|0  
[ :SOURCE ] :RADio:TETRa:TRIGger [ :SOURCE ] :EXtErnal:DELay:STATe?
```

This command enables or disables the operating state of the external trigger delay function.

For setting the delay time, see “[:TRIGger\[:SOURCE\]:EXtErnal:DELay](#)” on [page 1017](#), and for more information on configuring an external source, see “[:TRIGger\[:SOURCE\]](#)” on [page 1016](#).

***RST** 0
Key Entry **Ext Delay Off On**

TETRA Subsystem—Option 402 ([:SOURCE]:RADio:TETRa)**:TRIGger[:SOURCE]:EXternal:SLOPe**

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:TRIGger [ :SOURCE ] :EXternal:SLOPe POSitive|NEGative
[ :SOURCE ] :RADio:TETRa:TRIGger [ :SOURCE ] :EXternal:SLOPe?
```

This command sets the polarity for an external trigger signal while using the continuous, single triggering mode. To set the polarity for gating, see “[:TRIGger:TYPE:GATE:ACTive](#)” on page 1015.

The POSitive and NEGative selections correspond to the high (positive) and low (negative) states of the external trigger signal. For example, when you select POSitive, the waveform responds (plays) during the high state of the trigger signal. When the ESG receives multiple trigger occurrences when only one is required, the signal generator uses the first trigger and ignores the rest.

For more information on configuring an external trigger source and to select external as the trigger source, see “[:TRIGger\[:SOURCE\]](#)” on page 1016.

***RST** NEG

Key Entry Ext Polarity Neg Pos

:TRIGger[:SOURCE]:EXternal[:SOURCE]

Supported E4438C with Option 402

```
[ :SOURCE ] :RADio:TETRa:TRIGger [ :SOURCE ] :EXternal [ :SOURCE ] EPT1 |
EPT2 | EPTRIGGER1 | EPTRIGGER2
[ :SOURCE ] :RADio:TETRa:TRIGger [ :SOURCE ] :EXternal [ :SOURCE ] ?
```

This command selects which PATTERN TRIG IN connection the ESG uses to accept an externally applied trigger signal when external is the trigger source selection.

For more information on configuring an external trigger source and to select external as the trigger source, see “[:TRIGger\[:SOURCE\]](#)” on page 1016. For more information on the rear-panel connectors, see the *E4428C/38C ESG Signal Generators User’s Guide*.

The following list describes the command choices:

- | | |
|------------|---|
| EPT1 | This choice is synonymous with EPTRIGGER1 and selects the PATTERN TRIG IN rear-panel connector. |
| EPT2 | This choice is synonymous with EPTRIGGER2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector. |
| EPTRIGGER1 | This choice is synonymous with EPT1 and selects the PATTERN TRIG IN rear-panel connector. |
| EPTRIGGER2 | This choice is synonymous with EPT2 and selects the PATT TRIG IN 2 pin on the rear-panel AUXILIARY I/O connector. |

***RST** EPT1
Key Entry **Patt Trig In 1** **Patt Trig In 2**

[:STATe]

Supported E4438C with Option 402

[:SOURCE] :RADio:TETRa [:STATe] ON | OFF | 1 | 0
[:SOURCE] :RADio:TETRa [:STATe] ?

This command enables or disables the TETRA modulation format.

***RST** OFF
Key Entry TETRA Off On
Remarks Although the TETRA modulation is enabled with this command, the

RF carrier is not modulated unless you also activate the front panel
Mod On/Off hardkey.

Wideband CDMA Base Band Generator Subsystem—Option 400 [:SOURce]:RADio:WCDMa:TGPP[:BBG])

:BBCLock

Supported E4438C with Option 400

```
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:BBCLock INT[1] | EXT[1]
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:BBCLock?
```

This command selects the baseband generator chip clock source for the radio uplink channel.

***RST** INT

Key Entry **BBG Chip Clock Ext Int**

Remarks Refer to “:BBCLock:EXT:RATE” on page 1020 for the EXT clock rate selections.

:BBCLock:EXT:RATE

Supported E4438C with Option 400

```
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:BBCLock:EXT:RATE X1 | X2 | X4
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:BBCLock:EXT:RATE?
```

This command sets the external clock rate for the baseband generator.

X1 This choice sets an external clock rate that is identical to the chip clock (3.84 MHz).

X2 This choice sets an external clock rate that is two times the rate of the chip clock.

X4 This choice sets an external clock rate that is four times the rate of the chip clock.

***RST** X1

Key Entry **Ext Clock Rate x1 x2 x4**

Remarks This command only applies to uplink.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:APPLY****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:APPLY

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:APPLY?

This command immediately starts the channel coding generation process according to the channel setup and data entered for the downlink physical and transport channels.

Key Entry **Apply Channel Setup**

Remarks If pre-computing is required, then a progress bar will appear on the signal generator's display.

:DLINK:AWGN:CN**Supported** E4438C with Option 400 and 403

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:AWGN:CN <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:AWGN:CN?

This command sets the in band carrier to noise ratio (C/N) value in the AWGN carrier to noise.

RST** -10.2**Range** -20 to 20**Field Entry** C/N value**:DLINK:AWGN:CPOWer*Supported** E4438C with Option 400 and 403

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:AWGN:CPOWer?

This query returns the carrier power of the RF signal.

***RST** 0**Field Entry** C Power

:DLINK:AWGN:ECNO

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:AWGN:ECNO <val>

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:AWGN:ECNO?

This command sets the Ec/No value of the Ec Ref channel.

The variable <val> is expressed in decibels (dB).

***RST** 0

Range -30 to 30

Field Entry Ec/No value

:DLINK:AWGN:ECRPower

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:AWGN:ECRPower?

This query returns the carrier noise power in the Ec Ref channel.

***RST** 0

Field Entry Ec Ref Power

:DLINK:AWGN:ECRef

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:AWGN:ECRef DPCH1 | DPCH2 | PCCPCH | PICH | CPICH

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:AWGN:ECRef?

This command selects the reference used for the Ec/No value.

DPCH1 This choice selects 1 dedicated physical channel.

DPCH2 This choice selects 2 dedicated physical channel.

PCCPCH This choice selects a primary command control physical channel.

PICH This choice selects a paging indicator channel.

CPICH This choice selects a common pilot channel.

***RST** DPCH1

Key Entry DPCH + 1 DPCH + 2 PCCPCH PICH CPICH

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

Remarks White noise is a frequency spectrum that is uniform over a specific frequency band. White noise has equal power per hertz over the specific frequency band.

:DLINK:AWGN:FNBW

Supported E4438C with Option 400 and 403

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:AWGN:FNBW?

This query returns the flat noise bandwidth value.

***RST** +6.1440000E+006

:DLINK:AWGN:NPOWER

Supported E4438C with Option 400 and 403

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:AWGN:NPOWER?

This query returns the in-band noise power portion of the total RF power.

***RST** +0

:DLINK:AWGN:TICPower

Supported E4438C with Option 400 and 403

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:AWGN:TICPower?

This query returns the total in-channel power (carrier with noise) as defined by the 3GPP standard.

***RST** +0

Field Entry Total Pwr

Remarks The total in-channel power is a sum of carrier power and in-channel noise power. Changing the noise related parameters such as C/N, Eb/No, and Eb Ref will cause a recalculation of the total in-channel power.

The maximum value returned by this query depends on the power option that is installed in the signal generator.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:AWGN[:STATe]**

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:AWGN:STATe ON | OFF | 1 | 0

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:AWGN:STATe?

This command enables or disables the additive white gaussian noise (AWGN) physical channel.

***RST** 0

Key Entry Channel State Off On

:DLINK:BBCLock

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:BBCLock INT [1] | EXT [1]

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:BBCLock?

This command selects the baseband generator chip clock source for the channel.

***RST** INT

Key Entry BBG Data Clock Ext Int

:DLINK:CARB:CMODE:CCODE

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:CARB:CMODE:CCODE <val>

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:CARB:CMODE:CCODE?

This command sets the channel code for the chip ARB based dedicated physical channel (DPCH) in compressed mode.

***RST** 6

Range 0–511

Field Entry Channel Code

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])**:DLINK:CARB:CMODE:DATA****Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:CARB:CMODE:DATA PN9 | PN15

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:CARB:CMODE:DATA?

This command sets the dedicated physical channel (DPCH) data pattern in compressed mode (CM).

***RST** PN9**Key Entry** **PN9 PN15**

Remarks The data pattern contains one frame of each normal DPCH frame with a chosen slot structure. CM is enabled via spread factor reduction using a single frame method.

:DLINK:CARB:CMODE:FOFFset**Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:CARB:CMODE:FOFFset <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:CARB:CMODE:FOFFset?

This command sets the frame offset for the dedicated physical channel (DPCH) in compressed mode.

RST** 0**Range** 0–149**Field Entry** Frame Offset**:DLINK:CARB:CMODE:FSTRuct*Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:CARB:CMODE:FSTRuct A | B

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:CARB:CMODE:FSTRuct?

This command selects the frame structure for the downlink compressed mode.

A This choice maximizes the transmission gap length in a compressed frame.

B This choice optimized for power control during a compressed frame.

***RST** A**Key Entry** **A B**

:DLINK:CARB:CMODE:POWER

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:CARB:CMODE:POWER <val>
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:CARB:CMODE:POWER?
```

This command sets the power for the downlink compressed mode.

The variable <val> is expressed in units of decibels (dB).

***RST** +0.00000000E+000

Range -40 to 0

Field Entry Power

:DLINK:CARB:CMODE:PRATio

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:CARB:CMODE:PRATio <val>
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:CARB:CMODE:PRATio?
```

This command sets the playback ratio for the downlink compressed mode.

***RST** 2

Range 0–4096

Field Entry Playback Ratio

Remarks The value that is set represents the number of normal frames played between each compressed frame.

For example: 1:30

30 represents the un-compressed (normal) DPCH frames. The 30 frames will be played and then 1 compressed DPCH frame. The sequence then repeats.

:DLINK:CARB:CMODE:SCTYpe

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:CARB:CMODE:SCTYpe NORMal | RIGHT |
LEFT
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:CARB:CMODE:SCTYpe?
```

This command sets the scramble type for the downlink compressed mode.

NORMal This choice selects scramble codes 0–8191 (16 x 511 + 15 = 8191).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

RIGHT	This choice selects scramble codes 8192–16383 (Normal + 8192).		
LEFT	This choice selects scramble codes 16384–24575 (Normal + 16384).		
*RST	NORM		
Key Entry	Normal	Right	Left

:DLINK:CARB:CMODE:SFORmat

Supported E4438C with Option 400

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :DLINK:CARB:CMODE:SFORmat <val>
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :DLINK:CARB:CMODE:SFORmat?
```

This command sets the slot format value for the dedicated physical channel (DPCH) in compressed mode. This value is used for both compressed and uncompressed frames.

*RST	+11
Range	1–15
Field Entry	Slot Format

:DLINK:CARB:CMODE:SSCodeos

Supported E4438C with Option 400

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :DLINK:CARB:CMODE:SSCodeos <val>
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :DLINK:CARB:CMODE:SSCodeos?
```

This command sets the secondary scramble code offset for the dedicated physical channel (DPCH) in compressed mode.

*RST	+0
Range	0–15
Field Entry	SecScr Code OS

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:CARB:CMODE:TFIRST****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CARB:CMODE:TFIRST <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CARB:CMODE:TFIRST?

This command sets the first slot at which a gap appears.

RST** 7**Range** 0–7**Field Entry** Tfirst**:DLINK:CARB:CMODE:TGL*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CARB:CMODE:TGL <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CARB:CMODE:TGL?

This command sets the number of slots in the gap.

RST** 7**Range** 1–7**Field Entry** Tgl**:DLINK:CARB:CMODE[:STATE]*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CARB:CMODE[:STATE] ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CARB:CMODE[:STATE]?

This command enables or disables the downlink dedicated physical channel (DPCH) in compressed mode.

***RST** 0**Key Entry** Channel State Off On

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:CPICH:CCODE****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CPICH:CCODE?

This query returns the common paging indicator channel (CPICH) channel code value.

RST** +0**Remarks** The channelization code is always expected to be 0.**:DLINK:CPICH:POWer*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CPICH:POWer <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CPICH:POWer?

This command sets the power level for the common paging indicator channel (CPICH). The variable <val> is expressed in units of decibels (dB).

RST** -3.30000000E+000**Range** -40 to 0**Field Entry** Power**:DLINK:CPICH[:STATe]*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CPICH[:STATe]

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CPICH[:STATe]?

This command enables or disables the common paging indicator channel (CPICH).

***RST** 1**Key Entry** Channel State Off On

:DLINK:CRATe

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CRATe <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:CRATe?

This command adjusts the chip rate.

The variable <val> is expressed in units of cycle per second (cps).

***RST** +3.84000000E+006

Range 1000∠4250000

Field Entry Chip Rate

Remarks The chip rate is equivalent to the spreading rate.

:DLINK:DPCH[1]:BALance

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1]:BALance <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1]:BALance?

This command sets DPCH1 power while scaling the power of all available OCNS channels in order to maintain a total power of 0 dB.

The variable <val> is expressed in units of decibels (dB).

Key Entry **DPCH Channel Balance**

Remarks At least one DPCH and one OCNS channel must be on prior to channel balancing. Refer to “:DLINK:DPCH[1]2[:STATe]” on page 1037 and “:DLINK:OCNS[1]2|3|4|5|6|7|8|9|10|11|12|13|14|15|16[:STATe]” on page 1042.

The command [:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1]:BINitalize must be initiated prior to channel balancing.

:DLINK:DPCH[1]:BINitalize

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1]:BINitalize

This command initializes the DPCH1 or DPCH2 power of the OCNS channel balancing.

Remarks To insure proper balancing, this command must be called before the channel balancing.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])**:DLINK:DPCH[1] | 2:ALL[:STATE]****Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:DPCH[1] | 2:ALL[:STATE] ON|OFF | 1 | 0

This command enables or disables both of the downlink dedicated physical channels.

Key Entry **Channel State Off On****Remarks** If the parameter is changed, the apply command must be executed after the change. Refer to “:DLINK:APPLY” on page 1021.

To query the state of the individual channel, refer to “:DLINK:DPCH[1]|2[:STATE]” on page 1037

:DLINK:DPCH[1] | 2:CCODE**Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:DPCH[1] | 2:CCODE <val>
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:DPCH[1] | 2:CCODE?

This command sets the downlink dedicated physical channel (DPCH) code number.

***RST** DPCH 1: 10 DPCH 2: 11**Range** 0–511**Field Entry** Chan Code**Remarks** The channel code is coupled with the slot format and symbol rate. Refer to “:DLINK:DPCH[1]|2:SLOTformat” on page 1034 and “:DLINK:DPCH[1]|2:SRATE” on page 1034.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

:DLINK:DPCH[1] | 2:DATA**Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:DPCH[1] | 2:DATA PN9 | PN15 | FIX4 |
"<file name>" | TGRA | TGRB
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:DPCH[1] | 2:DATA?

This command configures the data pattern for the downlink dedicated physical channel (DPCH).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

TGRA	This choice selects transport channel A.
TGRB	This choice selects transport channel B.
"<file name>"	This variable specifies a data pattern that has been stored in memory.
*RST	PN9
Key Entry	PN9 PN15 FIX4 "User File" Transp Chan A Transp Chan B
Remarks	The data is now independent, on each of the DPCH channels. The data is limited to PN9 and PN15 when the DPCH is in slot format 16. If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to " :DLINK:APPLY " on page 1021.

:DLINK:DPCH[1] | 2:DATA:FIX4

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:DPCH [1] | 2:DATA:FIX4 <val>
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:DPCH [1] | 2:DATA:FIX4?
```

This command sets the data type to a FIX4 pattern for the downlink dedicated physical channel (DPCH). While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

***RST** #B0000

Range: 0–15

Key Entry **FIX4**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to "[:DLINK:APPLY](#)" on page 1021.

:DLINK:DPCH[1] | 2:POWer

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:DPCH [1] | 2:DATA:POWer <val>
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:DPCH [1] | 2:DATA:POWer?
```

This command sets the power level for the downlink dedicated physical channel (DPCH). The variable <val> is expressed in units of decibels (dB).

***RST** -1.02000000E+001

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

Range: –40 to 0

Field Entry Power

:DLINK:DPCH[1] | 2:RCSetup

Supported E4438C with Option 400

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:DPCH [1] | 2:RCSetup REF122 | REF64 | REF144 | REF384 | AMR122 | ISDN

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:DPCH [1] | 2:RCSetup?

This command selects the downlink DCPH reference measurement setup for the transport channel.

REF122	This choice configures the transport channel per the 3GPP TS 34.121 specification for a downlink reference measurement channel with a 12.2 kbps rate.	
REF64	This choice configures the transport channel per the 3GPP TS 34.121 specification for a downlink reference measurement channel with a 64 kbps rate.	
REF144	This choice configures the transport channel per the 3GPP TS 34.121 specification for a downlink reference measurement channel with a 144 kbps rate.	
REF384	This choice configures the transport channel per the 3GPP TS 34.121 specification for a downlink reference measurement channel with a 384 kbps rate.	
AMR122	This choice configures the transport channel per the 3GPP TS 25.944 specification for a downlink reference measurement channel AMR with 12.2 kbps rate.	
ISDN	This choice configures the transport channel as follows: 64 kbps rate, channel 1 with 4 blocks of 640 and channel 2 with 1 block of 148 as per the 3GPP TS 25.944 specification.	

Key Entry	12.2 kbps (34.121)	64 kbps (34.121)
	144 kbps (34.121)	384 kbps (34.121)
	AMR 12.2 (25.944)	UDI ISDN (25.944)

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

:DLINK:DPCH[1] | 2:SLOTformat**Supported** E4438C with Option 400

```
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:DATA:SLOTformat <val>
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:DATA:SLOTformat?
```

This command configures the slot format for the dedicated physical channel (DPCH).

***RST** 0**Range:** 0–16**Field Entry** Slot Format

Remarks The slot format is coupled with the channel code and symbol rate. The transmit power control (TPC), the transport format combination indicator (TFCI), and the Pilot bits are also set as per specification and not displayed.

For a description of slot formats, see the 3GPP Technical Specifications (TS 25.211 v3.10).

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

:DLINK:DPCH[1] | 2:SRATE**Supported** E4438C with Option 400

```
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:SRATE?
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:SRATE?
```

This query returns the symbol rate for the downlink dedicated physical channel.

RST** +7.50000000E+003**:DLINK:DPCH[1] | 2:SSCodeos*Supported** E4438C with Option 400

```
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:SSCodeos <val>
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:SSCodeos?
```

This command sets the secondary scrambling code offset for the downlink dedicated physical channel (DPCH).

***RST** +0**Range:** 0–15

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

Field Entry 2nd Scr Offset

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

:DLINK:DPCH[1] | 2:TFCI:PATtern

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:DPCH[1] | 2:TFCI:PATtern <val>
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:DPCH[1] | 2:TFCI:PATtern?
```

This command sets a 10-bit pattern for the transport format combination indicator (TFCI) for the dedicated physical channel (DPCH).

While the variable <val> is expressed in binary or decimal formats, the query returns only decimal values.

***RST** +0

Range: 0–1023

Field Entry TFCI Pat

Remarks The TFCI is optional and describes the services in use (for example, voice or data). If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

:DLINK:DPCH[1] | 2:TOFFset

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:DPCH[1] | 2:TOFFset <val>
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:DPCH[1] | 2:TOFFset?
```

This command adjusts the timing offset for the dedicated physical channel (DPCH). The variable <val> is expressed in chips.

***RST** +0

Range: 0–149

Field Entry tDPCH Offset

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:DPCH[1] | 2:TPC:NUMSteps****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:TPC:NUMSteps <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:TPC:NUMSteps?

This command sets the number of steps for increasing/decreasing the user's equipment (UE) power.

RST** +1**Range:** 1–80**Field Entry** TPC Steps**Remarks** The command is used with the transmit power control (TPC) patterns up/down (UDOWN), down/up (DUP), all down(DALL), all up (UALL), external (EXT), or user file ("**<file name>**"). Refer to **“:DLINK:DPCH[1]2:TPC:PATtern”**If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to **“:DLINK:APPLY”** on page 1021.**:DLINK:DPCH[1] | 2:TPC:PATtern*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:TPC:PATtern UDOWN | DUP |

UALL | DALL | EXT | "**<file name>**"

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1] | 2:TPC:PATtern?

This command controls the power of the user's equipment (UE). The increase/decrease direction for UE power level changes is determined by the transmit power control (TPC) pattern.

UDOWN This choice repetitively steps up and down the TPC pattern.

DUP This choice repetitively steps down and up the TPC pattern.

UALL This choice consecutively steps up the TPC pattern.

DALL This choice consecutively steps down the TPC pattern.

EXT This choice specifies an external TPC pattern.

"**<file name>**" This choice specifies a user file.***RST** UDOW**Key Entry** **All Down** **All Up** **Down/Up** **Up/Down** **Ext** **User File**

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURce]:RADio:WCDMa:TGPP[:BBG])

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

:DLINK:DPCH[1]|2[:STATe]

Supported E4438C with Option 400

```
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1]|2:ALL[:STATe] ON|OFF|1|0
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1]|2:ALL[:STATe]?
```

This command enables or disables the dedicated physical channels (DPCH1 or DPCH2).

***RST** DPCH1: 1 DPCH2: 0

Key Entry **Channel State Off On**

Remarks If the parameter is changed, the apply command must be executed after the change. Refer to “:DLINK:APPLY” on page 1021.

:DLINK:FILTer

Supported E4438C with Option 400

```
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:FILTer RNYQuist|NYQuist|GAUSSian|
RECTangle|IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|
"<user FIR>"
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:FILTer?
```

This command selects the filter type for the downlink configuration.

IS95 This choice selects a filter that meets the criteria of the IS-95 standard.

IS95_EQ This choice selects a filter which is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard. This filter is only used for IS-95 baseband filtering.

IS95_MOD This choice selects a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.

IS95_MOD_EQ This choice selects a filter which is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.

UGGaussian This choice selects a backwards compatible GSM Gaussian filter (Gaussian filter with a fixed BbT value of 0.300) for the ESG E44xxB Option UN3 or UN4.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

AC4Fm	This choice selects a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.
"<user FIR>"	This variable is any filter file that you have stored into memory.
*RST	RNYQ
Key Entry	Root Nyquist Nyquist Gaussian Rectangle IS-95 IS-95 w/EQ IS-95 Mod IS-95 Mod w/EQ APCO 25 C4FM UN3/4 GSM Gaussian User FIR
Remarks	See “File Name Variables” on page 13 for information on the file name syntax.

:DLINK:FILTer:ALPHa

Supported	E4438C with Option 400
	<code>[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:FILTer:ALPHa <val></code> <code>[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:FILTer:ALPHa?</code>
	Execute this command to change the alpha value for a Nyquist or root Nyquist filter.
*RST	+2.20000000E-001
Range	0-1
Key Entry	Filter Alpha
Remarks	This command is effective only after selection of a root Nyquist or Nyquist filter; it does not affect other types of filters. To change the current filter type, refer to “:DLINK:FILTer” on page 1037 .

:DLINK:FILTer:BBT

Supported	E4438C with Option 400
	<code>[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:FILTer:BBT <val></code> <code>[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:FILTer:BBT?</code>
	Execute this command to change the bandwidth-multiplied-by-bit-time filter parameter value.
*RST	+5.00000000E-001
Range	0.0000-1.0
Key Entry	Filter BbT
Remarks	This command is effective only after selecting a Gaussian filter; it does not affect other types of filters. See “:DLINK:FILTer” on page 1037 to change the filter type.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:FILTer:CHANnel**

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:FILTer:CHANnel EVM|ACP
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:FILTer:CHANnel?
```

Execute this command to optimize a filter for minimized error vector magnitude (EVM) or for minimized adjacent channel power (ACP).

EVM This choice provides the most ideal passband.

ACP This choice improves stopband rejection. This feature only applies to root Nyquist and Nyquist filters.

***RST** EVM

Key Entry **Optimize FIR For EVM ACP**

Remarks To change the current filter type, refer to “:DLINK:FILTer” on page 1037.

:DLINK:MSYNc

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:MSYNc
```

This command generates a one shot trigger pulse to synchronize multiple ESGs. This is a command only; there is no query.

Key Entry **Multi ESG Sync Trigger**

Remarks The trigger pulse will be generated when the user assigns the DRPS42 signal to any output port.

:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:ALL[:STATe]

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16 :ALL [ :STATe ] ON | OFF | 1 | 0
```

This command enables or disables all of the orthogonal channel noise simulator (OCNS) channels.

***RST** +0

Key Entry **Channel State Off On**

Remarks To query the state of the individual channel, refer to “:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16[:STATe]” on page 1042.

:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:CCODE**Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16:CCODE <val>
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16:CCODE?
```

This command sets the channel code number for the downlink orthogonal channel noise simulator (OCNS).

***RST** +24**Range** 0–255**Field Entry** Chan Code

Remarks The channel code is coupled with the symbol rate. Refer to
[“:DLINK:OCNS\[1\] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:SRATE” on page 1041.](#)

:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:DATA**Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16:DATA PN9 | PN15
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16:DATA?
```

This command configures the data pattern for the downlink orthogonal channel noise simulator (OCNS).

RST** PN9**Key Entry** **PN9** **PN15*:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16:POWer****Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16:POWer <val>
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16:POWer?
```

This command sets the power level for the orthogonal channel noise simulator (OCNS).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURce]:RADio:WCDMa:TGPP[:BBG])

The variable <val> is expressed in units of decibels (dB).

***RST** -1.200000000E+001

Range -40 to 0

Field Entry Power

:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:SRATe

Supported E4438C with Option 400

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16 :SRATe <val>
```

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16 :SRATe?
```

This command selects the symbol rate for the orthogonal channel noise simulator (OCNS).

The choices are expressed in units of kilo symbols per second (ksps).

***RST** +1.50000000E+004

Key Entry **7.5 ksps 15 ksps 30 ksps 60 ksps 120 ksps 240 ksps**
480 ksps 960 ksps

Remarks The symbol rate is coupled with the channel code. Refer to
“:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:CCODE” on page 1040.

:DLINK:OCNS[1]|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16:SSCodeos

Supported E4438C with Option 400

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16 :SSCodeos <val>
```

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:OCNS [1] | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 |
13 | 14 | 15 | 16 :SSCodeos?
```

This command sets the secondary scrambling code offset for the orthogonal channel noise simulator (OCNS).

***RST** +0

Range 0–15

Field Entry 2nd Scr Offset

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:OCNS[1|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16]:TOFFset****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16]:TOFFset <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16]:TOFFset?

This command adjusts the timing offset for the orthogonal channel noise simulator (OCNS) channel.

RST** +0**Range:** 0–149**Field Entry** tOCNS Offset**:DLINK:OCNS[1|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16]:STATE*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16]:STATE ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OCNS[1|2|3|4|5|6|7|8|9|10|11|12|13|14|15|16]:STATE?

This command enables or disables the orthogonal channel noise simulator (OCNS) channel.

RST** +0**Field Entry** On/Off**:DLINK:OOSTest[:STATE]*Supported** E4438C with Option 400 and 403

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OOSTest[:STATE] ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OOSTest[:STATE]?

This command enables or disables the Out-of-Sync-Test mode.

RST** 0**Key Entry** **Out-of-Sync Test Off On*Remarks** When **Compressed Mode Off On** is set to On, Out-of-Sync Test mode cannot be enabled.When **Out-of-Sync Test Off On** is set to On, ALC is automatically disabled; when **Out-of-Sync Test Off On** is set to Off, **ALC Off On** is automatically enabled.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

:DLINK:OOSTest:DTXGate:POLarity

Supported E4438C with Option 400 and 403

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OOSTest:DTXGate:
POLarity POSitive|NEGative
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:OOSTest:DTXGate:POLarity?
```

This command sets the multiple ESG synchronization trigger signal polarity.

***RST** POS

Key Entry **DPCH1 DTX-Gate Trigger Polarity Neg Pos**

:DLINK:PADJust

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PADJust EQUal|SCALE
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PADJust?
```

This command adjusts the code domain power levels of all downlink channels.

EQUal This choice will adjust all channel powers to equal power settings.

SCALE This choice will scale the channel power levels so that the sum of the powers are equal to 0 dB.

***RST** EQU

Key Entry **Equal Powers Scale To 0dB**

:DLINK:PCCPch:BCHData

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PCCPch:BCHData PN9|PN15|FIX4|
"<file name>"|TRANspch
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PCCPch:BCHData?
```

This command sets the broadcast channel (BCH) data format that will be transmitted on the physical common control physical channel (PCCPCH).

TRANspch This choice selects a dedicated transport channel data pattern.

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** FIX4

Key Entry **PN9 PN15 FIX4 User File Transport CH**

:DLINK:PCCPch:BCHData:FIX4**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PCCPch:BCHData:FIX4 <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PCCPch:BCHData:FIX4?

This command sets a fixed 4-bit binary data pattern for the primary common control physical channel (PCCPCH).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

RST** #B0000**Range** 0–15**Key Entry** **FIX4*:DLINK:PCCPch:CCODE****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PCCPch:CCODE <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PCCPch:CCODE?

This command sets the primary common control physical channel (PCCPCH) code to the desired code number.

RST** +1**Range** 0–255**Field Entry** Channel Code**:DLINK:PCCPch:POWer*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PCCPch:POWer <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PCCPch:POWer?

This command sets the power level for the primary common control physical channel (PCCPCH). The variable <val> is expressed in units of decibels (dB).

***RST** -5.30000000E+000**Range** -40 to 0**Field Entry** Power

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])**:DLINK:PCCPch[:STATE]****Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:PCCPch[:STATE] ON|OFF|1|0

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:PCCPch[:STATE] ?

This command enables or disables the primary common control physical channel (PCCPCH).

RST** 1**Key Entry** Channel State Off On**:DLINK:PICH:CCODE*Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:PICH:CCODE <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:PICH:CCODE?

This command sets the paging indicator channel (PICH) code to the desired code number.

RST** +3**Range** 0–255**Field Entry** Channel Code**:DLINK:PICH:DATA*Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:PICH:DATA PN9|PN15|FIX4|

<file name>"

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:PICH:DATA?

This command configures the data pattern for the downlink paging indicator channel (PICH).

<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** PN9**Key Entry** **PN9** **PN15** **FIX4** **User File**

:DLINK:PICH:DATA:FIX4

Supported E4438C with Option 400

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:PICH:DATA:FIX4 <val>

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:PICH:DATA:FIX4?

This command sets a fixed 4-bit data pattern to be transmitted on a paging indicator channel (PICH).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

***RST** #B0000

Range 0–15

Key Entry **FIX4**

:DLINK:PICH:PIBits

Supported E4438C with Option 400

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:PICH:PIBits?

This query returns the number of bits in the paging indicator field.

***RST** +288

Field Entry PI Bits

:DLINK:PICH:PINDicator

Supported E4438C with Option 400

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:PICH:PINDicator?

This query returns the number of paging indicator fields per frame.

***RST** +144

Field Entry Paging Indicator

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:PICH:POWer****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:POWer <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:POWer?

This command sets the power level of the paging indicator channel (PICH). The variable <val> is expressed in units of decibels (dB)

RST** -8.300000000E+000**Range** -40 to 0**Field Entry** Power**:DLINK:PICH[:STATe]*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH[:STATe] ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH[:STATe]?

This command enables or disables the paging indicator channel (PICH).

RST** 0**Key Entry** Channel State Off On**:DLINK:POLarity*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:POLarity NORMAL|INVERTed

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:POLarity?

This command selects the phase polarity of the downlink signal.

NORMAL This choice selects normal polarity.

INVERTed This choice inverts the internal Q signal.

***RST** NORM**Key Entry** Phase Polarity Normal Invert

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:PSCH:POWer**

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PSCH:POWer <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PSCH:POWer?

This command sets the power level for the primary synchronization physical channel (PSCH).

The variable <val> is expressed in units of decibels (dB).

***RST** -8.30000000E+000

Range -40 to 0

Field Entry Power

:DLINK:PSCH[:STATe]

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PSCH[:STATe] ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:PSCH[:STATe]?

This command enables or disables the primary synchronization physical channel (PSCH).

***RST** 1

Field Entry PSCH State

:DLINK:RPANel:INPut:ALTPower

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:RPANel:INPut:ALTPower?

This query returns the type of signal at the alternate power input (Alt power in AUX I/O connector pin#16) for the dedicated physical channel (DPCH) mode.

***RST** NONE

Remarks When **Compressed Mode Off On** is set to On, Compressed-mode stop-trigger Compressed-mode stop-trigger signal is assigned to pin 16 of the rear panel AUX I/O connector. For more information about the rear panel AUX I/O connector configuration, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

:DLINK:RPANel:INPut:BBGRef

Supported E4438C with Option 400

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:RPANel :INPut :BBGRef?

This query returns the type of signal at the baseband generator reference input (BASEBAND GEN REF IN, rear panel connector) for the dedicated physical channel (DPCH) mode.

***RST** CCL

Remarks The signal name is baseband generator chip clock (CCL). For more information about the rear panel connector configuration, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:DLINK:RPANel:INPut:BGATe

Supported E4438C with Option 400

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:RPANel :INPut :BGATe?

This query returns the type of signal at the gate burst (BURST GATE IN, rear panel connector) for the dedicated physical channel (DPCH) mode.

***RST** SFNR

Remarks System Frame Number Reset (SFNR) is used for synchronization in a two ESG setup. This signal is used to tell where the frame starts.

:DLINK:RPANel:INPut:PTRigger1

Supported E4438C with Option 400

[:SOURCE] :RADIO:WCDMA:TGPP [:BBG] :DLINK:RPANel :INPut :PTRigger1?

This query returns the type of signal at the pattern trigger input 1 (PATT TRIG IN, rear panel connector) for the dedicated physical channel (DPCH) mode.

***RST** MSTI

Remarks When **Compressed Mode Off On** is set to On, Compressed-mode start-trigger (CSTT) signal is assigned to the rear panel PATT TRIG IN connector; when **Out-of-Sync Test Off On** is set to On, DPCH1 DTX-Gate (DDTX) signal is assigned to the rear panel PATT TRIG IN connector.

Multiple ESG Synchronization Trigger In (MSTI) signal is used to synchronize signals from two ESGs that have different coding to simulate transmit diversity.

:DLINK:RPANel:INPut:PTRigger2**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:RPANel:INPut:PTRigger2?

This query returns the type of signal at the pattern trigger input 2 (PATT TRIG IN 2, AUX I/O connector pin#17) for the dedicated physical channel (DPCH) mode.

RST** TPCB**Remarks** Transmit Power Control Bit (TPCB) signal is used to control the DPCH TPC bit.**:DLINK:RPANel:OUTPut:DCLock*Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:RPANel:OUTPut:DCLock
DRPS0|DRPS4|DRPS5|DRPS6|DRPS10|DRPS11|DRPS13|DRPS20|DRPS21|DRPS22|
DRPS23|DRPS24|DRPS25|DRPS26|DRPS28|DRPS30|DRPS32|DRPS33|DRPS34|DRPS35|
DRPS36|DRPS37|DRPS38|DRPS39|DRPS40|DRPS41|DRPS42
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:RPANel:OUTPut:DCLock?
```

This command assigns a signal to the data clock output at the selected rear panel AUX I/O connector pin#6. Refer to [Table 9-3 on page 1050](#) for command parameters for the variable and output signal names.

Table 9-3 Downlink Rear Panel Signal (DRPS) Output Type

Command Parameter	Signal Out
DRPS0	NONE
DRPS4	3.84 MHz chip clock
DRPS5	SFN reset signal
DRPS6	SFN sync pulse
DRPS10	SCH slot pulse
DRPS11	10ms Frame pulse
DRPS13	80ms Frame pulse
DRPS20	DPCH data clock with DTX
DRPS21	DPCCH TPC data clock

Table 9-3 Downlink Rear Panel Signal (DRPS) Output Type

Command Parameter	Signal Out
DRPS22	DPCCH TFCI data clock
DRPS23	DPCCH Pilot data clock
DRPS24	DPCH data stream
DRPS25	DPCH TimeSlot pulse
DRPS26	DPCH 10ms Frame Pulse
DRPS28	DPCH data clock
DRPS30	DPDCH data clock w/oDTX
DRPS32	DPCH comp Frm Indicator
DRPS33	DPCH Gap Indicator
DRPS34	PICH data clock
DRPS35	PICH data
DRPS36	PICH TimeSlot pulse
DRPS37	PICH 10ms FramePulse
DRPS38	P-CCPCH data clock
DRPS39	P-CCPCH data
DRPS40	DPCH Chip-ARB-frame-pulse
DRPS41	DPCH TPC-bits-out
DRPS42	Multi-ESG Sync Trigger Out

*RST

RPS0

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Key Entry	NONE	3.84MHz chip-clk (DRPS4)	SFN reset-signal (DRPS5)
	SFN sync-pulse (DRPS6)	SCH slot-pulse (DRPS10)	
	10ms Frame Pulse (DRPS11)	80ms Frame Pulse (DRPS13)	
	DPDCH data-clk with DTX (DRPS20)	DPCCH TPC data-clk (DRPS21)	
	DPCCH TFC I data-clk (DRPS22)	DPCCH Pilot data-clk (DRPS23)	
	DPCH data stream (DRPS24)	DPCH TimeSlot pulse (DRPS25)	
	DPCH 10ms Frame-Pulse (DRPS26)	DPCH data-clk (0) (DRPS28)	
	DPDCH data-clk withoutDTX (DRPS30)		
	DPCH Compressed Frame Indicator (DRPS32)		
	DPCH Gap Indicator (DRPS33)	PICH data-clk (DRPS34)	
	PICH data (DRPS35)	PICH TimeSlot Pulse (DRPS36)	
	PICH 10ms FramePulse (DRPS37)	P-CCPCH data-clk (DRPS38)	
	P-CCPCH data (DRPS39)	DPCH ChipARB FramePulse (DRPS40)	
	DPCH TPC-Bit Out (DRPS41)	Mlt-ESG-Sync Trigger-Out (DRPS42)	
Remarks	For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the <i>E4428C/38C ESG Signal Generators User's Guide</i> .		

:DLINK:RPANel:OUTPut:DOUT

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:RPANel :OUTPut :DOUT
DRPS0 | DRPS4 | DRPS5 | DRPS6 | DRPS10 | DRPS11 | DRPS13 | DRPS20 | DRPS21 | DRPS22 |
DRPS23 | DRPS24 | DRPS25 | DRPS26 | DRPS28 | DRPS30 | DRPS32 | DRPS33 | DRPS34 | DRPS35 |
DRPS36 | DRPS37 | DRPS38 | DRPS39 | DRPS40 | DRPS41 | DRPS42
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:RPANel :OUTPut :DOUT?
```

This command assigns a signal to the data output at the selected rear panel AUX I/O connector pin#7. Refer to [Table 9-3 on page 1050](#) for command parameters and output signal names.

***RST** RPS0

Key Entry Refer to **Key Entry** on [page 1052](#).

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

:DLINK:RPANel:OUTPut:EVENT1

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:RPANel :OUTPut :EVENT1
DRPS0 | DRPS4 | DRPS5 | DRPS6 | DRPS10 | DRPS11 | DRPS13 | DRPS20 | DRPS21 | DRPS22 |
DRPS23 | DRPS24 | DRPS25 | DRPS26 | DRPS28 | DRPS30 | DRPS32 | DRPS33 | DRPS34 | DRPS35 |
DRPS36 | DRPS37 | DRPS38 | DRPS39 | DRPS40 | DRPS41 | DRPS42
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:RPANel :OUTPut :EVENT1?
```

This command assigns a signal to the EVENT 1 rear panel output connector. Refer to [Table 9-3 on page 1050](#) for command parameters and output signal names.

***RST** RPS0

Key Entry Refer to **Key Entry** on [page 1052](#).

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:DLINK:RPANel:OUTPut:EVENT2

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:RPANel :OUTPut :EVENT2
DRPS0 | DRPS4 | DRPS5 | DRPS6 | DRPS10 | DRPS11 | DRPS13 | DRPS20 | DRPS21 | DRPS22 |
DRPS23 | DRPS24 | DRPS25 | DRPS26 | DRPS28 | DRPS30 | DRPS32 | DRPS33 | DRPS34 | DRPS35 |
DRPS36 | DRPS37 | DRPS38 | DRPS39 | DRPS40 | DRPS41 | DRPS42
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:RPANel :OUTPut :EVENT2?
```

This command assigns a signal to the EVENT 2 rear panel output connector. Refer to [Table 9-3 on page 1050](#) for command parameters and output signal names.

***RST** RPS0

Key Entry Refer to **Key Entry** on [page 1052](#).

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:RPANel:OUTPut:EVENT3****Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:RPANel:OUTPut:EVENT3
DRPS0|DRPS4DRPS5|DRPS6|DRPS10|DRPS11|DRPS13|DRPS20|DRPS21|DRPS22|
DRPS23|DRPS24|DRPS25|DRPS26|DRPS28|DRPS30|DRPS32|DRPS33|DRPS34|DRPS35|
DRPS36|DRPS37|DRPS38|DRPS39|DRPS40|DRPS41|DRPS42
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:RPANel:OUTPut:EVENT3?
```

This command assigns a signal to the EVENT 3 at the selected rear panel AUX I/O connector pin#19. Refer to [Table 9-3 on page 1050](#) for command parameters and output signal names.

RST** RPS0**Key Entry** Refer to **Key Entry** on [page 1052](#).**Remarks** For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.**:DLINK:RPANel:OUTPut:EVENT4*Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:RPANel:OUTPut:EVENT4
DRPS0|DRPS4|DRPS5|DRPS6|DRPS10|DRPS11|DRPS13|DRPS20|DRPS21|DRPS22|
DRPS23|DRPS24|DRPS25|DRPS26|DRPS28|DRPS30|DRPS32|DRPS33|DRPS34|DRPS35
DRPS36|DRPS37|DRPS38|DRPS39|DRPS40|DRPS41|DRPS42
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:RPANel:OUTPut:EVENT4?
```

This command assigns a signal to the EVENT 4 at the selected rear panel AUX I/O connector pin#18. Refer to [Table 9-3 on page 1050](#) for command parameters and output signal names.

***RST** RPS0**Key Entry** Refer to **Key Entry** on [page 1052](#).**Remarks** For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

:DLINK:RPANel:OUTPut:SSYNc**Supported** E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:RPANel:OUTPut:SSYNc
DRPS0|DRPS4|DRPS5|DRPS6|DRPS10|DRPS11|DRPS13|DRPS20|DRPS21|DRPS22|
DRPS23|DRPS24|DRPS25|DRPS26|DRPS28|DRPS30|DRPS32|DRPS33|DRPS34|DRPS35|
DRPS36|DRPS37|DRPS38|DRPS39|DRPS40|DRPS41|DRPS42
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:RPANel:OUTPut:SSYNc?
```

This command assigns a signal to the SYM SYNC OUT at the selected rear panel AUX I/O connector pin#5. Refer to [Table 9-3 on page 1050](#) for command parameters and output signal names.

***RST** RPS0**Key Entry** Refer to **Key Entry** on [page 1052](#).

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:DLINK:SCH[:STATe]**Supported** E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:SCH[:STATe] ON|OFF|1|0
```

This command enables or disables the primary and secondary synchronization channel (SSCH).

***RST** 1**Key Entry** **Channel State Off On**

Remarks To query the state of the individual channel, refer to “:DLINK:PSCH[:STATe]” on [page 1048](#) and “:DLINK:SSCH[:STATe]” on [page 1057](#).

:DLINK:SCRamblecode**Supported** E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:SCRamblecode <val>
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:SCRamblecode?
```

This command selects the scramble code number.

***RST** +0**Range** 0–511**Field Entry** Scrambling Code

:DLINK:SDElay**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:SDElay <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:SDElay?

This command sets the delay of the system frame number (SFN) synchronization when a Multi-ESG-Sync Trigger-In signal is received. The variable <val> is expressed in unit of chips.

***RST** +0.00000000E+000**Range** 0–38399**Field Entry** Sync Delay

Remarks This function provides the capability of Inter-Cell Soft Handover test as described in TS.34.121 7.7.1 of the 3GPP standard. The test requires two base stations that generate the same signal but have a 10 chip timing offset. The two base stations are simulated by two ESGs and Sync Delay is the synchronization delay between the ESGs.

:DLINK:SSCH:POWer**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:SSCH:POWer <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:SSCH:POWer?

This command sets the power level for the secondary synchronization channel (SSCH). The variable <val> is expressed in units of decibels (dB).

RST** –8.30000000E+000**Range** –40 to 0**Field Entry** SSCH Power**:DLINK:SSCH:SSGRoup*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:SSCH:SSGRoup?

This command query returns the secondary scramble code group for the secondary synchronization channel (SSCH).

***RST** +0**Field Entry** SSCH 2nd Scramble Group

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:SSCH[:STATe]****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:SSCH[:STATe] ON|OFF|1|0

This command enables or disables the secondary synchronization channel (SSCH).

RST** 1**Field Entry** SSCH State**:DLINK:TGAP:FSTRUCT*Supported** E4438C with Option 400

[:SOURCE]:RADio[1]|2|3|4:WCDMa:TGPP[:BBG]:DLINK:TGAP:FSTRUCT A|B

[:SOURCE]:RADio[1]|2|3|4:WCDMa:TGPP[:BBG]:DLINK:TGAP:FSTRUCT?

This command selects the compressed frame structure for the transmission gaps.

A The pilot field of the last slot in the transmission gap is transmitted and transmission is turned off during the rest of the transmission gap.

B The TPC field of the first slot and the pilot field of the last slot in the transmission gap are transmitted and transmission is turned off during the rest of the transmission gap.

RST** A**Field Entry** Frame Struct**:DLINK:TGAP:POFFset*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:POFFset <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:POFFset?

This command specifies the amount of power to be increased when the data is being compressed for the transmission gap power offset.

The variable <val> is expressed in units of decibels (dB).

***RST** +0.00000000E+000**Range** 0–6**Field Entry** PwrOffs

:DLINK:TGAP:PSI[1]:CFN

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:TGAP:PSI [ 1 ] :CFN <val>
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:TGAP:PSI [ 1 ] :CFN?
```

This command sets the connection frame number (CFN) for the first radio of the first pattern 1.

***RST** 0

Range 1–255

Field Entry TGCFN

Remarks The connection frame number (CFN) is counted internally relative to the system sync signal.

:DLINK:TGAP:PSI[1]:CMMethod

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:TGAP:PSI [ 1 ] :CMMehtod SF2 | PUNcture
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :DLINK:TGAP:PSI [ 1 ] :CMMethod?
```

This command selects the compressed mode (CM) method.

SF2 This choice selects a compressed mode method that reduces the spread factor (SF) by 2. This is done by reducing the spreading factor in half. When the dedicated physical data channel's (DPDCH) symbol rate is 960 kbps, the frame is not compressed because it uses the lowest SF value and cannot be reduced.

PUNcture This choice selects a compressed mode method that punctures the convolutional encoder to a lower rate which reduces the number of symbols to be transmitted.

***RST** SF2

Key Entry **SF2** **Puncture**

Remarks To edit the parameters for this command using the ESG front panel keys, highlight the **CM Method** field and select either **SF2** or **Puncture** softkeys.

If the parameter is changed, the apply command must be executed after the change. Refer to “:DLINK:APPLY” on page 1021.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])

:DLINK:TGAP:PSI[1]:D**Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:D <val>

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:D?

This command sets the transmission gap distance.

RST** +0**Range** 0, 15–269**Field Entry** TGD**Remarks** This command specifies the number of slots between the starting slot of two consecutive transmission gaps within a gap pattern.**:DLINK:TGAP:PSI[1]:L1*Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:L1 3|4|5|7|10|14

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:L1?

This command specifies the length of the first transmission gap (TGL1).

The length is expressed in number of slots.

RST** 7**Field Entry** TGL1**:DLINK:TGAP:PSI[1]:L2*Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:L2 3|4|5|7|10|14|OMITted

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:L2?

This command specifies the length of the second transmission gap (TGL2).

The length is expressed in number of slots.

RST** OMIT**Field Entry** TGL2**Key Entry** **Omitted*Remarks** When OMITted is selected, TGL2 = TGL1.

:DLINK:TGAP:PSI[1]:PL1**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:PL1 <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:PL1?

This command specifies the duration of the transmission gap pattern length 1 (TGPL1).

The variable <val> is expressed in number of frames.

RST** +2**Range** 1–144**Field Entry** TGPL1**:DLINK:TGAP:PSI[1]:PL2*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:PL2 <val>|OMITted

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:PL2?

This command specifies the duration of the transmission gap pattern length 2 (TGPL2).

The variable is expressed in number of frames.

RST** OMIT**Range** 1–144**Key Entry** **Omitted*Remarks** When OMITted is selected, TGPL2 = TGPL1.**:DLINK:TGAP:PSI[1]:PRC****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:PRC <val>|INFIinity

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:PSI[1]:PRC?

This command sets the transmission gap pattern repetition count.

RST** 1**Range** 1–511**Key Entry** **Infinity*Field Entry** TGPRC

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

Remarks The pattern repetition count (PRC) sets the number of transmission gap patterns within the transmission gap pattern sequence. When INFINITY is selected, the PRC will continue indefinitely.

:DLINK:TGAP:PSI[1]:PS

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:TGAP:PSI[1]:PS ACTIVE|INACTIVE
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:TGAP:PSI[1]:PS?
```

This command sets the transmission gap pattern status.

ACTIVE This choice activates the compressed mode.

INACTIVE This choice sets the compressed mode to inactive.

***RST** INAC

Key Entry **Active** **Inactive**

:DLINK:TGAP:PSI[1]:SN

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:TGAP:PSI[1]:SN <val>
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:TGAP:PSI[1]:SN?
```

This command specifies the timeslot number of the first transmission gap within the first radio frame.

***RST** +11

Range 0–14

Field Entry TGSN

:DLINK:TGAP:RPARAMeter

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:TGAP:RPAMeter DREF11|DREF12|
DREF21|DREF22
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK:TGAP:RPAMeter?
```

This command sets the downlink reference compressed mode parameters as defined in 3GPP standard.

DREF11 This choice sets the reference parameter to 1.1.

DREF12 This choice sets the reference parameter to 1.2.

DREF21 This choice sets the reference parameter to 2.1.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

DREF22	This choice sets the reference parameter to 2.2.			
*RST	CUST			
Key Entry	DL Reference 1.1	DL Reference 1.2	DL Reference 2.1	DL Reference 2.2
Remarks	The query returns CUSTom when the parameters are set individually.			

:DLINK:TGAP:SCFN

Supported	E4438C with Option 400			
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:SCFN <val>			
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:SCFN?			
	This command sets the stop connection frame number (CFN) when the stop trigger is used.			
	When the stop trigger is received at the signal generator, the compressed mode will finish even if the transmission gap pattern repetition count (TGPRC) is still remaining.			
*RST	+0			
Range	0–255			
Field Entry	SCFN			
Remarks	The compressed mode stop trigger must be executed for this command to work. Refer to, “:DLINK:TGAP:STOP:TRIGger” on page 1063.			

:DLINK:TGAP:START:TRIGger

Supported	E4438C with Option 400			
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:START:TRIGger			
	This command starts the signal generator compressed pattern transmission. Compressed pattern transmission begins with the specified transmission gap connection frame number (TGCFN).			
Key Entry	Compressed Mode Start Trigger			

:DLINK:TGAP:START:TRIGger:POLarity

Supported	E4438C with Option 400			
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:START:TRIGger:POLarity			
	POSitive NEGative			
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:START:TRIGger:POLarity?			
	This command sets the compressed mode start trigger polarity. The compressed pattern transmission begins when this trigger is received.			

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

POSitive	This choice sets the trigger to start when the trigger signal is high.
NEGative	This choice sets the trigger to start when the trigger signal is low.
*RST	POS
Key Entry	Comp Mode Start Trigger Polarity Pos Neg

:DLINK:TGAP:STOP:TRIGger

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:STOP:TRIGger

This command stops the signal generator compressed pattern transmission. Compressed pattern transmission begins with the specified transmission gap connection frame number (TGCFN).

Key Entry **Compressed Mode Stop Trigger**

:DLINK:TGAP:STOP:TRIGger:POLarity

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:STOP:TRIGger:POLarity
POSitive|NEGative

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP:STOP:TRIGger:POLarity?

This command sets the compressed mode stop trigger polarity. The compressed pattern transmission stops when this trigger is received.

POSitive	This choice sets the trigger to stop when the trigger signal is high.
NEGative	This choice sets the trigger to stop when the trigger signal is low.
*RST	POS
Key Entry	Comp Mode Stop Trigger Polarity Pos Neg

:DLINK:TGAP[:STATe]

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP[:STATe] 1|0|ON|OFF
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TGAP[:STATe] ?

This command enables or disables the transmission gap compressed mode.

*RST	0
Key Entry	Compressed Mode On Off

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks When compressed mode is enabled, DPCH2 is automatically disabled and can't be enabled.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

:DLINK:TSETup

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :DLINK:TSETup REFSensitivity | MAXinput | ACS | BLOcking | SPURious | INTermod | PERFreq

This command configures the test setup for the downlink channels.

REFSensitivity This choice selects reference sensitivity. This is the minimum receiver input power measured at the antenna connector.

MAXinput This choice selects maximum input interference. The receiver is stressed with high-levels of interference from unwanted signals.

ACS This choice selects adjacent channel selectivity (ACS). This is the receiver ability to receive a wanted signal at the assigned channel frequency with the presence of adjacent signals.

ACS is the ratio of the receiver filter attenuation (on the assigned channel) to the receive filter attenuation on the adjacent channel(s).

BLOcking This choice selects the blocking characteristics. This is a measure of the receiver ability to receive a wanted signal at the assigned channel frequency in the presence of an unwanted interferer on frequencies other than those of the adjacent channels.

SPURious This choice selects spurious emission power. The emissions are generated or amplified by a receiver.

INTermod This choice selects intermodulation. Third order intermodulation (TIO) or higher mixing of the two interfering RF signals signal in the band of the desired channel.

PERFreq This choice selects the performance requirement of the dedicated channel. This is a static propagation conditions that is determined by the maximum block error rate (BLER) allowed when the receiver input signal is at a specified Eb/No limit.

Key Entry	Ref Sensitivity	Max Input	ACS	Blocking
	Spurious Response	Intermod	Performance Req	

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK:TXDV****Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TXDV NONE|OANT1|OANT2|OANTO1|OANTO2
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK:TXDV?

This command selects the transmit diversity mode of the downlink signal.

NONE This choice disables the transmit diversity mode.

OANT1 This choice selects a Transmit Diversity Openloop Antenna 1 mode.

OANT2 This choice selects a Transmit Diversity Openloop Antenna 2 mode.

OANTO1 This choice selects a Transmit Diversity Openloop Antenna 1 mode with the SCH TSTD (Synchronization Channel Transmit Switched Time Diversity) off.

OANTO2 This choice selects a Transmit Diversity Openloop Antenna 2 mode with the SCH TSTD (Synchronization Channel Transmit Switched Time Diversity) off.

***RST** NONE**Field Entry** TX Diversity**Key Entry** **None** **OpenLoop Ant1** **OpenLoop Ant2**
OpenLoop Ant1 SCH TSTD OFF **OpenLoop Ant2 SCH TSTD OFF**

:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:BLKSize**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:BLKSize <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:BLKSize?

This command sets the block size (BLKSize) for the selected dedicated transport channel (DCH). The transport channel position affects the behavior of this command as described below.

Transport Channel Mode	Signal Generator Behavior
FLEXible	Changing the block size causes the signal generator to recalculate the block set size. The block size, number of blocks and the block set size values are interdependent as shown in the following formula: $\text{block size} = \text{block set size} \div \text{number of blocks}$
FIXed	There are two signal generator behaviors in this mode: <ul style="list-style-type: none"> change the block size to zero, and it remains zero regardless of the block set size and number of blocks values change the block size to a value other than zero, and the signal generator recalculates the block size as a quotient of the block set size and the number of blocks (block set size \div number of blocks), ignoring the value entered by the command

***RST** 20**Range** 0–5000**Field Entry** Blk Size

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

For information on the number of blocks and block set size commands, see “:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:NBLocks” on page 1071, and “:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:BSSize” on page 1067.

Refer to the “:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:POSITION” command on page 1072 for information on setting the transport channel position.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:BPFFrame****Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH [1] | 2 | 3 | 4 | 5 | 6 :
BPFFrame?

This query returns the number of bits per frame for the selected dedicated transport channel (DCH).

RST** 60**Field Entry** Bits/Frame**:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:BRATe*Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH [1] | 2 | 3 | 4 | 5 | 6 :
BRATe?

This query returns the block rate for the selected dedicated transport channel (DCH).

RST** 20**:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:BSSize*Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH [1] | 2 | 3 | 4 | 5 | 6 :
BSSize <val>
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH [1] | 2 | 3 | 4 | 5 | 6 :
BSSize?This command sets the block set size (BSSize) for the selected dedicated transport channel (DCH).
The transport channel position affects the behavior of this command as described below.**Transport
Channel Mode****Signal Generator Behavior**

FLEXible	This command has no effect on the block size value. The block size value changes only when there is a value change in the number of blocks or the block size according to the following formula:
----------	--

$$\text{block set size} \geq \text{block size} \times \text{number of blocks}$$

Transport Channel Mode	Signal Generator Behavior
FIXed	<p>Changing the block set size value automatically changes the block size, so that the block set size approximates or is the product of the block size and number of blocks values:</p> $\text{block set size} \geq \text{block size} \times \text{number of blocks}$ <p>The change in the block set size value generates a settings conflict error, which the signal generator corrects when it recalculates the block size value.</p>
*RST	20
Range	0–200000
Field Entry	Blk Set Size
Remarks	<p>Refer to the “:DLINK[:TGRoup [A] B]:DCH[1] 2 3 4 5 6:POSition” command on page 1072 for information on setting the transport channel position.</p> <p>For information on the number of blocks and block size commands, see “:DLINK[:TGRoup [A] B]:DCH[1] 2 3 4 5 6:NBLocks” on page 1071, and “:DLINK[:TGRoup [A] B]:DCH[1] 2 3 4 5 6:BLKSize” on page 1066.</p> <p>If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.</p>

:DLINK[:TGRoup [A]|B]:DCH[1]|2|3|4|5|6:CODE

Supported	E4438C with Option 400
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] B]:DCH[1] 2 3 4 5 6:CODE HCONv TCONv TURBo NONE
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] B]:DCH[1] 2 3 4 5 6:CODE?
	This command selects the encoder type.
HCONv	This choice selects coding with the 1/2 rate convolutional encoder.
TCONv	This choice selects coding with the 1/3 rate convolutional encoder.
TURBo	This choice selects coding with the turbo coder.
NONE	This choice selects no coding.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

*RST	HCON
Key Entry	1/2 Conv 1/3 Conv Turbo None
Remarks	If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:CRC

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup[A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:
CRC <val>
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup[A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:
CRC?
```

This command sets the number of cyclic redundancy check (CRC) bits for the dedicated transport channel (DCH).

*RST	8
Field Entry	CRC Size
Remarks	If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup[A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:
DATA PN9 | FIX4 | "<file name>"
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup[A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:
DATA?
```

This command configures the data for the downlink dedicated transport channel (DCH) selected.

"<file name>" This variable specifies a data pattern that has been stored in memory.

*RST	PN9
Key Entry	PN9 FIX4 "<User File>"
Remarks	If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])**:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:EINSErt****Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:EINSErt BLER|BER|NONE

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:EINSErt?

This command selects the error insertion mode.

BLER This choice selects a block error rate (BLER) mode.**BER** This choice selects a bit error rate (BER) mode.**NONE** This choice selects no BLER or BER mode (no error blocks or bit are inserted)***RST** NONE**Key Entry** **BLER** **BER** **None****:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:FIX4****Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:FIX4 <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:FIX4?

This command sets a fixed data type to be transmitted on the selected downlink dedicated transport channel (DCH).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

RST** #B0000**Range** 0–15**Key Entry** **FIX4*Remarks** If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])

:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:NBLocks**Supported** E4438C with Option 400[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:
NBLocks <val>[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:
NBLocks?

This command sets the number of blocks (NBLocks) transmitted by the selected downlink dedicated transport channel (DCH). The transport channel position affects the behavior of this command as described below.

Transport Channel Mode	Signal Generator Behavior
FLEXible	<p>Changing the number of blocks causes the signal generator to recalculate the block set size; <i>block size</i> remains constant. The equation is as follows:</p> $\text{number of blocks} \leq \text{block set size} \div \text{block size}$
FIXed	<p>Changing the number of blocks causes the signal generator to recalculate the block size; <i>block set size</i> remains constant. Changing the number of blocks also causes the ESG to generate a settings conflict error that is corrected when the signal generator recalculates the block size. The equation is as follows:</p> $\text{number of blocks} \leq \text{block set size} \div \text{block size}$
*RST	1
Range	1–64
Field Entry	# of Blocks
Remarks	<p>Refer to the “:DLINK[:TGRoup [A] B]:DCH[1] 2 3 4 5 6:POsition” command on page 1072 for information on setting the transport channel position.</p> <p>For information on the block size (BLKSize) and block set size (BSSize) commands, see “:DLINK[:TGRoup [A] B]:DCH[1] 2 3 4 5 6:BLKSize” on page 1066 and “:DLINK[:TGRoup [A] B]:DCH[1] 2 3 4 5 6:BSSize” on page 1067.</p> <p>If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.</p>

:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:POSITION**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:POSITION FLEXible|FIXed

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:POSITION?

This command selects a position for the data transmitted by the downlink dedicated transport channel (DCH).

The transport position selection, flexible or fixed, determines how the three block settings, block set size, block size, and number of blocks, for the transport channel are determined.

FLEXible This choice allows the signal generator to automatically set the block set size. The relationship between block set size, block size, and number of blocks is as follows:
 $\text{block set size} = \text{number of blocks} \times \text{block size}$

FIXed This choice allows a user-defined block set size. The relationship between block set size, block size, and number of blocks is as follows:
 $\text{block set size} \geq \text{number of blocks} \times \text{block size}$

***RST** FLEX**Key Entry** **Transp Position Flexible Fixed**

Remarks For more information on the block parameters, refer to the “:DLINK[:TGRoup [A]|B]:DCH[1]|2|3|4|5|6:NBLocks” command on [page 1072](#), the “:DLINK[:TGRoup [A]|B]:DCH[1]|2|3|4|5|6:BSSize” command on [page 1067](#) and the “:DLINK[:TGRoup [A]|B]:DCH[1]|2|3|4|5|6:BLKSize” command on [page 1066](#).

:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:PPERcentage**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:PPERcentage?

This query returns the percentage of the total bits removed from or added to the fully coded channel.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:RMArch**Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH [1] | 2 | 3 | 4 | 5 | 6 :
RMArch <val>[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH [1] | 2 | 3 | 4 | 5 | 6 :
RMArch?

This command sets the rate matching attribute.

RST** 1**Range** 1–256**Field Entry** Rate Match Attr**Remarks** If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.**:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6:TTI*Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH [1] | 2 | 3 | 4 | 5 | 6 :
TTI 10000 | 20000 | 40000 | 80000[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:DLINK[:TGRoup [A] | B]:DCH [1] | 2 | 3 | 4 | 5 | 6 :
TTI?

This command sets the transmission time interval (TTI) allowed for the dedicated channel (DCH) to transmit.

The choices are expressed in units of milliseconds (msec) where 20000=20 msec.

***RST** 10000**Field Entry** TTI**Remarks** If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:DLINK:APPLY” on page 1021.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:DLINK[:TGRoup [A] | B]:DCH[1] | 2 | 3 | 4 | 5 | 6[:STATe]****Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup[A] | B]:DCH[1] | 2 | 3 | 4 | 5 |
6[:STATe] ON|OFF|1|0
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:DLINK[:TGRoup[A] | B]:DCH[1] | 2 | 3 | 4 | 5 |
6[:STATe] ?
```

This command enables or disables the selected dedicated transport channel (DCH).

RST** DCH 1: 1 DCH 2–6: 0**Key Entry** **TrCH State Off On*Remarks** DCH1 reset value cannot be turned off. The channels must be turned on sequentially. If one channel is turned off then all higher numbered channels will automatically be turned off.

If the parameter is changed, the apply command must be executed after the change. Refer to “[:DLINK:APPLY](#)” on page 1021.

:LINK**Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:LINK DOWN|UP
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:LINK?
```

This command sets the uplink or downlink mode.

RST** DOWN**Key Entry** **Link Down Up*:POLarity[:ALL]****Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:POLarity[:ALL] NORMal | INVert
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:POLarity[:ALL] ?
```

This command selects the polarity for the Q channel.

NORMal This choice selects normal phase polarity.

INVert This choice inverts the internal Q signal.

***RST** NORM**Key Entry** **Phase Polarity Normal Invert**

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])**:ULINK:APPLY****Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:APPLY

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:APPLY?

This command immediately starts the channel coding generation process according to the channel setup and data for the uplink physical and transport channels.

The query returns a response that determines whether or not the execution of the command is necessary. The response from the query is as follows:

1 This response is returned if the execution of the command is required.

0 This response is returned if the execution of the command is not required.

***RST** +0

Key Entry **Apply Channel Setup**

:ULINK:AWGN:CN**Supported** E4438C with Option 400 and 403

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:AWGN:CN <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:AWGN:CN?

This command sets the in band carrier to noise ratio. The noise is the total noise level of the in-channel.

The variable <val> is expressed in units of decibels (dB).

***RST** -1.80000000E+001

Range -30 to 30

Field Entry C/N value

Remarks In compressed mode, carrier power means normal frame power. A change in the C/N value will change the Eb/No value and vice versa.

:ULINK:AWGN:CPOWer

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:AWGN:CPOWer?

This query returns the carrier power level when the additive white gaussian noise (AWGN) is on.

The power value is expressed in units of decibels (dBm/3.84 MHz).

***RST** -1.56957537E+002

Field Entry C Power

Remarks In compressed mode, carrier power means normal frame power.

:ULINK:AWGN:DRATe

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:AWGN:DRATe?

This query returns the data rate of the Eb reference channel.

***RST** +1.22000000E+004

Field Entry Ref Data Rate

:ULINK:AWGN:EBNO

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:AWGN:EBNO <val>

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:AWGN:EBNO?

This command sets the Eb/No ratio. The Eb is defined as the carrier power divided by the bit rate. No is noise power divided by the bandwidth (3.84MHz).

The variable <val> setting is affected by the carrier to noise ratio (C/N) and the data rate. A change to either of these values will affect your Eb/No setting. Use the formula in the range field to determine a correct Eb/No value.

***RST** +6.97971394E+000

Range Eb/No = C/N x 3.84MHz/Data Rate

Field Entry Eb/No value (dB)

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])

:ULINK:AWGN:EBRef

Supported E4438C with Option 400 and 403

```
[ :SOURCE ] :RADIo:WCDMa:TGPP [ :BBG ] :ULINK:AWGN:EBRef DPCCh | DPDCh | DCH1 |
DCH2 | DCH3 | DCH4 | DCH5 | DCH6
[ :SOURCE ] :RADIo:WCDMa:TGPP [ :BBG ] :ULINK:AWGN:EBRef?
```

This command selects the Eb reference and it is used in the Eb/No value.

DPCCh This choice selects a dedicated physical control channel.

DPDCh This choice selects a dedicated physical data channel.

DCH1 This choice select dedicated transport channel 1.

DCH2 This choice select dedicated transport channel 2.

DCH3 This choice select dedicated transport channel 3.

DCH4 This choice select dedicated transport channel 4.

DCH5 This choice select dedicated transport channel 5.

DCH6 This choice select dedicated transport channel 6.

***RST** DCH1

Key Entry **DPCCH** **DPDCH** **DCH1** **DCH2**
DCH3 **DCH4** **DCH5** **DCH6**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:AWGN:FNBW

Supported E4438C with Option 400 and 403

```
[ :SOURCE ] :RADIo:WCDMa:TGPP [ :BBG ] :ULINK:AWGN:FNBW?
```

This query returns the flat noise bandwidth (BW). Flat noise bandwidth is calculated by $BW=(1.6) \times$ (Chip rate) and the result is close to the 0 dB roll-off point.

***RST** +6.14400000E+006

Field Entry Flat Noise BW

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:AWGN:NPOWer****Supported** E4438C with Option 400 and 403

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:AWGN:NPOWer?

This query returns the in-channel noise level when the additive white gaussian noise (AWGN) is on.

The power value is expressed in units of decibels (dBm/3.84 MHz).

RST** -1.38957537E+002**Field Entry** N Power**:ULINK:AWGN:TICPower*Supported** E4438C with Option 400 and 403

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:AWGN:TICPower?

This query returns the total in-channel power (carrier with noise) as defined by the 3GPP standard.

Field Entry TotalPwr**Remarks** The total in-channel power is a sum of carrier power and in-channel noise power. Changing the noise related parameters such as C/N, Eb/No, and Eb Ref will cause a recalculation of the total in-channel power.

The maximum value returned by this query depends on the power option that is installed in the signal generator.

:ULINK:AWGN[:STATe]**Supported** E4438C with Option 400 and 403

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:AWGN:STATe ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:AWGN:STATe?

This command enables or disables the additive white gaussian noise (AWGN). AWGN can only be turned on when DPCCH is selected as the physical channel. Refer to “:ULINK:PHYSical[1]:TYPE” on page 1100.

***RST** 0**Key Entry** Channel State Off On**Remarks** If the parameter is changed, the apply command must be executed after the change. Refer to “:ULINK:APPLY” on page 1075.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])**:ULINK:CRATE****Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:CRATE <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:CRATE?

This command sets the chip rate for the uplink configuration. The variable <val> is expressed in cycles per second (cps).

RST** +3.8400000E+006**Range** 1E3–4.25E6**Field Entry** Chip Rate**Remarks** The chip rate is equivalent to the spreading rate of the channel.**:ULINK:DPCCh:BETA*Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:DPCCh:BETA <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:DPCCh:BETA?

This command sets the beta value for the uplink dedicated physical control channel (DPCCH). The beta value and the power ratio are coupled. When the power ratio is updated, the beta value is converted to the beta ratio (amplitude ratio).

***RST** +11**Range** 0–15**Field Entry** Beta

Remarks After this command is sent, the channel power level for the DPCCH is re-calculated. If the channel power is set directly, the beta value of this command becomes invalid and is reset to –1.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:DPCCh:CCODE**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:CCODE <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:CCODE?

This command sets the channelization code for the uplink dedicated physical control channel (DPCCH).

***RST** 0**Range** 0–255**Field Entry** Channel Code

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:DPCCh:DATA**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:DATA PN9 | PN15 | FIX4 |

"<file name>" | STD

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:DATA?

This command configures the data pattern for the uplink dedicated physical control channel (DPCCH).

STD This choice sets the DPCCH to use the bits field as defined by the slot format.

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** STD**Key Entry** **PN9** **PN15** **FIX4** **User File** **3GPP STD**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])**:ULINK:DPCCh:DATA:FIX4**

Supported E4438C with Option 400

```
[ :SOURCE ] :RADIo:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:DATA:FIX4 <val>
```

```
[ :SOURCE ] :RADIo:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:DATA:FIX4?
```

This command sets the 4-bit data pattern of the uplink dedicated physical control channel (DPCCH).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

***RST** #B0000

Range 0–15

Key Entry **FIX4**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:DPCCh:FBI:PATtern

Supported E4438C with Option 400

```
[ :SOURCE ] :RADIo:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:FBI:PATtern PN9 | PN15 | FIX |  
"<file name>"
```

```
[ :SOURCE ] :RADIo:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:FBI:PATtern?
```

This command configures the pattern of the feedback information (FBI) for the uplink dedicated physical control channel (DPCCH).

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** FIX

Key Entry **PN9 PN15 FIX User File**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:DPCCh:FBI:PATtern:FIX**

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:DPCCh:FBI:PATtern:FIX <val>

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:DPCCh:FBI:PATtern:FIX?

This command sets the 30-bit feedback information (FBI) pattern for the uplink dedicated physical control channel (DPCCH).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only decimal values.

***RST** +0

Range 0–10737418235

Key Entry **FIX**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:DPCCh:FBI[:STATe]

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:DPCCh:FBI [:STATe] ?

This query returns whether or not the feedback information (FBI) bits are included in the uplink dedicated physical control channel (DPCCH). The FBI is included when a status of one is returned. A zero indicates no FBI.

***RST** 0

Range N/A

Field Entry FBI State

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])**:ULINK:DPCCh:POWer**

Supported E4438C with Option 400

[:SOURce] :RADIo:WCDMa:TGPP [:BBG] :ULINK:DPCCh:POWer <val>

[:SOURce] :RADIo:WCDMa:TGPP [:BBG] :ULINK:DPCCh:POWer?

This command sets the power level for the uplink dedicated physical control channel (DPCCH).

The variable <val> is expressed in units of decibels (dB).

***RST** -2.69000000E+000

Range -40 to 0

Field Entry DPCCH Power

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:DPCCh:RATE

Supported E4438C with Option 400

[:SOURce] :RADIo:WCDMa:TGPP [:BBG] :ULINK:DPCCh:RATE?

This query returns the symbol rate for the uplink dedicated physical control channel (DPCCH).

***RST** +1.50000000E+004

Field Entry Symbol Rate

:ULINK:DPCCh:SLOTformat

Supported E4438C with Option 400

[:SOURce] :RADIo:WCDMa:TGPP [:BBG] :ULINK:DPCCh:SLOTformat <val>

[:SOURce] :RADIo:WCDMa:TGPP [:BBG] :ULINK:DPCCh:SLOTformat?

This command sets the slot format for the uplink dedicated physical control channel (DPCCH). The variable <val> is expressed in unit of bits.

***RST** +0

Range 0–5

Field Entry Slot Format

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:DPCCh:TFCI:PATtern

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:TFCI:PATtern PN9 | PN15 | FIX |
"<file name>"
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:TFCI:PATtern?
```

This command configures the transport format combination indicator (TFCI) bit pattern for the uplink dedicated physical control channel (DPCCH).

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** FIX

Key Entry **PN9 PN15 FIX User File**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:DPCCh:TFCI:PATtern:FIX

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:TFCI:PATtern:FIX <val>
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:TFCI:PATtern:FIX?
```

This command sets the transport format combination indicator (TFCI) 10-bit data pattern for the uplink dedicated physical control channel (DPCCH).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only decimal values.

***RST** +0

Range 0–1023

Field Entry TFCI Pattern

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:DPCCh:TFCI[:STATe]****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:TFCI[:STATe]?

This query returns the status of the transport format combination indicator (TFCI) for the uplink dedicated physical control channel (DPCCH).

RST** 1**Range** N/A**Field Entry** TFCI State**:ULINK:DPCCh:TPC:NSTeps*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:TPC:NSTeps <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:TPC:NSTeps?

This command sets the number of steps to increase or decrease the transmit power control (TPC) for the uplink dedicated physical control channel (DPCCH).

The variable <val> is expressed in units of decibels (dB).

***RST** +1**Range** 1–80**Field Entry** TPC Pat Steps**Remarks** Refer to “:ULINK:DPCCh:TPC:PATtern” on page 1086.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:DPCCh:TPC:PATtern**Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:TPC:PATtern PN9 | PN15 | FIX4 |
"<file name>" | UDOW | DUP | UALL | DALL
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:TPC:PATtern?
```

This command configures the transmit power control (TPC) pattern for the uplink dedicated physical control channel (DPCCH).

"<file name>" This variable specifies a data pattern that has been stored in memory.

UDOW This choice repetitively steps up and down the TPC pattern.

DUP This choice repetitively steps down and up the TPC pattern.

UALL This choice consecutively steps up the TPC pattern.

DALL This choice consecutively steps down the TPC pattern.

***RST** PN9

Key Entry **PN9 PN15 FIX4 "<file name>" Up/Down Down/Up All Up**

All Down

Remarks Refer to [“:ULINK:DPCCh:TPC:NSTeps” on page 1085](#).

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])**:ULINK:DPCCh:TPC:PATtern:FIX4**

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:TPC:PATtern:FIX4 <val>
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:TPC:PATtern:FIX4?
```

This command sets the transmit power control (TPC) 4 bit data pattern for the uplink dedicated physical control channel (DPCCH).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

***RST** #B0000

Range 0–15

Field Entry TPC Pattern

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:DPCCh:TPC:PATtern:TRIGger:POLarity

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:TPC:PATtern:TRIGger:POLarity POSitive|NEGative
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:DPCCh:TPC:PATtern:TRIGger:POLarity?
```

This command sets the transmit power control (TPC) pattern trigger polarity for the uplink dedicated physical control channel (DPCCH).

POSitive This choice sets the pattern signal to trigger when the signal is high.

NEGative This choice sets the pattern signal to trigger when the signal is low.

***RST** POS

Key Entry **TPC Pat Trig Polarity Neg Pos**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:DPCCh:TPC:PATtern:TRIGger[:STATe]

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:TPC:PATtern:
TRIGger[:STATe] ON|OFF|1|0
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:TPC:PATtern:
TRIGger[:STATe]?
```

This command enables or disables the transmit power control (TPC) pattern trigger state for the uplink dedicated physical control channel (DPCCH).

***RST** 0

Field Entry TPC UserFile Trig

Remarks The TPC pattern trigger input is located on the AUX I/O connector (ALT PWR IN, pin#16). For more information about the rear panel AUX I/O connector, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*. If the parameter is changed, the apply command must be executed after the change. Refer to "[:ULINK:APPLY](#)" on page 1075.

:ULINK:DPCCh:TPOWer

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPCCh:TPOWer?
```

This query returns the "Total Power" value displayed on the user interface (UI). The power value is the relative power difference between the total in-channel signal power and the active channel reference power (0dB).

***RST** +0.00000000E+000

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to "[:ULINK:APPLY](#)" on page 1075.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])

:ULINK:DPCCh[:STATe]**Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:DPCCh[:STATe] ON|OFF|1|0

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:DPCCh[:STATe] ?

This command enables or disables the operating state for the uplink dedicated physical control channel (DPCCH).

***RST** 1**Field Entry** Channel State

Remarks If the parameter is changed, the apply command must be executed after the change. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:DPDCh:BETA**Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:DPDCh:BETA <val>

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:DPDCh:BETA?

This command sets the beta value for uplink dedicated physical data channel (DPDCH).

***RST** +15**Range** 0–15**Field Entry** Beta

Remarks The beta value and power ratio are coupled. After this command is sent, the value of the channel power level of the DPDCH is re-calculated.

If the channel power is set directly, the value of this command becomes invalid and is set to –1.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:DPDCh:CCODE

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:CCODE <val>
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:CCODE?
```

This command sets the channelization code for the uplink dedicated physical data channel (DPDCH). There are commands that are associated with the channelization code and they are the slot format and the symbol rate.

If the slot format is changed, so will the symbol rate. If the symbol rate is changed, so will the slot format. In addition, the channelization code will change. If current channelization code exceed the new maximum value for the specified slot format or symbol rate, a setting conflict error is generated and the value is clipped to the maximum value. Refer to [Table 9-4 on page 1090](#).

Table 9-4 Channelization Code Maximum Value

Channelization Code	Slot Format	Symbol Rate
255	0	15
127	1	30
63	2	60
31	3	120
15	4	240
7	5	780
3	6	960

***RST** +16

Range 0–255

Field Entry Channel Code

Remarks Refer to “:ULINK:DPDCh:SLOTformat” on page 1094 and “:ULINK:DPDCh:RATE” on page 1092. If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

:ULINK:DPDCh:DATA

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:DATA PN9 | PN15 | FIX4 |
"<file name>" | TRANspch
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:DATA?
```

This command configures the data pattern of the uplink dedicated physical data channel (DPDCH).

TRANspch This choice sets the data that is generated from the transport channel setup.

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** TRAN

Key Entry **PN9 PN15 FIX4 User File Transport CH**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:DPDCh:DATA:FIX4

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:DATA:FIX4 <val>
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:DATA:FIX4?
```

This command sets the fixed 4-bit binary data for the uplink dedicated physical data channel (DPDCH).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

***RST** #B0000

Range 0–15

Field Entry Data

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:DPDCh:POWer**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:POWer <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:POWer?

This command sets the power level for the uplink dedicated physical data channel (DPDCH).

The variable <val> is expressed in units of decibels (dB).

***RST** +0.00000000E+000**Range** -40 to 0**Field Entry** DPDCH Power

Remarks The power ratio and the beta value are coupled. After the beta value is specified and sent, the value of the channel power level of the DPDCH is re-calculated.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:DPDCh:RATE**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:RATE <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:RATE?

This command sets the symbol rate for the uplink dedicated physical data channel (DPDCH). There are commands that are associated with the symbol rate and they are the channelization code and the slot format.

If the slot format is changed, so will the symbol rate. If the symbol rate is changed, so will the slot format. In addition, the channelization code will change. If current channelization code exceed the new maximum value for the specified slot format or symbol rate, a setting conflict error is generated and the value is clipped to the maximum value. Refer to [Table 9-5](#).

Table 9-5 Channelization Code Maximum Value

Channelization Code	Slot Format	Symbol Rate
255	0	15
127	1	30

Table 9-5 Channelization Code Maximum Value

Channelization Code	Slot Format	Symbol Rate
63	2	60
31	3	120
15	4	240
7	5	780
3	6	960

The variable <val> is expressed in units of kilo symbols per second (ksps).

***RST** +6.00000000E+004

Range 15000–960000

Field Entry Symbol Rate

Remarks Refer to “:ULINK:DPDCh:CCODE” on page 1090 and “:ULINK:DPDCh:RATE” on page 1092. If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:DPDCh:RBER

Supported E4438C with Option 400

[[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:DPDCh:RBER?

This query returns inserted error bit rate which is specified by the transport channel cycle length and transport channel error length commands.

Inserted error bit rate is calculated by the following formula: $\text{TrCH BER ErrLen} / \text{TrCH BER Cycle}$. Refer to “:ULINK:DPDCh:TBER[:CLENGTH]” on page 1095 and “:ULINK:DPDCh:TBER:ELENGTH” on page 1095.

***RST** 0.0

Field Entry TrCH BER

:ULINK:DPDCh:SLOTformat

Supported E4438C with Option 400

```
[ :SOURCE] :RADIo:WCDMa:TGPP [ :BBG] :ULINK:DPDCh:SLOTformat <val>
```

```
[ :SOURCE] :RADIo:WCDMa:TGPP [ :BBG] :ULINK:DPDCh:SLOTformat?
```

This command sets the slot format for the uplink dedicated physical data channel (DPDCH).

There are commands that are associated with the slot format and they are the channelization code and the symbol rate.

If the slot format is changed, so will the symbol rate. If the symbol rate is changed, so will the slot format. In addition, the channelization code will change. If current channelization code exceed the new maximum value for the specified slot format or symbol rate, a setting conflict error is generated and the value is clipped to the maximum value. Refer to [Table 9-6 on page 1094](#).

Table 9-6 Channelization Code Maximum Value

Channelization Code	Slot Format	Symbol Rate
255	0	15
127	1	30
63	2	60
31	3	120
15	4	240
7	5	780
3	6	960

***RST** +2

Range 0–6

Field Entry Slot Format

Remarks Refer to “:ULINK:DPDCh:CCODE” on page 1090 and “:ULINK:DPDCh:RATE” on page 1092. If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

:ULINK:DPDCh:TBER[:CLENGTH]**Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:DPDCh:TBER[:CLENGTH] <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:DPDCh:TBER[:CLENGTH] ?

This command sets the cycle length of the Transport Channel BER insertion of dedicated physical channel (DPCH).

***RST** 0**Range** 0–65535**Field Entry** TrCH BER Cycle

Remarks A zero in the TrCH BER Cycle field, disables the error insertion function (error rate equals 0%).

:ULINK:DPDCh:TBER:ELENGTH**Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:DPDCh:TBER:ELENGTH <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:DPDCh:TBER:ELENGTH?

This command sets the error length of the Transport Channel BER.

***RST** 0**Range** 0–4095**Field Entry** TrCH BER ErrLen

Remarks The Transport Channel BER error length must be smaller than or equal to the Transport Channel BER cycle length.

The TrCH ELEN (transport channel error length) is truncated by the TrCH CLEN (transport channel cycle length) when the TrCH BER cycle length is smaller than TrCH BER length.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:DPDCh:TPOWer****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh:TPOWer?

This query returns the “Total Power” value displayed on the user interface (UI). The power value is the relative power difference between the total in-channel signal power and the active channel reference power (0dB).

RST** +0**:ULINK:DPDCh[:STATe]*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh[:STATe] ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:DPDCh[:STATe] ?

This command enables or disables the operating state for the uplink dedicated physical data channel (DPDCH).

***RST** 1**Field Entry** Channel State

Remarks If the parameter is changed, the apply command must be executed after the change. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:FCLock:INTerval**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:FCLock:INTerval FCL10|FCL20|FCL40|FCL80|FCL2560

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:FCLock:INTerval ?

This command selects the frame clock interval supplied to the source.

The frame clock interval is set in units of milliseconds (msec).

***RST** FCL80**Key Entry** 10 msec 20 msec 40 msec 80 msec 2560 msec

Remarks This command is not used when the sync source is set to ESG. Refer to “:ULINK:SYNC[:SOURCE]” on page 1152.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])**:ULINK:FCLOCK:POLARITY**

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:FCLOCK:POLARITY POSitive|NEGative
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:FCLOCK:POLARITY?
```

This command sets the polarity of the frame clock for the uplink synchronization source.

POSitive This choice sets the clock gate to trigger when the signal is high.

NEGative This choice sets the clock gate to trigger when the signal is low.

***RST** POS

Key Entry **Frame Clock Polarity Neg Pos**

Remarks This command is not used when the sync source is set to ESG. Refer to “:ULINK:SYNC[:SOURCE]” on page 1152.

:ULINK:FILT

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:FILT RNYQuist|NUQuist|GAUSSian|
RECTangle|IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm| UGGaussian|
"<user FIR>"
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:FILT?
```

This command selects the filter type for the uplink configuration.

IS95 This choice selects a filter that meets the criteria of the IS-95 standard.

IS95_EQ This choice selects a filter which is a combination of the IS-95 filter (above) and the equalizer filter described in the IS-95 standard. This filter is only used for IS-95 baseband filtering.

IS95_MOD This choice selects a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance) with lower passband rejection than the filter specified in the IS-95 standard.

IS95_MOD_EQ This choice selects a filter which is a combination of the equalizer filter described in the IS-95 standard and a filter that meets the criteria of the IS-95 error function (for improved adjacent channel performance), with lower passband rejection.

AC4Fm This choice selects a predefined Association of Public Safety Communications Officials (APCO) specified compatible 4-level frequency modulation (C4FM) filter.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

UGGaussian	This choice selects a backwards compatible GSM Gaussian filter (Gaussian filter with a fixed BbT value of 0.300) for the ESG E44xxB Option UN3 or UN4.					
"<user FIR>"	This variable is any filter file that you have stored into memory.					
*RST	RNYQ					
Key Entry	Root Nyquist	Nyquist	Gaussian	Rectangle	IS-95	IS-95 w/EQ
	IS-95 Mod	IS-95 Mod w/EQ	APCO 25 C4FM	UN3/4 GSM Gaussian		
	User FIR					
Remarks	Refer to “File Name Variables” on page 13 for information on the file name syntax.					

:ULINK:FILTER:ALPHA

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:FILTER:ALPHA <val>

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:FILTER:ALPHA?

This command changes the alpha value for the Nyquist or root Nyquist filter.

***RST** +2.20000000E-001

Range 0.000–1.000

Key Entry **Filter Alpha**

Remarks This command is effective only after a root Nyquist or Nyquist filter is selected; it does not affect other types of filters.

To change the current filter type, refer to “:ULINK:FILTER” on page 1097.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:FILTer:BBT**

Supported E4438C with Option 400

[:SOURce] :RADio:WCDMa:TGPP [:BBG] :ULINK:FILTer:BBT <value>

[:SOURce] :RADio:WCDMa:TGPP [:BBG] :ULINK:FILTer:BBT?

This command changes the bandwidth-multiplied-by-bit-time filter parameter value for the Gaussian filter.

***RST** +5.00000000E-001

Range **0.000–1.000**

Key Entry **Filter BbT**

Remarks This command is effective only after a Gaussian filter is selected; it does not affect other types of filters.

To change the current filter type, refer to “[:ULINK:FILTer]” on page 1097.

:ULINK:FILTer:CHANnel

Supported E4438C with Option 400

[:SOURce] :RADio:WCDMa:TGPP [:BBG] :ULINK:FILTer:CHANnel EVM|ACP

[:SOURce] :RADio:WCDMa:TGPP [:BBG] :ULINK:FILTer:CHANnel?

This command optimizes a filter for minimized error vector magnitude (EVM) or for minimized adjacent channel power (ACP).

EVM This choice provides the most ideal passband.

ACP This choice improves stopband rejection. This feature only applies to root Nyquist and Nyquist filters.

***RST** EVM

Key Entry **Optimize FIR For EVM ACP**

Remarks To change the current filter type, refer to “[:ULINK:FILTer]” on page 1097.

:ULINK:FOFFset

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:FOFFset <val>
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:FOFFset?
```

This command sets the SFN-CFN frame number offset. The command adds in delays of the internal frame counter by specifying the starting frame number count.

When the FOFFset is set to “0,” the frame number starts at the system sync trigger.

An example of specifying a frame number count: Set the FOFFset to 2. This makes the signal generator to trigger 2 frames after the SFN RST.

***RST** 0

Range 0–255

Key Entry SFN-CFN Frame Offset

Remarks For additional information, refer to 3GPP TS25.402 for SFN and CFN relationship.

:ULINK:PADJust

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PADJust EQUal|SCALE
```

This command adjusts the code domain power levels of all uplink channels.

EQUal This choice will adjust all channel powers to equal power settings.

SCALE This choice will scale the channel power levels so that the sum of the powers are equal to 0 dB.

Key Entry Equal Powers Scale To 0dB

:ULINK:PHYSical[1]:TYPE

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PHYSical[1]:TYPE PRACH|DPCCCh
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PHYSical[1]:TYPE?
```

This command sets the physical channel type.

PRACH This choice selects a physical random access channel type.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

DPCCh This choice selects a dedicated physical control channel type.

***RST** DPCC

Key Entry **PRACH** **DPCC**

:ULINK:PMODE:TPControl:HOLD

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:PMODE:TPControl:HOLD 1|0|ON|OFF
```

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:PMODE:TPControl:HOLD?
```

This command sets the transmission power control of the dedicated physical channel (DPCH).

ON This choice enables the power hold mode.

OFF This choice disables the power hold mode and enables the dynamic power control

***RST** 1

Key Entry **Power Hold** **Off** **On**

Remarks The power hold mode is automatically enabled when the dedicated physical channel (DPCH) **Power Mode Norm TPC** is set to **TPC** (refer to “:ULINK:PMODE[:SElect]” on page 1104).

:ULINK:PMODE:TPControl:POWER:INITial

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:PMODE:TPControl:POWER:
```

```
INITial <val>
```

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:PMODE:TPControl:POWER:INITial?
```

This command sets the initial power (in dB; relative to Max Power: 0.00 dB) of the DPCH power control.

***RST** +0.00000000E+000

Range 0 to -40

Field Entry Init Power

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks	<p>If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.</p> <p>The value of <val> must be smaller or equal to the value use for the command: “:ULINK:PMODE:TPControl:POWER:MINimum” on page 1102. Init Power is relative to Max Power (the amplitude set on the signal generator). For more information refer to “:ULINK:PMODE:TPControl:POWER:MAXimum” on page 1102.</p>
----------------	--

:ULINK:PMODE:TPControl:POWER:MAXimum

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PMODE:TPControl:POWER:MAXimum?
```

This query returns the maximum power (in dB; relative to Max Power) of the dedicated physical channel (DPCH).

Max Power is a grayed out field that will always be 0.00 dB. The value of this field is a relative value to the maximum amplitude set for the signal generator. For example, if the signal generator amplitude is set to -20 dBm, the Min Power set to -40 dB, and the Init Power is set to -10 dB, then the absolute initial power level will be -30 dBm (10 dBm below the signal generator amplitude) and the absolute minimum power will be -60 dBm (40 dBm below the signal generator amplitude).

***RST** +0.00000000E+000

Field Entry Max Power

Remarks The value of this query will always be zero. The maximum power is mapped to the actual RF output power.

:ULINK:PMODE:TPControl:POWER:MINimum

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PMODE:TPControl:POWER:MINimum <val>
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PMODE:TPControl:POWER:MINimum?
```

This command sets the minimum power of the dedicated physical channel (DPCH). The variable <val> is expressed in units of dB.

***RST** -4.00000000E+001

Range -40 to 0

Field Entry Min Power

Wideband CDMA Base Band Generator Subsystem—Option 400 [:SOURCE]:RADIo:WCDMa:TGPP[:BBG]

Remarks	<p>If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.</p> <p>The minimum power is decreased in increments determined by the value set for the Power Step. Refer to “:ULINK:PMODE:TPControl:POWer:STEP” on page 1103. Minimum power is limited by the amplitude set on the signal generator. The signal generator amplitude must be set to -96 dBm or lower for the minimum power to be set to -40 dB. For more information, refer to “:ULINK:PMODE:TPControl:POWer:MAXimum” on page 1102.</p>
----------------	--

:ULINK:PMODE:TPControl:POWer:RESet

Supported	E4438C with Option 400
	[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PMODE:TPControl:POWer:RESet
	[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PMODE:TPControl:POWer:MINimum?

This command resets the transmit power of the dedicated physical channel (DPCH) to the initial power.

Key Entry **Reset to Initial Power**

Remarks	When the DPCH power mode is changed to TPControl, this command is performed. Refer to “:ULINK:PMODE[:SElect]” on page 1104 to select the power mode. Any time the power mode is changed, the start power is always set to the initial power.
----------------	--

:ULINK:PMODE:TPControl:POWer:STEP

Supported	E4438C with Option 400
	[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PMODE:TPControl:POWer:STEP DB0_5 DB1_0 DB2_0 DB3_0
	[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PMODE:TPControl:POWer:STEP?

This command set the power step of the dedicated physical channel (DPCH) power control. Initial power can only be increased in steps set by the power step.

***RST** DB0_5

Key Entry Power Step

Remarks	If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.
----------------	---

:ULINK:PMODE:TPControl:TRIGger:POLarity**Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PMODE:TPControl:TRIGger:
POLarity POSitive|NEGative

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PMODE:TPControl:TRIGger:POLarity?

This command sets the uplink dedicated physical channel (DCPH) transmit power control signal polarity.

RST** POS**Key Entry** **Power Control Signal Polarity Neg Pos*:ULINK:PMODE[:SElect]****Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PMODE[:SElect] NORMal|TPControl
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PMODE[:SElect]?

This command sets the dedicated physical channel (DPCH) power control mode.

NORMal This choice selects the normal power mode. Compressed frames are available.

TPC This choice selects the TPC power mode. Compressed gaps are not available.

RST** NORM**Key Entry** **Power Mode Norm TPC*:ULINK:PRACH:AICH:NUMBER****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:AICH:NUMBER?

This query returns the number of received acquisition indication channel (AICH) trigger during one configured physical random access channel (PRACH) signal generation.

The result value can be queried after the PRACH signal generation is completed and until the next PRACH generation trigger is received.

The signal begins when the PRACH start trigger and ends when the specified number of signals are generated.

To specify a number of PRACHs, refer to “:ULINK:PRACH[:SINGLE]:PREamble:NUMBER” on [page 1134](#).

***RST** -1

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Field Entry	Number of AICH
Remarks	A -1 status represents a PRACH generation is on going.

:ULINK:PRACH:AICH:POLarity

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:AICH:
POLarity POSition|NEGative
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:AICH:POLarity?
```

This command sets the trigger signal polarity for the acquisition indication channel (AICH).

POSitive This choice sets the signal polarity to trigger when the signal goes high.

NEGative This choice sets the signal polarity to trigger when the signal goes low.

***RST** POS

Key Entry **AICH Trigger Polarity Pos Neg**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#)

:ULINK:PRACH:AWGN:CN

Supported E4438C with Option 400 and 403

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:AWGN:CN <val>
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:AWGN:CN?
```

This command sets the in band carrier to noise ratio.

The variable <val> is expressed in units of decibels (dB).

***RST** -2.25005194E+001

Range -30 to 30

Field Entry C/N value

Remarks A change in the C/N value will change the Eb/No value and vice versa.

:ULINK:PRACH:AWGN:CPOWer**Supported** E4438C with Option 400 and 403

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:AWGN:CPOWer?

This query returns the carrier power level when the physical random access channel's (PRACH) additive white gaussian noise (AWGN) is on.

RST** -1.61435521E+002**Field Entry** C Power**:ULINK:PRACH:AWGN:DRATe*Supported** E4438C with Option 400 and 403

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:AWGN:DRATe?

This query returns the data rate of the Eb reference channel.

RST** +1.22000000E+004**Field Entry** Ref Data Rate**:ULINK:PRACH:AWGN:EBNO*Supported** E4438C with Option 400 and 403

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:AWGN:EBNO <val>

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:AWGN:EBNO?

This command sets the Eb/No value. The Eb is defined as carrier divided by the bit rate. No is noise power divided by the bandwidth (3.84 MHz). This ratio is only referred when EREF is CONTrol or DATA.

The variable <val> setting is affected by the carrier to noise ratio (C/N) and the data rate. A change to either of these values will affect your Eb/No setting. Use the formula in the range field to determine a correct Eb/No value.

***RST** +4.10000000E+000**Range** Eb/No = C/N x 3.84MHz/DataRate**Field Entry** Eb/No

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

:ULINK:PRACH:AWGN:ECNO

Supported E4438C with Option 400 and 403

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:AWGN:ECNO <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:AWGN:ECNO?
```

This command sets the E_c/N_o value. The E_c is defined as carrier divided by the chip rate. N_o is the noise power divided by the bandwidth (3.84 MHz). This ratio is only referred when EREF is PREAMBLE.

***RST** -2.05000000E+001

Range -30 to 30

Field Entry E_c/N_o value

:ULINK:PRACH:AWGN:EREF

Supported E4438C with Option 400 and 403

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:AWGN:EREF PREAMBLE |  
CONTROL | DATA | RACH
```

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:AWGN:EREF?
```

This command selects the E_b (E_c) reference. It is used for specifying the bit (chip) rate of physical/transport channel.

PREAMBLE This choice selects a preamble part as the E_c/N_o reference.

CONTROL This choice selects a message control part as the E_b/N_o reference.

DATA This choice selects a message data part as the E_b/N_o reference.

RACH This choice selects a random access channel as the E_b/N_o reference.

***RST** RACH

Key Entry **Preamble** Msg Ctrl Msg Data **RACH TrCH**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:PRACH:AWGN:NPOWER**

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:PRACH:AWGN:NPOWER?

This query returns the in-channel noise level when the additive white gaussian noise (AWGN) is on.

***RST** -1.38935002E+002

Field Entry N Power

:ULINK:PRACH:AWGN:TICPower

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:PRACH:AWGN:TICPOWER?

This query returns the in-channel power within the 3.84 MHz bandwidth.

***RST** **DPCH:** -1.38924800E+002
 Single PRACH: -1.38924800E+002
 Multiple PRACH: -1.56970651E+002

Field Entry TotalPwr

:ULINK:PRACH:AWGN[:STATE]

Supported E4438C with Option 400 and 403

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:PRACH:AWGN [:STATE] ON | OFF | 1 | 0
 [:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:PRACH:AWGN [:STATE] ?

This command enables or disables the additive white gaussian noise (AWGN) for the physical random access channel (PRACH). The AWGN can only be turned on when PRACH is selected as the physical channel.

***RST** 0

Key Entry Channel State Off On

Remarks Refer to “:ULINK:PHYSical[1]:TYPE” on page 1100.

If the parameter is changed, the apply command must be executed after the change. Refer to “:ULINK:APPLY” on page 1075.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

:ULINK:PRACH:MESSAge:CPARt:BETA

Supported E4438C with Option 400

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:MESSAge:CPARt :BETA <val>
```

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:MESSAge:CPARt :BETA?
```

This command sets the beta ratio (amplitude ratio) for the physical random access channel (PRACH) message control part. The variable <val> is an integer value.

Changing the control power value (see “:ULINK:PRACH:MESSAge:CPARt:POWer” on page 1110 for information on setting PRACH control power) changes the beta to power ratio, and the ESG may not be able to compute a proper control beta value. If this occurs, the query will return a minus one (-1).

***RST** +11

Range 0–15

Field Entry Ctrl Beta

Remarks A change to the beta value will also cause a change to the control power setting.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH:MESSAge:CPARt:DATA

Supported E4438C with Option 400

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:MESSAge:CPARt :DATA PN9 |
PN15 | FIX4 | "<file name>" | STD
```

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:MESSAge:CPARt :DATA?
```

This command selects the data type to be inserted into the physical random access channel (PRACH) message control part.

STD This choice selects a slot format defined in the 3GPP standard.

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** STD

Key Entry **PN9** **PN15** **FIX4** **User File** **3GPP STD**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH:MESSAge:CPARt:DATA:FIX4**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MESSAge:CPARt:DATA:FIX4 <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MESSAge:CPARt:DATA:FIX4?

This command sets a fixed 4 bit pattern for use as physical random access channel (PRACH) message part data.

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

***RST** #B0000**Range** 0–15**Key Entry** Fix4

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:PRACH:MESSAge:CPARt:POWer**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MESSAge:CPARt:POWer <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MESSAge:CPARt:POWer?

This command sets the power level for the physical random access channel (PRACH) message control part.

The variable <val> is expressed in units of decibels (dB).

***RST** -2.69000000E+000**Range** -40 to 0**Field Entry** Ctrl Pwr

Remarks Changing the control power changes the beta to power ratio. Refer to [“:ULINK:PRACH:MESSAge:CPARt:BETA” on page 1109](#) for more information.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#)

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:PRACH:MESSAge:CPARt:RATE****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MESSAge:CPARt:RATE?

This query returns the message data part symbol rate for the physical random access channel (PRACH).

***RST** +1.50000000E+004**Key Entry** **Symbol Rate**

Remarks The symbol rate of 15 kbps is the only supported rate per the 3GPP standards, TS 25.211 v3.10 (2002-03).

:ULINK:PRACH:MESSAge:CPARt:SLOTformat**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MESSAge:CPARt:SLOTformat?

This query returns the message control part slot format for the physical random access channel (PRACH).

***RST** 0**Range** 0–3**Field Entry** Slot Format

Remarks The slot format is a static value set to zero in accordance with the 3GPP standards, TS 25.211 v3.10 (2002-03).

:ULINK:PRCh:MESSAge:CPARt:TFCI:PATtern**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRCh:MESSAge:CPARt:TFCI:PATtern PN9|PN15|FIX|"<file name>"

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRCh:MESSAge:CPARt:TFCI:PATtern?

This command selects data type to be inserted into the transport format combination indicator (TFCI) of the message control part located in the physical random access channel (PRACH).

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** FIX**Key Entry** **PN9 PN15 FIX User File**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:PRCh:MESSAge:CPARt:TFCI:PATtern:FIX**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRCh:MESSAge:CPARt:TFCI:PATtern:FIX <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRCh:MESSAge:CPARt:TFCI:PATtern:FIX?

This command sets a fixed bit pattern to be inserted into the transport format combination indicator (TFCI).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only decimal values.

***RST** +0**Range** 0–1023**Field Entry** TFCI Pattern

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])**:ULINK:PRACH:MESSAge:CPARt:TFCI[:STATe]****Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:MESSAge:CPARt:TFCI[:STATe]?

This query returns the transport format combination indicator (TFCI) bits to determine if they exist or not in the currently specified slot format. A query returned with a “1” determines a TFCI exists and a “0,” no bits exist.

RST** 1**Field Entry** TFCI State**:ULINK:PRACH:MESSAge:DPARt:BETA*Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:MESSAge:DPARt:BETA <val>

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:MESSAge:DPARt:BETA?

This command sets the beta ratio (amplitude ratio) for the message data part of the physical random access channel (PRACH).

The variable <val> is an integer value. Changing the data power value (refer to, “:ULINK:PRACH:MESSAge:DPARt:POWer” on page 1115 for more information on setting PRACH data power) changes the beta to power ratio, and the signal generator may not be able to compute a proper data beta value. If this occurs, the query will return a minus one (-1).

***RST** +15**Range** 0–15**Field Entry** Data Beta**Remarks** A change to the beta value will also cause a change to the data power setting.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLy” on page 1075.

:ULINK:PRACH:MESSAge:DPART:DATA

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK: PRACH:MESSAge:DPART :DATA PN9 |
PN15 |FIX4 | "<file name>" | TRANSpch
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK: PRACH:MESSAge:DPART :DATA?
```

This command sets the data type to be inserted into physical random access channel (PRACH) message data part.

TRANSpch This choice sets the data that is generated from the transport channel setup.

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** TRAN

Key Entry **PN9 PN15 FIX4 User File Transport CH**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:PRACH:MESSAge:DPART:DATA:FIX4

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK: PRACH:MESSAge:DPART :DATA:
FIX4 <val>
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK: PRACH:MESSAge:DPART :DATA:FIX4?
```

This command sets a pseudo-random pattern as output data type in the message data part of the physical random access channel (PRACH).

While the variable <val> is expressed in binary or decimal formats, the query returns only binary values.

***RST** #B0000

Range 0∠15

Key Entry **FIX4**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

:ULINK:PRACH:MESSAge:DPART:POWer**Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:PRACH:MESSAge:DPART:POWer <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:PRACH:MESSAge:DPART:POWer?

This command sets the power level for the physical random access channel (PRACH) message data part.

The variable <val> is expressed in units of decibels (dB).

***RST** +0.00000000E+000**Range** -40 to 0**Field Entry** Data Pwr

Remarks Changing the data power changes the beta to power ratio. Refer to [“:ULINK:PRACH:MESSAge:DPART:BETA” on page 1113](#) for more information.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#)

:ULINK:PRACH:MESSAge:DPART:RATE**Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:PRACH:MESSAge:DPART:RATE <val>

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:PRACH:MESSAge:DPART:RATE?

This command sets the symbol rate for the message data part of the physical random access channel (PRACH).

There are commands that are associated with the symbol rate and they are the channelization code and the slot format.

If the slot format is changed, so will the symbol rate. If the symbol rate is changed, so will the slot format. In addition, the channelization code will change. If current channelization code exceed the new maximum value for the specified slot format or symbol rate, a setting conflict error is generated and the value is clipped to the maximum value. Refer to [Table 9-7](#).

Table 9-7 Channelization Code Maximum Value

Channelization Code	Slot Format	Symbol Rate
255	0	15
127	1	30
63	2	60
31	3	120

The variable <val> is expressed in units of kilo symbols per second (ksps).

***RST** 60

Range 15–120

Field Entry Symbol Rate

Remarks Channel code value is determined by slot format choice. Refer to “:ULINK:PRACH:MESSAge:DPART:SLOTformat” on page 1116 and “:ULINK:PRACH[:SINGLE]:MESSAge:DPART:CCODE” on page 1132.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH:MESSAge:DPART:SLOTformat

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK: PRACH:MESSAge:DPART :
SLOTformat <val>
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK: PRACH:MESSAge:DPART :SLOTformat?
```

This command sets the slot format value for the message data part of the physical random access channel (PRACH).

There are commands that are associated with the slot format and they are the channelization code and the symbol rate.

If the slot format is changed, so will the symbol rate. If the symbol rate is changed, so will the slot format. In addition, the channelization code will change. If current channelization code exceed the new maximum value for the specified slot format or symbol rate, a setting conflict error is generated and the value is clipped to the maximum value. Refer to [Table 9-8](#).

Table 9-8 Channelization Code Maximum Value

Channelization Code	Slot Format	Symbol Rate
255	0	15
127	1	30
63	2	60
31	3	120

The variable <val> is expressed in units of kilo symbols per second (ksps).

***RST** 2

Range 0–3

Field Entry Slot Format

Remarks Refer to “[:ULINK:PRACH:MESSAge:DPARt:RATE]” on page 1115 and “[:ULINK:PRACH[:SINGLE]:MESSAge:DPARt:CCODE]” on page 1132.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “[:ULINK:APPLY]” on page 1075.

[:ULINK:PRACH:MODE[:SElect]]

Supported E4438C with Option 400

```
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:MODE[:SElect] SINGLE|MULTI
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:MODE[:SElect]?
```

This command sets the channel mode of the physical random access channel (PRACH).

SINGLE This choice generates a single PRACH.

MULTI This choice generates up to eight PRACHes.

***RST** SING

Key Entry **PRACH Mode** **Single** **Multi**

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:PRACH:MULTi:MESSAge:TPOWer****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:MESSAge:TPOWer <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:MESSAge:TPOWer?

This command sets the message total power value in the physical random access channel (PRACH). The total power indicates a power of one PRACH.

***RST** -1.54060000E+002**Range** -1.00 to 1.94**Field Entry** Msg Pwr

Remarks This value is used only when POWER:MODE is set to TOTAL. Refer to “:ULINK:PRACH:PREAmble:POWer:MODE” on page 1124.

The maximum power for this command is limited by the power of the signal generator (ESG maximum power – 18.06 dBm). If the signal generator power is set to +20 dBm, the maximum value of this command is +1.94 dBm.

:ULINK:PRACH:MULTi:MESSAge[:STATe]**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:MESSAge[:STATe]

ON|OFF

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:MESSAge[:STATe]?

This command enables or disables the message part of the physical random access channel (PRACH) for the multiple PRACH mode.

RST** ON**Field Entry** Message Part**:ULINK:PRACH:MULTi:NUMBer*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:NUMBer <val>|INFINITY

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:NUMBer?

This command specifies the number of the physical random access channel (PRACH) 80 ms configuration patterns to be transmitted after the PRACH start trigger has been received.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

INFINITY	This choice means the repeating number will continue while the PRACH mode is selected and the start trigger is ignored.
*RST	1
Range	1–2147447836
Field Entry	Number of 80ms
Remarks	If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH:MULTi:PREamble:NUMBER

Supported	E4438C with Option 400
	[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:PRACH:MULTi:PREamble:NUMBER?

This query returns the number of Preambles on the multiple physical random access channel (PRACH) mode. This number is fixed to 1 in the current version.

*RST	1
Field Entry	Num of Pre

:ULINK:PRACH:MULTi:PREamble:POWER:INITIAL

Supported	E4438C with Option 400
	[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:PRACH:MULTi:PREamble:POWER:INITIAL?

This query returns the initial power of PRACH preambles on the multiple physical random access channel (PRACH) mode.

*RST	–1.54060000E+002
Range	–154.06 to 10
Field Entry	Init Pwr
Remarks	For the multiple PRACH mode, the initial power is the same as the maximum power for the PRACH preamble.

:ULINK:PRACH:MULTi:PREamble:POWer:MAX**Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:PREamble:POWer:Max<val>
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:PREamble:POWer:Max?
```

This command sets the power of the preamble on the multiple physical random access channel (PRACH) mode.

***RST** -1.54060000E+002**Range** -1.0 to 1.94**Field Entry** Max Pwr

Remarks The maximum power for this command is limited by the power of the signal generator (ESG maximum power – 18.06 dBm). If the signal generator power is set to +20 dBm, the maximum value of this command is +1.94 dBm.

:ULINK:PRACH:MULTi:PREamble:POWer:RSTep**Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:PREamble:POWer:RSTep?
```

This query, for the multiple physical random access channel (PRACH) mode, always returns zero, because power ramping is not supported for the multiple PRACH mode.

RST** +0**Field Entry** Ramp Step**:ULINK:PRACH:MULTi:PREamble:PPM*Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:PREamble:PPM <val>
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:PREamble:PPM?
```

This command sets the difference between the preamble and the message control part in the physical random access channel (PRACH).

***RST** -4.56000000E+000**Range** -20 to 10**Field Entry** Pp-m

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])

:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8:MESSAge:CPART:CCODE**Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8:MESSAge:CPART:CCODE?

This query returns the channel code of the message control part of physical random access channel (PRACH) on the multiple PRACH mode.

RST** 255**Range** 0–255**Field Entry** CHCode Ctl**Remarks** This command affects the PRACH setting on the multiple PRACH mode only.**:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8:MESSAge:DPART:CCODE*Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8:MESSAge:DPART:CCODE?

This query returns the channel code of the message data part of physical random access channel (PRACH) on the multiple PRACH mode.

RST** 245**Range** 0–255**Field Entry** ChCode Dat**Remarks** This command affects the PRACH setting on the multiple PRACH mode only.**:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8:PREAmble:SIGNature*Supported** E4438C with Option 400

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8:PREAmble:SIGNature <val>

[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8:PREAmble:SIGNature?

This command sets the signature encoded in the multiple physical random access channel's (PRACH) preamble.

***RST**

	Signature
--	-----------

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

UE	1	0
	2	1
	3	2
	4	3
	5	4
	6	5
	7	6
	8	7

Field Entry Pre Sig**Remarks** If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).**:ULINK:PRACH:MULTi:UE[1]|2|3|4|5|6|7|8:SPOStion[1]|2|3|4|5|6|7|8[:ASLot]****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:UE[1]|2|3|4|5|6|7|8:SPOStion[1]|2|3|4|5|6|7|8[:ASLot] <val>|OFF

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:UE[1]|2|3|4|5|6|7|8:SPOStion[1]|2|3|4|5|6|7|8[:ASLot]?

This command sets each physical random access channel (PRACH) start access slot position within 80ms.

***RST**

		Start Access Slot Pos							
		1	2	3	4	5	6	7	8
UE	1	0	OFF	OFF	OFF	OFF	OFF	OFF	OFF
	2	0	OFF	OFF	OFF	OFF	OFF	OFF	OFF
	3	0	OFF	OFF	OFF	OFF	OFF	OFF	OFF
	4	0	OFF	OFF	OFF	OFF	OFF	OFF	OFF
UE	5	0	OFF	OFF	OFF	OFF	OFF	OFF	OFF
	6	0	OFF	OFF	OFF	OFF	OFF	OFF	OFF
	7	0	OFF	OFF	OFF	OFF	OFF	OFF	OFF
	8	0	OFF	OFF	OFF	OFF	OFF	OFF	OFF

Range 0–59**Field Entry** Start Access Slot Position in 80ms Period**Remarks** This command can only be executed while in the PRACH Mode is set to Multi. Refer to [“:ULINK:PRACH:MODE\[:SElect\]” on page 1117](#).If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8[:STATe]****Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8
[:STATe] 0 | 1 | ON | OFF
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:MULTi:UE[1] | 2 | 3 | 4 | 5 | 6 | 7 | 8
[:STATe] ?
```

This command enables or disables each physical random access channel (PRACH) individually on the multiple PRACH mode.

***RST**

		State
UE	1	ON
	2	OFF
	3	OFF
	4	OFF
	5	OFF
	6	OFF
	7	OFF
	8	OFF

Field Entry On/Off

Remarks This command will not run if the power of all assigned physical random access channels exceed the power of the signal generator.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH:PREamble:POWer:AVERage**Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:PREamble:POWer:AVERage?
```

This query returns the average power of preambles that were sent before the acquisition indication channel (AICH) trigger was received.

***RST** -999**Field Entry** Preamble power average

Remarks The average power value can be queried after the physical random access channel’s (PRACH) signal generation is completed. Refer to “:ULINK:PRACH[:SINGLE]:PREamble:NUMBER” on page 1134.

:ULINK:PRACH:PREamble:POWer:MODE**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:PREamble:POWer:MODE PPM | TOTAl

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:PREamble:POWer:MODE?

This command sets the message power calculation mode for the physical random access channel (PRACH).

PPM This choice calculates the message power based on the power differences between the preamble and the message control part. The difference is specified by the PPM command. This is based on 3GPP standards.

TOTAl This choice calculates message power based on power differences between preamble and message total part. The message total power is specified by the MESSage:TPOWer command. Refer to [“:ULINK:PRACH\[:SINGLE\]:MESSage:TPOWer” on page 1133](#).

***RST** PPM**Key Entry** **PRACH Power Setup Mode Pp-m Total**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:PRACH:RPARAmeter**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:RPARAmeter TB168 | TB360

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:RPARAmeter?

This command sets a set of parameters as defined in 3GPP Standard (TS25.104) Reference Measurement Channel for the uplink (UL) physical random access channel (PRACH).

TB168 This choice sets the parameters for the transport block size = 168.

TB360 This choice sets the parameters for the transport block size = 360.

***RST** TB168**Key Entry** **TrCh BlkSize 168** **TrCh BlkSize 360**

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

Remarks When parameters are sets individually, CUSTom is returned for the query.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH:SCRamblecode

Supported E4438C with Option 400

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:SCRamblecode <val>
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:SCRamblecode?
```

This command sets the physical random access channel’s (PRACH) scrambling code.

***RST** +0

Range 0–8191

Field Entry PRACH Scrambling Code

Remarks The signature data is scrambled against a 4096 chip segment of the 225 complex gold code generator.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH:SDElay

Supported E4438C with Option 400

```
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:SDElay <val>
[ :SOURCE ] :RADIO:WCDMA:TGPP [ :BBG ] :ULINK:PRACH:SDElay?
```

This command sets the number of timeslots to be delayed from the uplink synchronization source. One timeslot is equivalent to 2560 chips.

The variable <val> range is dependent on the Tp-a setting.

***RST** +0

Range	Tp-a Setting	<val>
	0	-14 to 119
	7680	-11 to 119
	12800	-9 to 119

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**Key Entry** **Timeslot Offset**

Remarks The actual amount of timing difference is
(TOFFset + SDELay * 2560) – (Tp–a).

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

To set the Tp-a value, refer to “:ULINK:PRACH:TPA” on page 1127.

:ULINK:PRACH:SUBChannel

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH:SUBChannel <val>
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH:SUBChannel?
```

This command sets the sub-channel number to send the first preamble of the physical random access channel’s (PRACH).

***RST** +0

Range 0–11

Field Entry Start Sub-Channel#

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH:TOFFset

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH:TOFFset <val>
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH:TOFFset?
```

This command sets additional timing offset for the physical random access channel (PRACH).

The timing offset is to adjust the time distance from the uplink PRACH frame timing which is the downlink’s AICH framing timing minus the Tp–a to the actual uplink PRACH signal frame timing from the signal generator.

The downlink’s AICH frame timing is provided by the synchronization signal. The

The variable <val> is expressed in chips.

***RST** +0

Wideband CDMA Base Band Generator Subsystem—Option 400 [:SOURCE]:RADio:WCDMa:TGPP[:BBG]

Range	–512 to 2560
Key Entry	Timing Offset
Remarks	<p>The actual timing offset is the timing difference from the synchronization signal from the signal generator’s RF signal (TOFFset + SDElay * 2560) – (Tp–a).</p> <p>If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.</p>

:ULINK:PRACH:TPA

Supported	E4438C with Option 400
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TPA 0 7680 12800
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TPA?
	This command sets the time period (distance) between the physical random access channel’s (PRACH) preamble to the acquisition indication channel’s (AICH) frame.
	The variable <val> is expressed in units of “chip”.
*RST	7680
Key Entry	Base Delay Tp–a
Remarks	<p>The actual timing offset is (TOFFset + SDElay * 2560) – (Tp–a).</p> <p>If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.</p> <p>This command is not used when the sync source is set to ESG. Refer to “:ULINK:SYNC[:SOURCE]” on page 1152.</p>

:ULINK:PRACH:TPM

Supported	E4438C with Option 400
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TPM <val>
	[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TPM?
	This command sets the time period between the preamble and the message part.
	The variable <val> is expressed in access slot units.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

*RST	+3
Range	1–15
Field Entry	Tp-m
Remarks	If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075 . This command is used for single and multiple physical random access channel (PRACH) modes.

:ULINK:PRACH:TPOWer

Supported	E4438C with Option 400
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TPOWer?	
This query returns the total power value of the physical random access channels (PRACH).	
The value is the relative power difference between the total in-channel signal power of the PRACH message part and the active channel reference power (0dB) in the message part.	
*RST	+0
Remarks	This command is used for single and multiple physical random access channel (PRACH) modes.

:ULINK:PRACH:TPP

Supported	E4438C with Option 400
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TPP <val>	
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TPP?	
This command sets the time period between the preamble and another preamble before the message part.	
The variable <val> is expressed in access slot units.	
*RST	+3
Range	1–60
Field Entry	Tp-p

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

This command is used for single and multiple physical random access channel (PRACH) modes.

:ULINK:PRACH:TRIGger

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TRIGger
```

This command specifies the start of the physical random access channel’s (PRACH) pattern.

Key Entry **PRACH Trigger**

Remarks The PRACH trigger source must be set to “Trigger” before executing this command. Refer to [“:ULINK:PRACH:TRIGger:SOURce” on page 1129](#).

:ULINK:PRACH:TRIGger:POLarity

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TRIGger:
POLarity POSitive|NEGative
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TRIGger:POLarity?
```

This command sets the trigger polarity of the physical random access channel type (PRACH).

POSitive This choice sets the signal to trigger when the trigger signal is high.

NEGative This choice sets the signal to trigger when the trigger signal is low.

***RST** POS

Key Entry **PRACH Trigger Polarity Neg Pos**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:PRACH:TRIGger:SOURce

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TRIGger:
SOURce IMMEDIATE|TRIGger
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH:TRIGger:SOURce?
```

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

This command sets the trigger source of the physical random access channel (PRACH).

IMMediate This choice resets the waveform and immediately replays it from the start.

TRIGger This choice plays the waveform after receiving the trigger command.

***RST** IMMediate

Key Entry **PRACH Trigger Source Immedi Trigger**

Remarks Refer to “:ULINK:PRACH:TRIGger:POLarity” on page 1129 and “:ULINK:PRACH:TRIGger” on page 1129 for additional information.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH:TTI

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH:TTI 10000 | 20000
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH:TTI ?
```

This command sets the transmission time interval (TTI) period of the message part.

The choices are expressed in units of milliseconds (msec) where 20000=20 msec.

***RST** +20000

Field Entry TTI

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH[:SINGLE]:MESSAge[:STATe]

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH [ :SINGLE ] :MESSAge [ :STATe ]  
ON | OFF | AICH
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH [ :SINGLE ] :MESSAge [ :STATe ] ?
```

This command enables or disables the message part of the physical random access channel (PRACH).

ON This choice enables the message part to be generated after the number of preambles are generated. The “Number of Preamble” must be specified.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

OFF	This choice does not allow the message part to be generated. Only the preambles are transmitted.
AICH	This choice enables the acquisition indication channel preamble power ramping mode.
*RST	ON
Key Entry	On Off AICH
Remarks	For more information about the rear panel AUX I/O connector, refer to "Signal Generator Overview" in the <i>E4428C/38C ESG Signal Generators User's Guide</i> . If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to " :ULINK:APPLY " on page 1075.

:ULINK:PRACH[:SINGLE]:NUMBER

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH [ :SINGLE ] :NUMBER <val> |
INFinity
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH [ :SINGLE ] :NUMBER?
```

This command specifies the number of the physical random access channel (PRACH) patterns to repeat after the PRACH start trigger has been received.

INFinity This choice means the repeating number will continue while the PRACH mode is selected and the start trigger is ignored.

***RST** 1

Range 1–2147483647

Field Entry Number of PRACH

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to "[:ULINK:APPLY](#)" on page 1075.

:ULINK:PRACH[:SINGLE]:MESSAGE:CPART:CCODE

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH [ :SINGLE ] :MESSAGE:CPART :
CCODE <val>
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:PRACH [ :SINGLE ] :MESSAGE:CPART :
```

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

CCODE?

This command sets the channelization code for the physical random access channel (PRACH) message control part.

***RST** +15

Range 0–255

Field Entry Channel Code

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH[:SINGLE]:MESSAGE:DPART:CCODE

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:PRACH [:SINGLE] :MESSAGE:DPART :CCODE <val>

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:PRACH [:SINGLE] :MESSAGE:DPART :CCODE?

This command sets the channelization code for the physical random access channel (PRACH) message data part.

There are commands that are associated with the channelization code and they are the slot format and the symbol rate.

If the slot format is changed, so will the symbol rate. If the symbol rate is changed, so will the slot format. In addition, the channelization code will change. If current channelization code exceeded the new maximum value for the specified slot format or symbol rate, a setting conflict error is generated and the value is clipped to the maximum value. Refer to [Table 9-9](#).

Table 9-9 Channelization Code Maximum value

Channelization Code	Slot Format	Symbol Rate
255	0	15
127	1	30
63	2	60
31	3	120

***RST** +0

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Range	0–255
Field Entry	Channel Code
Remarks	Channel code value is determined by slot format choice. Refer to “:ULINK:PRACH:MESSAGE:DPART:SLOTformat” on page 1116 and “:ULINK:PRACH:MESSAGE:DPART:RATE” on page 1115. If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH[:SINGLE]:MESSAGE:TPOWer

Supported E4438C with Option 400

```
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : MESSAGE :
TPOWer <val>
```

```
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : MESSAGE : TPOWer?
```

This command sets the message total power value for the single physical random access channel (PRACH) and multiple PRACH modes. The variable <val> is expressed in units of decibels (dB). The RF output power is limited to the signal generator’s specifications

***RST** –1.36000000E+002

Range –136 to 20

Field Entry Msg Pwr

Remarks This value is used only when POWER:MODE is set to TOTAL. Refer to [“:ULINK:PRACH:PREamble:POWER:MODE”](#) on page 1124.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY”](#) on page 1075.

:ULINK:PRACH[:SINGLE]:NUMBer

Supported E4438C with Option 400

```
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] :
NUMBer <val> | INFINity
```

```
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : NUMBer?
```

This command specifies the number of the physical random access channel (PRACH) patterns to repeat after the PRACH start trigger has been received.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

INFINITY	This choice means the repeating number will continue while the PRACH mode is selected and the start trigger is ignored.
*RST	1
Range	1–2147447836
Field Entry	Number of PRACH
Remarks	If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH[:SINGLE]:PREAmble:NUMBER

Supported E4438C with Option 400

```
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : PREAmble :
NUMBER <val> | INFINITY
```

```
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : PREAmble : NUMBER ?
```

This command specifies the number of preambles to repeat in one physical random access channel (PRACH) pattern.

INFINITY	This choice means the repeating preamble will play continuously while the PRACH mode is selected.
-----------------	---

*RST	1
-------------	---

Range	1–8388607
--------------	-----------

Field Entry	PRACH Timing Setup: Number of Preamble PRACH Power Setup: Num of Pre
--------------------	---

:ULINK:PRACH[:SINGLE]:PREAmble:POWER:INITIAL

Supported E4438C with Option 400

```
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : PREAmble :
POWER : INITIAL ?
```

This query returns the initial preamble power from POWER:Max value, RSTeP (ramp step) and PREAmble:NUMBER commands.

*RST	–1.36000000E+002
-------------	------------------

Field Entry	Init Pwr
--------------------	----------

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

:ULINK:PRACH[:SINGLE]:PREamble:POWer:MAX**Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH[:SINGLE]:PREamble:
POWer:MAX <val>[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH[:SINGLE]:PREamble:
POWer:MAX?

This command sets the maximum preamble power for the physical random access channel (PRACH).

In power ramping mode (RSTep is a non-zero value), the preamble power can go up until the acquisition indication channel's (AICH) signal is not received (maximum power).

The variable <val> is expressed in units of decibels (dB).

***RST** -1.36000000E+002**Range** -136 to 20**Field Entry** Max Pwr**Remarks** The actual RF output is limited to the signal generator's specifications although the value can be entered up to 20 dBm.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:PRACH[:SINGLE]:PREamble:POWer:RSTep**Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH[:SINGLE]:PREamble:POWer:
RSTep <val>[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:PRACH[:SINGLE]:PREamble:POWer:
RSTep?

This command sets the power ramping steps for the single physical random access channel (PRACH) preamble.

The variable <val> is expressed in units of decibels (dB).

***RST** 0**Range** 0–10**Field Entry** Ramp Step

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

This command is used for single and multiple physical random access channel (PRACH) modes.

:ULINK:PRACH[:SINGLE]:PREamble:PPM

Supported E4438C with Option 400

```
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : PREamble : PPM <val>
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : PREamble : PPM?
```

This command sets the power difference between the preamble and the message control part in the single physical random access channel (PRACH).

The variable <val> is expressed in units of decibels (dB).

***RST** -4.56032509E+000

Range -20 to 10

Field Entry Pp-m

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:PRACH[:SINGLE]:PREamble:SIGNature

Supported E4438C with Option 400

```
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : PREamble :
SIGNature <val>
[ :SOURCE ] : RADio : WCDMa : TGPP [ : BBG ] : ULINK : PRACH [ : SINGLE ] : PREamble :
SIGNature?
```

This command sets the signature encoded in the single physical random access channel’s (PRACH) preamble.

***RST** +0

Range 0–15

Field Entry Signature

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:RMCHannel

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RMCHannel RMC122 | RMC64 | RMC144 |
RMC384 | UDI64 | AMR122
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RMCHannel?
```

This command configures the uplink reference measurement (RMC) channel by providing a one command access to a typical RMC configuration.

RMC122 This choice selects a reference measurement channel with a 12.2 kbps rate as per 3GPP TS 25.141.

RMC64 This choice selects a reference measurement channel with a 64.0 kbps rate as per 3GPP TS 25.141.

RMC144 This choice selects a reference measurement channel with a 144.0 kbps rate as per 3GPP TS 25.141.

RMC384 This choice selects a reference measurement channel with a 384.0 kbps rate as per 3GPP TS 25.141.

UDI64 This choice selects an ISDN unrestricted digital information 1B with a 64.0 kbps rate as per 3GPP TS 25.944.

ARM122 This choice selects an adaptive multiple rate of 12.2 kbps as per 3GPP TS 25.944.

***RST** RMC122

Key Entry	RMC122 kbps (25.141)	RMC64 kbps (25.141)
	RMC144 kbps (25.141)	RMC384 kbps (25.141)
	AMR 122 kbps	UDI 64 kbps

:ULINK:RPANel:DPCH:INPut:ALTPower

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RPANel:DPCH:INPut:ALTPower?
```

This query returns the type of signal at the alternate power input (ALT PWR IN, AUX I/O connector pin#16) for the dedicated physical channel (DPCH) mode.

***RST** USER

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks The signal name is TPC user file trigger (USER). For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:DPCH:INPut:BBGRef

Supported E4438C with Option 400

[:SOURCE] : RADio : WCDMa : TGPP [:BBG] : ULINK : RPANel : DPCH : INPut : BBGRef ?

This query returns the type of signal at the baseband generator reference input (BASEBAND GEN REF IN, rear panel connector) for the dedicated physical channel (DPCH) mode.

***RST** CCL

Remarks The signal name is baseband generator chip clock (CCL). For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:DPCH:INPut:BGATe

Supported E4438C with Option 400

[:SOURCE] : RADio : WCDMa : TGPP [:BBG] : ULINK : RPANel : DPCH : INPut : BGATe ?

This query returns the type of signal at the gate burst (BURST GATE IN, rear panel connector) for the dedicated physical channel (DPCH) mode.

***RST** CSTT

Remarks In compressed mode the signal name is compressed mode start trigger (CSST). In power control mode, the signal name is DPCH power control signal (DPCS). For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*

:ULINK:RPANel:DPCH:INPut:PTRigger1

Supported E4438C with Option 400

[:SOURCE] : RADio : WCDMa : TGPP [:BBG] : ULINK : RPANel : DPCH : INPut : PTRigger1 ?

This query returns the type of signal at the pattern trigger input 1 (PATT TRIG IN 1, rear panel) for the dedicated physical channel (DPCH) mode.

***RST** FSYN

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])

Remarks The signal name is frame synchronization (FSYN). For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:DPCH:INPut:PTRigger2

Supported E4438C with Option 400

```
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:RPANel:DPCH:INPut:PTRigger2?
```

This query returns the type of signal at the pattern trigger input 2 (PATT TRIG IN 2, AUX I/O connector pin#17) for the dedicated physical channel (DPCH) mode.

***RST** CSPT

Remarks The signal name is compress mode stop trigger (CSPT). For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:DPCH:OUTPut:DCLock

Supported E4438C with Option 400

```
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:RPANel:DPCH:OUTPut:DCLock RPS0 |
RPS1 | RPS2 | RPS3 | RPS4 | RPS5 | RPS6 | RPS7 | RPS8 | RPS9 | RPS10
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:RPANel:DPCH:OUTPut:DCLock?
```

This command assigns a signal to the data clock output at the selected rear panel AUX I/O connector pin#6. Refer to [Table 9-10 on page 1139](#) for command parameters and output signal type.

Table 9-10 Rear Panel Signal (RPS) Output Type

Command Parameter	Signal Out
RPS0	None
RPS1	Chip Clock
RPS2	DPDCH raw data
RPS3	DPDCH raw data clock
RPS4	DPCCH raw data
RPS5	DPCCH raw data clock

Table 9-10 Rear Panel Signal (RPS) Output Type

Command Parameter	Signal Out
RPS6	10ms frame pulse
RPS7	Trigger sync reply
RPS8	Compressed frame
RPS9	TTI frame pulse
RPS10	CFN #0 frame pulse

***RST** RPS1

Key Entry NONE (RPS0) Chip Clock (RPS1) DPDCH Raw Data (RPS2)
 DPDCH Data Raw Clock (RPS3) DPCCH Raw Data (RPS4)
 DPCCH Raw Data Clock (RPS5) 10 ms Frame Pulse (RPS6)
 Trigger Sync Reply (RPS7) Compressed Frame (RPS8)
 TTI Frame Clock (RPS9) CFN #0 Frame Pulse (RPS10)

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:DPCH:OUTPut:DOUT

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:RPANel:DPCH:OUTPut:DOUT RPS0 |
RPS1 | RPS2 | RPS3 | RPS4 | RPS5 | RPS6 | RPS7 | RPS8 | RPS9 | RPS10
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:RPANel:DPCH:OUTPut:DOUT?
```

This command assigns a signal to the data output at the selected rear panel AUX I/O connector pin#7. Refer to [Table 9-10 on page 1139](#) for command parameters and output signal type.

***RST** RPS4

Key Entry NONE (RPS0) Chip Clock (RPS1) DPDCH Raw Data (RPS2)
 DPDCH Data Raw Clock (RPS3) DPCCH Raw Data (RPS4)
 DPCCH Raw Data Clock (RPS5) 10 ms Frame Pulse (RPS6)
 Trigger Sync Reply (RPS7) Compressed Frame (RPS8)
 TTI Frame Clock (RPS9) CFN #0 Frame Pulse (RPS10)

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:DPCH:OUTPut:EVENT1

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:RPANel:DPCH:OUTPut:
EVENT1 RPS0|RPS1|RPS2|RPS3|RPS4|RPS5|RPS6|RPS7|RPS8|RPS9|RPS10
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:RPANel:DPCH:OUTPut:EVENT1?
```

This command assigns a signal to the EVENT 1 at the rear panel output connector. Refer to [Table 9-10 on page 1139](#) for command parameters and output signal type.

***RST** RPS2

Key Entry	NONE (RPS0)	Chip Clock (RPS1)	DPDCH Raw Data (RPS2)
	DPDCH Data Raw Clock (RPS3)		DPCCH Raw Data (RPS4)
	DPCCH Raw Data Clock (RPS5)		10 ms Frame Pulse (RPS6)
	Trigger Sync Reply (RPS7)		Compressed Frame (RPS8)
	Frame Clock (RPS9)		CFN #0 Frame Pulse (RPS10)

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:DPCH:OUTPut:EVENT2

Supported E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:RPANel:DPCH:OUTPut:
EVENT2 RPS0|RPS1|RPS2|RPS3|RPS4|RPS5|RPS6|RPS7|RPS8|RPS9|RPS10
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:RPANel:DPCH:OUTPut:EVENT2?
```

This command assigns a signal to the EVENT 2 at the rear panel output connector. Refer to [Table 9-10 on page 1139](#) for command parameters and output signal types.

***RST** RPS3

Key Entry	NONE (RPS0)	Chip Clock (RPS1)	DPDCH Raw Data (RPS2)
	DPDCH Data Raw Clock (RPS3)		DPCCH Raw Data (RPS4)
	DPCCH Raw Data Clock (RPS5)		10 ms Frame Pulse (RPS6)
	Trigger Sync Reply (RPS7)		Compressed Frame (RPS8)

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

	TTI Frame Clock (RPS9)	CFN #0 Frame Pulse (RPS10)
Remarks	For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the <i>E4428C/38C ESG Signal Generators User's Guide</i> .	

:ULINK:RPANel:DPCH:OUTPut:EVENT3

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RPANel:DPCH:OUTPut :
EVENT3 RPS0|RPS1|RPS2|RPS3|RPS4|RPS5|RPS6|RPS7|RPS8|RPS9|RPS10
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RPANel:DPCH:OUTPut:EVENT3?
```

This command assigns a signal to the EVENT 3 output at the selected rear panel AUX I/O connector pin#19. Refer to [Table 9-10 on page 1139](#) for command parameters and output signal type.

***RST** RPS0

Key Entry	NONE (RPS0)	Chip Clock (RPS1)	DPDCH Raw Data (RPS2)
	DPDCH Data Raw Clock (RPS3)	DPCCH Raw Data (RPS4)	
	DPCCH Raw Data Clock (RPS5)	10 ms Frame Pulse (RPS6)	
	Trigger Sync Reply (RPS7)	Compressed Frame (RPS8)	
	TTI Frame Clock (RPS9)	CFN #0 Frame Pulse (RPS10)	

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:DPCH:OUTPut:EVENT4

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RPANel:DPCH:OUTPut :
EVENT4 RPS0|RPS1|RPS2|RPS3|RPS4|RPS5|RPS6|RPS7|RPS8|RPS9|RPS10
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RPANel:DPCH:OUTPut:EVENT4?
```

This command assigns a signal to the EVENT 4 output at the selected rear panel AUX I/O connector pin#18. Refer to [Table 9-10 on page 1139](#) for command parameters and output signal type.

***RST** RPS0

Key Entry	NONE (RPS0)	Chip Clock (RPS1)	DPDCH Raw Data (RPS2)
	DPDCH Data Raw Clock (RPS3)	DPCCH Raw Data (RPS4)	
	DPCCH Raw Data Clock (RPS5)	10 ms Frame Pulse (RPS6)	

Wideband CDMA Base Band Generator Subsystem—Option 400 [:SOURCE]:RADio:WCDMa:TGPP[:BBG]

	Trigger Sync Reply (RPS7)	Compressed Frame (RPS8)
	TTI Frame Clock (RPS9)	CFN #0 Frame Pulse (RPS10)
Remarks	For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the <i>E4428C/38C ESG Signal Generators User's Guide</i> .	

:ULINK:RPANel:DPCH:OUTPut:SSYNc

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RPANel:DPCH:OUTPut:SSYNc RPS0 |
RPS1 | RPS2 | RPS3 | RPS4 | RPS5 | RPS6 | RPS7 | RPS8 | RPS9 | RPS10
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RPANel:DPCH:OUTPut:SSYNc?
```

This command assigns a signal to SYM SYNC OUT at the selected rear panel AUX I/O connector pin#5. Refer to [Table 9-10 on page 1139](#) for command parameters and output signal type.

***RST** RPS6

Key Entry	NONE (RPS0)	Chip Clock (RPS1)	DPDCH Raw Data (RPS2)
	DPDCH Data Raw Clock (RPS3)	DPCCH Raw Data (RPS4)	
	DPCCH Raw Data Clock (RPS5)	10 ms Frame Pulse (RPS6)	
	Trigger Sync Reply (RPS7)	Compressed Frame (RPS8)	
	TTI Frame Clock (RPS9)	CFN #0 Frame Pulse (RPS10)	

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:PRACH:INPut:ALTPower

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:RPANel:PRACH:INPut:ALTPower?
```

This query returns the signal type at the ALT PWR IN (alternate power in) connector pin for the physical random access channel (PRACH) mode.

***RST** NONE

Field Entry Alt power in

Remarks For more information about the rear panel AUX I/O connector pin configuration, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:PRACH:INPut:BBGRef

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:RPANel :PRACH: INPut :BBGRef?

This query returns the type of signal at the baseband generator reference input (BASEBAND GEN REF IN, rear panel connector) for the physical random access channel (PRACH) mode.

***RST** CCL

Remarks The signal name is baseband generator chip clock (CCL). For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:PRACH:INPut:BGATe

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:RPANel :PRACH: INPut :BGATe?

This query returns the signal type at the BURST GATE IN connector for the physical random access channel (PRACH) mode.

***RST** PSTR

Field Entry Burst gate in

Remarks The signal name is PRACH start trigger (PSTR). For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:PRACH:INPut:PTRigger1

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:RPANel :PRACH: INPut :PTRigger1?

This query returns the signal type at the pattern trigger in 1 (PATT TRIG IN) connector for the physical random access channel (PRACH) mode.

***RST** FSYN

Field Entry Pattern trigger in 1

Remarks The signal name is frame synchronization (FSYN). For more information about the rear panel I/O connectors' configuration, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:PRACH:INPut:PTRigger2**Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:RPANel:PRACH:INPut:PTRigger2?

This query returns the signal type at the pattern trigger input 2 (PATT TRIG IN 2 AUX I/O connector pin#17) for the physical random access channel (PRACH) mode.

***RST** AITR**Field Entry** Pattern trigger in 2

Remarks The signal name is AICH trigger (AITR). For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:PRACH:OUTPut:DCLock**Supported** E4438C with Option 400

```
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:DCLock RPS0 |
RPS1 | RPS6 | RPS7 | RPS11 | RPS12 | RPS13 | RPS14 | RPS15 | RPS16 |
RPS17 | RPS19 | RPS20 | RPS21 | RPS22 | RPS23 | RPS24 | RPS25
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:DCLock?
```

This command assigns a signal at the data clock output for the selected rear panel AUX I/O connector pin#6.

RPS0 none

RPS1 This choice assigns the chip clock signal.

RPS6 This choice assigns the 10ms frame pulse signal.

RPS7 This choice assigns the trigger sync reply signal.

RPS11 This choice assigns the message-data raw data signal. In the multiple PRACH mode, RPS11 outputs the message-data raw data signal of PRACH#1. If the PRACH#1 is not "on", no signal output is output.

RPS12 This choice assigns the message-data raw clock signal. In the multiple PRACH mode, RPS12 outputs the message-data raw clock signal of PRACH#1. If the PRACH#1 is not "on", no signal output is output.

RPS14 This choice assigns the message-ctrl raw data clock signal. In the multiple PRACH mode, RPS14 outputs the message-control raw data clock signal of PRACH#1. If the PRACH#1 is not "on", no signal output is output.

RPS15 This choice assigns the preamble raw data signal. In the multiple PRACH mode,

	RPS15 outputs the preamble raw data signal of PRACH#1. If the PRACH#1 is not “on”, no signal output is output.
RPS16	This choice assigns the preamble raw data clock signal. In the multiple PRACH mode, RPS16 outputs the preamble raw data clock signal of PRACH#1. If the PRACH#1 is not “on”, no signal output is output.
RPS17	This choice assigns the sub channel timing signal. Sub channel timing is used on the single PRACH mode.
RPS19	This choice assigns the PRACH processing signal. This signal indicates the PRACH is generating.
RPS20	This choice assigns the 80ms frame pulse signal.
RPS21	This choice assigns the preamble pulse signal. This signal indicates the preamble timing of all configured PRACHes. One pulse for one preamble. In the multiple PRACH mode, this output relates to PRACH#1. If the PRACH#1 in not “on”, no signal is output.
RPS22	This choice assigns the message pulse signal. This signal indicates the message part timing of all configured PRACHes. In the multiple PRACH mode, this output relates to PRACH#1. If the PRACH#1 in not “on”, no signal is output.
RPS23	This choice assigns the PRACH pulse signal. This signal indicates the start timing of all configured PRACHes. In the multiple PRACH mode, this output relates to PRACH#1. If the PRACH#1 in not “on”, no signal is output.
RPS24	This choice assigns the ESG synchronization signal. This signal is used for the multiple EAG synchronization on the multiple PRACH mode.
RPS25	This choice assigns the PRACH start trigger echo back signal. The PRACH start trigger echo back signal is used for the multiple ESG connection on the multiple PRACH mode.
*RST	RPS0
Key Entry	NONE (RPS0) Chip Clock (RPS1) Message-Data Raw Data (RPS11) 10ms Frame Pulse (RPS6) Trigger Sync Reply (RPS7) Message-Data Raw Clock (RPS12) Message-Control Raw Data (RPS13) Message-Control Raw Data Clock(RPS14) Preamble Raw Data(RPS15) Preamble Raw Data Clock(RPS16) Sub Channel Timing(RPS17) PRACH Processing(RPS19) 80ms Frame Pulse(RPS20) Preamble Pulse(RPS21) Message Pulse(RPS22) PRACH Pulse(RPS23)

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])

	ESG-Sync Sig(RPS24)	Start-Trigger EchoBack(RPS25)
Remarks	For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the <i>E4428C/38C ESG Signal Generators User's Guide</i> .	

:ULINK:RPANel:PRACH:OUTPut:DOUT

Supported E4438C with Option 400

```
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:DOUT RPS0 |
RPS1 | RPS6 | RPS7 | RPS11 | RPS12 | RPS13 | RPS14 | RPS14 | RPS15 | RPS16 | RPS17 | RPS19 |
RPS20 | RPS21 | RPS22 | RPS23 | RPS24 | RPS25
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:DOUT?
```

This command assigns a signal to the data output at the selected rear panel AUX I/O connector pin#7.

For parameter descriptions refer to “:ULINK:RPANel:PRACH:OUTPut:DCLock” on page 1145.

***RST** RPS0

Key Entry	NONE (RPS0)	Chip Clock (RPS1)	Message-Data Raw Data (RPS11)
	10ms Frame Pulse (RPS6)	Trigger Sync Reply (RPS7)	
	Message-Data Raw Clock (RPS12)	Message-Control Raw Data (RPS13)	
	Message-Control Raw Data Clock(RPS14)		
	Preamble Raw Data(RPS15)	Preamble Raw Data Clock(RPS16)	
	Sub Channel Timing(RPS17)	PRACH Processing(RPS19)	
	80ms Frame Pulse(RPS20)	Preamble Pulse(RPS21)	
	Message Pulse(RPS22)	PRACH Pulse(RPS23)	
	ESG-Sync Sig(RPS24)	Start-Trigger EchoBack(RPS25)	

Remarks	For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the <i>E4428C/38C ESG Signal Generators User's Guide</i> .		
----------------	--	--	--

:ULINK:RPANel:PRACH:OUTPut:EVENT1

Supported E4438C with Option 400

```
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:EVENT1 RPS0 |
RPS1 | RPS6 | RPS7 | RPS11 | RPS12 | RPS13 | RPS14 | RPS14 | RPS15 | RPS16 | RPS17 | RPS19 |
RPS20 | RPS21 | RPS22 | RPS23 | RPS24 | RPS25
[:SOURCE]:RADIo:WCDMa:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:EVENT1?
```

This command assigns a signal to the EVENT 1 at the selected rear panel connector.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

For parameter descriptions refer to “:ULINK:RPANel:PRACH:OUTPut:DCLock” on page 1145.

*RST	RPS0
Key Entry	NONE (RPS0) Chip Clock (RPS1) Message-Data Raw Data (RPS11) 10ms Frame Pulse (RPS6) Trigger Sync Reply (RPS7) Message-Data Raw Clock (RPS12) Message-Control Raw Data (RPS13) Message-Control Raw Data Clock(RPS14) Preamble Raw Data(RPS15) Preamble Raw Data Clock(RPS16) Sub Channel Timing(RPS17) PRACH Processing(RPS19) 80ms Frame Pulse(RPS20) Preamble Pulse(RPS21) Message Pulse(RPS22) PRACH Pulse(RPS23) ESG-Sync Sig(RPS24) Start-Trigger EchoBack(RPS25)

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:PRACH:OUTPut:EVENT2

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:RPANel :PRACH:OUTPut :EVENT2 RPS0
 RPS1|RPS6|RPS7|RPS11|RPS12|RPS13|RPS14|RPS14|RPS15|RPS16|RPS17|RPS19|RPS20|RPS21
 RPS22|RPS23|RPS24|RPS25

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:RPANel :PRACH:OUTPut :EVENT2?

This command assigns a signal to the EVENT 2 at the rear panel connector.

For parameter descriptions refer to “:ULINK:RPANel:PRACH:OUTPut:DCLock” on page 1145.

*RST	RPS0
Key Entry	NONE (RPS0) Chip Clock (RPS1) Message-Data Raw Data (RPS11) 10ms Frame Pulse (RPS6) Trigger Sync Reply (RPS7) Message-Data Raw Clock (RPS12) Message-Control Raw Data (RPS13) Message-Control Raw Data Clock(RPS14) Preamble Raw Data(RPS15) Preamble Raw Data Clock(RPS16) Sub Channel Timing(RPS17) PRACH Processing(RPS19) 80ms Frame Pulse(RPS20) Preamble Pulse(RPS21) Message Pulse(RPS22) PRACH Pulse(RPS23)

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

	ESG-Sync Sig(RPS24)	Start-Trigger EchoBack(RPS25)
Remarks	For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the <i>E4428C/38C ESG Signal Generators User's Guide</i> .	

:ULINK:RPANel:PRACH:OUTPut:EVENT3

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:EVENT3 RPS0 |
RPS1 | RPS6 | RPS7 | RPS11 | RPS12 | RPS13 | RPS14 | RPS14 | RPS15 | RPS16 | RPS17 | RPS19 |
RPS20 | RPS21 | RPS22 | RPS23 | RPS24 | RPS25
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:EVENT3?
```

This command assigns a signal to the EVENT 3 output at the selected rear panel AUX I/O connector pin#19.

For parameter descriptions refer to “:ULINK:RPANel:PRACH:OUTPut:DCLock” on page 1145.

***RST** RPS0

Key Entry	NONE (RPS0)	Chip Clock (RPS1)	Message-Data Raw Data (RPS11)
	10ms Frame Pulse (RPS6)	Trigger Sync Reply (RPS7)	
	Message-Data Raw Clock (RPS12)	Message-Control Raw Data (RPS13)	
	Message-Control Raw Data Clock(RPS14)		
	Preamble Raw Data(RPS15)	Preamble Raw Data Clock(RPS16)	
	Sub Channel Timing(RPS17)	PRACH Processing(RPS19)	
	80ms Frame Pulse(RPS20)	Preamble Pulse(RPS21)	
	Message Pulse(RPS22)	PRACH Pulse(RPS23)	
	ESG-Sync Sig(RPS24)	Start-Trigger EchoBack(RPS25)	

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:PRACH:OUTPut:EVENT4

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:EVENT4 4RPS0 |
RPS1 | RPS6 | RPS7 | RPS11 | RPS12 | RPS13 | RPS14 | RPS14 | RPS15 | RPS16 | RPS17 | RPS19 |
RPS20 | RPS21 | RPS22 | RPS23 | RPS24 | RPS25
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:EVENT4?
```

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

This command assigns a signal to the EVENT 4 output at the selected rear panel AUX I/O connector pin#18.

For parameter descriptions refer to “:ULINK:RPANel:PRACH:OUTPut:DCLock” on page 1145.

***RST** RPS0

Key Entry **NONE (RPS0)** **Chip Clock (RPS1)** **Message-Data Raw Data (RPS11)**
10ms Frame Pulse (RPS6) **Trigger Sync Reply (RPS7)**
Message-Data Raw Clock (RPS12) **Message-Control Raw Data (RPS13)**
Message-Control Raw Data Clock(RPS14)
Preamble Raw Data(RPS15) **Preamble Raw Data Clock(RPS16)**
Sub Channel Timing(RPS17) **PRACH Processing(RPS19)**
80ms Frame Pulse(RPS20) **Preamble Pulse(RPS21)**
Message Pulse(RPS22) **PRACH Pulse(RPS23)**
ESG-Sync Sig(RPS24) **Start-Trigger EchoBack(RPS25)**

Remarks For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the *E4428C/38C ESG Signal Generators User's Guide*.

:ULINK:RPANel:PRACH:OUTPut:SSYNc

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:RPANel:PRACH:OUTPut:SSYNc RPS0 | RPS1 | RPS6 | RPS7 | RPS11 | RPS12 | RPS13 | RPS14 | RPS14 | RPS15 | RPS16 | RPS17 | RPS19 | RPS20 | RPS21 | RPS22 | RPS23 | RPS24 | RPS25
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:RPANel:PRACH:OUTPut:SSYNc?

This command assigns a signal to SYM SYNC OUT at the selected rear panel AUX I/O connector pin#5.

For parameter descriptions refer to “:ULINK:RPANel:PRACH:OUTPut:DCLock” on page 1145.

***RST** RPS0

Key Entry **NONE (RPS0)** **Chip Clock (RPS1)** **Message-Data Raw Data (RPS11)**
10ms Frame Pulse (RPS6) **Trigger Sync Reply (RPS7)**
Message-Data Raw Clock (RPS12) **Message-Control Raw Data (RPS13)**
Message-Control Raw Data Clock(RPS14)
Preamble Raw Data(RPS15) **Preamble Raw Data Clock(RPS16)**
Sub Channel Timing(RPS17) **PRACH Processing(RPS19)**

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURce]:RADio:WCDMa:TGPP[:BBG])

	80ms Frame Pulse(RPS20)	Preamble Pulse(RPS21)
	Message Pulse(RPS22)	PRACH Pulse(RPS23)
	ESG-Sync Sig(RPS24)	Start-Trigger EchoBack(RPS25)
Remarks	For more information about the rear panel connector configurations, refer to "Signal Generator Overview" in the <i>E4428C/38C ESG Signal Generators User's Guide</i> .	

:ULINK:SCRamblecode

Supported	E4438C with Option 400
	<code>[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:SCRamblecode <val></code>
	<code>[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:SCRamblecode?</code>
	This command sets the uplink scramble code.
*RST	+0
Range	0–16777215
Field Entry	Scrambling Code

:ULINK:SDElay

Supported	E4438C with Option 400
	<code>[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:SDElay <val></code>
	<code>[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:SDElay?</code>
	This command sets the number of timeslots to be delayed for the dedicated physical channel (DPCH).
*RST	+0
Range	0–119
Key Entry	Timeslot Offset
Remarks	The actual amount of timing offset is $(T0) + (TOFFset) + (SDElay) * 2560$ chips, where $T0 = 1024$ chips. This command is not used when the sync source is set to ESG. Refer to “:ULINK:SYNC[:SOURce]” on page 1152 .

:ULINK:SFNRst:POLarity

Supported	E4438C with Option 400
------------------	------------------------

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:SFNRst:POLarity POSitive|NEGative
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:SFNRst:POLarity?
```

This command sets the polarity of the system frame number reset signal for the uplink synchronization source.

POSitive This choice sets the signal to trigger when the trigger signal is high.

NEGative This choice sets the signal to trigger when the trigger signal is low.

***RST** POS

Key Entry **SFN RST Polarity Neg Pos**

Remarks This command is not used when the sync source is set to ESG. Refer to “:ULINK:SYNC[:SOURCE]” on page 1152.

:ULINK:SYNC:MODE

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:SYNC:MODE SINGLE|CONTinuous
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:SYNC:MODE?
```

This command selects the uplink frame synchronization triggering mode.

SINGLE This choice sets the signal generator, once triggered, to generate frames based on the reference clock.

CONTinuous This choice sets the signal generator to continuously align the frame sync trigger signal and the frame timing.

***RST** SING

Key Entry **Frame Sync Trigger Mode Single Cont**

:ULINK:SYNC[:SOURCE]

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:SYNC[:SOURCE] SFN_RST|FCLock|ESG
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:SYNC[:SOURCE] ?
```

This command selects the uplink frame synchronization source type.

SFN_RST This choice sets the signal to trigger on the system frame number reset signal.

FCLock This choice sets the signal to trigger on the frame clock.

ESG This choice sets the signal to trigger on the synchronization signal of a primary ESG.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

*RST	FCL				
Key Entry	Sync Source	SFN	FCIk	ESG	

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:TGAP:POFFset**

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:TGAP:POFFset <val> | AUTO
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:TGAP:POFFset?
```

This command specifies the amount of power to be increased when the data is being compressed for the transmission gap power offset.

AUTO This choice sets the power to increase using the gap pattern parameters calculation based on 3GPP standard. When AUTO is selected, the query returns “AUTO” as the value.

The variable <val> is expressed in units of decibels (dB).

***RST** AUTO

Range 0–6

Field Entry PwrOffs

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK:TGAP:PSI[1] | 2 | 3 | 4 | 5 | 6:CFN

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:TGAP:PSI [1] | 2 | 3 | 4 | 5 | 6 :CFN <val>
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:TGAP:PSI [1] | 2 | 3 | 4 | 5 | 6 :CFN?
```

This command sets the connection frame number (CFN) for the first radio frame of the first pattern 1.

***RST** 0

Range 1–255

Field Entry TGCFN

Remarks In the signal generator, CFN is counted internally relative to the system sync signal.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

:ULINK:TGAP:PSI[1]:CMMethod**Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:TGAP:PSI[1]:CMMethod SF2|HIGHER
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:TGAP:PSI[1]:CMMethod?

This command selects the compressed mode (CM) method.

SF2 This choice selects a compressed mode method that reduced the spread factor (SF) by 2. This is done by increasing the data rate by reducing the spreading factor in half. When the dedicated physical data channel's (DPDCH) symbol rate is 960 kbps, the frame is not compressed because it uses the lowest SF value and it cannot be reduced.

HIGHER This choice selects a higher layer scheduling method. The emulated higher layer scheduling method mode keeps the same physical layer data rate even when a transmission gap is created.

***RST** SF2**Key Entry** SF/2 Higher Layer

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

The ULINK:APPLY command will fail if the CM method is higher layer and DPDCH data is TrCH. CM method should be SF/2 if the DPDCH data is TrCH.

:ULINK:TGAP:PSI[1]|2|3|4|5|6:D**Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:D
<val>|UNDEFINED
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:D?

This command sets the transmission gap distance. The command specifies the number of slots between the starting slots of two consecutive transmission gaps within a transmission gap pattern.

UNDEFINED This choice sets one transmission gap. When UNDEFINED is selected, then there is only one transmission gap within the transmission gap pattern.

***RST** UND**Range** 15–269**Field Entry** TGD

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:TGAP:PSI[1]|2|3|4|5|6:L1****Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6
:L1 3|4|5|7|10|14

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:L1?

This command specifies the length of the first transmission gap (TGL1). The length is expressed in number of slots.

RST** +7**Field Entry** TGL1**:ULINK:TGAP:PSI[1]|2|3|4|5|6:L2*Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6
:L2 3|4|5|7|10|14|OMITted

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:L2?

This command specifies the length of the second transmission gap (TGL2). When OMITted is selected, TGL2=TGL1.

RST** OMIT**Field Entry** TGL2**:ULINK:TGAP:PSI[1]|2|3|4|5|6:PL1*Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:PL1 <val>
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:PL1?

This command specifies the duration of the transmission gap pattern length 1 (TGPL1). The pattern length is expressed in number of frames.

***RST** +2**Range** 1–144**Field Entry** TGPL1

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK:TGAP:PSI[1]|2|3|4|5|6:PL2****Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:PL2 <val> |
OMITted

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:PL2?

This command specifies the duration of the transmission gap pattern length 2 (TGPL2).

The variable <val> is expressed in number of frames. When OMITted is selected, TGPL2=TGPL1.

RST** OMIT**Range** 1–144**Field Entry** TGPL2**Key Entry** **Omitted*:ULINK:TGAP:PSI[1]|2|3|4|5|6:POWer****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:POWer?

This query returns each power level for a compressed slot.

The return string has five real numbers followed by dBm (for normal power) or dB (for before/after gap power) separated by a single space character. When a value does not exist because of a specified compressed pattern (Example: Gap2 does not exist when TGD is “UNDefined”), it returns “–dB.”

Normal power value represents an actual power level in dBm and relative power is represented in dB.

:ULINK:TGAP:PSI[1]|2|3|4|5|6:PRC**Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:PRC <val> |
INFIinity

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1]|2|3|4|5|6:PRC?

This command sets the transmission gap pattern repetition count. The pattern repetition count (PRC) sets the number of transmission gap patterns within the transmission gap pattern sequence.

***RST** INF**Range** 1–511**Field Entry** TGPRC

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**Key Entry** **Infinity****Remarks** When INFINITY is selected, the PRC will continue indefinitely.**:ULINK:TGAP:PSI[1] | 2 | 3 | 4 | 5 | 6:PS****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1] | 2 | 3 | 4 | 5 | 6:PS ACTIVE | INACTIVE

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1] | 2 | 3 | 4 | 5 | 6:PS?

This command sets the transmission gap pattern status.

ACTIVE This choice sets the compressed mode active.

INACTIVE This choice sets the compressed mode inactive.

RST** INAC**Key Entry** **TGPS Active Inactive*:ULINK:TGAP:PSI[1] | 2 | 3 | 4 | 5 | 6:SN****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1] | 2 | 3 | 4 | 5 | 6:SN <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:PSI[1] | 2 | 3 | 4 | 5 | 6:SN?

This command specifies the timeslot number of the first transmission gap within the first radio frame.

RST** +11**Range** 0–14**Field Entry** TGSN**:ULINK:TGAP:RPARAMeter*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:RPARAMeter DREF11 | DREF12 | DREF21 | DREF22

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:RPARAMeter?

This command sets the downlink reference compressed mode parameters as defined in 3GPP Standard TS25.101.

DREF11 This choice sets the reference parameter to 1.1.

DREF12 This choice sets the reference parameter to 1.2.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

DREF21	This choice sets the reference parameter to 2.1.		
DREF22	This choice sets the reference parameter to 2.2.		
*RST	CUST		
Key Entry	DL Reference 1.1	DL Reference 1.2	DL Reference 2.1
	DL Reference 2.2		
Remarks	The query returns CUSTom when the parameters are set individually.		

:ULINK:TGAP:SCFN

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:TGAP:SCFN <val>

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:TGAP:SCFN?

This command sets the stop connection frame number (CFN) when the stop trigger is used.

When the stop trigger is received at the signal generator, the next stop CFN, the compressed mode will finish even if the transmission gap pattern repetition count (TGPRC) is still remaining.

*RST +0

Range 0–255

Field Entry SCFN

Remarks The compressed mode stop trigger must be used for this command to executed. Refer to “:ULINK:TGAP:STOP:TRIGger” on page 1160.

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

This command is not used when the sync source is set to ESG. Refer to “:ULINK:SYNC[:SOURCE]” on page 1152.

:ULINK:TGAP[:STATe]

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:TGAP [:STATe] ON|OFF|1|0

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK:TGAP [:STATe] ?

This command enables or disables the uplink transmission gap pattern.

*RST 1

Key Entry **Compress Mode Off On**

:ULINK:TGAP:START:TRIGger

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:START:TRIGger

This command starts the compressed mode trigger.

Key Entry **Compressed Mode Start Trigger**

:ULINK:TGAP:START:TRIGger:POLarity

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:START:TRIGger:
POLarity POSitive|NEGative

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:START:TRIGger:POLarity?

This command sets the compressed mode start trigger signal polarity.

POSitive This choice sets the trigger to start when the trigger signal is high.

NEGative This choice sets the trigger to start when the trigger signal is low.

***RST** POS

Key Entry **Comp Mode Start Trigger Polarity Neg Pos**

:ULINK:TGAP:STOP:TRIGger

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:STOP:TRIGger

This command stops the compressed mode trigger.

Key Entry **Compressed Mode Stop Trigger**

:ULINK:TGAP:STOP:TRIGger:POLarity

Supported E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:STOP:TRIGger:
POLarity POSitive|NEGative

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TGAP:STOP:TRIGger:POLarity?

This command sets the compressed mode stop trigger signal polarity.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURce]:RADio:WCDMa:TGPP[:BBG])

POSitive	This choice sets the trigger to stop when the trigger signal is high.
NEGative	This choice sets the trigger to stop when the trigger signal is low.
*RST	POS
Key Entry	Comp Mode Stop Trigger Polarity Neg Pos

:ULINK:TOffset

Supported E4438C with Option 400

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:TOffset <val>
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:TOffset?
```

This command sets additional timing offset for the dedicated physical channel (DPCH). Timing offset is the time delay between the downlink signal and the uplink signal. The downlink signal timing is provided by the synchronization signal.

*RST	+0
Range	–512 to 2560
Key Entry	Timing Offset
Remarks	The actual amount of timing offset is (T0) + (TOFFset) + (SDElay) where T0 = 1024 chips.

:ULINK:TStatus:COMPRESSED

Supported E4438C with Option 400

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:TStatus:COMPRESSED?
```

This query returns the status of compressed pattern generation. A “0” response indicates the compressed mode pattern signal is not generating. A “1” response indicates that the compressed mode pattern signal is generating.

*RST	0
------	---

:ULINK:TStatus:RACH

Supported E4438C with Option 400

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK:TStatus:RACH?
```

This query returns the status of the physical random access channel (PRACH). A “0” response indicates the PRACH signal is not generating. A “1” response indicates that the PRACH signal is generating.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

***RST** 0

:ULINK:TStatus:RECeive

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TStatus:RECeive?
```

This query returns the frame synchronization signal reception status.

When the frame synchronization signal is received after synchronization configuration, the received value becomes “1.” If the signal is not received, the value is “0.”

***RST** 0

:ULINK:TStatus:SYNC

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:TStatus:SYNC?
```

This query returns the frame synchronization status. A “0” status indicates frame synchronization is fine or no frame synchronization signal is received). A “1” indicates frame synchronization is out sync and the synchronization signal does not match with the signal generator’s timing. The signal generator will generate incorrect data

***RST** 0

:ULINK:[TGRoup[1]]:DCH[1]|2|3|3|5|6:BLKSize

Supported E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:[TGRoup[1]]:DCH[1]|
2|3|4|5|6:BLKSize <val>
```

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:[TGRoup[1]]:DCH[1]|
2|3|4|5|6:BLKSize?
```

This command sets the block size for the selected uplink dedicated channel (DCH).

***RST** DCH1: 244 DCH2: 100 DCH3,4,5,6: 20

Range 0–5000

Key Entry Blk Size

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:BPFRame**Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:BPFRame?

This query returns the number of bits per frame for the selected dedicated transport channel (DCH).

RST** DCH1: 490 DCH2: 110 DCH3–6: 60**Field Entry** Bits/Frame**:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:BRATe*Supported** E4438C with Option 400

[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:BRATe?

This query returns the bit rate for the selected dedicated transport channel (DCH)

RST** DCH1: 12200 DCH2: 2500 DCH3–6: 2000**Range** 0–5000**:ULINK[:TGRoup[1]]:DCH[1]|2|3|3|5|6:CODE*Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:CODE HCONv|TCONv|TURBo|NONE
[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:CODE?

This command sets the encoder type for the uplink dedicated channel (DCH) selected.

HCONv This choice selects a coding with the 1/2 rate convolutional encoder.**TCONv** This choice selects a coding with the 1/3 rate convolutional encoder.**TURBo** This choice selects a coding with the turbo coder.**NONE** This choice selects no coding type.***RST** DCH1,2: TCONv DCH3,4,5,6: HCONv**Key Entry** 1/2 Conv 1/3 Conv Turbo NONE**Remarks** If the choice, set by this command, is changed while the signal is active, the apply command must be sent to set the change. See “:ULINK:APPLY” on page 1075.

:ULINK:[TGRoup[1]]:DCH[1]|2|3|3|5|6:CRc**Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:[TGRoup[1]]:DCH[1]|
2|3|4|5|6:CRc 0|8|12|16|24
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:[TGRoup[1]]:DCH[1]|
2|3|4|5|6:CRc?
```

This command specifies the number of cyclic redundancy code (CRC) bits to be added to each transport channel block.

***RST** DCH1: 16 DCH2: 12 DCH3,4,5,6: 8**Field Entry** CRC Size

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK:[TGRoup[1]]:DCH[1]|2|3|3|5|6:DATA**Supported** E4438C with Option 400

```
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:[TGRoup[1]]:DCH[1]|
2|3|4|5|6:DATA PN9|FIX4|"<file name>"
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:[TGRoup[1]]:DCH[1]|
2|3|4|5|6:DATA?
```

This command configures the data type to be inserted into the selected uplink dedicated channel (DCH).

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** PN9**Key Entry** **PN9** **FIX4** **User File**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])**:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BER:ACTual****Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1] |
2 | 3 | 4 | 5 | 6:DATA:BER:ACTual?

This query returns the actual inserted error ratio in the uplink dedicated channel (DCH) selected.

RST** +0.0000000E+000**Remarks** The actual bit error rate can be different from the specified bit error rate due to the internal bit generation.**:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BER:ERRor:BIT*Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:
DATA:BER:ERRor:BIT?

This query returns the actual error bits inserted in total number of bits.

RST** +0**Field Entry** Error Bits**:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BER:TOTal:BIT*Supported** E4438C with Option 400[:SOURCE]:RADIO:WCDMA:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:
DATA:BER:TOTal:BIT?

This query returns the total number of bits inserted for the bit error ratio calculation.

***RST** 0**Field Entry** Total Bits

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BER[:VALue]**

Supported E4438C with Option 400

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [1] ] :DCH [1] | 2 | 3 | 4 | 5 | 6 :
DATA:BER [ :VALue ] <val>
```

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [1] ] :DCH [1] | 2 | 3 | 4 | 5 | 6 :
DATA:BER [ :VALue ] ?
```

This command specifies the bit error rate (BER) value to be inserted into the selected uplink dedicated channel (DCH). The variable <val> is expressed in decimal form as a percent ratio (1.0=100%).

***RST** 0.0000000+000

Range 0.0001–1.0

Field Entry BER

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BLER:ACTual

Supported E4438C with Option 400

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [1] ] :DCH [1] |
2 | 3 | 4 | 5 | 6 :DATA:BLER:ACTual?
```

This query returns the actual block error ratio inserted.

***RST** 0.0000000E+000

Remarks The actual block error rate can be different from the specified block error rate due to the internal bit generation.

:ULINK[:TGRoup[1]] | 2:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BLER:ERRor:BLOCK

Supported E4438C with Option 400

```
[ :SOURce ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [1] ] | 2 :DCH [1] | 2 | 3 | 4 | 5 | 6 :
DATA:BLER:ERRor:BLOCK?
```

This query returns the number of error blocks inserted.

***RST** +0

Field Entry Error Blocks

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK[:TGRoup[1] | 2:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BLER:TOTal:BLOCK****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1] | 2:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BLER:TOTal:BLOCK?

This query returns the error blocks actually inserted in total number of blocks.

RST** +0**Field Entry** Total Blocks**:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BLER[:VALue]*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BLER[:VALue] <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1] | 2 | 3 | 4 | 5 | 6:DATA:BLER[:VALue]?

This command specifies the block error rate (BLER) value to be inserted into the selected uplink dedicated channel (DCH).

The variable <val> is expressed in decimal form as a percent ratio (1.0=100%).

***RST** +0.00000000E+000**Range** 0.0–1.00**Field Entry** BLER**Remarks** If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:DATA:EINSert****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:DATA:EINSert BLER|BER|NONE

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:DATA:EINSert?

This command selects the error insertion mode.

BLER This choice selects a block error rate (BLER) mode.**BER** This choice selects a bit error rate (BER) mode.**NONE** This choice selects no BLER or BER mode (no error blocks or bits inserted).***RST** NONE**Key Entry** **BLER** **BER** **None****:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:DATA:FIX4****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:DATA:FIX4 <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:DATA:FIX4?

This command sets the 4 bit data pattern for the selected uplink dedicated channel (DCH).

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

***RST** #B0000**Range** 0–15**Key Entry** **FIX4**

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:NBLock****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:NBLock <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:NBLock?

This command specifies the number of transport blocks coded on to the selected dedicated channel (DCH).

RST** +1**Range** 0–4095**Field Entry** Num of Blk**:ULINK[:TGRoup [1]]:DCH[1]|2|3|4|5|6:PPERcentage*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:PPERcentage?

This query returns the percentage of the total bits removed from or added to the fully coded channel.

The value is returned in the unit of percent and a negative value means repetition.

Field Entry Puncture**:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:RMATch****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:RMATch <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:RMATch?

This command specifies the rate matching parameters of each dedicated channel (DCH) selected.

***RST** DCH1: 2 DCH2: 12 DCH3,4,5,6: 1**Range** 1–256**Field Entry** Rate Match Attr

:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:TTI**Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:
TTI 10000|20000|40000|80000

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6:TTI?

This command sets the transmission time interval (TTI) period for the dedicated channel (DCH) selected. TTI is the time interval of the amount of data to be transmitted.

The choices are expressed in units of milliseconds (msec) where 20000 = 20 msec.

RST** DCH1: 20000 DCH2: 40000 DCH3,4,5,6: 10000**Field Entry** TTI**Remarks** The data amount equals the block size (BLKsize) times the number of transport blocks (NBlock).**:ULINK[:TGRoup[1]]:DCH[1]|2|3|4|5|6[:STATe]*Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|
2|3|4|5|6[:STATe] ON|OFF|1|0[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:DCH[1]|
2|3|4|5|6[:STATe]?

This command enables or disables the operating state of the dedicated channel (DCH) selected.

RST** DCH1,2: 1 DCH3,4,5,6: 0**Key Entry** TrCH State Off On**:ULINK[:TGRoup[1]]:RACH[1]:BLKSize*Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:RACH[1]:BLKSize <val>
[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:RACH[1]:BLKSize?

This command sets the transport block size for the random access channel (RACH) coding where the input data is carried.

***RST** +168**Range** 0–5000**Field Entry** Blk Size

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK[:TGRoup [1]]:RACH[1]:BPFRame

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK [:TGRoup [1]] :RACH [1] :BPFRame?

This query returns the bits per frame for the selected random access channel (RACH).

***RST** +600

:ULINK[:TGRoup [1]]:RACH[1]:BRATe

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK [:TGRoup [1]] :RACH [1] :BRATe?

This query returns the bit rate for the random access transport channel (RACH).

***RST** +8400

:ULINK[:TGRoup[1]]:RACH[1]:CODE

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK [:TGRoup [1]] :RACH [1] :CODE?

This query returns the type of channel coding for error protection.

***RST** HCON

:ULINK[:TGRoup[1]]:RACH[1]:CRC

Supported E4438C with Option 400

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK [:TGRoup [1]] :RACH [1] :
CRC 0 | 8 | 12 | 16 | 24

[:SOURCE] :RADio:WCDMa:TGPP [:BBG] :ULINK [:TGRoup [1]] :RACH [1] :CRC?

This command specifies the number of cyclic redundancy code (CRC) bits that are to be added to each transport channel block.

***RST** +16

Field Entry CRC Size

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK[:TGRoup[1]]:RACH[1]:DATA

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [ 1 ] ] :RACH [ 1 ] :DATA PN9 |
FIX4 | "<file name>"
```

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [ 1 ] ] :RACH [ 1 ] :DATA?
```

This command sets the type of data to be inserted into the random access channel (RACH).

"<file name>" This variable specifies a data pattern that has been stored in memory.

***RST** PN9

Key Entry **PN9** **FIX4** **User File**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK[:TGRoup[1]]:RACH[1]:DATA:BER:ACTual

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [ 1 ] ] :RACH [ 1 ] :DATA:BER :
ACTual?
```

This query returns the actual error ratio inserted.

***RST** +0

Range 0–5000

Key Entry **Actual BER**

Remarks The specified error ratio and actual ratio will not match when the internal bit generation goes into “pre-computing” mode.

:ULINK[:TGRoup[1]]:RACH[1]:DATA:BER:ERRor:BIT

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [ 1 ] ] :RACH [ 1 ] :DATA:BER :
ERRor:BIT?
```

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIo:WCDMa:TGPP[:BBG])

This query returns the actual error bits inserted for the total number of bits.

***RST** 0

:ULINK[:TGRoup[1]]:RACH[1]:DATA:BER:TOTal:BIT

Supported E4438C with Option 400

[:SOURCE] :RADIo:WCDMa:TGPP [:BBG] :ULINK [:TGRoup [1]] :RACH [1] :DATA:BER:TOTal:BIT?

This query returns the total number of bits inserted for the bit error ratio calculation.

***RST** 0

Remarks The specified error ratio and actual ratio will not match when the internal bit generation goes into “pre-computing” mode.

:ULINK[:TGRoup[1]]:RACH[1]:DATA:BER[:VALue]

Supported E4438C with Option 400

[:SOURCE] :RADIo:WCDMa:TGPP [:BBG] :ULINK [:TGRoup [1]] :RACH [1] :DATA:BER [:VALue] <val>

[:SOURCE] :RADIo:WCDMa:TGPP [:BBG] :ULINK [:TGRoup [1]] :RACH [1] :DATA:BER [:VALue] ?

This command sets the bit error rate value for the random access channel (RACH).

***RST** +0.00000000E+000

Range 0.0000–1.0

Field Entry BER

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK[:TGRoup[1]]:RACH[1]:DATA:BLER:ACTual

Supported E4438C with Option 400

[:SOURCE] :RADIo:WCDMa:TGPP [:BBG] :ULINK [:TGRoup [1]] :RACH [1] :DATA:BLER:ACTual?

This query returns the actual error ratio inserted.

***RST** 0.00000000E+000

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])

Remarks The specified error ratio and actual error ratio will not match when the internal bit generation goes into “pre-computing” mode.

:ULINK[:TGRoup[1]]:RACH[1]:DATA:BLER:ERROR:BLOCK

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [ 1 ] ] :RACH [ 1 ] :DATA:
BLER:ERROR:BLOCK?
```

This query returns the actual block errors inserted in the total number of blocks.

***RST** +0

Remarks The specified error ratio and actual error ratio will not match when the internal bit generation goes into “pre-computing” mode.

:ULINK[:TGRoup[1]]:RACH[1]:DATA:BLER:TOTAL:BLOCK

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [ 1 ] ] :RACH [ 1 ] :DATA:
BLER:TOTAL:BLOCK?
```

This query returns the total blocks inserted for the block error ratio calculation.

***RST** +0

Remarks The specified error ratio and actual error ratio will not match when the internal bit generation goes into “pre-computing” mode.

:ULINK[:TGRoup[1]]:RACH[1]:DATA:BLER[:VALue]

Supported E4438C with Option 400

```
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [ 1 ] ] :RACH [ 1 ] :DATA:
BLER [ :VALue ] <val>
[ :SOURCE ] :RADio:WCDMa:TGPP [ :BBG ] :ULINK [ :TGRoup [ 1 ] ] :RACH [ 1 ] :DATA:
BLER [ :VALue ] ?
```

This command sets the inserted block error rate value. The variable <val> is expressed in decimal form, but it is a percent ratio (1.0=100%).

***RST** 0

Range 0.0001–1.0

Field Entry BLER

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADIO:WCDMA:TGPP[:BBG])

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK[:TGRoup[1]]:RACH[1]:DATA:EINSert

Supported E4438C with Option 400

```
[ :SOURCE ] : RADIo : WCDMA : TGPP [ : BBG ] : ULINK [ : TGRoup [ 1 ] ] : RACH [ 1 ] : DATA :
EINSert BLER | BER | NONE
[ :SOURCE ] : RADIo : WCDMA : TGPP [ : BBG ] : ULINK [ : TGRoup [ 1 ] ] : RACH [ 1 ] : DATA : EINSert ?
```

This command selects an error mode or no error insertion.

BLER This choice selects block error rate (BLER) mode.

BER This choice selects a bit error rate (BER) mode.

NONE This choice selects no BLER or BER mode (no error blocks or bits inserted).

***RST** NONE

Key Entry **BLER** **BER** **None**

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

:ULINK[:TGRoup[1]]:RACH[1]:DATA:FIX4

Supported E4438C with Option 400

```
[ :SOURCE ] : RADIo : WCDMA : TGPP [ : BBG ] : ULINK [ : TGRoup [ 1 ] ] : RACH [ 1 ] : DATA :
FIX4 <val>
[ :SOURCE ] : RADIo : WCDMA : TGPP [ : BBG ] : ULINK [ : TGRoup [ 1 ] ] : RACH [ 1 ] : DATA : FIX4 ?
```

This command sets a fixed 4 bit pattern for use as a data pattern.

While the variable <val> can be entered in binary, hexadecimal, or decimal formats, the query returns only binary values.

***RST** #B0000

Range 0–15

Field Entry Data

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075.

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK[:TGRoup[1]]:RACH[1]:NBLOCK****Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:RACH[1]:NBLOCK <val>

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:RACH[1]:NBLOCK?

This command sets the number of transport blocks coded into one random access channel (RACH).

***RST** +1**Range** 0–4095**Field Entry** Num of Blk**Remarks** The total input data into one RACH is the block size (BLKsize) multiplied by the number of transport blocks (NBLOCK).

If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to “:ULINK:APPLY” on page 1075

:ULINK[:TGRoup [1]]:RACH[1]:PPERcentage**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:RACH[1]:PPERcentage?

This query returns the percentage of the total bits removed from or added to the fully coded channel.

RST** –2.12500000E+002**Field Entry** Puncture**:ULINK[:TGRoup[1]]:RACH[1]:RMArch*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK:RACH[1]:RMArch?

This query returns the rate match parameters of each random access channel (RACH).

***RST** +1

Wideband CDMA Base Band Generator Subsystem—Option 400 ([:SOURCE]:RADio:WCDMa:TGPP[:BBG])**:ULINK[:TGRoup[1]]:RACH[1]:TTI****Supported** E4438C with Option 400[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:RACH[1]:
TTI 10000|20000

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:RACH[1]:TTI?

This command sets the transmission time interval (TTI) period for the random access channel (RACH).

The choices are expressed in units of milliseconds (msec) where 20000=20 msec.

***RST** 20000**Field Entry** TTI

Remarks If the parameter set by this command is changed while the signal is active, the apply command must be executed for the change to occur. Refer to [“:ULINK:APPLY” on page 1075](#).

:ULINK[:TGRoup[1]]:RACH[1][:STATe]**Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG]:ULINK[:TGRoup[1]]:RACH[1][:STATe]?

This query returns the state of the random access channel (RACH).

RST** 1**[:STATe]*Supported** E4438C with Option 400

[:SOURCE]:RADio:WCDMa:TGPP[:BBG][:STATe] ON|OFF|1|0

[:SOURCE]:RADio:WCDMa:TGPP[:BBG][:STATe]?

This command enables or disables W-CDMA functionality.

***RST** 0**Key Entry** **W-CDMA Off On**

Symbols

of Blocks field, [1071](#)
 # of Carriers softkey, [283](#), [285](#)
 # Points softkey, [57](#)
 # Skipped Points softkey, [302](#)
 ΦM Dev, [197](#)
 ΦM Dev Couple Off On, [197](#)
 FM ΦM Normal High BW, [192](#)
 ΦM Off On, [196](#)
 ΦM Path 1 2, [191](#)
 ΦM Stop Rate, [194](#)
 ΦM Sweep Time, [195](#)
 ΦM Tone 2 Ampl Percent of Peak, [194](#)

Numerics

0.7V,1.4V,1.65V,2.5V softkey, [421](#)
 1 DPCH softkey, [348](#), [353](#)
 1.23 MHz softkey, [263](#)
 1.25 MHz softkey, [263](#)
 1/2 Conv softkey, [1068](#), [1070](#), [1163](#)
 1/3 Conv softkey, [1068](#), [1070](#), [1163](#)
 10 msec softkey, [1096](#)
 1048576 softkey, [212](#)
 10ms Frame Pulse (DRPS11) softkey, [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
 10ms Frame Pulse (RPS6) softkey
See wideband CDMA base band generator
 subsystem keys and fields
 12.2 kbps (34.121) softkey, [1033](#)
 128QAM softkey
See custom subsystem keys
See DECT subsystem keys
See Dmodulation subsystem keys
See EDGE subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PDC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys
 131072 softkey, [212](#)
 144 kbps (34.121) softkey, [1033](#)
 16 1's & 16 0's softkey
See custom subsystem keys
See DECT subsystem keys

16 1's & 16 0's softkey (continued)
See EDGE subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PDC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys
 16384 softkey, [212](#)
 16-Lvl FSK softkey
See DECT subsystem keys
See PHS subsystem keys
 16PSK softkey
See custom subsystem keys
See DECT subsystem keys
See Dmodulation subsystem keys
See EDGE subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PDC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys
 16QAM softkey
See custom subsystem keys
See DECT subsystem keys
See Dmodulation subsystem keys
See EDGE subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PDC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys
 2 Carriers softkey, [349](#)
 2 SR3 Carriers softkey, [248](#)
 2.100 MHz softkey, [32](#), [208](#), [222](#), [246](#), [275](#), [299](#),
[329](#), [346](#), [473](#)
 20 msec softkey, [1096](#)
 2560 msec softkey, [1096](#)
 256QAM softkey
See custom subsystem keys
See DECT subsystem keys
See Dmodulation subsystem keys
See EDGE subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PDC subsystem keys

Index

- 256QAM softkey (*continued*)
 - See PHS subsystem keys
 - See TETRA subsystem keys
- 262144 softkey, [212](#)
- 2-Lvl FSK softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- 2nd Scr Offset field, [1034](#), [1041](#)
- 3 Carriers softkey, [230](#), [248](#), [349](#)
- 3 DPCH softkey, [348](#), [353](#)
- 3.84MHz chip-clk (DRPS4) softkey, [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
- 32 1's & 32 0's softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- 32 Ch Fwd softkey, [228](#), [231](#)
- 32768 softkey, [212](#)
- 32QAM softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- 384 kbps (34.121) softkey, [1033](#)
- 3GPP W-CDMA HSPA SCPI commands, [668](#)
- 4 1's & 4 0's softkey
 - See custom subsystem keys
 - See DECT subsystem keys
- 4 1's & 4 0's softkey (*continued*)
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- 4 Carriers softkey, [230](#), [248](#), [349](#)
- 40 msec softkey, [1096](#)
- 40.000 MHz softkey, [32](#), [205](#), [208](#), [217](#), [222](#), [241](#),
[246](#), [270](#), [275](#), [298](#), [299](#), [327](#), [329](#), [344](#), [346](#),
[466](#), [473](#)
- 4-Lvl FSK softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- 4QAM softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- 5 Channel softkey, [254](#)
- 524288 softkeys, [212](#)
- 64 1's & 64 0's softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- 64 Ch Fwd softkey, [228](#), [231](#)
- 64 kbps (34.121) softkey, [1033](#)

- 64QAM softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
 - 65536 softkey, [212](#)
 - 8 1's & 8 0's softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
 - 8 Bit Pattern softkey, [465](#)
 - 8 Channel softkey, [254](#)
 - 80 msec softkey, [1096](#)
 - 80ms Frame Pulse (DRPS13) softkey, [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
 - 80ms Frame Pulse (RPS20) softkey
 - See wideband CDMA base band generator
subsystem keys and fields
 - 8648A/B/C/D softkey, [156](#), [158](#)
 - 8656B,8657A/B softkey, [156](#), [158](#)
 - 8657D NADC softkey, [156](#), [158](#)
 - 8657D PDC softkey, [156](#), [158](#)
 - 8657J PHS softkey, [156](#), [158](#)
 - 8-Lvl FSK softkey
 - See DECT subsystem keys
 - See PHS subsystem keys
 - 8PSK softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - 8PSK softkey (continued)
 - See TETRA subsystem keys
 - 9 Ch Fwd softkey, [228](#), [231](#)
 - 9 Channel softkey, [247](#)
- ## A
- A field softkey
 - See DECT subsystem keys
 - A softkey, [1025](#)
 - abort list/step sweep, [166](#)
 - Access denied, [116](#)
 - Access softkey, [802](#)
 - ACS softkey, [1064](#)
 - Activate Secure Display softkey, [160](#)
 - Active softkey, [1061](#)
 - Actual BER softkey, [1172](#)
 - Actual BLER field, [1166](#), [1173](#)
 - Add Comment To Seq[n] Reg[nn] softkey, [123](#)
 - Adjust Gain softkey, [437](#)
 - Adjust Phase softkey, [47](#)
 - AICH softkey, [1130](#)
 - AICH Trigger Polarity Pos Neg softkey, [1105](#)
 - ALC
 - BW
 - 100 Hz, 1 kHz, 10 kHz, [58](#)
 - Auto, [58](#), [59](#)
 - Off,On, [58](#), [59](#)
 - ALC BW Normal Narrow, [22](#)
 - ALC BW Setting
 - Auto, [58](#), [59](#)
 - alc hold markers
 - awgn subsystem, [209](#)
 - cdma subsystem, [223](#)
 - cdma2000 arb subsystem, [257](#)
 - dmodulation subsystem, [276](#)
 - dual arb subsystem, [305](#)
 - multitone subsystem, [330](#), [331](#)
 - wideband CDMA ARB subsystem, [367](#)
 - wideband CDMA ARBsubsystem, [367](#)
 - ALC level, [60](#)
 - ALC Off On softkey, [62](#)
 - All Down softkey, [1036](#), [1086](#)
 - All softkey, [104](#), [122](#)
 - All Timeslots softkey
 - See DECT subsystem keys

Index

All Timeslots softkey (*continued*)

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

All Up softkey, [1036](#), [1086](#)

Alt Amp Delta softkey, [63](#)

Alt Ampl Off On softkey, [64](#)

Alt power in field, [1143](#)

alternate amplitude markers

awgn arb subsystem, [209](#)

cdma subsystem, [222](#)

cdma2000 arb subsystem, [257](#)

dmodulation subsystem, [276](#)

dual arb subsystem, [305](#)

multitone arb subsystem, [329](#)

multitone subsystem, [329](#)

wideband CDMA ARB subsystem, [367](#)

AM softkeys

AM Depth, [177](#)

AM Depth Couple Off On, [178](#)

AM Off On, [177](#)

AM Off On softkey, [173](#)

AM Path 1 2, [172](#)

AM Stop Rate, [174](#)

AM Sweep Rate, [175](#)

AM Tone 2 Ampl Percent Of Peak, [175](#)

AM Tone 2 Rate, [174](#)

AM wideband, [173](#)

AM_ADDR softkey, [464](#)

Ampl softkeys

Ampl, [49](#), [66](#)

Ampl Offset, [68](#)

Ampl Ref Off On, [67](#)

Ampl Ref Set, [66](#)

Ampl Start, [49](#), [67](#)

Ampl Stop, [49](#), [68](#)

Amplitude hardkey, [66](#), [69](#)

amplitude modulation subsystem keys

AM Depth, [177](#)

AM Depth Couple Off On, [178](#)

AM Off On, [173](#), [177](#)

AM Path 1 2, [172](#)

amplitude modulation subsystem keys (*continued*)

AM Stop Rate, [174](#)

AM Sweep Rate, [175](#)

AM Tone 2 Ampl Percent Of Peak, [175](#)

AM Tone 2 Rate, [174](#)

Bus, [176](#)

Dual-Sine, [175](#)

Ext, [176](#)

Ext Coupling DC AC, [173](#)

Ext1, [176](#)

Ext2, [176](#)

Free Run softkey, [176](#)

Incr Set, [172](#), [178](#)

Internal, [176](#)

Noise, [175](#)

Ramp, [175](#)

Sine, [175](#)

Square, [175](#)

Swept-Sine, [175](#)

Triangle, [175](#)

Trigger Key, [176](#)

amplitude step, [69](#)

AMR 12.2 kbps softkey, [1033](#), [1137](#)

APCO 25 C4FM softkey

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See CDMA2000 BBG subsystem keys and fields

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See EDGE subsystem keys

See GPS subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA ARB subsystem keys

See wideband CDMA base band generator
subsystem keys and fields

APCO 25 w/C4FM softkey, [282](#), [283](#), [284](#)

APCO 25 w/C4QPSK softkey, [282](#), [283](#), [284](#)

APCO 25 w/CQPSK softkey, [567](#)

Apply Channel Setup softkey, [251](#), [255](#), [356](#), [364](#),
[1021](#), [1075](#)

- Apply to Waveform softkey, [300](#), [302](#)
Arb AWGN Off On softkey, [214](#)
ARB Off On softkey, [324](#)
ARB Reference Ext Int softkey
 See AWGN subsystem keys
 See bluetooth subsystem keys
 See CDMA ARB subsystem keys
 See CDMA2000 ARB subsystem keys
 See Dmodulation subsystem keys
 See dual ARB subsystem keys
 See multitone subsystem keys
 See wideband CDMA ARB subsystem keys
ARB Sample Clock softkey, [213](#), [228](#), [262](#), [282](#),
 [313](#), [335](#), [372](#), [478](#)
arbitrary waveform
 runtime scaling, [312](#), [335](#)
 scaling files, [312](#)
Atten Hold Off On softkey, [65](#)
Auto softkey, [58](#), [59](#)
automatic leveling control, [62](#)
Aux I/O Trigger Polarity Pos Neg softkey, [460](#)
Aux softkey
 See sense subsystem keys
Auxiliary Software Options softkey, [82](#)
AWGN Off On softkey, [468](#)
AWGN subsystem keys
 1048576, [212](#)
 131072, [212](#)
 16384, [212](#)
 2.100 MHz, [208](#)
 262144, [212](#)
 32768, [212](#)
 40.000 MHz, [205](#), [208](#)
 524288, [212](#)
 65536, [212](#)
 Arb AWGN Off On, [214](#)
 ARB Reference Ext Int, [213](#)
 ARB Sample Clock, [213](#)
 Bandwidth, [205](#)
 Clear Header, [206](#)
 I/Q Mod Filter Manual Auto, [208](#)
 I/Q Output Filter Manual Auto, [206](#)
 Marker 1, [209](#), [210](#)
 Marker 1 Polarity Neg Pos, [212](#)
 Marker 2, [209](#), [210](#)
 AWGN subsystem keys (*continued*)
 Marker 2 Polarity Neg Pos, [212](#)
 Marker 3, [209](#), [210](#)
 Marker 3 Polarity Neg Pos, [212](#)
 Marker 4, [209](#), [210](#)
 Marker 4 Polarity Neg Pos, [212](#)
 Modulator Atten Manual Auto, [207](#)
 Noise Seed Fixed Random, [214](#)
 None, [209](#), [210](#)
 Reference Freq, [212](#)
 Save Setup To Header, [206](#)
 Through, [205](#), [208](#)
 Waveform Length, [212](#)
- B**
B softkey, [999](#), [1004](#), [1025](#)
B1 softkey, [997](#), [1002](#)
B2 softkey, [997](#), [1002](#)
Bandwidth softkey, [205](#), [463](#)
Base Delay Tp-a softkey, [1127](#)
BBG Chip Clock Ext Int softkey
 See wideband CDMA base band generator
 subsystem keys and fields
BBG Data Clock Ext Int softkey
 See custom subsystem keys
 See DECT subsystem keys
 See GSM subsystem keys
 See NADC subsystem keys
 See PHS subsystem keys
 See TETRA subsystem keys
BBG Data Clock field, [480](#)
BBG Ref Ext Int softkey
 See custom subsystem keys
 See DECT subsystem keys
 See EDGE subsystem keys
 See GSM subsystem keys
 See NADC subsystem keys
 See PDC subsystem keys
 See PHS subsystem keys
 See TETRA subsystem keys
BBG1 softkey, [24](#), [35](#)
BD_ADDR softkey, [464](#)
Begin Data Format Pattern Framed softkey
 See DECT subsystem keys
 See EDGE subsystem keys

Index

Begin Data Format Pattern Framed softkey

(continued)

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

Begin Frame softkey

See DECT subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

Begin Timeslot # softkey

See DECT subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

BER Display % Exp softkey, 407

BER field, 1166, 1173

BER Mode Off On softkey

See sense subsystem keys

BER softkey, 1168, 1175

BERT Off On softkey, 457

BERT Resync Off On softkey, 457

Beta field, 1079, 1089

Binary softkey, 94, 124

binary values, 18

Bit Count softkey

See sense subsystem keys

Bit Delay Off On softkey, 459

Bit Order softkey, 384

Bit Rate field

See CDMA2000 BBG subsystem keys and fields

Bit softkey, 94

BLER field, 1167, 1174

BLER softkey, 1168, 1175

Blk Set Size field, 1067

Blk Size field, 1066, 1162, 1170

Block Count softkey

See calculate subsystem keys

See sense subsystem keys

Block Erasure softkey

See sense subsystem keys

Blocking softkey, 1064

Bluetooth Off On softkey, 478

Bluetooth softkey, 567

bluetooth subsystem keys

2.100 MHz, 473

40.000 MHz, 466, 473

8 Bit Pattern, 465

AM_ADDR, 464

ARB Reference Ext Int, 477

ARB Sample Clock, 478

AWGN Off On, 468

BD_ADDR, 464

Bluetooth Off On, 478

Burst Off On, 464

Burst Power Ramp, 478

C/N[1 MHz], 468

Clear Header, 467

Clock/Gate Delay, 465

Continuous PN9, 465

Drift Deviation, 469

Freq Drift Type Linear Sine, 470

Freq Offset, 470

I/Q Mod Filter Manual Auto, 474

I/Q Output Filter Manual Auto, 466

Impairments Off On, 467

Marker 1, 474, 475

Marker 1 Polarity Neg Pos, 475

Marker 2, 474, 475

Marker 2 Polarity Neg Pos, 476

Marker 3, 474, 475

Marker 3 Polarity Neg Pos, 476

Marker 4, 474, 475

Marker 4 Polarity Neg Pos, 476

Mod Index, 471

Modulator Atten Manual Auto, 472, 473

Noise Seed, 469

None, 474, 475

Packet (DH1), 476

Reference Freq, 477

Save Setup To Header, 467

bluetooth subsystem keys (*continued*)

Symbol Timing Err, 472

Through, 466, 473

Truncated PN9, 465

boolean SCPI parameters, 10

boolean, numeric response data, 11

BPSK softkey

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

Brightness softkey, 86

Build New Waveform Sequence softkey, 313

burst

shape, 115

Burst Envelope Int Ext Off softkey, 22

Burst gate in field, 1144

Burst Gate In Polarity Neg Pos softkey, 130, 131

Burst Off On softkey, 464

Burst Power Ramp softkey, 478

Bus softkey

list trigger source, 54

See amplitude modulation subsystem keys

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See dual ARB subsystem keys

See EDGE subsystem keys

See frequency modulation subsystem keys

See GSM subsystem keys

See low frequency output subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See phase modulation subsystem keys

See PHS subsystem keys

See sense subsystem keys

See TETRA subsystem keys

See trigger subsystem keys

See wideband CDMA ARB subsystem keys

C

C Power field, 1076, 1106

C/N softkey, 505, 517

C/N value field, 1021, 1075, 1105

C/N[1 MHz] softkey, 468

C4FM softkey, 962

calculate subsystem keys

BER Display % Exp, 407

Block Count, 425

Class II RBER, 404, 405

Class 1b RBER, 404, 405

Cycle End, 405

Error Rate, 398, 399, 400, 401, 402, 403

Exceeds Any Limit, 405

Fail Hold, 405

Frame Erasure, 404, 405

No Limits, 399, 402, 403, 405

Pass/Fail Limits, 406

Pass/Fail Off On, 406

Update Display Cycle End Cont, 407

calibration subsystem keys

DCFM/DCΦM Cal, 72

Execute Cal, 72, 73

I/Q Calibration, 72

Revert to Default Cal Settings, 73

Start Frequency, 74

Stop Frequency, 74

Carrier Bandwidth softkey, 309

Carrier Phases Fixed Random softkey, 283

Carrier to Noise Ratio softkey, 309

CC softkey, 926, 930, 932

CDL softkey, 894

CDMA ARB subsystem keys

2.100 MHz, 222

3 Carriers, 230

32 Ch Fwd, 228, 231

4 Carriers, 230

40.000 MHz, 217, 222

64 Ch Fwd, 228, 231

9 Ch Fwd, 228, 231

APCO 25 C4FM, 218

ARB Reference Ext Int, 227

ARB Sample Clock, 228

Bus, 235

CDMA Off On, 239

Index

CDMA ARB subsystem keys (*continued*)

Chip Rate, [216](#)
Clear Header, [220](#)
Clip II+jQI To, [216](#)
Clip III To, [215](#)
Clip IQI To, [215](#)
Clip At PRE POST FIR Filter, [215](#)
Clipping Type II+jQI III,IQI, [216](#)
Continuous, [233](#), [263](#)
CPICH, [357](#)
Custom CDMA Multicarrier, [230](#)
Custom CDMA State, [228](#), [231](#)
Equal Powers, [229](#)
Ext, [235](#)
Ext Delay Off On, [237](#)
Ext Delay Time, [236](#)
Ext Polarity Neg Pos, [237](#)
Filter Alpha, [219](#)
Filter BbT, [219](#)
Free Run, [234](#)
Gate Active Low High, [235](#)
Gated, [233](#), [263](#)
Gaussian, [218](#)
I/Q Mapping Normal Invert, [221](#)
I/Q Mod Filter Manual Auto, [222](#)
I/Q Output Filter Manual Auto, [217](#)
Immediate, [227](#)
IS-2000 SR3 DS, [218](#)
IS-95, [218](#)
IS-95 Mod, [218](#)
IS-95 Mod w/EQ, [218](#)
IS-95 w/EQ, [218](#)
IS-97 Levels, [229](#)
Marker 1, [222](#), [223](#), [224](#)
Marker 1 Polarity Neg Pos, [226](#)
Marker 2, [222](#), [223](#), [224](#)
Marker 2 Polarity Neg Pos, [226](#)
Marker 3, [222](#), [223](#), [224](#)
Marker 3 Polarity Neg Pos, [226](#)
Marker 4, [222](#), [223](#), [224](#)
Marker 4 Polarity Neg Pos, [226](#)
Modulator Atten Manual Auto, [221](#)
Multicarrier Off On, [228](#)
None, [222](#), [223](#), [224](#)
Nyquist, [218](#)

CDMA ARB subsystem keys (*continued*)

Off, [227](#)
On, [227](#)
Optimize FIR For EVM ACP, [220](#)
Oversample Ratio, [226](#)
Paging, [229](#)
Patt Trig In 1, [238](#)
Patt Trig In 2, [238](#)
Pilot, [228](#), [229](#), [231](#)
Rectangle, [218](#)
Reference Freq, [226](#)
Reset & Run, [234](#)
Reverse, [228](#)
Root Nyquist, [218](#)
Save Setup To Header, [220](#)
Scale to 0dB, [229](#)
Single, [233](#), [263](#)
Store Custom CDMA State, [232](#)
Store Custom Multicarrier, [231](#)
Sync, [229](#)
Through, [217](#), [222](#)
Traffic, [229](#)
Trigger & Run, [234](#)
Trigger Key, [235](#)
UN3/4 GSM Gaussian, [218](#)
User FIR, [218](#)
Waveform Length, [238](#)
WCDMA, [218](#)
CDMA Freq field, [499](#)
CDMA Off On softkey, [239](#)
CDMA softkey, [95](#)
CDMA2000 ARB subsystem keys
1.23 MHz, [263](#)
1.25 MHz, [263](#)
2 SR3 Carriers, [248](#)
2.100 MHz, [246](#)
3 Carriers, [248](#)
4 Carriers, [248](#)
40.000 MHz, [241](#), [246](#)
5 Channel, [254](#)
8 Channel, [254](#)
9 Channel, [247](#)
APCO 25 C4FM, [242](#)
Apply Channel Setup, [251](#), [255](#)
ARB Reference Ext Int, [260](#)

CDMA2000 ARB subsystem keys (*continued*)

ARB Sample Clock, 262
 Bus, 266
 CDMA2000 Off On, 269
 Clear Header, 245
 Clip II+jQI To, 241
 Clip III To, 240
 Clip IQI To, 240
 Clip At PRE POST FIR Filter, 240
 Clipping Type II+jQI III,IQI, 241
 Config, 252, 255
 Continuous, 263
 Custom CDMA2000 Carrier, 247, 249
 Custom CDMA2000 Multicarrier, 248
 Custom CDMA2000 State, 254
 Edit Channel Setup, 252, 255
 Equal Powers, 253, 256
 Ext, 266
 Ext Delay Off On, 268
 Ext Delay Time, 267
 Ext Polarity Neg Pos, 268
 Filter Alpha, 243
 Filter BbT, 244
 Free Run, 265
 Gate Active Low High, 266
 Gated, 263
 Gaussian, 242
 I/Q Mapping Normal Invert, 247
 I/Q Mod Filter Manual Auto, 246
 I/Q Output Filter Manual Auto, 242
 Immediate, 261
 Insert Row, 252, 255
 IS-2000 SR3 DS, 242
 IS-95, 242
 IS-95 Mod, 242
 IS-95 Mod w/EQ, 242
 IS-95 w/EQ, 242
 Link Forward Reverse, 247
 Marker 1, 257, 258
 Marker 1 Polarity Neg Pos, 260
 Marker 2, 257, 258
 Marker 2 Polarity Neg Pos, 260
 Marker 3, 257, 258
 Marker 3 Polarity Neg Pos, 260
 Marker 4, 257, 258

CDMA2000 ARB subsystem keys (*continued*)

Marker 4 Polarity Neg Pos, 260
 Modulator Atten Manual Auto, 245, 246
 Multicarrier Off On, 247
 None, 257, 258
 Nyquist, 242
 Off, 261
 On, 261
 Optimize FIR For EVM ACP, 244
 Patt Trig In 1, 269
 Patt Trig In 2, 269
 Pilot, 247, 254
 PN Offset, 252, 255
 Radio Config, 253
 Rate, 252, 255
 Rectangle, 242
 Reference Freq, 260
 Reset & Run, 265
 Root Nyquist, 242
 Save Setup To Header, 245
 Scale to 0dB, 253, 256
 Single, 263
 Spread Rate 1, 247, 254, 262
 Spread Rate 3, 247, 254, 262
 Spreading Type Direct Mcarrier, 247, 263
 SR1 9 Channel, 249
 SR1 Pilot, 249
 SR3 Direct 9 Channel, 249
 SR3 Direct Pilot, 249
 SR3 Mcarrier 9 Channel, 249
 SR3 MCarrier Pilot, 249
 Store Custom CDMA State, 251, 254
 Store Custom Multicarrier, 249
 Through, 241, 246
 Trigger & Run, 265
 Trigger Key, 266
 UN3/4 GSM Gaussian, 242
 User FIR, 242
 Walsh Code, 252, 255
 WCDMA, 242

CDMA2000 BBG subsystem keys and fields

APCO 25 C4FM, 481, 514
 BBG Data Clock, 480
 Bit Rate, 488, 492, 497, 511, 521, 523, 527, 532,
 537, 541, 544

Index

CDMA2000 BBG subsystem keys and fields

(continued)

C/N, 505, 517
CDMA Freq, 499
CDMA2000 Off On, 547
Change, 509
Chip Rate, 480, 513
DAYLT, 499
EbNo, 484, 489, 495, 500, 506, 509, 519, 525, 527, 531, 536, 539, 542
EcNo, 493, 528, 533
Equal Powers, 508, 517
Even Second Delay, 480, 513
Ext, 483, 494, 522
Ext CDMA Freq, 500
External, 512
Falling, 547
Field 1, 490
Field 2, 490
Field 3, 491
Filter Alpha, 482, 515
Filter BbT, 482, 485, 515
FIX4, 483, 484, 494, 518, 519, 522, 524, 525, 530, 535, 539, 542
Frame Length, 520, 522, 526, 536, 540, 543
Frame Offset, 495, 520, 523, 526, 531, 536, 540, 543
FSYNCH Type, 504
Full, 529, 534
Gaussian, 481, 514
Half, 529, 534
Header, 486, 496
Internal, 512
Inverted, 517
IS-95, 481, 514
IS-95 MOD, 514
IS-95 Mod, 481
IS-95 MOD w/EQ, 514
IS-95 Mod w/EQ, 481
IS-95 w/EQ, 481, 514
Leap Seconds, 501
Link Forward Reverse, 479
Long Code Mask, 516
Long Code State, 483, 516
LTM OFF, 501

CDMA2000 BBG subsystem keys and fields

(continued)

Message Type, 502
Network ID, 502
Noise Off On, 506, 518
Normal, 517
Nyquist, 481, 514
Optimize FIR For EVM ACP, 482, 516
P Rev, 503
P Rev Min, 501
Paging Indicator, 510
Permuted ESN, 486, 496
Phase Polarity, 509
PN Offset, 512
PN15, 483, 494, 518, 522, 524, 530, 535, 538, 542
PN9, 483, 494, 518, 522, 524, 530, 535, 538, 542
Power, 486, 491, 493, 497, 502, 507, 510, 520, 523, 526, 529, 532, 534, 537, 540, 544
PRAT, 503
QOF, 487, 497
Quarter, 529, 534
Radio Config, 488, 498, 521, 524, 532, 537, 541, 544
RadioConfig 1/2 Access, 479
RadioConfig 1/2 Traffic, 479
RadioConfig 3/4 Common Control, 479
RadioConfig 3/4 Enhanced Access, 479
RadioConfig 3/4 Traffic, 479
Ramp, 487
Ramp Time, 487
Rectangle, 481, 514
Reserved, 503
Rising, 547
Root Nyquist, 481, 514
Scale to 0dB, 508, 517
Spread Rate, 511
State, 492, 494, 499, 505, 508, 511, 521, 524, 528, 530, 533, 535, 538, 541, 545
State field, 489
System ID, 504
Time, 504
Trigger Advance, 546
Turbo Coding, 498, 545
UN3/4 GSM Gaussian, 481, 514

- CDMA2000 BBG subsystem keys and fields
 - (continued)
 - User File, [483](#), [489](#), [494](#), [518](#), [522](#), [524](#), [530](#), [535](#), [538](#), [542](#)
 - User FIR, [481](#), [514](#)
 - Walsh, [492](#), [498](#), [505](#), [508](#), [511](#), [527](#), [529](#), [533](#), [534](#), [538](#), [541](#), [545](#)
 - Walsh field, [488](#)
- CDMA2000 Off On softkey, [269](#), [547](#)
- CDPD softkey, [282](#), [283](#), [284](#), [567](#)
- CDVCC softkey, [894](#), [897](#)
- CFN #0 Frame Pulse (RPS10) softkey
 - See wideband CDMA base band generator subsystem keys and fields
- Chan Code field, [1031](#), [1040](#)
- Chan Code softkey, [1030](#)
- Change field, [509](#)
- Channel Code field, [1090](#), [1131](#)
 - See wideband CDMA base band generator subsystem keys and fields
- Channel Number softkey, [40](#)
- Channel softkey, [356](#), [364](#)
- Channel State field, [1089](#), [1096](#)
- Channel State Off On softkey, [1108](#)
 - See wideband CDMA base band generator subsystem keys and fields
- ChCode Ctl field, [1121](#)
- ChCode Dat field, [1121](#)
- Chip Clock (RPS1) softkey
 - See wideband CDMA base band generator subsystem keys and fields
- Chip Rate field, [480](#), [513](#), [1030](#), [1079](#)
- Chip Rate softkey, [216](#), [342](#)
- Class Ib Bit Error softkey, [451](#), [452](#)
- Class II Bit Error softkey, [452](#)
- Class II RBER softkey, [404](#), [405](#)
- Class Ib RBER softkey, [404](#), [405](#)
- Clear Header softkey, [206](#), [220](#), [245](#), [273](#), [295](#), [326](#), [344](#), [467](#)
- clearing markers, [300](#)
- Clip II+jQI To softkey, [216](#), [241](#)
- Clip III To softkey, [215](#), [240](#), [340](#), [350](#)
- Clip IQI To softkey, [215](#), [240](#), [340](#), [351](#)
- Clip At PRE POST FIR Filter, [215](#)
- Clip At PRE POST FIR Filter softkey, [240](#), [340](#)
- Clip Type II+jQI To softkey, [341](#), [351](#)
- Clipping Type II+jQI III,IQI softkey, [216](#), [241](#), [294](#), [341](#), [351](#)
- Clock Delay Off On softkey, [419](#)
- Clock Per Sample softkey, [380](#)
- Clock Phase softkey, [380](#)
- Clock Polarity Neg Pos softkey, [420](#)
- Clock Polarity softkey, [381](#)
- Clock Rate softkey, [382](#)
- Clock Skew softkey, [383](#)
- Clock Source softkey, [383](#)
- Clock Time Delay softkey, [419](#)
- Clock/Gate Delay softkey, [465](#)
- command tree, SCPI, [6](#), [7](#)
- Common Mode I/Q Offset softkey, [26](#)
- communication subsystem keys
 - Default Gateway, [76](#)
 - GPIB Address, [75](#)
 - Hostname, [76](#)
 - IP Address, [76](#)
 - LAN Config, [75](#)
 - Meter Address, [77](#)
 - Meter Channel A B, [77](#)
 - Meter Timeout, [78](#)
 - Power Meter, [78](#)
 - Reset RS-232, [79](#)
 - RS-232 Baud Rate, [79](#)
 - RS-232 ECHO Off On, [79](#)
 - RS-232 Timeout, [80](#)
 - Subnet Mask, [77](#)
- Comp Mode Start Trigger Polarity Neg Pos softkey, [1160](#)
- Comp Mode Start Trigger Polarity Pos Neg softkey, [1062](#), [1063](#)
- Comp Mode Stop Trigger Polarity Neg Pos softkey, [1160](#)
- Comp Mode Stop Trigger Polarity Pos Neg softkey, [1063](#)
- Compressed Frame (RPS8) softkey
 - See wideband CDMA base band generator subsystem keys and fields
- Compressed Mode Off On softkey, [1159](#)
- Compressed Mode Start Trigger softkey, [1039](#), [1062](#), [1160](#)
- Compressed Mode Stop Trigger softkey, [1063](#), [1160](#)

Index

- Config softkey, [252](#), [255](#)
- Configure Cal Array softkey, [20](#)
- continuous
 - segment advance, [318](#)
- Continuous PN9 softkey, [465](#)
- Continuous softkey
 - dual ARB subsystem keys, [318](#)
 - See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* custom subsystem keys
 - See* DECT subsystem keys
 - See* Dmodulation subsystem keys
 - See* dual ARB subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
 - See* wideband CDMA ARB subsystem keys
- Copy File softkey, [105](#), [114](#), [124](#)
- correction subsystem keys
 - Configure Cal Array, [20](#)
 - Flatness Off On, [21](#)
 - Load From Selected File, [20](#)
 - Preset List, [21](#)
 - Store To File, [21](#)
- CPICH softkey, [357](#)
- CRC Size field, [1069](#), [1164](#), [1171](#)
- creating a waveform
 - sequence, dual ARB, [313](#)
- creating a waveform, multitone, [326](#)
- CS-1 softkey, [641](#), [642](#), [794](#)
- CS-4 softkey, [641](#), [643](#), [798](#)
- CSID softkey, [954](#), [972](#)
- Ctrl Beta field, [1109](#)
- Ctrl Pwr field, [1110](#)
- Custom CDMA Multicarrier softkey, [230](#)
- Custom CDMA State softkey, [228](#), [231](#)
- Custom CDMA2000 Carrier softkey, [247](#), [249](#)
- Custom CDMA2000 Multicarrier softkey, [248](#)
- Custom CDMA2000 State softkey, [254](#)
- Custom Digital Mod State softkey, [283](#), [284](#)
- Custom Off On softkey, [572](#)
- Custom softkey, [589](#), [600](#), [656](#), [802](#), [957](#)
- custom subsystem keys
 - 128QAM, [564](#)
 - 16 1's & 16 0's, [557](#)
 - 16PSK, [564](#)
 - 16QAM, [564](#)
 - 256QAM, [564](#)
 - 2-Lvl FSK, [564](#)
 - 32 1's & 32 0's, [557](#)
 - 32QAM, [564](#)
 - 4 1's & 4 0's, [557](#)
 - 4-Lvl FSK, [564](#)
 - 4QAM, [564](#)
 - 64 1's & 64 0's, [557](#)
 - 64QAM, [564](#)
 - 8 1's & 8 0's, [557](#)
 - 8PSK, [564](#)
 - APCO 25 C4FM, [561](#)
 - APCO 25 w/CQPSK, [567](#)
 - BBG Data Clock Ext Int, [549](#)
 - BBG Ref Ext Int, [560](#)
 - Bit Rate, [550](#)
 - Bluetooth, [567](#)
 - BPSK, [564](#)
 - Bus, [569](#)
 - CDPD, [567](#)
 - Continuous, [567](#)
 - Custom Off On, [572](#)
 - D8PSK, [564](#)
 - Diff Data Encode Off On, [559](#)
 - Ext, [557](#), [569](#)
 - Ext BBG Ref Freq, [560](#)
 - Ext Data Clock Normal Symbol, [559](#)
 - Ext Delay Bits, [570](#)
 - Ext Delay Off On, [570](#)
 - Ext Polarity Neg Pos, [571](#)
 - Fall Delay, [552](#), [553](#)
 - Fall Time, [552](#), [553](#)
 - Filter Alpha, [548](#)
 - Filter BbT, [549](#)
 - FIX4, [557](#), [558](#)
 - Free Run, [568](#)
 - Freq Dev, [563](#)
 - Gate Active Low High, [568](#)
 - Gated, [567](#)
 - Gaussian, [561](#)

custom subsystem keys (*continued*)

Gray Coded QPSK, [564](#)
 I/Q Scaling, [562](#)
 IS-95, [561](#)
 IS-95 Mod, [561](#)
 IS-95 Mod w/EQ, [561](#)
 IS-95 OQPSK, [564](#)
 IS-95 QPSK, [564](#)
 IS-95 w/EQ, [561](#)
 MSK, [564](#)
 None, [567](#)
 Nyquist, [561](#)
 Optimize FIR For EVM ACP, [557](#)
 OQPSK, [564](#)
 $\pi/4$ DQPSK, [564](#)
 Patt Trig In 1, [571](#)
 Patt Trig In 2, [571](#)
 Phase Dev, [563](#)
 Phase Polarity Normal Invert, [565](#)
 PN11, [557](#)
 PN15, [557](#)
 PN20, [557](#)
 PN23, [557](#)
 PN9, [557](#)
 PRAM Files, [558](#)
 QPSK, [564](#)
 Rectangle, [561](#)
 Reset & Run, [568](#)
 Rise Delay, [554](#)
 Rise Time, [555](#), [556](#)
 Root Nyquist, [561](#)
 Single, [567](#)
 Symbol Rate, [565](#)
 Trigger & Run, [568](#)
 Trigger Key, [569](#)
 UN3/4 GSM Gaussian, [561](#)
 User File, [557](#)
 User FIR, [561](#)
 User FSK, [564](#)
 User I/Q, [564](#)
 Custom TS softkey, [645](#), [655](#), [793](#), [800](#)
 Custom WCDMA State softkey, [363](#)
 Cycle Count softkey, [459](#)
 Cycle End softkey, [405](#)

D

D8PSK softkey
 See custom subsystem keys
 See DECT subsystem keys
 See Dmodulation subsystem keys
 See EDGE subsystem keys
 See GSM subsystem keys
 See NADC subsystem keys
 See PDC subsystem keys
 See PHS subsystem keys
 See TETRA subsystem keys
 data
 memory subsystem, [105](#)
 data append
 memory subsystem, [106](#)
 Data Beta field, [1113](#)
 data bit, [107](#)
 data block, [114](#)
 Data Clock Out Neg Pos softkey, [133](#)
 Data Clock Polarity Neg Pos softkey, [130](#), [132](#), [134](#)
 Data field, [1091](#), [1175](#)
 data files, [105](#)
 data FSK, [109](#)
 data IQ, [110](#)
 Data Mode Raw Enc TLM softkey, [763](#), [764](#)
 Data Out Polarity Neg Pos softkey, [133](#), [135](#)
 Data Polarity Neg Pos softkey, [131](#), [132](#), [420](#)
 Data Pwr field, [1115](#)
 Data Rate field, [1041](#)
 data subsystem keys
 Error Out, [413](#)
 PN9, [413](#)
 Reference Out, [413](#)
 Data Type softkey, [392](#)
 DATA/CLK/SYNC Rear Outputs Off On softkey, [135](#)
 DAYLT field, [499](#)
 dBm softkey, [170](#)
 dBuV softkey, [170](#)
 dBuVemf softkey, [170](#)
 DC softkey, [189](#)
 DCFM/DC Φ M Cal softkey, [72](#)
 DCH1 softkey, [1077](#)
 DCH2 softkey, [1077](#)
 DCH3 softkey, [1077](#)

Index

- DCH4 softkey, [1077](#)
- DCH5 softkey, [1077](#)
- DCH6 softkey, [1077](#)
- decimal values, [18](#)
- Dect Off On softkey, [621](#)
- DECT softkey, [282](#), [283](#), [284](#)
- DECT subsystem keys
 - 128QAM, [588](#)
 - 16 1's & 16 0's, [582](#), [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - 16-Lvl FSK, [582](#)
 - 16PSK, [588](#)
 - 16QAM, [588](#)
 - 256QAM, [588](#)
 - 2-Lvl FSK, [588](#)
 - 32 1's & 32 0's, [582](#), [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - 32QAM, [588](#)
 - 4 1's & 4 0's, [582](#), [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - 4-Lvl FSK, [588](#)
 - 4QAM, [588](#)
 - 64 1's & 64 0's, [582](#), [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - 64QAM, [588](#)
 - 8 1's & 8 0's, [582](#), [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - 8-Lvl FSK, [582](#)
 - 8PSK, [588](#)
 - A field, [590](#), [593](#), [596](#), [598](#), [601](#), [602](#), [603](#), [606](#), [608](#), [610](#)
 - All Timeslots, [614](#)
 - APCO 25 C4FM, [585](#)
 - BBG Data Clock Ext Int, [573](#)
 - BBG Ref Ext Int, [584](#)
 - Begin Frame, [614](#)
 - Begin Timeslot #, [614](#), [615](#)
 - Bit Rate, [574](#)
 - BPSK, [588](#)
 - Bus, [613](#), [618](#)
 - Continuous, [616](#)
 - Custom, [589](#), [600](#)
 - D8PSK, [588](#)
 - Data Format Pattern Framed, [581](#)
 - Dect Off On, [621](#)
 - DECT subsystem keys (*continued*)
 - DM0, [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - DM1, [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - Dummy Bearer 1, [600](#)
 - Dummy Bearer 2, [600](#)
 - Ext, [582](#), [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#), [613](#), [618](#)
 - Ext Data Clock Normal Symbol, [584](#)
 - Ext Delay Bits, [619](#)
 - Ext Delay Off On, [621](#)
 - Ext Polarity Neg Pos, [620](#)
 - FACC, [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - Fall Delay, [576](#), [577](#)
 - Fall Time, [576](#), [577](#)
 - FDEV1_FS, [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - FDEV1_HS, [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - FDEV2_FS, [589](#), [592](#), [595](#), [597](#), [599](#), [600](#), [604](#), [607](#), [609](#), [611](#)
 - Filter Alpha, [573](#)
 - Filter BbT, [574](#)
 - FIX4, [582](#), [589](#), [590](#), [592](#), [595](#), [597](#), [599](#), [600](#), [601](#), [604](#), [605](#), [607](#), [608](#), [609](#), [610](#), [611](#), [612](#)
 - Free Run, [617](#)
 - Freq Dev, [586](#)
 - Gate Active Low High, [618](#)
 - Gated, [616](#)
 - Gaussian, [585](#)
 - Gray Coded QPSK, [588](#)
 - I/Q Scaling, [586](#)
 - IS-95, [585](#)
 - IS-95 Mod, [585](#)
 - IS-95 Mod w/EQ, [585](#)
 - IS-95 OQPSK, [588](#)
 - IS-95 QPSK, [588](#)
 - IS-95 w/EQ, [585](#)
 - Low Capacity, [589](#), [600](#)
 - Low Capacity with Z field, [589](#), [600](#)
 - MSK, [588](#)
 - Nyquist, [585](#)
 - Optimize FIR For EVM ACP, [581](#)

- DECT subsystem keys (*continued*)
- OQPSK, 588
 - P, 591, 594, 596, 598, 602, 603, 604, 606, 608, 610
 - $\pi/4$ DQPSK, 588
 - Patt Trig In 1, 620
 - Patt Trig In 2, 620
 - Phase Dev, 587
 - Phase Polarity Normal Invert, 588
 - PN11, 582, 589, 592, 595, 597, 599, 600, 607, 609, 611
 - PN15, 582, 589, 592, 595, 597, 599, 600, 604, 607, 609, 611
 - PN20, 582, 589, 592, 595, 597, 599, 600, 607, 609, 611
 - PN23, 582, 589, 592, 595, 597, 599, 600, 607, 609, 611
 - PN9, 582, 589, 592, 595, 597, 599, 600, 604, 607, 609, 611
 - PN9 Mode Normal Quick, 575
 - QPSK, 588
 - Recall Secondary Frame State, 612
 - Rectangle, 585
 - Reset & Run, 617
 - Restore DECT Factory Default, 583
 - Rise Delay, 578
 - Rise Time, 579, 580
 - Root Nyquist, 585
 - S, 591, 594, 596, 598, 602, 603, 604, 607, 609, 611
 - Save Secondary Frame State, 612
 - Secondary Frame Off On, 613
 - Sine, 556, 580
 - Single, 616
 - Sync Out Offset, 614
 - Timeslot Ampl Main Delta, 593, 605
 - Timeslot Off On, 593, 606
 - Traffic Bearer, 589, 600
 - Traffic Bearer with Z field, 589, 600
 - Trigger & Run, 617
 - Trigger Key, 613, 618
 - UN3/4 GSM Gaussian, 585
 - User File, 556, 580, 582, 589, 592, 595, 597, 599, 600, 604, 607, 609, 611
 - User FIR, 585
 - User FSK, 587, 588
 - User I/Q, 588
 - dect subsystem keys
 - PRAM File, 583
 - DECT subsystem keys
 - Symbol Rate, 615
 - Default Gateway softkey, 76
 - Delay Bits softkey, 459
 - Delete All NVWFM Files softkey, 125
 - Delete All WFM Files softkey, 125
 - Delete All WFM1 Files softkey, 125
 - Delete File softkey, 126
 - Delete softkeys
 - Delete All ARB CDMA Files, 118
 - Delete All ARB DMOD Files, 118
 - Delete All ARB DWCDMA Files, 119
 - Delete All ARB FCDMA Files, 119
 - Delete All ARB MCDMA Files, 120
 - Delete All ARB MDMOD Files, 120
 - Delete All ARB MDWCDMA Files, 120
 - Delete All ARB MFCDMA Files, 120
 - Delete All ARB MTONE Files, 121
 - Delete All ARB RCDMA Files, 121
 - Delete All ARB UWCDMA Files, 122
 - Delete All Binary Files, 118
 - Delete All Bit Files, 118
 - Delete All Files, 117
 - Delete All FIR Files, 119
 - Delete All FSK Files, 119
 - Delete All I/Q Files, 119
 - Delete All List Files, 120
 - Delete All SEQ Files, 121
 - Delete All SHAPE Files, 121
 - Delete All State Files, 121
 - Delete All UFLT Files, 122
 - Delete File, 122
 - DHCP, 75
 - Diagnostic Info softkey, 81, 82, 83, 84, 89
 - diagnostic subsystem keys
 - Auxiliary Software Options, 82
 - Diagnostic Info, 81, 82, 83, 84
 - Installed Board Info, 81
 - Options Info, 83
 - diagnostic subsystem softkeys
 - Waveform Licenses, 82, 84
 - Diff Data Encode Off On softkey, 559, 784
 - Diff. Mode I Offset softkey, 26

Index

- Diff. Mode Q Offset softkey, [27](#)
- Digital Modulation Off On softkey, [293](#)
- digital modulation subsystem keys
 - 2.100 MHz, [32](#)
 - 40.000 MHz, [32](#)
 - ALC BW Normal Narrow, [22](#)
 - BBG1, [24](#), [35](#)
 - Burst Envelope Int Ext Off, [22](#)
 - Common Mode I/Q Offset, [26](#)
 - Diff. Mode I Offset, [26](#)
 - Diff. Mode Q Offset, [27](#)
 - Ext 50 Ohm, [24](#), [35](#)
 - Ext 600 Ohm, [24](#), [35](#)
 - Ext In 600 Ohm I Offset, [27](#)
 - Ext In 600 Ohm Q Offset, [28](#)
 - High Crest Mode Off On, [23](#)
 - I Offset, [29](#)
 - I/Q Adjustments Off On, [32](#)
 - I/Q Gain Balance Source 1, [29](#)
 - I/Q Mod Filter Manual Auto, [33](#)
 - I/Q Off On, [37](#)
 - I/Q Out Gain Balance, [27](#)
 - I/Q Output Atten, [28](#)
 - I/Q Timing Skew, [31](#)
 - I/Q Timing Skew Path softkey, [32](#)
 - Int I/Q Skew Corrections RF BB Off, [35](#)
 - Int Phase Polarity Normal Invert, [24](#), [34](#)
 - Modulator Atten Manual Auto, [33](#), [34](#)
 - Off, [24](#), [35](#)
 - Q Offset, [30](#)
 - Quadrature Angle Adjustment, [25](#), [30](#)
 - Sum, [24](#)
 - Summing Ratio (SRC1/SRC2) x.xx dB, [36](#)
 - Through, [32](#)
- digital signal interface module, [380](#)
- digital subsystem softkeys, [387](#)
 - Bit Order, [384](#)
 - Clock Per Sample, [380](#)
 - Clock Phase, [380](#)
 - Clock Polarity, [381](#)
 - Clock Rate, [382](#)
 - Clock Skew, [383](#)
 - Clock Source, [383](#)
 - Data Type, [392](#)
 - Direction, [385](#)
 - digital subsystem softkeys, [387](#) (*continued*)
 - Frame Polarity, [387](#)
 - I Gain, [385](#)
 - I Offset, [386](#)
 - IQ Polarity, [388](#)
 - Logic Type, [393](#)
 - Loop Back Test Type, [393](#)
 - N5102A Off On, [395](#)
 - Negate I, [386](#)
 - Negate Q, [389](#)
 - Pass Through Preset, [395](#)
 - Port Config, [394](#)
 - Q Gain, [388](#)
 - Q Offset, [390](#)
 - Reference Frequency, [382](#)
 - Rotation, [390](#)
 - Scaling, [391](#)
 - Signal Type, [392](#)
 - Swap IQ, [387](#)
 - Word Alignment, [384](#)
 - Word Size, [391](#)
 - Direction softkey, [385](#)
 - discrete response data, [11](#)
 - discrete SCPI parameters, [9](#)
 - display
 - secure mode, [160](#)
 - display contrast hardkeys, [86](#)
 - display subsystem keys
 - Brightness, [86](#)
 - display contrast, [86](#)
 - Inverse Video Off On, [87](#)
 - Update in Remote Off On, [87](#)
 - DL Reference 1.1 softkey, [1158](#)
 - wideband CDMA base band generator subsystem softkeys
 - DL Reference 1.1, [1061](#)
 - DL Reference 1.2 softkey, [1158](#)
 - wideband CDMA base band generator subsystem softkeys
 - DL Reference 1.2, [1061](#)
 - DL Reference 2.1 softkey, [1158](#)
 - wideband CDMA base band generator subsystem softkeys
 - DL Reference 2.1, [1061](#)

- DL Reference 2.2 softkey, [1158](#)
 - wideband CDMA base band generator subsystem softkeys
 - DL Reference 2.2, [1061](#)
- DM0 softkey
 - See DECT subsystem keys
- DM1 softkey
 - See DECT subsystem keys
- DMOD softkey, [95](#)
- Dmodulation subsystem keys
 - # of Carriers, [283](#), [285](#)
 - 128QAM, [279](#)
 - 16PSK, [279](#)
 - 16QAM, [279](#)
 - 2.100 MHz, [275](#)
 - 256QAM, [279](#)
 - 2-Lvl FSK, [279](#)
 - 32QAM, [279](#)
 - 40.000 MHz, [270](#), [275](#)
 - 4-Lvl FSK, [279](#)
 - 4QAM, [279](#)
 - 64QAM, [279](#)
 - 8PSK, [279](#)
 - APCO 25 C4FM, [271](#)
 - APCO 25 w/C4FM, [282](#), [283](#), [284](#)
 - APCO 25 w/C4QPSK, [282](#), [283](#), [284](#)
 - ARB Reference Ext Int, [281](#)
 - ARB Sample Clock, [282](#)
 - BPSK, [279](#)
 - Bus, [290](#)
 - Carrier Phases Fixed Random, [283](#)
 - CDPD, [282](#), [283](#), [284](#)
 - Clear Header, [273](#)
 - Continuous, [287](#)
 - Custom Digital Mod State, [283](#), [284](#)
 - D8PSK, [279](#)
 - DECT, [282](#), [283](#), [284](#)
 - Digital Modulation Off On, [293](#)
 - EDGE, [282](#), [283](#), [284](#)
 - Ext, [290](#)
 - Ext Delay Off On, [291](#)
 - Ext Delay Time, [291](#)
 - Ext Polarity Neg Pos, [292](#)
 - Filter Alpha, [272](#)
 - Filter BbT, [272](#)
 - Dmodulation subsystem keys (*continued*)
 - Free Run, [288](#)
 - Freq Dev, [279](#)
 - Freq Spacing, [283](#)
 - Gate Active Low High, [289](#)
 - Gated, [287](#)
 - Gaussian, [271](#)
 - Gray Coded QPSK, [279](#)
 - GSM, [282](#), [283](#), [284](#)
 - I/Q Mod Filter Manual Auto, [275](#)
 - I/Q Output Filter Manual Auto, [270](#)
 - Immediate, [281](#)
 - Initialize Table, [284](#)
 - Insert Row, [249](#), [284](#)
 - IS-2000 SR3 DS, [271](#)
 - IS-95, [271](#)
 - IS-95 Mod, [271](#)
 - IS-95 Mod w/EQ, [271](#)
 - IS-95 OQPSK, [279](#)
 - IS-95 QPSK, [279](#)
 - IS-95 w/EQ, [271](#)
 - Load/Store, [284](#)
 - Marker 1, [276](#), [277](#)
 - Marker 1 Polarity Neg Pos, [280](#)
 - Marker 2, [276](#), [277](#)
 - Marker 2 Polarity Neg Pos, [280](#)
 - Marker 3, [276](#), [277](#)
 - Marker 3 Polarity Neg Pos, [280](#)
 - Marker 4, [276](#), [277](#)
 - Marker 4 Polarity Neg Pos, [280](#)
 - Modulator Atten Manual Auto, [274](#)
 - MSK, [279](#)
 - Multicarrier Off On, [282](#)
 - NADC, [282](#), [283](#), [284](#)
 - None, [276](#), [277](#)
 - Nyquist, [271](#)
 - Off, [281](#)
 - On, [281](#)
 - Optimize FIR For EVM ACP, [273](#)
 - OQPSK, [279](#)
 - $\pi/4$ DQPSK, [279](#)
 - Patt Trig In 1, [292](#)
 - Patt Trig In 2, [292](#)
 - PDC, [282](#), [283](#), [284](#)
 - PHS, [282](#), [283](#), [284](#)

Index

Dmodulation subsystem keys (*continued*)

- PWT, [282](#), [283](#), [284](#)
- QPSK, [279](#)
- Rectangle, [271](#)
- Reference Freq, [212](#), [280](#)
- Reset & Run, [288](#)
- Root Nyquist, [271](#)
- Save Setup To Header, [273](#)
- Select File, [249](#), [282](#)
- Single, [287](#)
- Store Custom Dig Mod State, [285](#)
- Symbol Rate, [286](#)
- TETRA, [282](#), [283](#), [284](#)
- Through, [270](#), [275](#)
- Trigger & Run, [288](#)
- Trigger Key, [290](#)
- UN3/4 GSM Gaussian, [271](#)
- User FIR, [271](#)
- WCDMA, [271](#)
- Dn Custom Cont softkey, [1010](#)
- Dn Normal Cont softkey, [1010](#)
- Dn Normal Disc softkey, [1010](#)
- Dn Sync Cont softkey, [1010](#)
- Dn Sync Disc softkey, [1010](#)
- Do Power Search softkey, [60](#), [62](#)
- documentation, [lxxiii](#)
- Doppler Shift softkey, [764](#)
- Down Custom softkey, [899](#), [933](#)
- Down TCH All softkey, [899](#), [933](#)
- Down TCH softkey, [899](#), [933](#)
- Down/Up softkey, [1036](#), [1086](#)
- Downlink MCS-1 softkey, [641](#), [643](#), [794](#)
- Downlink MCS-5 softkey, [646](#)
- Downlink MCS-9 softkey, [646](#)
- downloading files, [116](#)
- DPCCH + 1 DPDCH softkey, [363](#)
- DPCCH + 2 DPDCH softkey, [363](#)
- DPCCH + 3 DPCCH softkey, [363](#)
- DPCCH + 4 DPDCH softkey, [363](#)
- DPCCH + 5 DPDCH softkey, [363](#)
- DPCCH Pilot data-clk (DRPS23) softkey, [1050](#),
[1052](#), [1053](#), [1054](#), [1055](#)
- DPCCH Power field, [1083](#)
- DPCCH Raw Data (RPS4) softkey
 - See* wideband CDMA base band generator subsystem keys and fields
- DPCCH Raw Data Clock (RPS5) softkey
 - See* wideband CDMA base band generator subsystem keys and fields
- DPCCH softkey, [363](#), [1077](#), [1100](#)
- DPCCH TFC I data-clk (DRPS22) softkey, [1050](#),
[1052](#), [1053](#), [1054](#), [1055](#)
- DPCCH TPC indicator (DRPS21) softkey, [1050](#),
[1052](#), [1053](#), [1054](#), [1055](#)
- DPCH + 1 softkey, [1022](#), [1023](#)
- DPCH + 2 softkey, [1022](#), [1023](#)
- DPCH Channel Balance softkey, [1030](#)
- DPCH Compressed Frame Indicator (DRPS32) softkey, [1050](#), [1052](#), [1053](#), [1054](#), [1055](#)
- DPCH data stream (DRPS24) softkey, [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
- DPCH data-clk (0) (DRPS28) softkey, [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
- DPCH Gap Indicator (DRPS33) softkey, [1050](#),
[1052](#), [1053](#), [1054](#), [1055](#)
- DPCH softkey, [357](#)
- DPCH TimeSlot pulse (DRPS25) softkey, [1050](#),
[1052](#), [1053](#), [1054](#), [1055](#)
- DPCH10ms Frame-Pulse (DRPS26) softkey, [1050](#),
[1052](#), [1053](#), [1054](#), [1055](#)
- DPDCH data-clk withDTX (DRPS20) softkey,
[1050](#), [1052](#), [1053](#), [1054](#), [1055](#)
- DPDCH data-clk WithOutDTX (DRPS30) softkey,
[1050](#), [1052](#), [1053](#), [1054](#), [1055](#)
- DPDCH Power field, [1092](#)
- DPDCH Raw Data (RPS2) softkey
 - See* wideband CDMA base band generator subsystem keys and fields
- DPDCH Raw DataClock (RPS3) softkey
 - See* wideband CDMA base band generator subsystem keys and fields
- DPDCH softkey, [1077](#)
- Drift Deviation softkey, [469](#)
- dual ARB subsystem
 - generate sine, [294](#)
 - markers, *See* markers
 - runtime scaling, [312](#)
 - scaling waveform files, [312](#)

dual ARB subsystem (*continued*)
 Through, 298

dual ARB subsystem keys
 # Skipped Points, 302
 2.100 MHz, 299
 40.000 MHz, 298, 299
 Apply to Waveform, 300, 302
 ARB Off On, 324
 ARB Reference Ext Int, 23, 311
 ARB Sample Clock, 313
 Build New Waveform Sequence, 313
 Bus, 320
 Carrier Bandwidth, 309
 Carrier to Noise Ratio, 309
 Clear Header, 295
 Clipping Type II+jQI III,IQI, 294
 Continuous, 318
 Edit Repetitions, 313
 Ext, 320
 Ext Delay, 321
 Ext Delay Samples, 321
 Ext Delay Time, 322
 Ext Polarity Neg Pos, 322
 First Mkr Point, 300, 302
 Free Run, 317
 Gate Active Low High, 317
 Gated, 315
 Header RMS, 295
 I/Q Mod Filter Manual Auto, 300
 I/Q Output Filter Manual Auto, 297, 298
 Immediate, 311
 Insert Waveform, 313
 Last Mkr Point, 300, 302
 Marker 1, 305
 Marker 1 2 3 4, 300
 Marker 2, 305
 Marker 3, 305
 Marker 4, 305
 Marker Polarity Neg Pos, 308, 333, 370, 475
 Markers, 302, 306
 Modulator Atten Manual Auto, 298, 299
 Name and Store, 313
 Noise Bandwidth Factor, 308
 None, 305, 306
 Off, 311, 321

dual ARB subsystem keys (*continued*)
 On, 311
 Patt Trig In 1, 323
 Patt Trig In 2, 323
 Real-time Noise Off On, 310
 Reference Freq, 310
 Reset & Run, 317
 Samples, 321
 Save Setup To Header, 297
 Scale Waveform Data, 312
 Scaling, 312
 Segment Advance, 315
 Select Waveform, 323, 324
 Set Marker Off All Points, 301
 Set Marker Off Range Of Points, 300
 Set Marker On Range Of Points, 302
 Single, 315, 318
 Through, 298, 299
 Time, 321
 Toggle Marker 1 2 3 4, 313
 Trigger & Run, 317
 Trigger Key, 320
 Waveform Runtime Scaling, 312

Dual-Sine softkey, 175, 182, 189, 195
 Dummy Bearer 1 softkey, 600
 Dummy Bearer 2 softkey, 600
 Dummy softkey, 802
 DWCDMA softkey, 96
 Dwell Type List Step softkey, 51

E

Eb/No field, 1106
 Eb/No value (dB) field, 1076
 EbNo field, 506
See CDMA2000 BBG subsystem keys and fields
 Ec/No value field, 1022, 1107
 EcNo field, 493, 528, 533
 EDGE BERT Off On softkey, 442
 EDGE Off On softkey, 665
 EDGE softkey, 282, 283, 284, 634
 EDGE subsystem keys
 128QAM, 637
 16 1's & 16 0's, 630, 639, 641, 646
 16PSK, 637
 16QAM, 637

Index

EDGE subsystem keys (*continued*)

256QAM, 637
2-Lvl FSK, 637
32 1's & 32 0's, 630, 639, 641, 646
32QAM, 637
4 1's & 4 0's, 630, 639, 641, 646
4-Lvl FSK, 637
4QAM, 637
64 1's & 64 0's, 630, 639, 641, 646
64QAM, 637
8 1's & 8 0's, 630, 639, 641, 646
8PSK, 637
All Timeslots, 657
APCO 25 C4FM, 634
BBG Ref Ext Int, 633
Begin Frame, 657
Begin Timeslot #, 657, 658
BPSK, 637
Bus, 638, 662
Continuous, 660
CS-1, 641, 642
CS-4, 641, 643
Custom, 656
Custom TS, 645, 655
D8PSK, 637
Data Format Pattern Framed, 629
Downlink MCS-1, 641, 643
Downlink MCS-5, 646
Downlink MCS-9, 646
EDGE, 634
EDGE Off On, 665
E-TCH/F43.2, 646
Ext, 630, 638, 639, 646, 662
Ext BBG Ref Freq, 633
Ext Data Clock Ext Int, 622
Ext Data Clock Normal Symbol, 632
Ext Delay Bits, 663
Ext Delay Off On, 664
Ext Polarity Neg Pos, 664
Fall Delay, 623, 624
Fall Time, 625
Filter Alpha, 622
Filter BbT, 623
FIX4, 630, 631, 639, 640, 641, 643, 646, 652
Free Run, 660

EDGE subsystem keys (*continued*)

Freq Dev, 635
G, 640, 654
Gate Active Low High, 661
Gated, 660
Gaussian, 634
GMSK, 656
Gray Coded QPSK, 637
I/Q Scaling, 635
IS-95, 634
IS-95 Mod, 634
IS-95 Mod w/EQ, 634
IS-95 OQPSK, 637
IS-95 QPSK, 637
IS-95 w/EQ, 634
MSK, 637
Multislot Off On, 646
Normal, 656
Normal All, 656
Nyquist, 634
Optimize FIR For EVM ACP, 630
OQPSK, 637
 $\pi/4$ DQPSK, 637
Patt Trig In 1, 665
Patt Trig In 2, 665
Phase Dev, 636
Phase Polarity Normal Invert, 637
PN11, 630, 639, 646
PN15, 630, 639, 641, 642, 643, 644, 646, 650, 651, 652, 653
PN20, 630, 639, 646
PN23, 630, 639, 646
PN9, 630, 639, 641, 642, 643, 644, 646, 650, 651, 652, 653
QPSK, 637
Recall Secondary Frame State, 638
Rectangle, 634
Reset & Run, 660
Restore EDGE Factory Default, 632
Rise Delay, 626, 627
Rise Time, 627, 628
Root Nyquist, 634
S, 645
Save Secondary Frame State, 638
Secondary Frame Off On, 639

- EDGE subsystem keys (*continued*)
- Sine, 629
 - Single, 660
 - Symbol Rate, 658
 - Sync Out Offset, 657
 - T1, 654
 - T2, 655
 - TCH/FS, 641, 644
 - Timeslot Ampl Main Delta, 655
 - Timeslot Off On, 656
 - Trigger & Run, 660
 - Trigger Key, 638, 662
 - TSC0, 645, 655
 - TSC1, 645, 655
 - TSC2, 645, 655
 - TSC3, 645, 655
 - TSC4, 645, 655
 - TSC5, 645, 655
 - TSC6, 645, 655
 - TSC7, 645, 655
 - UN3/4 GSM Gaussian, 634
 - Uncoded, 646
 - Uplink MCS-1, 641, 644
 - Uplink MCS-5, 646
 - Uplink MCS-9, 646
 - User File, 629, 630, 639, 641, 646
 - User FIR, 634
 - User FSK, 636, 637
 - User I/Q, 636, 637
- edge subsystem keys
- PRAM File, 631
- Edit Channel Setup softkey, 252, 255
- Edit Repetitions softkey, 313
- Enter Secure Mode softkey, 162
- Equal Energy per Symbol softkey, 361
- Equal Powers softkey
- See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* CDMA2000 BBG subsystem keys and fields
 - See* wideband CDMA base band generator subsystem keys and fields
- Erase All softkey, 161
- Erase and Overwrite All softkey, 163
- Erase and Sanitize All softkey, 163
- Erase softkey, 161
- ERROR
- 221, 116
 - Error BER softkey, 1172
 - Error Bits softkey, 1165
 - Error Blocks field, 1166
 - Error Count softkey, 442
 - See* sense subsystem keys
 - Error Info softkey, 155
 - error messages, resolving, 670, 814
 - Error Out softkey, 413
 - Error Rate softkey
 - See* calculate subsystem keys
 - See* calculate subsystem keys
- ESG file overview, 668, 812
- ET softkey, 792
- E-TCH/F43.2 softkey, 646
- Even Second Delay field, 480, 513
- Exceeds Any Limit softkey, 405
- Exceeds Any Thresholds softkey
- See* sense subsystem keys
- Execute Cal softkey, 72, 73
- Ext 50 Ohm softkey, 24, 35
- Ext 600 Ohm softkey, 24, 35
- Ext BBG Ref Freq softkey
- See* custom subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
- Ext CDMA Freq field, 500
- Ext Clock Rate x1 x2 x4 softkey, 1020
- Ext Data Clock Ext Int softkey
- See* EDGE subsystem keys
 - See* PDC subsystem keys
- Ext Data Clock Normal Symbol softkey
- See* custom subsystem keys
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys

Index

Ext Delay Bits softkey

- See custom subsystem keys
- See DECT subsystem keys
- See EDGE subsystem keys
- See GSM subsystem keys
- See NADC subsystem keys
- See PDC subsystem keys
- See PHS subsystem keys
- See TETRA subsystem keys

Ext Delay Off On softkey

- See CDMA ARB subsystem keys
- See CDMA2000 ARB subsystem keys
- See custom subsystem keys
- See DECT subsystem keys
- See Dmodulation subsystem keys
- See EDGE subsystem keys
- See GSM subsystem keys
- See NADC subsystem keys
- See PDC subsystem keys
- See PHS subsystem keys
- See TETRA subsystem keys
- See wideband CDMA ARB subsystem keys

Ext Delay Samples softkey, [321](#)

Ext Delay softkey, [321](#)

Ext Delay Time softkey, [236](#), [267](#), [291](#), [322](#), [376](#)

Ext Frame Trigger Delay softkey, [427](#)

Ext In 600 Ohm I Offset softkey, [27](#)

Ext In 600 Ohm Q Offset softkey, [28](#)

Ext Polarity Neg Pos softkey

- See CDMA ARB subsystem keys
- See CDMA2000 ARB subsystem keys
- See custom subsystem keys
- See DECT subsystem keys
- See Dmodulation subsystem keys
- See dual ARB subsystem keys
- See EDGE subsystem keys
- See GSM subsystem keys
- See NADC subsystem keys
- See PDC subsystem keys
- See PHS subsystem keys
- See TETRA subsystem keys
- See wideband CDMA ARB subsystem keys

Ext softkey

- List/Sweep subsystem, [54](#)
- See amplitude modulation subsystem keys

Ext softkey (continued)

- See CDMA ARB subsystem keys
- See CDMA2000 ARB subsystem keys
- See CDMA2000 BBG subsystem keys and fields
- See custom subsystem keys
- See DECT subsystem keys
- See Dmodulation subsystem keys
- See dual ARB subsystem keys
- See EDGE subsystem keys
- See frequency modulation subsystem keys
- See GSM subsystem keys
- See low frequency output subsystem keys
- See NADC subsystem keys
- See PDC subsystem keys
- See phase modulation subsystem keys
- See PHS subsystem keys
- See sense subsystem keys
- See TETRA subsystem keys
- See trigger subsystem keys
- See wideband CDMA ARB subsystem keys
- See wideband CDMA base band generator subsystem keys and fields

Ext softkeys

- Ext Coupling DC AC, [173](#), [180](#), [193](#)
- Ext Detector, [63](#)
- Ext Pulse, [202](#)
- Ext1, [176](#), [184](#), [196](#)
- Ext2, [176](#), [184](#), [196](#)

extended numeric SCPI parameter, [8](#)

External Frame Trigger Polarity Neg Pos softkey, [427](#)

External softkey, [512](#)

F

FACC softkey

- See DECT subsystem keys

Fail Hold softkey, [405](#)

Fall Delay softkey

- See custom subsystem keys
- See DECT subsystem keys
- See EDGE subsystem keys
- See GSM subsystem keys
- See NADC subsystem keys
- See PDC subsystem keys
- See PHS subsystem keys

Fall Delay softkey (continued)

See TETRA subsystem keys

Fall Time softkey

See custom subsystem keys

See DECT subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

Falling softkey, [547](#)

FBI State field, [1082](#)

FCDMA softkey, [96](#)

FCOR softkey, [999](#), [1004](#)

FCorr softkey, [802](#)

FDEV1_FS softkey

See DECT subsystem keys

FDEV1_HS softkey

See DECT subsystem keys

FDEV2_FS softkey

See DECT subsystem keys

Field 1 field, [490](#)

Field 2 field, [490](#)

Field 3 field, [491](#)

file

names, [105](#)

retrieval, [116](#)

systems, [14](#)

types, [14](#)

file overview, HSPA, [812](#)

file overview, HSPA, [668](#)

Filter Alpha softkey, [1098](#)

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See CDMA2000 BBG subsystem keys and fields

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See EDGE subsystem keys

See GPS subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

Filter Alpha softkey, 1098 (continued)

See TETRA subsystem keys

See wideband CDMA ARB subsystem keys

See wideband CDMA base band generator
subsystem keys and fields

Filter BbT softkey, [1099](#)

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See CDMA2000 BBG subsystem keys and fields

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See EDGE subsystem keys

See GPS subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA ARB subsystem keys

See wideband CDMA base band generator
subsystem keys and fields

FIR data, [108](#)

FIR softkey, [97](#)

First Mkr Point softkey, [300](#), [302](#)

First Spread Code softkey, [356](#), [364](#)

FIX softkey, [1082](#)

FIX4 softkey, [643](#), [1081](#), [1110](#), [1114](#)

See CDMA2000 BBG subsystem keys and fields

See custom subsystem keys

See DECT subsystem keys

See EDGE subsystem keys

See GPS subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA baseband generator
subsystem keys and fields

Flat Noise BW field, [1077](#)

Flatness Off On softkey, [21](#)

FM softkeys

FM Dev, [185](#)

FM Dev Couple Off On, [185](#)

Index

FM softkeys (*continued*)

- FM Off On, [184](#)
- FM Path 1 2, [179](#)
- FM Stop Rate, [181](#)
- FM Sweep Rate, [183](#)
- FM Tone 2 Amp Percent of Peak, [182](#)
- FM Tone 2 Rate, [181](#)
- forgiving listening and precise talking, [7](#)
- Frame Clock Polarity Neg Pos softkey, [1097](#)
- Frame Count softkey
 - See sense subsystem keys
- Frame Erasure softkey, [452](#)
 - See calculate subsystem keys
- Frame Length field
 - See CDMA2000 BBG subsystem keys and fields
- Frame Offset field
 - See CDMA2000 BBG subsystem keys and fields
- Frame offset field, [536](#)
- Frame Polarity softkey, [387](#)
- Frame Repeat Single Cont softkey, [891](#)
- Frame Struct field, [1057](#)
- Frame Sync Trigger Mode Single Cont softkey, [1152](#)
- Frame Trigger Source Int Ext softkey, [428](#)
- Free Run softkey
 - list trigger source, [54](#)
 - See amplitude modulation subsystem keys
 - See CDMA ARB subsystem keys
 - See CDMA2000 ARB subsystem keys
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See dual ARB subsystem keys
 - See EDGE subsystem keys
 - See frequency modulation subsystem keys
 - See GSM subsystem keys
 - See low frequency output subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See phase modulation subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
 - See trigger subsystem keys
 - See wideband CDMA ARB subsystem keys

Freq Dev softkey

- See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See TETRA subsystem keys
- ### Freq softkeys
- Freq, [42, 49](#)
 - Freq & Ampl, [49](#)
 - Freq Channels Off On, [41](#)
 - Freq Drift Type Linear Sine, [470](#)
 - Freq Multiplier, [42](#)
 - Freq Offset, [43, 470](#)
 - Freq Ref Off On, [44](#)
 - Freq Ref Set, [43](#)
 - Freq Spacing, [283, 336, 337](#)
 - Freq Start, [44, 49](#)
 - Freq Stop, [45, 49](#)
- ### Frequency hardkey, [38, 41, 42, 45, 46](#)
- ### frequency modulation subsystem keys
- Bus, [183](#)
 - Dual-Sine, [182](#)
 - Ext, [183](#)
 - Ext Coupling DC AC, [180](#)
 - Ext1, [184](#)
 - Ext2, [184](#)
 - FM Dev, [185](#)
 - FM Dev Couple Off On, [185](#)
 - FM Off On, [184](#)
 - FM Path 1 2, [179](#)
 - FM Stop Rate, [181](#)
 - FM Sweep Rate, [183](#)
 - FM Tone 2 Amp Percent of Peak, [182](#)
 - FM Tone 2 Rate, [181](#)
 - Free Run, [183](#)
 - Incr Set, [180](#)
 - Internal 1, [184](#)
 - Internal 2, [184](#)
 - Noise, [182](#)
 - Ramp, [182](#)
 - Sine, [182](#)
 - Square, [182](#)

- frequency modulation subsystem keys (*continued*)
 Swept-Sine, 182
 Triangle, 182
 Trigger Key, 183
- frequency subsystem keys
 Adjust Phase, 47
 Channel Number, 40
 Freq, 42, 49
 Freq Channels Off On, 41
 Freq Multiplier, 42
 Freq Offset, 43
 Freq Ref Off On, 44
 Freq Ref Set, 43
 Freq Start, 44, 49
 Freq Stop, 45, 49
 Frequency, 38, 41, 42, 45, 46
 Off, 42, 49
 Phase Ref Set, 47
 Ref Oscillator Source Auto Off On, 48
- FSK softkey, 97
- FSYNCH Type field, 504
- Full softkey, 529, 534
- Function Generator softkey, 190
- G**
- G softkey, 640, 654
- Gain Unit dB Lin Index softkey, 366
- Gate Active Low High softkey
See CDMA ARB subsystem keys
See CDMA2000 ARB subsystem keys
See custom subsystem keys
See DECT subsystem keys
See Dmodulation subsystem keys
See dual ARB subsystem keys
See EDGE subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PDC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys
See wideband CDMA ARB subsystem keys
- Gate Clk Delay softkey, 416
- Gate Delay Off On softkey, 417
- Gate Mode Time Clk softkey, 416
- Gate Off On softkey, 418
- Gate Polarity Neg Pos softkey, 418
- Gate Time Delay softkey, 417
- Gated softkey
See CDMA ARB subsystem keys
See CDMA2000 ARB subsystem keys
See custom subsystem keys
See DECT subsystem keys
See Dmodulation subsystem keys
See dual ARB subsystem keys
See EDGE subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PDC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys
See wideband CDMA ARB subsystem keys
- Gaussian softkey
See CDMA ARB subsystem keys
See CDMA2000 ARB subsystem keys
See CDMA2000 BBG subsystem keys and fields
See custom subsystem keys
See DECT subsystem keys
See Dmodulation subsystem keys
See EDGE subsystem keys
See GPS subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PDC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys
See wideband CDMA ARB subsystem keys
See wideband CDMA base band generator
 subsystem keys and fields
- generate sine, 294
- GMSK softkey, 656
- Goto Row softkey, 334
- GPIB Address softkey, 75
- GPS Ref (f0) softkey, 768, 771
- GPS Ref Clk Ext Int softkey, 768, 771
- GPS subsystem
 Data Mode Raw Enc TLM, 764
- GPS subsystem keys
 APCO 25 C4FM, 764
 Data Mode Raw Enc TLM, 763
 Doppler Shift, 764

Index

GPS subsystem keys (*continued*)

Filter Alpha, [765](#)
Filter BbT, [766](#)
FIX4, [763](#)
Gaussian, [764](#)
GPS Ref (f0), [768](#)
GPS Ref Clk Ext Int, [768](#)
IQ Phase Normal Invert, [767](#)
IS-95, [764](#)
IS-95 Mod, [764](#)
IS-95 Mod w/EQ, [764](#)
IS-95 w/EQ, [764](#)
Nyquist, [764](#)
Optimize FIR For EVM ACP, [766](#)
P Code Pwr, [767](#)
PN15, [763](#)
PN9, [763](#)
Ranging Code C/A P C/A+P, [767](#)
Real-time GPS Off On, [769](#)
Rectangle, [764](#)
Root Nyquist, [764](#)
Satellite ID, [769](#)
UN3/4 GSM Gaussian, [764](#)
User File, [763](#)
User FIR, [764](#)

Gray Coded QPSK softkey

See custom subsystem keys
See DECT subsystem keys
See Dmodulation subsystem keys
See EDGE subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PDC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys

GSM BERT Off On softkey, [455](#)

GSM Off On softkey, [811](#)

GSM softkey, [282](#), [283](#), [284](#)

GSM subsystem keys

128QAM, [789](#)
16 1's & 16 0's, [782](#), [791](#), [792](#), [794](#), [801](#)
16PSK, [789](#)
16QAM, [789](#)
256QAM, [789](#)
2-Lvl FSK, [789](#)

GSM subsystem keys (*continued*)

32 1's & 32 0's, [782](#), [791](#), [792](#), [794](#), [801](#)
32QAM, [789](#)
4 1's & 4 0's, [782](#), [791](#), [792](#), [794](#), [801](#)
4-Lvl FSK, [789](#)
4QAM, [789](#)
64 1's & 64 0's, [782](#), [791](#), [792](#), [794](#), [801](#)
64QAM, [789](#)
8 1's & 8 0's, [782](#), [791](#), [792](#), [794](#), [801](#)
8PSK, [789](#)
Access, [802](#)
All Timeslots, [803](#)
APCO 25 C4FM, [786](#)
BBG Data Clock Ext Int, [773](#)
BBG Ref Ext Int, [785](#)
Begin Frame, [803](#)
Begin Timeslot #, [803](#), [804](#)
Bit Rate, [774](#)
BPSK, [789](#)
Bus, [790](#), [807](#)
Continuous, [806](#)
CS-1, [794](#)
CS-4, [798](#)
Custom, [802](#)
Custom TS, [793](#), [800](#)
D8PSK, [789](#)
Data Format Pattern Framed, [781](#)
Diff Data Encode Off On, [784](#)
Downlink MCS-1, [794](#)
Dummy, [802](#)
ET, [792](#)
Ext, [782](#), [790](#), [791](#), [792](#), [801](#), [807](#)
Ext BBG Ref Freq, [585](#), [785](#)
Ext Data Clock Normal Symbol, [784](#)
Ext Delay Bits, [808](#)
Ext Delay Off On, [809](#)
Ext Polarity Neg Pos, [809](#)
Fall Delay, [776](#), [777](#)
Fall Time, [776](#), [778](#)
FCorr, [802](#)
Filter Alpha, [773](#)
Filter BbT, [774](#)
FIX4, [782](#), [783](#), [791](#), [792](#), [793](#), [794](#), [799](#), [801](#), [802](#)
Free Run, [806](#)
Freq Dev, [787](#)

GSM subsystem keys (*continued*)

Gate Active Low High, 807
 Gated, 806
 Gaussian, 786
 Gray Coded QPSK, 789
 GSM Off On, 811
 I/Q Scaling, 787
 IS-95, 786
 IS-95 Mod, 786
 IS-95 Mod w/EQ, 786
 IS-95 OQPSK, 789
 IS-95 QPSK, 789
 IS-95 w/EQ, 786
 MSK, 789
 Multislot Off On, 793
 Normal, 802
 Normal All, 802
 Nyquist, 786
 Optimize FIR For EVM ACP, 782
 OQPSK, 789
 $\pi/4$ DQPSK, 789
 Patt Trig In 1, 810
 Patt Trig In 2, 810
 Phase Dev, 788
 Phase Polarity Normal Invert, 789
 PN11, 782, 801
 PN15, 782, 791, 792, 794, 798, 799, 801
 PN20, 782, 801
 PN23, 782, 801
 PN9, 782, 791, 792, 794, 798, 799, 801
 PN9 Mode Normal Quick, 775
 QPSK, 789
 Recall Secondary Frame State, 790
 Rectangle, 786
 Reset & Run, 806
 Restore Factory Default, 783
 Rise Delay, 778, 779
 Rise Time, 780
 Root Nyquist, 786
 S, 800
 Save Secondary Frame State, 790
 Secondary Frame Off On, 791
 Sine, 781
 Single, 806
 SS, 792

GSM subsystem keys (*continued*)

Symbol Rate, 804
 Sync, 802
 Sync Out Offset, 803
 TCH/FS, 794
 Timeslot Ampl Main Delta, 801
 Timeslot Off On, 801
 Trigger & Run, 806
 Trigger Key, 790, 807
 TS, 802
 TSC0, 793, 800
 TSC1, 793, 800
 TSC2, 793, 800
 TSC3, 793, 800
 TSC4, 793, 800
 TSC5, 793, 800
 TSC6, 793, 800
 TSC7, 793, 800
 UN3/4 GSM Gaussian, 786
 Uplink MCS-1, 794
 User File, 781, 782, 791, 792, 794, 801
 User FIR, 786
 User FSK, 788, 789
 User I/Q, 788, 789
 gsm subsystem keys
 PRAM Files, 783
 guides, lxxiii

H

Half softkey, 529, 534
 Header field, 486, 496
 Help Mode Single Cont softkey, 156
 hexadecimal values, 18
 High Amplitude softkey
 See sense subsystem keys
 High Crest Mode Off On softkey, 23
 Higher Layer softkey, 1155
 Hostname softkey, 76
 HSDPA file overview, 812
 HSDPA over W-CDMA SCPI commands, 812
 HSDPA user files, 812
 HSPA file overview, 668
 HSPA user files, 668

Index

- I
- I Gain softkey, 385
- I Offset softkey, 29, 386
- I/Q Adjustments Off On softkey, 32
- I/Q Calibration softkey, 72
- I/Q Gain Balance Source 1 softkey, 29
- I/Q Mapping Normal Invert softkey, 221, 247, 345
- I/Q Mod Filter Manual Auto softkey, 33, 208, 222, 246, 275, 300, 329, 347, 474
- I/Q Off On softkey, 37
- I/Q Out Gain Balance softkey, 27
- I/Q Output Atten softkey, 28
- I/Q Output Filter Manual Auto softkey, 206, 217, 242, 270, 297, 298, 327, 345, 466
- I/Q Scaling softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- I/Q softkey, 98
- I/Q Timing Skew Path, 32
- I/Q timing Skew softkey, 31
- IDLE softkey, 954, 973
- IEEE 488.2 common command keys
 - Diagnostic Info, 89
 - Instrument Options, 90
 - RECALL Reg, 90
 - Run Complete Self Test, 92
 - Save Reg, 91
 - Save Seq[n] Reg[nn], 91
 - Select Seq, 90
- Immediate softkey, 227, 261, 281, 311
 - See sense subsystem keys
- Impairments Off On softkey, 467
- Impedance 75 Ohm High softkey, 420
- Incr Set hardkey, 69
 - See amplitude modulation subsystem keys
 - See frequency modulation subsystem keys
 - See phase modulation subsystem keys
- Increment Scramble Code softkey, 352
- Increment Timing Offset softkey, 355
- Infinity softkey, 1060, 1157
- Init Power field, 1101
- Init Pwr field, 1119, 1134
- Initial Bit Count softkey, 441
- Initial Block Count softkey, 431, 434
- Initial Frame Count softkey, 451
- Initialize Phase Fixed Random softkey, 338
- Initialize Table softkey, 284
- input subsystem keys
 - 0.7V, 421
 - 1.4V, 421
 - 1.6V, 421
 - 2.5V, 421
 - Clock Delay Off On, 419
 - Clock Polarity Neg Pos, 420
 - Clock Time Delay, 419
 - Data Polarity Neg Pos, 420
 - Gate Clk Delay, 416
 - Gate Delay Off On, 417
 - Gate Mode Time Clk, 416
 - Gate Off On, 418
 - Gate Polarity Neg Pos, 418
 - Gate Time Delay, 417
 - Impedance 75 Ohm High, 420
 - Resolution, 418
- Insert Row softkey, 249, 252, 255, 284
- Insert Waveform softkey, 313
- installation guide, lxxiii
- Installed Board Info softkey, 81
- Instrument Options softkey, 90
- Int I/Q Skew Corrections RF BB Off softkey, 35
- Int softkeys
 - Int Doublet, 202
 - Int Free-Run, 202
 - Int Gated, 202
 - Int Phase Polarity Normal Invert, 24, 34
 - Int Triggered, 202
- integer response data, 11
- Intermod softkey, 1064
- Internal softkeys
 - Internal, 63, 176, 512
 - Internal 1, 184, 196
 - Internal 2, 184, 196
 - Internal Monitor, 190
 - Internal Square, 202

- Inverse Video Off On softkey, 87
- Inverted softkey, 517
- IP address, 75
- IP Address softkey, 76
- IQ Phase Normal Invert softkey, 767, 770
- IQ Polarity softkey, 388
- IS-2000 SR3 DS softkey
 - See CDMA ARB subsystem keys
 - See CDMA2000 ARB subsystem keys
 - See Dmodulation subsystem keys
 - See wideband CDMA ARB subsystem keys
- IS-95 Mod softkey
 - See CDMA ARB subsystem keys
 - See CDMA2000 ARB subsystem keys
 - See CDMA2000 BBG subsystem keys and fields
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GPS subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
 - See wideband CDMA ARB subsystem keys
 - See wideband CDMA base band subsystem keys and fields
- IS-95 Mod w/EQ softkey
 - See CDMA ARB subsystem keys
 - See CDMA2000 ARB subsystem keys
 - See CDMA2000 BBG subsystem keys and fields
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GPS subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
 - See wideband CDMA ARB subsystem keys
 - See wideband CDMA base band generator subsystem keys and fields
- IS-95 OQPSK softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- IS-95 QPSK softkey
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- IS-95 softkey
 - See CDMA ARB subsystem keys
 - See CDMA2000 ARB subsystem keys
 - See CDMA2000 BBG subsystem keys and fields
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys
 - See GPS subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
 - See wideband CDMA ARB subsystem keys
 - See wideband CDMA base band generator subsystem keys and fields
- IS-95 w/EQ softkey
 - See CDMA ARB subsystem keys
 - See CDMA2000 ARB subsystem keys
 - See CDMA2000 BBG subsystem keys and fields
 - See custom subsystem keys
 - See DECT subsystem keys
 - See Dmodulation subsystem keys
 - See EDGE subsystem keys

Index

IS-95 w/EQ softkey (*continued*)

See GPS subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA ARB subsystem keys

IS-97 Levels softkey, 229

J

jy, 935

L

LAN Config softkey, 75

Last Mkr Point softkey, 300, 302

Leap Seconds field, 501

Left Alternate softkey, 356

Left softkey, 1026

LF Out softkeys

LF Out Amplitude, 186

LF Out Off On, 190

LF Out Stop Freq, 186, 187, 193

LF Out Sweep Rate, 188

LF Out Sweep Time, 189

LF Out Tone 2 Ampl % of Peak, 187

LF Out Tone 2 Freq, 186, 187, 193

Link Down Up softkey, 347, 1074

Link Forward Reverse softkey, 247, 479

list data, 114

List softkey, 98, 124

list/sweep subsystem keys

Points, 57

Ampl, 49, 66

Ampl Start, 49, 67

Ampl Stop, 49, 68

Dwell Type List Step, 51

Freq, 42, 49

Freq & Ampl, 49

Freq Start, 44, 49

Freq Stop, 45, 49

Load List From Step Sweep, 55

Manual Mode Off On, 53

Manual Point, 52

list/sweep subsystem keys (*continued*)

Off, 42, 49, 66

Preset List, 56

Step Dwell, 56

Sweep Direction Down Up, 50

Sweep Retrace Off On, 54

Sweep Type List Step, 55

Load From Selected File softkey, 20, 123, 127, 336

Load List From Step Sweep softkey, 55

Load/Store softkey, 284

Logic Type softkey, 393

Long Code Mask field, 516

Long Code State field, 483, 516

Loop Back Test Type softkey, 393

Low Amplitude softkey, 430, 433

See sense subsystem keys

Low Capacity softkey, 589, 600

Low Capacity with Z field softkey, 589, 600

low frequency output subsystem keys

Bus, 189

DC, 189

Dual-Sine, 189

Ext, 189

Free Run, 189

Function Generator, 190

Internal Monitor, 190

LF Out Amplitude, 186

LF Out Off On, 190

LF Out Stop Freq, 186, 187, 193

LF Out Sweep Rate, 188

LF Out Sweep Time, 189

LF Out Tone 2 Ampl % of Peak, 187

LF Out Tone 2 Freq, 186, 187, 193

Noise, 189

Ramp, 189

Sine, 189

Square, 189

Swept-Sine, 189

Triangle, 189

Trigger Key, 189

LTM OFF field, 501

M

Manual Mode Off On softkey, 53

Manual Point softkey, 52

- Marker 1 2 3 4 softkey, [302](#)
- Marker 1 Polarity Neg Pos softkey, [212](#), [226](#), [260](#), [280](#), [475](#)
 - dual ARB subsystem, [308](#), [333](#), [475](#)
 - wideband CDMA ARB subsystem, [370](#)
- Marker 1 softkey, [209](#), [210](#), [222](#), [223](#), [224](#), [257](#), [258](#), [276](#), [277](#), [305](#), [329](#), [330](#), [331](#), [367](#), [368](#), [474](#), [475](#)
 - dual ARB subsystem, [306](#)
- Marker 2 Polarity Neg Pos softkey, [212](#), [226](#), [260](#), [280](#), [476](#)
 - dual ARB subsystem, [308](#), [333](#), [370](#), [475](#)
- Marker 2 softkey, [209](#), [210](#), [222](#), [223](#), [224](#), [257](#), [258](#), [276](#), [277](#), [305](#), [329](#), [330](#), [331](#), [367](#), [368](#), [474](#), [475](#)
 - dual ARB subsystem, [306](#)
- Marker 3 Polarity Neg Pos softkey, [212](#), [226](#), [260](#), [280](#), [476](#)
 - dual ARB subsystem, [308](#), [333](#), [475](#)
 - wideband CDMA ARB subsystem, [370](#)
- Marker 3 softkey, [209](#), [210](#), [222](#), [223](#), [224](#), [257](#), [258](#), [276](#), [277](#), [305](#), [329](#), [330](#), [331](#), [367](#), [368](#), [474](#), [475](#)
 - dual ARB subsystem, [306](#)
- Marker 4 Polarity Neg Pos softkey, [212](#), [226](#), [260](#), [280](#), [476](#)
 - dual ARB subsystem, [308](#), [333](#), [475](#)
 - wideband CDMA ARB subsystem, [370](#)
- Marker 4 softkey, [209](#), [210](#), [222](#), [223](#), [224](#), [257](#), [258](#), [276](#), [277](#), [305](#), [329](#), [330](#), [331](#), [367](#), [368](#), [474](#), [475](#)
 - dual ARB subsystem, [306](#)
- marker polarity, [212](#)
- Marker softkey, [300](#)
- Markers, [300](#)
- markers
 - alc hold
 - AWGN subsystem, [209](#)
 - CDMA ARB subsystem, [223](#)
 - CDMA2000 ARB subsystem, [257](#)
 - Dmodulation subsystem, [276](#)
 - dual ARB subsystem, [305](#)
 - multitone subsystem, [330](#), [331](#)
 - wideband CDMA ARB subsystem, [367](#)
 - alternate amplitude
 - AWGN subsystem, [209](#)
 - CDMA ARB subsystem, [222](#)
 - CDMA2000 ARB subsystem, [257](#)
 - Dmodulation subsystem, [276](#)
- markers (*continued*)
 - alternate amplitude
 - dual ARB subsystem, [305](#)
 - multitone subsystem, [329](#)
 - wideband CDMA ARB subsystem, [367](#)
 - clearing, [300](#)
 - marker polarity
 - CDMA ARB subsystem, [226](#)
 - CDMA2000 ARB subsystem, [260](#)
 - Dmodulation subsystem, [280](#)
 - dual ARB subsystem, [308](#), [475](#)
 - multitone subsystem, [333](#)
 - wideband CDMA ARB subsystem, [370](#)
 - polarity
 - AWGN subsystem, [212](#)
 - RF blanking/pulse
 - AWGN subsystem, [210](#)
 - CDMA ARB subsystem, [224](#)
 - CDMA2000 ARB subsystem, [258](#)
 - Demodulation subsystem, [277](#)
 - dual ARB subsystem, [306](#)
 - wideband CDMA ARB subsystem, [368](#)
 - setting, [302](#)
 - shifting points, [302](#)
- mass memory subsystem keys
 - Binary, [124](#)
 - Copy File, [124](#)
 - Delete All NVWFM Files, [125](#)
 - Delete All WFM Files, [125](#)
 - Delete All WFM1 Files, [125](#)
 - Delete File, [126](#)
 - List, [124](#)
 - Load From Selected File, [127](#)
 - Rename File, [127](#)
 - State, [124](#)
 - Store To File, [127](#)
 - User Flatness, [124](#)
- Max Input softkey, [1064](#)
- Max Power field, [1102](#)
- Max Pwr field, [1120](#), [1135](#)
- MCDMA softkey, [99](#)
- MDMOD softkey, [99](#)
- MDWCDMA softkey, [100](#)
- Measurement Mode BER% Search softkey, [450](#)
- Measurement Mode BLER% Search softkey, [436](#)

Index

- memory subsystem, [107](#), [109](#), [110](#)
- memory subsystem keys, [113](#), [115](#)
 - Add Comment To Seq[n] Reg[nn], [123](#)
 - All, [104](#), [122](#)
 - Binary, [94](#)
 - Bit, [94](#)
 - CDMA, [95](#)
 - Copy File, [105](#), [114](#)
 - Data PRAM, [112](#)
 - Delete All ARB CDMA Files, [118](#)
 - Delete All ARB DMOD Files, [118](#)
 - Delete All ARB DWCDMA Files, [119](#)
 - Delete All ARB FCDMA Files, [119](#)
 - Delete All ARB MCDMA Files, [120](#)
 - Delete All ARB MDWCDMA Files, [120](#)
 - Delete All ARB MTONE Files, [121](#)
 - Delete All ARB RCDMA Files, [121](#)
 - Delete All ARB UWCDMA Files, [122](#)
 - Delete All Binary Files, [118](#)
 - Delete All Bit Files, [118](#)
 - Delete All Files, [117](#)
 - Delete All FIR Files, [119](#)
 - Delete All FSK Files, [119](#)
 - Delete All I/Q Files, [119](#)
 - Delete All List Files, [120](#)
 - Delete All MDMOD Files, [120](#)
 - Delete All MFCDMA Files, [120](#)
 - Delete All SEQ Files, [121](#)
 - Delete All SHAPE Files, [121](#)
 - Delete All State Files, [121](#)
 - Delete All UFLT Files, [122](#)
 - Delete File, [122](#)
 - DMOD, [95](#)
 - DWCDMA, [96](#)
 - FCDMA, [96](#)
 - FIR, [97](#)
 - FSK, [97](#)
 - I/Q, [98](#)
 - List, [98](#)
 - Load From Selected File, [123](#)
 - MCDMA, [99](#)
 - MDMOD, [99](#)
 - MDWCDMA, [100](#)
 - MFCDMA, [100](#)
 - MTONE, [101](#)
- memory subsystem keys, [113](#), [115](#) (*continued*)
 - Oversample Ratio, [108](#)
 - RCDMA, [101](#)
 - Rename File, [123](#)
 - SEQ, [102](#)
 - SHAPE, [102](#)
 - State, [103](#)
 - Store To File, [123](#)
 - User Flatness, [103](#)
 - UWCDMA, [104](#)
- Message Data Raw Data (RPS11) softkey
 - See* wideband CDMA base band generator subsystem keys and fields
- Message Part field, [1118](#)
- Message Pulse (RPS22) softkey
 - See* wideband CDMA base band generator subsystem keys and fields
- Message Type field, [502](#)
- Message-Control Raw Data Clock (RPS12) softkey
 - See* wideband CDMA base band generator subsystem keys and fields
- Meter Address softkeys, [77](#)
- Meter Channel A B softkey, [77](#)
- Meter Timeout softkey, [78](#)
- MFCDMA softkey, [100](#)
- Min Power field, [1102](#)
- Mod Index softkey, [471](#)
- Mod On/Off hardkey, [129](#)
- Modulator Atten Manual Auto softkey, [33](#), [34](#), [207](#), [221](#), [245](#), [246](#), [274](#), [298](#), [299](#), [328](#), [346](#), [472](#), [473](#)
- Msg Ctrl softkey, [1107](#)
- Msg Data softkey, [1107](#)
- Msg Pwr field, [1118](#), [1133](#)
- MSGPS subsystem keys
 - GPS Ref (f0), [771](#)
 - GPS Ref Clk Ext Int, [771](#)
 - IQ Phase Normal Invert, [770](#)
 - Number of Satellites, [772](#)
 - Pause/Resume, [770](#)
 - Real-time MSGPS Off On, [772](#)
 - Restart, [771](#)
 - Scenario, [772](#)
 - Select Scenario, [772](#)
- MSK softkey
 - See* custom subsystem keys

MSK softkey (continued)

- See* DECT subsystem keys
- See* Dmodulation subsystem keys
- See* EDGE subsystem keys
- See* GSM subsystem keys
- See* NADC subsystem keys
- See* PDC subsystem keys
- See* PHS subsystem keys
- See* TETRA subsystem keys

MTONE softkey, [101](#)

multicarrier, [348](#)

Multicarrier Off On softkey, [228](#), [247](#), [282](#)

Multicarrier softkey, [348](#)

Multislot Off On softkey, [646](#), [793](#)

Multitone Off On softkey, [339](#)

multitone subsystem keys

2.100 MHz, [329](#)

40.000 MHz, [327](#), [329](#)

ARB Reference Ext Int, [333](#)

ARB Sample Clock, [335](#)

Clear Header, [326](#)

Freq Spacing, [336](#), [337](#)

Goto Row, [334](#)

I/Q Mod Filter Manual Auto, [329](#)

I/Q Output Filter Manual Auto, [327](#)

Initialize Phase Fixed Random, [338](#)

Load From Selected File, [336](#)

Marker 1, [329](#), [330](#), [331](#)

Marker 2, [329](#), [330](#), [331](#)

Marker 3, [329](#), [330](#), [331](#)

Marker 4, [329](#), [330](#), [331](#)

Modulator Atten Manual Auto, [328](#)

Multitone Off On, [339](#)

None, [329](#), [330](#), [331](#)

Number Of Tones, [336](#), [337](#)

Random Seed Fixed Random, [338](#)

Reference Freq, [333](#)

Save Setup To Header, [326](#)

Store To File, [336](#)

Through, [327](#), [329](#)

Toggle State, [334](#), [336](#)

Waveform Runtime Scaling, [335](#)

mV softkey, [170](#)

mVemf softkey, [170](#)

N

N Power field, [1078](#), [1108](#)

N5102A, [380](#)

See digital subsystem

N5102A Off On softkey, [395](#)

NADC Off On softkey, [907](#)

NADC softkey, [282](#), [283](#), [284](#)

NADC subsystem keys

128QAM, [890](#)

16 1's & 16 0's, [884](#), [893](#), [895](#), [897](#), [898](#)

16PSK, [890](#)

16QAM, [890](#)

256QAM, [890](#)

2-Lvl FSK, [890](#)

32 1's & 32 0's, [884](#), [893](#), [895](#), [897](#), [898](#)

32QAM, [890](#)

4 1's & 4 0's, [884](#), [893](#), [895](#), [897](#), [898](#)

4-Lvl FSK, [890](#)

4QAM, [890](#)

64 1's & 64 0's, [884](#), [893](#), [895](#), [897](#), [898](#)

64QAM, [890](#)

8 1's & 8 0's, [884](#), [893](#), [895](#), [897](#), [898](#)

8PSK, [890](#)

All Timeslots, [900](#)

APCO 25 C4FM, [887](#)

BBG Data Clock Ext Int, [874](#)

BBG Ref Ext Int, [886](#)

Begin Frame, [900](#)

Begin Timeslot #, [900](#), [901](#)

Bit Rate, [875](#)

BPSK, [890](#)

Bus, [892](#), [904](#)

CDL, [894](#)

CDVCC, [894](#), [897](#)

Continuous, [902](#)

D8PSK, [890](#)

Data Format Pattern Framed, [882](#)

Down Custom, [899](#)

Down TCH, [899](#)

Down TCH All, [899](#)

Ext, [884](#), [892](#), [893](#), [895](#), [897](#), [898](#), [904](#)

Ext BBG Ref Freq, [887](#)

Ext Data Clock Normal Symbol, [886](#)

Ext Delay Bits, [905](#)

Ext Delay Off On, [906](#)

Index

NADC subsystem keys (*continued*)

Ext Polarity Neg Pos, 906
Fall Delay, 877, 878
Fall Time, 878, 879
Filter Alpha, 874
Filter BbT, 875
FIX4, 884, 885, 893, 895, 896, 897, 898, 899
Frame Repeat Single Cont, 891
Free Run, 903
Freq Dev, 889
Gate Active Low High, 904
Gated, 902
Gaussian, 887
Gray Coded QPSK, 890
I/Q Scaling, 888
IS-95, 887
IS-95 Mod, 887
IS-95 Mod w/EQ, 887
IS-95 OQPSK, 890
IS-95 QPSK, 890
IS-95 w/EQ, 887
MSK, 890
NADC Off On, 907
Nyquist, 887
Optimize FIR For EVM ACP, 883
OQPSK, 890
 $\pi/4$ DQPSK, 890
Patt Trig In 1, 906
Patt Trig In 2, 906
Phase Dev, 889
PN11, 884, 893, 895, 897, 898
PN15, 884, 893, 895, 897, 898
PN20, 884, 893, 895, 897, 898
PN23, 884, 893, 895, 897, 898
PN9, 884, 893, 895, 897, 898
PN9 Mode Normal Quick, 876
Polarity Normal Invert, 891
QPSK, 890
Rate Full Half, 888
Recall Secondary Frame State, 891
Rectangle, 887
Reset & Run, 903
Restore NADC Factory Default, 885
Rise Delay, 880
Rise Time, 881, 882

NADC subsystem keys (*continued*)

Root Nyquist, 887
SACCH, 894, 898
Save Secondary Frame State, 892
Secondary Frame Off On, 892
Sine, 877, 883
Single, 902
Symbol Rate, 901
SYNC, 895, 898
Sync Out Offset, 900
Timeslot Ampl Main Delta, 896
Timeslot Off On, 896
Trigger & Run, 903
Trigger Key, 892, 904
UN3/4 GSM Gaussian, 887
Up Custom, 899
Up TCH, 899
Up TCH All, 899
User File, 877, 883, 884, 893, 895, 897, 898
User FIR, 887
User FSK, 889, 890
User I/Q, 890
nadc subsystem keys
PRAM Files, 884
Name and Store softkey, 313
Negate I softkey, 386
Negate Q softkey, 389
Network ID field, 502
No Limits softkey
See calculate subsystem keys
No Thresholds softkey
See sense subsystem keys
Noise Bandwidth Factor softkey, 308
Noise Off On softkey, 506, 518
Noise Seed Fixed Random softkey, 214
Noise Seed softkey, 469
Noise softkey, 175, 182, 189, 195
NONE (RPS0) softkey
See wideband CDMA base band generator
subsystem keys and fields
NONE softkey, 1163
None softkey, 161, 209, 210, 222, 223, 224, 257,
258, 276, 277, 305, 306, 329, 330, 331, 367,
368, 474, 475, 567, 1068, 1070, 1168, 1175
Normal All softkey, 656, 802

- Normal softkey, [517](#), [656](#), [802](#), [1026](#)
 - Num of Blk field, [1169](#), [1176](#)
 - Num of Pre field, [1119](#), [1134](#)
 - Number of AICH field, [1104](#)
 - Number of PRACH 80ms field, [1118](#)
 - Number of PRACH field, [1131](#), [1133](#)
 - Number of Preamble field, [1134](#)
 - Number of Satellites softkey, [772](#)
 - Number Of Tones softkey, [336](#), [337](#)
 - numeric boolean response data, [11](#)
 - Numeric Format, [387](#)
 - Numeric Format softkey, [387](#)
 - numeric SCPI parameter, [8](#)
 - numeric, extended SCPI parameter, [8](#)
 - Nyquist softkey
 - See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* CDMA2000 BBG subsystem keys and fields
 - See* custom subsystem keys
 - See* DECT subsystem keys
 - See* Dmodulation subsystem keys
 - See* EDGE subsystem keys
 - See* GPS subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
 - See* wideband CDMA ARB subsystem keys
 - See* wideband CDMA base band generator subsystem keys and fields
- 0**
- OCNS softkey, [357](#)
 - octal values, [18](#)
 - Off softkey, [24](#), [35](#), [42](#), [49](#), [66](#), [227](#), [261](#), [281](#), [311](#), [1130](#)
 - Off softkey, dual ARB trigger delay, [321](#)
 - Omitted softkey, [1060](#), [1157](#)
 - On softkey, [227](#), [261](#), [281](#), [311](#), [1130](#)
 - On/Off field, [1042](#), [1123](#)
 - OpenLoop Ant1 SCH TSTD OFF softkey, [1065](#)
 - OpenLoop Ant1 softkey, [1065](#)
 - OpenLoop Ant2 SCH TSTD OFF softkey, [1065](#)
 - OpenLoop Ant2 softkey, [1065](#)
 - Optimize ACP ADJ ALT softkey, [347](#), [362](#)
 - Optimize FIR For EVM ACP softkey, [1099](#)
 - See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* CDMA2000 BBG subsystem keys and fields
 - See* custom subsystem keys
 - See* DECT subsystem keys
 - See* Dmodulation subsystem keys
 - See* EDGE subsystem keys
 - See* GPS subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
 - See* wideband CDMA ARB subsystem keys
 - See* wideband CDMA base band generator subsystem keys and fields
 - options
 - 001/002
 - all subsystem, [204](#), [462](#)
 - custom subsystem, [548](#)
 - Dmodulation subsystem, [270](#)
 - dual ARB subsystem, [294](#)
 - multitone subsystem, [326](#)
 - 400
 - wideband CDMA ARB subsystem, [340](#)
 - wideband CDMA base band generator subsystem, [1020](#)
 - 401
 - CDMA ARB subsystem, [215](#)
 - CDMA2000 ARB subsystem, [240](#)
 - CDMA2000 BBG subsystem, [479](#)
 - 402
 - DECT subsystem, [573](#)
 - EDGE subsystem, [622](#)
 - GSM subsystem, [773](#)
 - NADC subsystem, [874](#)
 - PDC subsystem, [908](#)
 - PHS subsystem, [941](#)
 - TETRA subsystem, [977](#)
 - 403
 - AWGN real-time subsystem, [463](#)
 - AWGN subsystem, [205](#)

Index

options (*continued*)

406

 bluetooth subsystem, [464](#)

409

 GPS subsystem, [763](#)

424

 GPS subsystem, [763](#)

 MSGPS subsystem, [770](#)

UN7/300

 calculate subsystem, [398](#)

 data subsystem, [408](#)

 input subsystem, [416](#), [422](#)

 sense subsystem, [425](#)

Options Info softkey, [83](#)

OQPSK softkey

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

Output Blanking Off On Auto softkey, [128](#)

output subsystem keys

 Mod On/Off, [129](#)

 Output Blanking Off On Auto, [128](#)

 RF On/Off, [129](#)

Oversample Ratio softkey, [108](#), [226](#)

Overwrite softkey, [161](#)

P

P Code Pwr softkey, [767](#)

P Rev field, [503](#)

P Rev Min field, [501](#)

P softkey, [591](#)

$\pi/4$ DQPSK softkey

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

$\pi/4$ DQPSK softkey (*continued*)

See PHS subsystem keys

See TETRA subsystem keys

Packet (DH1) softkey, [476](#)

Paging Indicator field, [510](#), [1046](#)

Paging softkey, [229](#)

parameter types. *See* SCPI commands parameter types

Pass Amplitude softkey, [430](#), [434](#)

See sense subsystem keys

Pass Through Preset softkey, [395](#)

Pass/Fail Limits softkey, [406](#)

Pass/Fail Off On softkey, [406](#)

paths, SCPI command tree, [7](#)

Patt Trig In 1 softkey

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See dual ARB subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA ARB subsystem keys

Patt Trig In 2 softkey

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See dual ARB subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA ARB subsystem keys

Pattern trigger in 1 field, [1144](#)

- Pattern trigger in 2 field, [1145](#)
- Pause/Resume softkey, [770](#)
- PCCPCH + SCH + 3 DPCH softkey, [348](#), [353](#)
- PCCPCH + SCH +1 DPCH softkey, [348](#), [353](#)
- PCCPCH + SCH softkey, [348](#), [353](#)
- P-CCPCH data (DRPS39) softkey, [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
- P-CCPCH data-clk (DRPS38) softkey, [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
- PCCPCH softkey, [1022](#), [1023](#)
- PDC Off On softkey, [940](#)
- PDC softkey, [282](#), [283](#), [284](#)
- PDC subsystem keys
 - 128QAM, [923](#)
 - 16 1's & 16 0's, [917](#), [926](#), [927](#), [929](#), [931](#)
 - 16PSK, [923](#)
 - 16QAM, [923](#)
 - 256QAM, [923](#)
 - 2-Lvl FSK, [923](#)
 - 32 1's & 32 0's, [917](#), [926](#), [927](#), [929](#), [931](#)
 - 32QAM, [923](#)
 - 4 1's & 4 0's, [917](#), [926](#), [927](#), [929](#), [931](#)
 - 4-Lvl FSK, [923](#)
 - 4QAM, [923](#)
 - 64 1's & 64 0's, [917](#), [926](#), [927](#), [929](#), [931](#)
 - 64QAM, [923](#)
 - 8 1's & 8 0's, [917](#), [926](#), [927](#), [929](#), [931](#)
 - 8PSK, [923](#)
 - All Timeslots, [933](#)
 - APCO 25 C4FM, [920](#)
 - BBG Ref Ext Int, [919](#)
 - Begin Frame, [933](#)
 - Begin Timeslot #, [933](#), [934](#)
 - Bit Rate, [909](#)
 - BPSK, [923](#)
 - Bus, [925](#), [937](#)
 - CC, [926](#), [930](#), [932](#)
 - Continuous, [936](#)
 - D8PSK, [923](#)
 - Data Format Pattern Framed, [916](#)
 - Down Custom, [933](#)
 - Down TCH, [933](#)
 - Down TCH All, [933](#)
 - Ext, [917](#), [925](#), [926](#), [927](#), [929](#), [931](#), [937](#)
 - Ext BBG Ref Freq, [920](#)
- PDC subsystem keys (*continued*)
 - Ext Data Clock Ext Int, [908](#)
 - Ext Data Clock Normal Symbol, [919](#)
 - Ext Delay Bits, [938](#)
 - Ext Delay Off On, [939](#)
 - Ext Polarity Neg Pos, [939](#)
 - Fall Delay, [911](#), [912](#)
 - Fall Time, [911](#), [913](#)
 - Filter Alpha, [908](#)
 - Filter BbT, [909](#)
 - FIX4, [917](#), [918](#), [926](#), [927](#), [928](#), [929](#), [931](#)
 - Free Run, [936](#)
 - Freq Dev, [922](#)
 - Gate Active Low High, [937](#)
 - Gated, [936](#)
 - Gaussian, [920](#)
 - Gray Coded QPSK, [923](#)
 - I/Q Scaling, [921](#)
 - IS-95, [920](#)
 - IS-95 Mod, [920](#)
 - IS-95 Mod w/EQ, [920](#)
 - IS-95 OQPSK, [923](#)
 - IS-95 QPSK, [923](#)
 - IS-95 w/EQ, [920](#)
 - MSK, [923](#)
 - Nyquist, [920](#)
 - Optimize FIR For EVM ACP, [917](#)
 - OQPSK, [923](#)
 - $\pi/4$ DQPSK, [923](#)
 - Patt Trig In 1, [940](#)
 - Patt Trig In 2, [940](#)
 - PDC Off On, [940](#)
 - Phase Dev, [922](#)
 - Phase Polarity Normal Invert, [924](#)
 - PN11, [917](#), [927](#), [929](#), [931](#)
 - PN15, [917](#), [926](#), [927](#), [929](#), [931](#)
 - PN20, [917](#), [927](#), [929](#), [931](#)
 - PN23, [917](#), [927](#), [929](#), [931](#)
 - PN9, [917](#), [926](#), [927](#), [929](#), [931](#)
 - PN9 Mode Normal Quick, [910](#)
 - QPSK, [923](#)
 - Rate Full Half, [921](#)
 - Recall Secondary Frame State, [924](#)
 - Rectangle, [920](#)
 - Reset & Run, [936](#)

PDC subsystem keys (*continued*)

- Restore PDC Factory Default, [918](#)
 - Rise Delay, [913](#), [914](#)
 - Rise Time, [915](#)
 - Root Nyquist, [920](#)
 - SACCH, [927](#), [930](#), [932](#)
 - Save Secondary Frame State, [924](#)
 - Secondary Frame Off On, [925](#)
 - Sine, [916](#)
 - Single, [936](#)
 - SW, [927](#), [930](#), [932](#)
 - Symbol Rate, [934](#)
 - Sync Out Offset, [933](#)
 - Timeslot Ampl Main Delta, [928](#)
 - Timeslot Off On, [929](#)
 - Trigger & Run, [936](#)
 - Trigger Key, [925](#), [937](#)
 - UN3/4 GSM Gaussian, [920](#)
 - Up Custom, [933](#)
 - Up TCH, [933](#)
 - Up TCH All, [933](#)
 - Up VOX, [933](#)
 - User File, [916](#), [917](#), [926](#), [927](#), [929](#), [931](#)
 - User FIR, [920](#)
 - User FSK, [923](#)
 - User I/Q, [923](#)
- pdcc subsystem keys
- PRAM Files, [918](#)
- Performance Req softkey, [1064](#)
- Permuted ESN field, [486](#), [496](#)
- Phase Dev softkey
- See* custom subsystem keys
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
- phase modulation subsystem keys
- ΦM Sweep Time softkey, [195](#)
 - FM ΦM Normal High BW softkey, [192](#)
 - ΦM Dev Couple Off On, [197](#)
 - ΦM Dev softkey, [197](#)
 - ΦM Off On softkey, [196](#)

πηασε μοδυλατιον συβσψστεμ κευσ
(*continued*)

- ΦM Path 1 2, [191](#)
 - ΦM Tone 2 Ampl Percent of Peak, [194](#)
 - ΦM Tone 2 Rate, [194](#)
 - Bus, [195](#)
 - Dual-Sine, [195](#)
 - Ext, [195](#)
 - Ext Coupling DC AC, [193](#)
 - Ext1, [196](#)
 - Ext2, [196](#)
 - Free Run, [195](#)
 - Incr Set, [192](#), [198](#)
 - Internal 1, [196](#)
 - Internal 2, [196](#)
 - Noise, [195](#)
 - Ramp, [195](#)
 - Sine, [195](#)
 - Square, [195](#)
 - Swept-Sine, [195](#)
 - Triangle, [195](#)
 - Trigger Key, [195](#)
- Phase Polarity field, [509](#)
- Phase Polarity Normal Invert softkey
- See* custom subsystem keys
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
 - See* wideband CDMA base band generator subsystem keys and fields
- Phase Polarity Normal Inverted softkey, [1074](#)
- Phase Ref Set softkey, [47](#)
- PHS Off On softkey, [976](#)
- PHS softkey, [282](#), [283](#), [284](#)
- PHS subsystem keys
- 128QAM, [962](#)
 - 16 1's & 16 0's, [951](#), [953](#), [956](#), [971](#), [975](#)
 - 16-Lvl FSK, [962](#)
 - 16PSK, [962](#)
 - 16QAM, [962](#)
 - 256QAM, [962](#)
 - 2-Lvl FSK, [962](#)

PHS subsystem keys (*continued*)

32 1's & 32 0's, 951, 953, 956, 971, 975
32QAM, 962
4 1's & 4 0's, 951, 953, 956, 971, 975
4-Lvl FSK, 962
4QAM, 962
64 1's & 64 0's, 951, 953, 956, 971, 975
64QAM, 962
8 1's & 8 0's, 951, 953, 956, 971, 975
8-Lvl FSK, 962
8PSK, 962
All Timeslots, 964
APCO 25 C4FM, 959
BBG Data Clock Ext Int, 941
BBG Ref Ext Int, 958
Begin Frame, 964
Begin Timeslot #, 964, 965
Bit Rate, 942
BPSK, 962
Bus, 963, 970
C4FM, 962
Continuous, 966
CSID, 954, 972
Custom, 957
D8PSK, 962
Data Format Pattern Framed, 950
Ext, 951, 953, 956, 963, 970, 971, 975
Ext BBG Ref Freq, 958
Ext Data Clock Normal Symbol, 957
Ext Delay Bits, 968
Ext Delay Off On, 969
Ext Polarity Neg Pos, 969
Fall Delay, 945, 946
Fall Time, 945, 947
Filter Alpha, 941
Filter BbT, 942
FIX4, 951, 952, 953, 956, 971, 972, 975
Free Run, 967
Gate Active Low High, 968
Gated, 966
Gaussian, 959
Gray Coded QPSK, 962
I/Q Scaling, 960
IDLE, 954, 973
IS-95, 959

PHS subsystem keys (*continued*)

IS-95 Mod, 959
IS-95 Mod w/EQ, 959
IS-95 OQPSK, 962
IS-95 QPSK, 962
IS-95 w/EQ, 959
MSK, 962
Nyquist, 959
Optimize FIR For EVM ACP, 951
OQPSK, 962
 $\pi/4$ DQPSK, 962
Patt Trig In 1, 969
Patt Trig In 2, 969
Phase Dev, 960, 961
Phase Polarity Normal Invert, 962
PHS Off On, 976
PN11, 951, 953, 956, 971, 975
PN15, 951, 953, 956, 971, 975
PN20, 951, 953, 956, 971, 975
PN23, 951, 953, 956, 971, 975
PN9, 951, 953, 956, 971, 975
PN9 Mode Normal Quick, 943
PSID, 954, 973
QPSK, 962
Recall Secondary Frame State, 962
Rectangle, 959
Reset & Run, 967
Restore PHS Factory Default, 952
Rise Delay, 947, 948
Rise Time, 949
Root Nyquist, 959
SA, 955, 974
Save Secondary Frame State, 963
Scramble Off On, 944
Scramble Seed, 944
Secondary Frame Off On, 963
Sine, 950
Single, 966
Symbol Rate, 965
SYNC, 957
Sync Out Offset, 964
TCH, 957
TCH All, 957
Timeslot Ampl Main Delta, 953, 972
Timeslot Off On, 955, 974

Index

PHS subsystem keys (*continued*)

- Timeslot Type, [975](#)
 - Trigger & Run, [967](#)
 - Trigger Key, [963](#), [970](#)
 - UN3/4 GSM Gaussian, [959](#)
 - User File, [950](#), [951](#), [953](#), [956](#), [971](#), [975](#)
 - User FIR, [959](#)
 - User FSK, [961](#), [962](#)
 - User I/Q, [961](#), [962](#)
 - UW, [955](#), [956](#), [973](#), [974](#)
- ### phs subsystem keys
- PRAM Files, [952](#)
- ### PI Bits field, [1046](#)
- ### PICH 10ms FramePulse (DRPS37) softkey, [1050](#), [1052](#), [1053](#), [1054](#), [1055](#)
- ### PICH data (DRPS35) softkey, [1050](#), [1052](#), [1053](#), [1054](#), [1055](#)
- ### PICH data-clk (DRPS34) softkey, [1050](#), [1052](#), [1053](#), [1054](#), [1055](#)
- ### PICH softkey, [357](#), [1022](#), [1023](#)
- ### PICH TimeSlot Pulse (DRPS36) softkey, [1050](#), [1052](#), [1053](#), [1054](#), [1055](#)
- ### Pilot softkey, [228](#), [229](#), [231](#), [247](#), [254](#)
- ### Playback Ratio field, [1026](#)
- ### PN Offset field, [512](#)
- ### PN Offset softkey, [252](#), [255](#)
- ### PN11 softkey
- See* custom subsystem keys
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* sense subsystem keys
 - See* TETRA subsystem keys
- ### PN15 softkey
- See* CDMA2000 BBG subsystem keys and fields
 - See* custom subsystem keys
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* GPS subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys

PN15 softkey (*continued*)

- See* PHS subsystem keys
 - See* sense subsystem keys
 - See* TETRA subsystem keys
 - See* wideband CDMA base band generator subsystem keys and fields
- ### PN20 softkey
- See* custom subsystem keys
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* sense subsystem keys
 - See* TETRA subsystem keys
- ### PN23 softkey
- See* custom subsystem keys
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* sense subsystem keys
 - See* TETRA subsystem keys
- ### PN9 Mode Normal Quick softkey
- See* DECT subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
- ### PN9 Mode Preset softkey, [159](#)
- ### PN9 softkey
- See* CDMA2000 BBG subsystem keys and fields
 - See* custom subsystem keys
 - See* data subsystem keys
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* GPS subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys

- PN9 softkey (continued)*
 See sense subsystem keys
 See TETRA subsystem keys
 See wideband CDMA base band generator
 subsystem keys and fields
- polarity
 awgn subsystem, 212
 markers
 cdma arb subsystem, 226
 cdma2000 arb subsystem, 260
 dmodulation subsystem, 280
 dual ARB subsystem, 308, 475
 multitone subsystem, 333
 wideband CDMA ARB subsystem, 370
- polarity markers
 awgn subsystem, 212
- Polarity Normal Invert softkey, 891
- Port Config softkey, 394
- Power Control Signal Polarity Neg Pos softkey, 1104
- Power field
 See CDMA2000 BBG subsystem keys and fields
 See wideband CDMA baseband generator
 subsystem keys and fields
- Power Hold Off On softkey, 1101
- Power Meter softkey, 78
- Power Mode Norm TPC softkey, 1104
- Power On Last Preset softkey, 157
- Power Search Manual Auto softkey, 60, 62
- Power Search Reference Fixed Mod softkey, 61
- Power softkey, 364
- power subsystem keys
 ALC Off On, 62
 Alt Amp Delta, 63
 Alt Ampl Off On, 64
 Ampl, 49, 66
 Ampl Offset, 68
 Ampl Ref Off On, 67
 Ampl Ref Set, 66
 Ampl Start, 49, 67
 Ampl Stop, 49, 68
 Amplitude, 66, 69
 Atten Hold Off On, 65
 Auto, 58, 59
 Do Power Search, 60, 62
- power subsystem keys (*continued*)
 Ext Detector, 63
 Internal, 63
 Off, 49, 66
 Power Search Manual Auto, 60, 62
 Power Search Reference Fixed Mod, 61
 Set ALC Level, 60
 Set Atten, 65
 Source Module, 63
 Span Type User Full softkey, 62
 Start Frequency, 61
 step, 69
 Stop Frequency, 61
- PPCCPCH softkey, 357, 358
- Pp-m field, 1120, 1136
- PRACH Mode Single Multi softkey, 1117
- PRACH Power Setup Mode Pp-m Total softkey, 1124
- PRACH Processing (RPS19) softkey
 See wideband CDMA base band generator
 subsystem keys and fields
- PRACH Scrambling Code field, 1125
- PRACH softkey, 1100
- PRACH Trigger Polarity Neg Pos softkey, 1129
- PRACH Trigger softkey, 1129
- PRACH Trigger Source Immedi Trigger softkey, 1129
- PRAM
 downloads, 112
 list, 113
- PRAM DATA BLOCK, 114
- pram files
 CUSTOM subsystem keys, 558
 DECT subsystem keys, 583
 EDGE subsystem keys, 631
 GSM subsystem keys, 783
 NADC subsystem keys, 884
 PDC subsystem keys, 918
 PHS subsystem keys, 952
 TETRA subsystem keys, 988
- PRAM LIST, 114
- PRAM?, 114
- PRAT field, 503
- Pre Sig field, 1121
- Preamble power average field, 1123

Index

Preamble Pulse (RPS21) softkey
 See wideband CDMA base band generator
 subsystem keys and fields

Preamble Raw Data (RPS15) softkey
 See wideband CDMA base band generator
 subsystem keys and fields

Preamble Raw Data Clock (RPS16) softkey
 See wideband CDMA base band generator
 subsystem keys and fields

Preamble softkey, 1107

precise talking and forgiving listening, 7

Preset hardkey, 158

Preset List softkey, 21, 56

Preset Normal User softkey, 160

programming guide, lxxiii

PSCH softkey, 357

PSCH State field, 1048

PSID softkey, 954, 973

pulse modulation subsystem keys

- Ext Pulse, 202
- Int Doublet, 202
- Int Free-Run, 202
- Int Gated, 202
- Int Triggered, 202
- Internal Square, 202
- Pulse Off On, 202
- Pulse Period, 200
- Pulse Rate, 199
- Pulse Width, 201

Pulse softkeys

- Pulse Off On, 202
- Pulse Period, 200
- Pulse Rate, 199
- Pulse Width, 201

Pulse/RF blanking, 306

pulse/RF blanking markers

- awgn subsystem, 210
- cdma arb subsystem, 224
- cdma2000 arb, 258
- dmodulation, 277
- dual ARB subsystem, 306
- wideband cdma arb, 368

Puncture fields, 1169, 1176

Puncture softkey, 1058

PwrOffs field, 1057, 1154

PWT softkey, 282, 283, 284

Q

Q Gain softkey, 388

Q Offset softkey, 30, 390

QOF field, 487, 497

QPSK softkey

- See* custom subsystem keys
- See* DECT subsystem keys
- See* Dmodulation subsystem keys
- See* EDGE subsystem keys
- See* GSM subsystem keys
- See* NADC subsystem keys
- See* PDC subsystem keys
- See* PHS subsystem keys
- See* TETRA subsystem keys

Quadrature Angle Adjustment softkey, 25, 30

Quarter softkey, 529, 534

quotes, SCPI command use of, 17

R

RACH TrCH softkey, 1107

Radio Config field

- See* CDMA2000 BBG subsystem keys and fields

Radio Config softkey, 253

RadioConfig 1/2 Access softkey, 479

RadioConfig 1/2 Traffic softkey, 479

RadioConfig 3/4 Common Control softkey, 479

RadioConfig 3/4 Enhanced Access softkey, 479

RadioConfig 3/4 Traffic softkey, 479

Ramp field, 487

Ramp softkey, 175, 182, 189, 195

Ramp Step field, 1120, 1135

Ramp Time field, 487

Random Seed Fixed Random softkey, 338

Random softkey, 356, 364

Ranging Code C/A P C/A+P softkey, 767

Rate Full Half softkey, 888, 921

Rate Match Attr field, 1073, 1169, 1176

Rate softkey, 252, 255

RCDMA softkey, 101

real response data, 10

Real-time AWGN Off On softkey, 463

- real-time AWGN subsystem keys
 - Bandwidth, [463](#)
 - Real-time AWGN Off On, [463](#)
- Real-time GPS Off On softkey, [769](#)
- Real-time MSGPS Off On softkey, [772](#)
- Real-time Noise softkey, [310](#)
- RECALL Reg softkey, [90](#)
- Recall Secondary Frame State softkey
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
- Rectangle softkey
 - See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* CDMA2000 BBG subsystem keys and fields
 - See* custom subsystem keys
 - See* DECT subsystem keys
 - See* Dmodulation subsystem keys
 - See* EDGE subsystem keys
 - See* GPS subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
 - See* wideband CDMA ARB subsystem keys
 - See* wideband CDMA base band generator subsystem keys and fields
- Ref Data Rate field, [1076](#), [1106](#)
- Ref Oscillator Source Auto Off On softkey, [48](#)
- Ref Sensitivity softkey, [1064](#)
- Reference Freq softkey, [477](#)
 - See* AWGN subsystem keys
 - See* bluetooth subsystem keys
 - See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* Dmodulation subsystem keys
 - See* dual ARB subsystem keys
 - See* multitone subsystem keys
 - See* wideband CDMA ARB subsystem keys
- Reference Frequency softkey, [382](#)
- Reference Out softkey, [413](#)
- references, [lxxiii](#)
- Rename File, [123](#)
- Rename File softkey, [127](#)
- Reserved field, [503](#)
- Reset & Run softkey
 - See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* custom subsystem keys
 - See* DECT subsystem keys
 - See* Dmodulation subsystem keys
 - See* dual ARB subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
 - See* wideband CDMA ARB subsystem keys
- Reset RS-232 softkey, [79](#)
- Reset to Initial Power softkey, [1103](#)
- Resolution softkey, [418](#)
- resolving error messages/setting conflicts, [670](#), [814](#)
- response data types. *See* SCPI commands response types
- Restart softkey, [771](#)
- Restore DECT Factory Default softkey, [583](#)
- Restore EDGE Factory Default softkey, [632](#)
- Restore Factory Default softkey, [783](#)
- Restore NADC Factory Default softkey, [885](#)
- Restore PDC Factory Default softkey, [918](#)
- Restore PHS Factory Default softkey, [952](#)
- Restore Sys Defaults softkey, [159](#)
- Restore TETRA Factory Default softkey, [989](#)
- Resync Limits softkey, [456](#)
- Retrigger Mode Off On softkey, [371](#)
- Reverse softkey, [228](#)
- Revert to Default Cal Settings softkey, [73](#)
- rf blanking, [306](#)
- RF blanking/pulse markers
 - awgn subsystem, [210](#)
 - cdma arb subsystem, [224](#)
 - cdma2000 arb subsystem, [258](#)
 - dmodulation subsystem, [277](#)
 - dual ARB subsystem, [306](#)

Index

RF blanking/pulse markers (*continued*)

wideband cdma arb subsystem, [368](#)

RF On/Off hardkey, [129](#)

Right Alternate softkey, [356](#)

Right softkey, [1026](#)

Rise Delay softkey

See custom subsystem keys

See DECT subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

Rise Time softkey

See custom subsystem keys

See DECT subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

Rising softkey, [547](#)

RMC 144 kbps (25.141) softkey, [1137](#)

RMC 384 kbps (25.141) softkey, [1137](#)

RMC 64 kbps (25.141) softkey, [1137](#)

RMC122 kbps (25.141) softkey, [1137](#)

RMS header info, [295](#)

Root Nyquist softkey

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See CDMA2000 BBG subsystem keys and fields

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See EDGE subsystem keys

See GPS subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA ARB subsystem keys

Root Nyquist softkey (continued)

See wideband CDMA base band generator

subsystem keys and fields

rotate markers, [302](#)

Rotation softkey, [390](#)

route subsystem keys

Burst Gate In Polarity Neg Pos, [130](#), [131](#)

Data Clock Out Neg Pos, [133](#)

Data Clock Polarity Neg Pos, [130](#), [132](#), [134](#)

Data Out Polarity Neg Pos, [133](#), [135](#)

Data Polarity Neg Pos, [131](#), [132](#)

DATA/CLK/SYNC Rear Outputs Off On, [135](#)

Symbol Sync Out Polarity Neg Pos, [134](#), [135](#)

Symbol Sync Polarity Neg Pos, [131](#), [132](#)

RS-232 Baud Rate softkey, [79](#)

RS-232 ECHO Off On softkeys, [79](#)

RS-232 Timeout softkeys, [80](#)

Run Complete Self Test softkey, [92](#)

runtime scaling, [312](#), [335](#)

S

S softkey, [645](#), [800](#)

See DECT subsystem keys

SA softkey, [955](#), [974](#)

SACCH softkey, [894](#), [898](#), [927](#), [930](#), [932](#)

Samples softkey, dual ARB trigger delay, [321](#)

Sanitize softkey, [161](#)

Satellite ID softkey, [769](#)

Save Reg softkey, [91](#)

Save Secondary Frame State softkey

See DECT subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

Save Seq[n] Reg[nn] softkey, [91](#)

Save Setup To Header softkey, [206](#), [220](#), [245](#), [273](#),
[297](#), [326](#), [344](#), [467](#)

Save User Preset softkey, [160](#)

Scale to 0dB softkey

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See CDMA2000 BBG subsystem keys and fields

Scale to 0dB softkey (continued)

See wideband CDMA ARB subsystem keys

See wideband CDMA base band generator
subsystem keys and fields

Scale Waveform Data softkey, 312

scaling

during playback, 312, 335

waveform files, 312

Scaling softkey, 312, 391

SCCPCH softkey, 357, 358

Scenario softkey, 772

SCFN field, 1062, 1159

SCH slot-pulse (DRPS10) softkey, 1050, 1052,
1053, 1054, 1055

SCPI

errors, 155

SCPI command subsystems

3GPP W-CDMA HSPA, 668

all, 462

amplitude modulation, 172

AWGN, 205

AWGN real-time, 463

bluetooth, 464

calculate, 398

calibration, 72

CDMA ARB, 215

CDMA2000 ARB, 240

CDMA2000 BBG, 479

communication, 75

correction, 20

custom, 548

data, 408

DECT, 573

diagnostic, 81

digital, 380

digital modulation, 22

display, 85

Dmodulation, 270

Dual ARB, 294

E4438C, 204

EDGE, 622

frequency, 38

frequency modulation, 179

GPS subsystem, 763

GSM, 773

SCPI command subsystems (*continued*)

HSDPA over W-CDMA, 812

IEEE 488.2 common commands, 88

input, 416, 422

list/sweep, 49

low frequency output, 186

mass memory, 124

memory, 94

MSGPS subsystem, 770

multitone, 326

N5102A, 380

NADC, 874

output, 128

PDC, 908

phase modulation, 191

PHS, 941

power, 58

pulse modulation, 199

route, 130

sense, 425

status, 136

system, 154

TETRA, 977

trigger, 166

unit, 170

wideband CDMA ARB, 340

wideband CDMA base band generator, 1020

SCPI commands

command tree paths, 7

parameter and response types, 7

parameter types

boolean, 10

discrete, 9

extended numeric, 8

numeric, 8

string, 10

response data types

discrete, 11

integer, 11

numeric boolean, 11

real, 10

string, 11

root command, 6

SCPI reference, lxxiii

SCPI softkey, 156, 158

Index

- Scramble Code softkey, 356, 362, 364
- Scramble Off On softkey, 944, 980
- Scramble Offset softkey, 356, 364
- Scramble Seed softkey, 944, 980
- Scrambling Code field, 1055, 1056, 1151
- Screen Saver Delay
 - 1 hr softkey, 163
- Screen Saver Mode softkeys, 164
- Screen Saver Off On softkeys, 164
- Second DPDCH I Q softkey, 362
- Secondary Frame Off On softkey
 - See DECT subsystem keys
 - See EDGE subsystem keys
 - See GSM subsystem keys
 - See NADC subsystem keys
 - See PDC subsystem keys
 - See PHS subsystem keys
 - See TETRA subsystem keys
- secure wave directory, 116
- security functions
 - erase, 161
 - none, 161
 - overwrite, 161, 163
 - sanitize, 161, 163
 - secure display, 160
 - secure mode, 162
- segment advance
 - trigger response, 318
- Segment Advance softkey, 315
- Select File softkey, 249, 282
- Select Scenario softkey, 772
- Select Seq softkey, 90
- Select Waveform softkey, 323, 324
- sense subsystem keys
 - Adjust Gain, 437
 - Aux, 438, 454, 460
 - Aux I/O Trigger Polarity Pos Neg, 460
 - BER Mode Off On, 425, 429, 448
 - BERT Off On, 457
 - BERT Resync Off On, 457
 - Bit Count, 439, 441
 - Bit Delay Off On, 459
 - Block Count, 428, 430, 432, 444, 448
 - Block Erasure, 426, 431, 444, 445, 446, 448, 449
 - Bus, 438, 454, 460
 - sense subsystem keys (*continued*)
 - Class Ib Bit Error, 451, 452
 - Class II Bit Error, 452
 - Cycle Count, 459
 - Delay Bits, 459
 - EDGE BERT Off On, 442
 - Error Count, 442, 457
 - Exceeds Any Thresholds, 452
 - Ext, 438, 454, 460
 - Ext Frame Trigger Delay, 427
 - External Frame Polarity Net Pos, 427
 - Frame Count, 447, 450
 - Frame Erasure, 452
 - Frame Trigger Source Int Ext, 428
 - GSM BERT Off On, 455
 - High Amplitude, 429, 433, 440
 - Immediate, 438, 454, 460
 - Initial Bit Count, 441
 - Initial Block Count, 431, 434
 - Initial Frame Count, 451
 - Low Amplitude, 430, 433, 440, 447
 - Measurement Mode BER% Search, 450
 - Measurement Mode BLER% Search, 436
 - No Thresholds, 426, 431, 446, 449, 452, 458
 - Pass Amplitude, 430, 434, 441
 - PN11, 456
 - PN15, 456
 - PN20, 456
 - PN23, 456
 - PN9, 456
 - Resync Limits, 456
 - Spcl Pattern 0's 1's, 455
 - Spcl Pattern Ignore Off On, 456
 - Spectrum Invert Off On, 437, 451
 - Stop Measurement, 435, 449
 - Sync Source BCH PDCH, 438
 - Sync Source BCH TCH, 454
 - Synchronize to BCH/PDCH, 437
 - Synchronize to BCH/TCH, 453
 - Target BER %, 429, 432
 - Timeslot, 436, 449
 - Total Bits, 458
 - Trigger Key, 438, 454, 460
 - Uplink Timing Advance, 439, 455
 - SEQ softkey, 102

- sequence, creating, [313](#)
- service
 - guide, [lxxiii](#)
- Set ALC Level softkey, [60](#)
- Set Atten softkey, [65](#)
- Set Marker Off All Points softkey, [301](#)
- Set Marker Off Range Of Points softkey, [300](#)
- Set Marker On Range Of Points softkey, [302](#)
- setting conflicts, resolving, [670](#), [814](#)
- setting markers, [302](#)
- setup sweep, [49](#)
- SF/2 softkey, [1155](#)
- SF2 softkey, [1058](#)
- SFN reset-signal (DRPS5) softkey, [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
- SFN RST Polarity softkey, [1151](#)
- SFN-CFN Frame Offset softkey, [1100](#)
- SHAPE softkey, [102](#)
- shift markers, [302](#)
- Signal Type softkey, [392](#)
- Signature field, [1136](#)
- Sine softkey
 - See* amplitude modulation subsystem keys
 - See* DECT subsystem keys
 - See* EDGE subsystem keys
 - See* frequency modulation subsystem keys
 - See* GSM subsystem keys
 - See* low frequency output subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* phase modulation subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
- single
 - segment advance, [318](#)
- Single softkey
 - dual ARB subsystem keys, [318](#)
 - See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* custom subsystem keys
 - See* DECT subsystem keys
 - See* Dmodulation subsystem keys
 - See* dual ARB subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - Single softkey (continued)*
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
 - See* wideband CDMA ARB subsystem keys
- Single Sweep softkey, [167](#)
- skew, [31](#), [32](#)
- skew, quadrature (angle) adjustment
 - BBG, [25](#)
 - RF path, [30](#)
- Slot Format field, [1027](#), [1034](#), [1083](#), [1094](#), [1111](#),
[1116](#)
- softkey, [123](#)
- software options, [82](#)
- Source Module softkey, [63](#)
- Span Type User Full softkey, [62](#)
- Spcl Pattern 0's 1's softkey, [455](#)
- Spcl Pattern Ignore Off On softkey, [456](#)
- Spectrum Invert Off On softkey
 - See* sense subsystem keys
- Spread Rate 1 softkey, [247](#), [254](#), [262](#)
- Spread Rate 3, [254](#)
- Spread Rate 3 softkey, [247](#), [262](#)
- Spread Rate field, [511](#)
- Spreading Type Direct Mcarrier, [247](#)
- Spreading Type Direct Mcarrier softkey, [263](#)
- Spurious Response softkey, [1064](#)
- Square softkey, [175](#), [182](#), [189](#), [195](#)
- square wave pulse rate
 - internally generated, [199](#)
- SR1 9 Channel softkey, [249](#)
- SR1 Pilot softkey, [249](#)
- SR3 Direct 9 Channel softkey, [249](#)
- SR3 Direct Pilot softkey, [249](#)
- SR3 Mcarrier 9 Channel softkey, [249](#)
- SR3 MCarrier Pilot softkey, [249](#)
- SS softkey, [792](#)
- SSB softkey, [999](#), [1004](#)
- SSCH 2nd Scramble Group field, [1056](#)
- SSCH Power field, [1056](#)
- SSCH softkey, [357](#)
- SSCH State field, [1057](#)
- Standard softkey, [356](#)
- Start Access Slot Position in 80ms Period field, [1122](#)

Index

- Start Frequency softkey, [61](#), [74](#)
- Start Sub-Channel# field, [1126](#)
- State field
 - See* CDMA2000 BBG subsystem keys and fields
- State softkey, [103](#), [124](#)
- STD softkey, [1080](#)
- Step Dwell softkey, [56](#)
- Step Power field, [1103](#)
- Stop Frequency softkey, [61](#), [74](#)
- Stop Measurement softkey
 - See* sense subsystem keys
- Store Custom CDMA State softkey, [232](#), [251](#), [254](#)
- Store Custom Dig Mod State softkey, [285](#)
- Store Custom Multicarrier softkey, [231](#), [249](#)
- Store Custom W-CDMA State softkey, [352](#), [355](#)
- Store To File softkey, [21](#), [123](#), [127](#), [336](#), [364](#)
- string response data, [11](#)
- string SCPI parameter, [10](#)
- strings, quote usage, [17](#)
- STS softkey, [1000](#), [1005](#)
- Sub Channel Timing (RPS17) softkey
 - See* wideband CDMA base band generator subsystem keys and fields
- Subnet Mask softkey, [77](#)
- subsystems, SCPI commands
 - See* SCPI command subsystems
- Sum softkey, [24](#)
- Summing Ratio (SRC1/SRC2) x.xx dB softkey, [36](#)
- SW softkey, [927](#), [930](#), [932](#)
- Swap IQ softkey, [387](#)
- Sweep Direction Down Up softkey, [50](#)
- Sweep Repeat Single Cont softkey, [166](#)
- Sweep Retrace Off On softkey, [54](#)
- sweep setup, [49](#)
- Sweep Type List Step softkey, [55](#)
- sweep/list subsystem keys
 - Load From Selected File
 - Store to File, [49](#)
- Swept-Sine softkey, [175](#), [182](#), [189](#), [195](#)
- Symbol Out Polarity Neg Pos softkey, [134](#)
- Symbol Rate field, [1083](#), [1092](#), [1115](#)
- Symbol Rate softkey, [286](#), [356](#), [364](#), [658](#), [1111](#)
- Symbol Sync Out Polarity Neg Pos softkey, [135](#)
- Symbol Sync Polarity Neg Pos softkey, [131](#), [132](#)
- Symbol Timing Err softkey, [472](#)
- Sync Out Offset softkey, [614](#), [657](#), [803](#), [900](#), [933](#), [964](#), [1011](#)
- SYNC softkey, [895](#), [898](#), [957](#)
- Sync softkey, [229](#), [802](#)
- Sync Source BCH PDCH softkey, [438](#)
- Sync Source BCH TCH softkey, [454](#)
- Sync Source SFN FCIk ESG softkey, [1152](#)
- Synchronize to BCH/PDCH softkey, [437](#)
- Synchronize to BCH/TCH softkey, [453](#)
- System ID field, [504](#)
- system subsystem keys
 - 8648A/B/C/D, [156](#), [158](#)
 - 8656B,8657A/B, [156](#), [158](#)
 - 8657D NADC, [156](#), [158](#)
 - 8657D PDC, [156](#), [158](#)
 - 8657J PHS, [156](#), [158](#)
 - Activate Secure Display, [160](#)
 - Enter Secure Mode, [162](#)
 - erase, [161](#)
 - Erase All, [161](#)
 - Erase and Overwrite All, [163](#)
 - Erase and Sanitize All, [163](#)
 - Error Info, [155](#)
 - Help Mode Single Cont, [156](#)
 - none, [161](#)
 - overwrite, [161](#)
 - PN9 Mode Preset, [159](#)
 - Power On Last Preset, [157](#)
 - Preset, [158](#)
 - Preset Normal User, [160](#)
 - Restore Sys Defaults, [159](#)
 - sanitize, [161](#)
 - Save User Preset, [160](#)
 - SCPI, [156](#), [158](#)
 - Screen Saver Delay
 - 1 hr, [163](#)
 - Screen Saver Mode, [164](#)
 - Screen Saver Off On, [164](#)
 - Time/Date, [154](#), [165](#)
 - View Next Error Message, [155](#)

T

- T1 softkey, [654](#)
- T2 softkey, [655](#)

- Target BER % softkey
 - See sense subsystem keys
- TCH All softkey, [957](#)
- TCH softkey, [957](#)
- TCH/FS softkey, [641](#), [644](#), [794](#)
- tDPCH Offset field, [1035](#)
- Test Model 1 w/16 DPCH softkey, [348](#), [353](#)
- Test Model 1 w/32 DPCH softkey, [348](#), [353](#)
- Test Model 1 w/64 DPCH softkey, [348](#), [353](#)
- Test Model 2 softkey, [348](#), [353](#)
- Test Model 3 w/16 DPCH softkey, [348](#), [353](#)
- Test Model 3 w/32 DPCH softkey, [348](#), [353](#)
- Test Model 4 softkey, [348](#), [353](#)
- Test Model 5 w/2HSPDSCH softkey, [348](#), [353](#)
- Test Model 5 w/4HSPDSCH softkey, [348](#), [353](#)
- Test Model 5 w/8HSPDSCH softkey, [348](#), [353](#)
- TETRA Off On softkey, [1019](#)
- TETRA softkey, [282](#), [283](#), [284](#)
- TETRA subsystem keys
 - 128QAM, [994](#)
 - 16 1's & 16 0's, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#), [1007](#), [1008](#), [1009](#)
 - 16PSK, [994](#)
 - 16QAM, [994](#)
 - 256QAM, [994](#)
 - 2-Lvl FSK, [994](#)
 - 32 1's & 32 0's, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#), [1007](#), [1008](#), [1009](#)
 - 32QAM, [994](#)
 - 4 1's & 4 0's, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#), [1007](#), [1008](#), [1009](#)
 - 4-Lvl FSK, [994](#)
 - 4QAM, [994](#)
 - 64 1's & 64 0's, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#), [1007](#), [1008](#), [1009](#)
 - 64QAM, [994](#)
 - 8 1's & 8 0's, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#), [1007](#), [1008](#), [1009](#)
 - 8PSK, [994](#)
 - All Timeslots, [1011](#)
 - APCO 25 C4FM, [991](#)
 - B, [999](#), [1004](#)
 - B1, [997](#), [1002](#)
 - B2, [997](#), [1002](#)
 - BBG Data Clock Ext Int, [977](#)
 - TETRA subsystem keys (*continued*)
 - BBG Ref Ext Int, [990](#)
 - Begin Frame, [1011](#)
 - Begin Timeslot #, [1011](#), [1012](#)
 - Bit Rate, [978](#)
 - BPSK, [994](#)
 - Bus, [995](#), [1016](#)
 - Continuous, [1014](#)
 - D8PSK, [994](#)
 - Data Format Pattern Framed, [986](#)
 - Dn Custom Cont, [1010](#)
 - Dn Normal Cont, [1010](#)
 - Dn Normal Disc, [1010](#)
 - Dn Sync Cont, [1010](#)
 - Dn Sync Disc, [1010](#)
 - Ext, [987](#), [995](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#), [1007](#), [1008](#), [1009](#), [1016](#)
 - Ext BBG Ref Freq, [990](#)
 - Ext Data Clock Normal Symbol, [989](#)
 - Ext Delay Bits, [1017](#)
 - Ext Delay Off On, [1017](#)
 - Ext Polarity Neg Pos, [1018](#)
 - Fall Delay, [980](#), [982](#)
 - Fall Time, [981](#), [982](#)
 - FCOR, [999](#), [1004](#)
 - Filter Alpha, [977](#)
 - Filter BbT, [978](#)
 - FIX4, [987](#), [988](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#), [1007](#), [1008](#), [1009](#), [1010](#)
 - Free Run, [1014](#)
 - Freq Dev, [992](#)
 - Gate Active Low High, [1015](#)
 - Gated, [1014](#)
 - Gaussian, [991](#)
 - Gray Coded QPSK, [994](#)
 - I/Q Scaling, [992](#)
 - IS-95, [991](#)
 - IS-95 Mod, [991](#)
 - IS-95 Mod w/EQ, [991](#)
 - IS-95 OQPSK, [994](#)
 - IS-95 QPSK, [994](#)
 - IS-95 w/EQ, [991](#)
 - MSK, [994](#)
 - Nyquist, [991](#)
 - Optimize FIR For EVM ACP, [987](#)

Index

TETRA subsystem keys (*continued*)

OQPSK, [994](#)
 $\pi/4$ DQPSK, [994](#)
Patt Trig In 1, [1018](#)
Patt Trig In 2, [1018](#)
Phase Dev, [993](#)
Phase Polarity Normal Invert, [994](#)
PN11, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#),
[1007](#), [1008](#), [1009](#)
PN15, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#),
[1007](#), [1008](#), [1009](#)
PN20, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#),
[1007](#), [1008](#), [1009](#)
PN23, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#),
[1007](#), [1008](#), [1009](#)
PN9, [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#), [1005](#),
[1007](#), [1008](#), [1009](#)
PN9 Mode Normal Quick, [979](#)
QPSK, [994](#)
Recall Secondary Frame State, [995](#)
Rectangle, [991](#)
Reset & Run, [1014](#)
Restore TETRA Factory Default, [989](#)
Rise Delay, [983](#), [984](#)
Rise Time, [984](#), [985](#)
Root Nyquist, [991](#)
Save Secondary Frame State, [995](#)
Scramble Off On, [980](#)
Scramble Seed, [980](#)
Secondary Frame Off On, [996](#)
Sine, [986](#)
Single, [1014](#)
SSB, [999](#), [1004](#)
STS, [1000](#), [1005](#)
Symbol Rate, [1012](#)
Sync Out Offset, [1011](#)
TETRA Off On, [1019](#)
Timeslot Ampl Main Delta, [1006](#)
Timeslot Off On, [1006](#)
Trigger & Run, [1014](#)
Trigger Key, [995](#), [1016](#)
TS, [997](#), [1002](#), [1006](#), [1007](#), [1009](#)
UN3/4 GSM Gaussian, [991](#)
Up Control 1, [1010](#)
Up Control 2, [1010](#)

TETRA subsystem keys (*continued*)

Up Custom, [1010](#)
Up Normal, [1010](#)
User File, [986](#), [987](#), [996](#), [998](#), [1000](#), [1001](#), [1003](#),
[1005](#), [1007](#), [1008](#), [1009](#)
User FIR, [991](#)
User FSK, [993](#), [994](#)
User I/Q, [993](#), [994](#)
tetra subsystem keys
PRAM Files, [988](#)
TFCI Field Off On softkey, [356](#), [361](#), [364](#), [366](#)
TFCI Pat field, [1035](#)
TFCI Pattern field, [1084](#), [1112](#)
TFCI State field, [1085](#), [1113](#)
Tfirst field, [1028](#)
TGCFN field, [1058](#), [1154](#)
TGD field, [1059](#), [1155](#)
Tgl field, [1028](#)
TGL1 field, [1059](#), [1156](#)
TGL2 field, [1059](#), [1156](#), [1157](#)
TGPL1 field, [1060](#), [1156](#)
TGPRC field, [1157](#)
TGPS Inactive Active softkey, [1158](#)
TGSN field, [1061](#), [1158](#)
Through softkey, [32](#), [205](#), [208](#), [217](#), [222](#), [241](#), [246](#),
[270](#), [275](#), [298](#), [299](#), [327](#), [329](#), [344](#), [346](#), [466](#), [473](#)
Time field, [504](#)
Time softkey, dual ARB trigger delay, [321](#)
Time/Date softkey, [154](#), [165](#)
Timeslot Ampl Main Delta softkey
See DECT subsystem keys
See EDGE subsystem keys
See NADC subsystem keys
See PDC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys
Timeslot Off On softkey
See DECT subsystem keys
See EDGE subsystem keys
See GSM subsystem keys
See NADC subsystem keys
See PHS subsystem keys
See TETRA subsystem keys
Timeslot Offset softkey, [1125](#)

- Timeslot softkey
 - See* sense subsystem keys
- Timeslot Type softkey, 975
- Timing Offset softkey, 1126, 1151, 1161
- tOCNS Offset field, 1042
- Toggle Marker 1 2 3 4 softkey, 313
- Toggle State softkey, 334, 336
- Total Bits field, 1165
- Total Bits softkey, 458
- Total Block field, 1167
- TotalPwr field, 1078, 1108
- TPC Pat Steps field, 1085
- TPC Pat Trig Polarity Neg Pos softkey, 1087
- TPC Pattern field, 1087
- TPC Steps field, 1036
- TPC UserFile Trig field, 1088
- Tp-m field, 1127
- Tp-p field, 1128
- Traffic Bearer softkey, 589, 600
- Traffic Bearer with Z field softkey, 589, 600
- Traffic softkey, 229
- Transp Chan A softkey, 1031
- Transp Chan B softkey, 1031
- Transp Position Flexible Fixed softkey, 1072
- Transport CH softkey, 1043
- TrCH BER field, 1093
- TrCh BlkSize 168 softkey, 1124
- TrCh BlkSize 360 softkey, 1124
- TrCH State Off On softkey, 1177
- TrCHI State Off On softkey, 1074
- Triangle softkey, 175, 182, 189, 195
- Trigger & Run softkey
 - See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* custom subsystem keys
 - See* DECT subsystem keys
 - See* Dmodulation subsystem keys
 - See* dual ARB subsystem keys
 - See* EDGE subsystem keys
 - See* GSM subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* PHS subsystem keys
 - See* TETRA subsystem keys
 - See* wideband CDMA ARB subsystem keys
- Trigger Advance field, 546
- Trigger In Polarity Neg Pos softkey, 168
- Trigger Key softkey
 - list/sweep subsystem, 54
 - See* amplitude modulation subsystem keys
 - See* CDMA ARB subsystem keys
 - See* CDMA2000 ARB subsystem keys
 - See* DECT subsystem keys
 - See* Dmodulation subsystem keys
 - See* dual ARB subsystem keys
 - See* EDGE subsystem keys
 - See* frequency modulation subsystem keys
 - See* GSM subsystem keys
 - See* low frequency output subsystem keys
 - See* NADC subsystem keys
 - See* PDC subsystem keys
 - See* phase modulation subsystem keys
 - See* PHS subsystem keys
 - See* sense subsystem keys
 - See* TETRA subsystem keys
 - See* trigger subsystem keys
 - See* wideband CDMA ARB subsystem keys
- Trigger Out Polarity Neg Pos softkey, 167
- trigger source, list sweep, 54
- trigger subsystem keys
 - Bus, 168, 546
 - Ext, 168, 546
 - Free Run, 168, 546
 - Single Sweep, 167
 - Sweep Repeat Single Cont, 166
 - Trigger In Polarity Neg Pos, 168
 - Trigger Key, 168, 546
 - Trigger Out Polarity Neg Pos, 167
- Trigger Sync Reply (RPS7) softkey
 - See* wideband CDMA base band generator subsystem keys and fields
- triggers
 - response selection
 - segment advance mode, dual ARB, 318
- Truncated PN9 softkey, 465
- TS softkey, 802, 997, 1002, 1006, 1007, 1009
- TSC0 softkey, 645, 655, 793, 800
- TSC1 softkey, 645, 655, 793, 800
- TSC2 softkey, 645, 655, 793, 800
- TSC3 softkey, 645, 655, 793, 800

Index

TSC4 softkey, [645](#), [655](#), [793](#), [800](#)

TSC5 softkey, [645](#), [655](#), [793](#), [800](#)

TSC6 softkey, [645](#), [655](#), [793](#), [800](#)

TSC7, [645](#), [793](#), [800](#)

TSC7 softkey, [645](#), [655](#), [793](#), [800](#)

TTI field, [1073](#), [1130](#), [1170](#), [1177](#)

TTI Frame Clock (RPS9) softkey

See wideband CDMA base band generator
subsystem keys and fields

Turbo Coding field, [498](#), [545](#)

Turbo softkey, [1068](#), [1070](#), [1163](#)

Type softkey, [356](#), [364](#)

U

UDI 64 kbps softkey, [1137](#)

UDI ISDN (25.101) softkey, [1033](#)

UN3/4 GSM Gaussian softkey

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See CDMA2000 BBG subsystem keys and fields

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See EDGE subsystem keys

See GPS subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA ARB subsystem keys

See wideband CDMA base band generator
subsystem keys and fields

Uncoded softkey, [646](#)

unit subsystem keys

dBm, [170](#)

dBuV, [170](#)

dBuVemf, [170](#)

mV, [170](#)

mVemf, [170](#)

uV, [170](#)

uVemf, [170](#)

unprotected

memory subsystem, [116](#)

unspecified RMS, [295](#)

Up Control 1 softkey, [1010](#)

Up Control 2 softkey, [1010](#)

Up Custom softkey, [899](#), [933](#), [1010](#)

Up Normal softkey, [1010](#)

Up TCH All softkey, [899](#), [933](#)

Up TCH softkey, [899](#), [933](#)

Up VOX softkey, [933](#)

Up/Down softkey, [1036](#), [1086](#)

Update Display Cycle End Cont softkey, [407](#)

Update in Remote Off On softkey, [87](#)

Uplink MCS-1 softkey, [641](#), [644](#), [794](#)

Uplink MCS-5 softkey, [646](#)

Uplink MCS-9 softkey, [646](#)

Uplink Timing Advance softkey

See sense subsystem keys

uploading files, [116](#)

user

documentation, [lxxiii](#)

User File softkey

See CDMA2000 BBG subsystem keys and fields

See custom subsystem keys

See DECT subsystem keys

See EDGE subsystem keys

See GPS subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA base band generator
subsystem keys and fields

user files, HSDPA, [812](#)

user files, HSPA, [668](#)

User FIR softkey

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See CDMA2000 BBG subsystem keys and fields

See custom subsystem keys

See DECT subsystem keys

See Dmodulation subsystem keys

See EDGE subsystem keys

See GPS subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

User FIR softkey (continued)

See PHS subsystem keys

See TETRA subsystem keys

See wideband CDMA ARB subsystem keys

See wideband CDMA base band generator
subsystem keys and fields

User Flatness softkey, [103](#), [124](#)

User FSK softkey

See custom subsystem keys

See DECT subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

User I/Q softkey

See custom subsystem keys

See DECT subsystem keys

See EDGE subsystem keys

See GSM subsystem keys

See NADC subsystem keys

See PDC subsystem keys

See PHS subsystem keys

See TETRA subsystem keys

uV softkey, [170](#)

uVemf softkey, [170](#)

UW softkey, [955](#), [956](#), [973](#), [974](#)

UWCDMA softkey, [104](#)

V

View Next Error Message softkey, [155](#)

W

Walsh Code softkey, [252](#), [255](#)

Walsh field

See CDMA2000 BBG subsystem keys and fields

waveform

sequence, dual ARB, [313](#)

Waveform Length softkey, [212](#), [238](#)

waveform license time remaining, [84](#)

Waveform Licenses softkey, [82](#), [84](#)

Waveform Runtime Scaling softkey, [312](#), [335](#)

waveform scaling

during playback, [312](#), [335](#)

files, [312](#)

waveform, creating a multitone, [326](#)

W-CDMA Off On softkey, [378](#), [1177](#)

WCDMA softkey

See CDMA ARB subsystem keys

See CDMA2000 ARB subsystem keys

See Dmodulation subsystem keys

See wideband CDMA ARB subsystem keys

wideband AM, [173](#)

wideband CDMA ARB subsystem keys

1 DPCH, [348](#), [353](#)

2 Carriers, [349](#)

2.100 MHz, [346](#)

3 Carriers, [349](#)

3 DPCH, [348](#), [353](#)

4 Carriers, [349](#)

40.000 MHz, [344](#), [346](#)

APCO 25 C4FM, [342](#)

Apply Channel Setup, [356](#), [364](#)

ARB Reference Ext Int, [370](#)

ARB Sample Clock, [372](#)

Bus, [375](#)

Channel, [356](#), [364](#)

Chip Rate, [342](#)

Clear Header, [344](#)

Clip III To, [340](#), [350](#)

Clip IQI To, [340](#), [351](#)

Clip At PRE POST FIR Filter, [340](#)

Clip Type II+jQI To, [341](#), [351](#)

Clipping Type II+jQI III,IQI, [341](#), [351](#)

Continuous, [372](#)

Custom WCDMA State, [363](#)

DPCCH, [363](#)

DPCCH + 1 DPDCH, [363](#)

DPCCH + 2 DPDCH, [363](#)

DPCCH + 3 DPDCH, [363](#)

DPCCH + 4 DPDCH, [363](#)

DPCCH + 5 DPDCH, [363](#)

DPCH, [357](#)

Equal Energy per Symbol, [361](#)

Ext Delay Off On, [376](#)

Ext Delay Time, [376](#)

Ext Key, [375](#)

Index

wideband CDMA ARB subsystem keys (*continued*)

Ext Polarity Neg Pos, 377
Filter Alpha, 343
Filter BbT, 343
First Spread Code, 356, 364
Free Run, 374
Gain Unit dB Lin Index, 366
Gate Active Low High, 374
Gated, 372
Gaussian, 342
I/Q Mapping Norma Invert, 345
I/Q Mod Filter Manual Auto, 347
I/Q Output Filter Manual Auto, 345
Increment Scramble Code, 352
Increment Timing Offset, 355
IS-2000 SR3 DS, 342
IS-95, 342
IS-95 Mod, 342
IS-95 Mod w/EQ, 342
IS-95 w/EQ, 342
Left Alternate, 356
Link Down Up, 347
Marker 1, 367, 368
Marker 2, 367, 368
Marker 3, 367, 368
Marker 4, 367, 368
Marker Polarity Neg Pos, 370
Modulator Atten Manual Auto, 346
None, 367, 368
Nyquist, 342
OCNS, 357
Optimize ACP ADJ ALT, 347, 362
Optimize FIR For EVM ACP, 344
Patt Trig In 1, 377
Patt Trig In 2, 377
PCCPCH + SCH, 348, 353
PCCPCH + SCH + 1 DPCH, 348, 353
PCCPCH + SCH + 3 DPCH, 348, 353
PICH, 357
Power, 364
PPCCPCH, 357, 358
PSCH, 357
Random, 356, 364
Rectangle, 342
Reference Freq, 370

wideband CDMA ARB subsystem keys (*continued*)

Reset & Run, 374
Retrigger Mode Off On, 371
Right Alternate, 356
Root Nyquist, 342
Save Setup To Header, 344
Scale to 0dB, 361
SCCPCH, 357, 358
Scramble Code, 356, 362, 364
Scramble Offset, 356, 364
Second DPDCH I Q, 362
Single, 372
SSCH, 357
Standard, 356
Store Custom W-CDMA State, 352, 355
Store To File, 364
Symbol Rate, 356, 364
Test Model 1 w/16 DPCH, 348, 353
Test Model 1 w/32 DPPCH, 348, 353
Test Model 1 w/64 DPCH, 348, 353
Test Model 2, 348, 353
Test Model 3 w/16 DPCH, 348, 353
Test Model 3 w/32 DPCH, 348, 353
Test Model 4, 348, 353
Test Model 5 w/2HSPDSCH, 348, 353
Test Model 5 w/4HSPDSCH, 348, 353
Test Model 5 w/8HSPDSCH, 348, 353
TFCI Field Off On, 356, 361, 364, 366
Through, 344, 346
Trigger & Run, 374
Trigger Key, 375
Type, 356, 364
UN3/4 GSM Gaussian, 342
User FIR, 342
WCDMA, 342
W-CDMA Off On, 378

wideband CDMA base band generator subsystem

keys and fields
of Blocks, 1071
1/2 Conv, 1068, 1070, 1163
1/3 Conv, 1068, 1070, 1163
10 msec, 1096
10ms Frame Pulse (DRPS11), 1050, 1052, 1053, 1054, 1055

- wideband CDMA base band generator subsystem
 keys and fields (*continued*)
 10ms Frame Pulse (RPS6), [1145](#), [1147](#), [1148](#),
[1149](#), [1150](#)
 12.2 kbps (34.121), [1033](#)
 144 kbps (34.121), [1033](#)
 20 msec, [1096](#)
 2560 msec, [1096](#)
 2nd Scr Offset, [1034](#), [1041](#)
 3.84MHz chip-clk (DRPS4), [1050](#), [1052](#), [1053](#),
[1054](#), [1055](#)
 384 kbps (34.121), [1033](#)
 40 msec, [1096](#)
 64 kbps (34.121), [1033](#)
 80 msec, [1096](#)
 80ms Frame Pulse (DRPS13), [1050](#), [1052](#), [1053](#),
[1054](#), [1055](#)
 80ms Frame Pulse (RPS20), [1145](#), [1147](#), [1148](#),
[1149](#), [1150](#)
 A, [1025](#)
 ACS, [1064](#)
 Active, [1061](#)
 Actual BER, [1172](#)
 Actual BLER, [1166](#), [1173](#)
 AICH, [1130](#)
 AICH Trigger Polarity Pos Neg, [1105](#)
 All Down, [1036](#), [1086](#)
 All Up, [1036](#), [1086](#)
 Alt power in, [1143](#)
 AMR 12.2 kbps, [1033](#), [1137](#)
 APCO 25 C4FM, [1037](#), [1097](#)
 Apply Channel Setup, [1021](#), [1075](#)
 B, [1025](#)
 Base Delay Tp-a, [1127](#)
 BBG Chip Clock Ext Int, [1020](#)
 BBG Data Clock Ext In, [1024](#)
 BER, [1166](#), [1168](#), [1173](#), [1175](#)
 Beta, [1079](#), [1089](#)
 BLER, [1167](#), [1168](#), [1174](#), [1175](#)
 Blk Set Size, [1067](#)
 Blk Size, [1066](#), [1162](#), [1170](#)
 Blocking, [1064](#)
 Burst gate in, [1144](#)
 C Power, [1076](#)
 C Power value, [1106](#)
- wideband CDMA base band generator subsystem
 keys and fields (*continued*)
 C/N value, [1021](#), [1075](#), [1105](#)
 CFN #0 Frame Pulse (RPS10), [1139](#)
 Chan Code, [1030](#), [1031](#), [1040](#)
 Channel Code, [1045](#), [1080](#), [1090](#), [1131](#), [1132](#)
 Channel Code field, [1044](#)
 Channel State, [1089](#), [1096](#)
 Channel State Off On, [1024](#), [1028](#), [1029](#), [1031](#),
[1037](#), [1039](#), [1042](#), [1043](#), [1045](#), [1047](#), [1055](#),
[1078](#), [1108](#), [1163](#), [1170](#), [1171](#)
 ChCode Ctl, [1121](#)
 ChCode Dat, [1121](#)
 Chip Clock (RPS1), [1139](#), [1145](#), [1147](#), [1148](#), [1149](#),
[1150](#)
 Chip Rate, [1030](#), [1079](#)
 Comp Mode Start Trigger Polarity Neg Pos, [1160](#)
 Comp Mode Start Trigger Polarity Pos Neg, [1062](#),
[1063](#)
 Comp Mode Stop Trigger Polarity Neg Pos, [1160](#)
 Comp Mode Stop Trigger Polarity Pos Neg, [1063](#)
 Compressed Mode Off On, [1159](#)
 Compressed Mode Start Trigger, [1039](#), [1062](#), [1160](#)
 Compressed Mode Stop Trigger, [1063](#), [1160](#)
 CRC Size, [1069](#), [1164](#), [1171](#)
 Ctrl Beta, [1109](#)
 Ctrl Pwr, [1110](#)
 Data, [1091](#)
 Data Beta, [1113](#)
 Data field, [1175](#)
 Data Pwr, [1115](#)
 Data Rate, [1041](#)
 DCH1, [1077](#)
 DCH2, [1077](#)
 DCH3, [1077](#)
 DCH4, [1077](#)
 DCH5, [1077](#)
 DCH6, [1077](#)
 DL Reference 1.1, [1158](#)
 DL Reference 1.2, [1158](#)
 DL Reference 2.1, [1158](#)
 DL Reference 2.2, [1158](#)
 Down/Up, [1036](#), [1086](#)
 DPCCH, [1077](#), [1100](#)

Index

wideband CDMA base band generator subsystem
 keys and fields (*continued*)
 DPCCH Pilot data-clk (DRPS23), 1050, 1052,
 1053, 1054, 1055
 DPCCH Power, 1083
 DPCCH Raw Data (RPS4), 1139
 DPCCH Raw Data Clock (RPS5), 1139
 DPCCH TFCI data-clk (DRPS22), 1050, 1052,
 1053, 1054, 1055
 DPCCH TPC indicator (DRPS21), 1050, 1052,
 1053, 1054, 1055
 DPCH + 1, 1022, 1023
 DPCH + 2, 1022, 1023
 DPCH 10ms Frame-Pulse (DRPS26), 1050, 1052,
 1053, 1054, 1055
 DPCH Channel Balance, 1030
 DPCH Compressed Frame Indicator (DRPS32),
 1050, 1052, 1053, 1054, 1055
 DPCH data stream (DRPS24), 1050, 1052, 1053,
 1054, 1055
 DPCH data-clk (0) (DRPS28), 1050, 1052, 1053,
 1054, 1055
 DPCH Gap Indicator (DRPS33), 1050, 1052,
 1053, 1054, 1055
 DPCH TimeSlot pulse (DRPS25), 1050, 1052,
 1053, 1054, 1055
 DPDCH, 1077
 DPDCH data-clk withDTX (DRPS20), 1050,
 1052, 1053, 1054, 1055
 DPDCH data-clk WithOutDTX (DRPS30), 1050,
 1052, 1053, 1054, 1055
 DPDCH Power, 1092
 DPDCH Raw Data (RPS2), 1139
 DPDCH Raw Data Clock (RPS3), 1139
 Eb/No, 1106
 Eb/No value (dB), 1076
 Ec/No value, 1022, 1107
 Equal Powers, 1043, 1100
 Error BER, 1172
 Error Bits, 1165
 Error Blocks, 1166
 Ext, 1036
 Ext Clock Rate x1 x2 x4, 1020
 FBI State, 1082
 Filter Alpha, 1038, 1098

wideband CDMA base band generator subsystem
 keys and fields (*continued*)
 Filter BbT, 1038, 1099
 FIX, 1082
 FIX4, 1032, 1043, 1044, 1045, 1046, 1069, 1070,
 1081, 1091, 1109, 1110, 1112, 1114, 1168,
 1172
 Flat Noise BW, 1077
 Frame Clock Polarity Neg Pos, 1097
 Frame Struct, 1057
 Frame Sync Trigger Mode Single Cont, 1152
 Gaussian, 1037, 1097
 Higher Layer, 1155
 Infinity, 1060, 1157
 Init Power, 1101
 Init Pwr, 1119, 1134
 Intermod, 1064
 IS-95, 1037, 1097
 IS-95 Mod, 1037, 1097
 IS-95 Mod w/EQ, 1037, 1097
 IS-95 w/EQ, 1097
 Left, 1026
 Link Down Up, 1074
 Max Input, 1064
 Max Power, 1102
 Max Pwr, 1120, 1135
 Message Data Raw Data (RPS11), 1145, 1147,
 1148, 1149, 1150
 Message Part, 1118
 Message Pulse (RPS22), 1145, 1147, 1148, 1149,
 1150
 Message-Control Raw Data (RPS13), 1147, 1148,
 1149, 1150
 Message-Control Raw Data Clock (RPS12), 1145,
 1147, 1148, 1149, 1150
 Min Power, 1102
 Msg Ctrl, 1107
 Msg Data, 1107
 Msg Pwr, 1118, 1133
 N Power, 1078, 1108
 NONE, 1163
 None, 1068, 1070, 1168, 1175
 NONE (RPS0), 1139, 1145, 1147, 1148, 1149,
 1150
 Normal, 1026

- wideband CDMA base band generator subsystem
 keys and fields (*continued*)
 Num of Blk, [1169](#), [1176](#)
 Num of Pre, [1119](#), [1134](#)
 Number of AICH, [1104](#)
 Number of PRACH, [1131](#), [1133](#)
 Number of PRACH 80ms, [1118](#)
 Number of Preamble, [1134](#)
 Nyquist, [1037](#), [1097](#)
 Off, [1130](#)
 Omitted, [1060](#), [1157](#)
 On, [1130](#)
 On/Off, [1042](#), [1123](#)
 OpenLoop Ant1, [1065](#)
 OpenLoop Ant1 SCH TSTD OFF, [1065](#)
 OpenLoop Ant2, [1065](#)
 OpenLoop Ant2 SCH TSTD OFF, [1065](#)
 Optimize FIR For EVM ACP, [1039](#), [1099](#)
 Paging Indicator, [1046](#)
 Pattern trigger in 1, [1144](#)
 Pattern trigger in 2, [1145](#)
 PCCPCH, [1022](#), [1023](#)
 P-CCPCH data (DRPS39), [1050](#), [1052](#), [1053](#),
[1054](#), [1055](#)
 P-CCPCH data-clk (DRPS38), [1050](#), [1052](#), [1053](#),
[1054](#), [1055](#)
 Performance Req, [1064](#)
 Phase Polarity Normal Invert, [1047](#)
 Phase Polarity Normal Inverted, [1074](#)
 PI Bits, [1046](#)
 PICH, [1022](#), [1023](#)
 PICH 10ms FramePulse (DRPS37), [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
 PICH data (DRPS35), [1050](#), [1052](#), [1053](#), [1054](#),
[1055](#)
 PICH data-clk (DRPS34), [1050](#), [1052](#), [1053](#),
[1054](#), [1055](#)
 PICH TimeSlot Pulse (DRPS36), [1050](#), [1052](#),
[1053](#), [1054](#), [1055](#)
 Playback Ratio, [1026](#)
 PN15, [1025](#), [1031](#), [1040](#), [1043](#), [1045](#), [1080](#), [1081](#),
[1084](#), [1086](#), [1091](#), [1109](#), [1112](#), [1114](#)
 PN9, [1025](#), [1031](#), [1040](#), [1043](#), [1045](#), [1069](#), [1080](#),
[1081](#), [1084](#), [1086](#), [1091](#), [1109](#), [1112](#), [1114](#),
[1164](#), [1172](#)
- wideband CDMA base band generator subsystem
 keys and fields (*continued*)
 Power, [1026](#), [1029](#), [1032](#), [1040](#), [1044](#), [1047](#), [1048](#)
 Power Control Signal Polarity Neg Pos, [1104](#)
 Power Hold Off On, [1101](#)
 Power Mode Norm TPC, [1104](#)
 Pp-m, [1120](#), [1136](#)
 PRACH, [1100](#)
 PRACH Mode Single Multi, [1117](#)
 PRACH Power Setup Mode Pp-m Total, [1124](#)
 PRACH Processing (RPS19), [1145](#), [1147](#), [1148](#),
[1149](#), [1150](#)
 PRACH Scrambling Code, [1125](#)
 PRACH Trigger, [1129](#)
 PRACH Trigger Polarity Neg Pos, [1129](#)
 PRACH Trigger Source Immedi Trigger, [1129](#)
 Pre Sig, [1121](#)
 Preamble, [1107](#)
 Preamble power average, [1123](#)
 Preamble Pulse (RPS21), [1145](#), [1147](#), [1148](#), [1149](#),
[1150](#)
 Preamble Raw Data (RPS15), [1145](#), [1147](#), [1148](#),
[1149](#), [1150](#)
 Preamble Raw Data Clock (RPS16), [1145](#), [1147](#),
[1148](#), [1149](#), [1150](#)
 PSCH State, [1048](#)
 Puncture, [1058](#), [1169](#), [1176](#)
 PwrOffs, [1057](#), [1154](#)
 RACH TrCH, [1107](#)
 Ramp Step, [1120](#), [1135](#)
 Rate Match Attr, [1073](#), [1169](#), [1176](#)
 Rectangle, [1037](#), [1097](#)
 Ref Data Rate, [1076](#), [1106](#)
 Ref Sensitivity, [1064](#)
 Reset to Initial Power, [1103](#)
 Right, [1026](#)
 RMC 144 kbps (25.141), [1137](#)
 RMC 384 kbps (25.141), [1137](#)
 RMC 64 kbps (25.141), [1137](#)
 RMC122 kbps (25.141), [1137](#)
 Root Nyquist, [1037](#), [1097](#)
 Scale to 0dB, [1043](#), [1100](#)
 SCFN, [1062](#), [1159](#)
 SCH slot-pulse (DRPS10), [1050](#), [1052](#), [1053](#),
[1054](#), [1055](#)

Index

wideband CDMA base band generator subsystem
 keys and fields (*continued*)
 Scrambling Code, [1055](#), [1056](#), [1151](#)
 SF/2, [1155](#)
 SF2, [1058](#)
 SFN reset-signal (DRPS5), [1050](#), [1052](#), [1053](#),
 [1054](#), [1055](#)
 SFN RST Polarity, [1151](#)
 SFN-CFN Frame Offset, [1100](#)
 Signature, [1136](#)
 Slot Format, [1027](#), [1034](#), [1083](#), [1094](#), [1111](#), [1116](#)
 Spurious Response, [1064](#)
 SSCH 2nd Scramble Group, [1056](#)
 SSCH Power, [1056](#)
 SSCH State, [1057](#)
 Start Access Slot Position in 80ms Period, [1122](#)
 Start Sub-Channel#, [1126](#)
 STD, [1080](#)
 Step Power, [1103](#)
 Sub Channel Timing (RPS17), [1145](#), [1147](#), [1148](#),
 [1149](#), [1150](#)
 Symbol Rate, [1083](#), [1092](#), [1111](#), [1115](#)
 Sync Source SFN FCk ESG, [1152](#)
 tDPCH Offset, [1035](#)
 TFCI Pat, [1035](#)
 TFCI Pattern, [1084](#), [1112](#)
 TFCI State, [1085](#), [1113](#)
 Tfirst, [1028](#)
 TGCFN, [1058](#), [1154](#)
 TGD, [1059](#), [1155](#)
 Tgl, [1028](#)
 TGL1, [1059](#), [1156](#)
 TGL2, [1059](#), [1156](#)
 TGPL1, [1060](#), [1156](#)
 TGPL2, [1157](#)
 TGPRC, [1157](#)
 TGPS Inactive Active, [1158](#)
 TGSN, [1061](#), [1158](#)
 Timeslot Offset, [1125](#)
 Timing Offset, [1126](#), [1151](#), [1161](#)
 tOCNS Offset, [1042](#)
 Total Bits, [1165](#)
 Total Blocks, [1167](#)
 TotalPwr, [1078](#), [1108](#)
 TPC Pat Steps, [1085](#)

wideband CDMA base band generator subsystem
 keys and fields (*continued*)
 TPC Pat Trig Polarity Neg Pos, [1087](#)
 TPC Pattern, [1087](#)
 TPC Steps, [1036](#)
 TPC UserFile Trig, [1088](#)
 Tp-m, [1127](#)
 Tp-p, [1128](#)
 Transp Chan A, [1031](#)
 Transp Chan B, [1031](#)
 Transp Position Flexible Fixed, [1072](#)
 Transport CH, [1043](#)
 TrCH BER, [1093](#)
 TrCh BlkSize 168, [1124](#)
 TrCh BlkSize 360, [1124](#)
 TrCH State Off On, [1074](#), [1177](#)
 Trigger Sync Reply (RPS7), [1145](#), [1147](#), [1148](#),
 [1149](#), [1150](#)
 TTI, [1073](#), [1130](#), [1170](#), [1177](#)
 TTI Frame Clock (RPS9), [1139](#)
 Turbo, [1068](#), [1070](#), [1163](#)
 UDI 64 kbps, [1137](#)
 UDI ISDN (25.101), [1033](#)
 UN3/4 GSM Gaussian, [1037](#)
 Up/Down, [1036](#), [1086](#)
 User File, [1031](#), [1036](#), [1043](#), [1045](#), [1069](#), [1080](#),
 [1081](#), [1084](#), [1091](#), [1109](#), [1112](#), [1114](#), [1164](#),
 [1172](#)
 User FIR, [1037](#), [1097](#)
 W-CDMA Off On, [1177](#)
 Word Alignment softkey, [384](#)
 Word Size softkey, [391](#)