



# EXT Wireless Communications Test Set E6607B

## Data Sheet

*The Agilent Technologies E6607B EXT wireless communications test set integrates an innovative test sequencer, vector signal analyzer, vector signal generator, and multi-port RF input/output hardware all in a single box, allowing you to accelerate non-signaling test in cellular and wireless device manufacturing.*



# Definitions and Conditions

## Specification

Specifications describe the performance parameters covered by the product warranty and are valid from 20 to 35 °C unless otherwise noted.

## Typical

Typical describes additional product performance information that is not covered by the product warranty. It is performance beyond specifications that 95 percent of the units exhibit with a 95 percent confidence level. This data, shown in *italics*, does not include measurement uncertainty, and is valid only at room temperature (approximately 25 °C).

## Nominal

Nominal values indicate expected performance, or describe product performance that is useful in the application of the product, but are not covered by the product warranty.

The test set will meet its specification when:

- The test set is within its calibration cycle
- The test set has been stored at an ambient temperature within the allowed operating range for at least two hours before being turned on; if it had previously been stored at a temperature range inside the allowed storage range, but outside the allowed operating range.
- The test set has been turned on for at least 30 minutes with Auto Align<sup>1</sup> set to normal.
- Error vector magnitude (EVM) specifications apply after execution of a source alignment when the instrument is maintained within  $\pm 5$  °C of the alignment temperature.

---

1. For more information on using Alignments in a manufacturing environment, please see the EXT user documentation.

# Vector Signal Analyzer Performance

Performance	
Capture depth	256 MSa of IQ data
Frequency and time specifications	
Frequency range	10 MHz to 3.8 GHz (Option 504)
Frequency reference	
Accuracy	$\pm [( \text{time since last adjustment} \times \text{aging rate} ) + \text{temperature stability} + \text{calibration accuracy}]$
Aging rate <sup>1</sup>	
Standard	$\pm 1.0$ ppm/year
Option PRF	$\pm 0.1$ ppm/year, $\pm 0.15$ ppm/2 years
Temperature stability <sup>1</sup>	
Standard	$\pm 2.0$ ppm
Option PRF	$\pm 0.015$ ppm
Achievable initial calibration accuracy <sup>1</sup>	
Standard	$\pm 1.4$ ppm
Option PRF	$\pm 0.04$ ppm
Residual FM <sup>1</sup>	
Standard	$\leq 10$ Hz p-p in 20 ms nominal
Option PRF	$\leq 0.25$ Hz-p-p in 20 ms nominal
CW measurement frequency accuracy	
Accuracy	(Transmitter frequency x frequency reference accuracy) $\pm 50$ Hz
Resolution	1 Hz
Analysis bandwidth	
Maximum bandwidth	40 MHz
Triggering	
Trigger	
Sequence analyzer	Free run, external 1, external 2, RF burst, video, internal
IQ analyzer	Free run, external 1, external 2, RF burst, video, line, periodic
Trigger delay range	-150 to 500 ms
Resolution	0.1 $\mu$ s

1. Standard and Option PFR values apply to units purchased prior to October 1, 2012; for units purchased after October 1, 2012 Option PFR is included in the standard configuration and these (PFR) values apply to all units.

## Vector Signal Analyzer Performance (con't)

### Amplitude accuracy and range specifications

#### Electromechanical attenuator

Input electromechanical attenuator range	0 to 50 dB, 2 dB steps
--	------------------------

#### Electronic attenuator

Frequency range	10 MHz to 3.8 GHz
Electronic attenuator range	0 to 24 dB, 1 dB steps

#### Input level ranges (average power)

RF I/O 1 and 2	−65 to +33 dBm
RF INPUT	−70 to +24 dBm

#### Total absolute amplitude accuracy

RF I/O 1 and 2, input signal −35 to + 33 dBm	
10 MHz to 3.6 GHz	< ±0.65 dB, < ±0.35 dB typical
3.6 GHz to 3.8 GHz	< ±0.80 dB, < ±0.40 dB typical
RF INPUT, input signal −70 to + 24 dBm	
10 MHz to 3.6 GHz	< ±0.70 dB, < ±0.40 dB typical
3.6 GHz to 3.8 GHz	< ±0.90 dB, < ±0.45 dB typical

#### IF flatness

RF I/O 1 and 2, RF INPUT	
10 MHz BW	< ±0.12 dB typical
25 MHz BW	< ±0.40 dB typical
40 MHz BW	< ±0.34 dB typical

#### Input voltage standing wave ratio (VSWR)

RF I/O 1 & 2, 10 MHz to 2.4 GHz	< 1.2:1 typical
RF I/O 1 & 2, 2.4 to 2.7 GHz	< 1.34:1 typical
RF I/O 1 & 2, 2.7 to 3.8 GHz	< 1.42:1 typical
RF INPUT	< 1.3:1 typical

#### Spurious responses

Residual responses, 10 MHz to 3.8 GHz (1.5 kHz res BW)	
10 MHz BW	< −78 dBm typical
25 MHz BW	< −77 dBm typical
40 MHz BW	< −81 dBm typical
Other spurious, $f \geq 10$ MHz from carrier	< −67 dBc typical

#### Phase noise (noise sidebands (CF = 1 GHz))

10 kHz offset	< −104 dBc/Hz typical
1 MHz offset	< −130 dBc/Hz typical

# Vector Signal Generator Performance

## Performance

Arb sample rate range and bandwidth	
Clock rate	100 Sa/s to 60 MSa/s
Bandwidth	48 MHz
Arb sample memory (storage capacity)	
	2 GB memory, 256 MSa of IQ data

## Frequency specifications

Frequency range	10 MHz to 3.8 GHz (Option 504)
Frequency accuracy	Refer to vector signal analyzer frequency reference accuracy
Frequency resolution	0.01 Hz

## Amplitude specifications

### Output level ranges

RF I/O 1 and 2 <sup>1</sup>	
10 MHz to 3.8 GHz	–120 to –5 dBm typical
RF OUTPUT <sup>2</sup>	
10 MHz to 3.8 GHz	–100 to +10 dBm typical

### Absolute level accuracy

RF I/O 1 and 2; 10 MHz to 3.8 GHz	
–120 to –110 dBm	< ±0.8 dB typical
–110 to –90 dBm	< ±0.3 dB typical
–90 to –5 dBm	< ±0.6 dB, < ±0.3 dB typical
RF OUTPUT; 10 MHz to 3.8 GHz	
–100 to –80 dBm	< ±0.4 dB typical
–80 to –10 dBm	< ±0.6 dB, < ±0.3 dB typical
Setting resolution	0.01 dB
VSWR RF I/O 1 and 2	
10 MHz to 2.7 GHz	< 1.32:1 typical
2.7 to 3.8 GHz	< 1.42:1 typical
VSWR RF OUTPUT	
10 MHz to 2.7 GHz	< 1.2:1 typical
2.7 to 3.8 GHz	< 1.4:1 typical

### Harmonics and spurious

RF OUTPUT; harmonics	
+5 dBm output power	< –30 dBc typical
RF I/O 1 and 2; harmonics	
–10 dBm output power	< –30 dBc typical
RF I/O 1 and 2; RF OUTPUT; non-harmonic spurious (CW mode)	
10 to 375 MHz	< –54 dBc typical
375 MHz to 3.8 GHz	< –51 dBc typical

### Phase noise

RF I/O 1 & 2, –15 dBm; RF OUT, +5 dBm,	
1 MHz offset	
10 MHz to 3 GHz	≤ –123 dBc typical
3 to 3.8 GHz	≤ –118 dBc typical

1. Power level is user-settable from –130 to 0 dBm.

2. Power level is user-settable from –130 to +20 dBm.

# General Specifications

## Power requirements

Voltage and frequency (nominal)	100/120 V, 50/60 Hz, and 220/240 V, 50/60 Hz
Power consumption	350 W maximum

## Data storage

Internal	80 GB (SSD)
External	Supports USB 2.0-compatible memory devices

## Size and weight

Dimensions (H x W x L)	177 x 426 x 368 mm (7.0 x 16.8 x 14.5 in)
Weight	18.6 kg (41 lbs) nominal (net), 32.4 kg (71.4 lbs) nominal (shipping – carton only, no accessories included)

## Environmental characteristics

Operating temperature	+5 to +50 °C
Storage temperature	–40 to +65 °C
EMC	<p>Complies with European EMC Directive 2004/108/EC</p> <ul style="list-style-type: none"><li>• IEC/EN 61326-1 or IEC/EN 61326-2-1</li><li>• CISPR Pub 11 Group 1, class A</li><li>• AS/NZS CISPR 11:2002</li><li>• ICES/NMB-001</li></ul> <p>This ISM device complies with Canadian ICES-001 Cet appareil ISM est conforme a la norme NMB-001 du Canada</p>
Environmental stress	<p>Samples of this product have been type tested in accordance with the Agilent Environmental Test Manual and verified to be robust against the environmental stresses of storage, transportation, and end-use; those stresses include, but are not limited to, temperature, humidity, shock, vibration, altitude, and power line conditions; test methods are aligned with IEC 60068-2 and levels are similar to MILPRF-28800F Class 3</p>

## Safety

Complies with European Low Voltage Directive 2006/95/EC
IEC/EN 61010-1
Canada: CSA C22.2 No. 61010-1-04
USA: UL Std. 61010-1

## Audio noise

Acoustic noise emission	Geraeuschemission
LpA < 70 dB	LpA < 70 dB
Operator position	Am Arbeitsplatz
Normal position	Normaler Betrieb
Per ISO 7779	Nach DIN 45635 t.19

## Remote programming

GPIO IEEE standard 488.2
LAN 1 RJ45 rear-panel connector
USB-B 1 rear-panel connector

## General Specifications *(con't)*

### Warranty

This test set is supplied with a standard one-year warranty.

### Calibration cycle

The recommended calibration cycle is two years; calibration services are available through Agilent service centers

### Maximum applied reverse power

RF IN/OUT 1 and 2	3 W CW
RF OUT	< +24 dBm CW
RF IN	< +24 dBm CW
RF port isolation	> 45 dB nominal

## Front Panel

### RF IN/OUT 1 and 2

Connector	Type-N female, 50 $\Omega$ nominal
-----------	------------------------------------

### RF IN

Connector	Type-N female, 50 $\Omega$ nominal
-----------	------------------------------------

### RF OUT

Connector	Type-N female, 50 $\Omega$ nominal
-----------	------------------------------------

### USB ports

Master (2 ports)	
Standard	Compatible with USB 2.0
Connector	USB Type-A female
Output current	0.5 A nominal

## Rear Panel

Ext Ref In	
Connector	BNC female, 50 $\Omega$ nominal
Input amplitude range	–5 to 10 dBm nominal
Input frequency	1 to 50 MHz nominal
Frequency lock range	$\pm 5 \times 10^{-6}$ of specified external reference input frequency
10 MHz Out	
Connector	BNC female, 50 $\Omega$ nominal
Output amplitude	$\geq 0$ dBm nominal
Frequency	10 MHz $\pm$ frequency reference accuracy
Trigger 1 and Trigger 2 inputs	
Connector	BNC female
Impedance	$> 10$ k $\Omega$ nominal
Trigger level range	–5 to +5 V
Trigger 1 and Trigger 2 outputs	
Connector	BNC female
Impedance	50 $\Omega$ nominal
Trigger level range	5 V TTL nominal
Sync (reserved for future use)	
Connector	BNC female
Monitor output	
Connector	VGA compatible, 15-pin mini D-SUB
Format	XGA (60 Hz vertical sync rates, non-interlaced) analog RGB
Resolution	1024 x 768
Digital bus (reserved for future use)	
Connector	MDR-80
Analog out (reserved for future use)	
Connector	BNC female
USB 2.0 ports	
Master (4 ports)	
Standard	Compatible with USB 2.0
Connector	USB Type-A female
Output current	0.5 A nominal
Slave (1 port)	
Standard	Compatible with USB 2.0
Connector	USB Type-B female
Output current	0.5 A nominal
GPIB interface	
Connector	IEEE-488 bus connector
GPIB codes	SH1, AH1, T6, SR1, RL1, PP0, DC1, C1, C2, C3, C28, DT1, L4, C0
GPIB mode	Controller or device
LAN TCP/IP interface	
Standard	1000 Base-T
Connector	RJ45 Ethertwist



# U9071A GSM/EDGE/Evo Measurement Application

## Key Specifications<sup>1</sup>

Power versus time (PvT)	
Minimum carrier power at RF input	–28 dBm (RF INPUT port), –14 dBm (RFIO ports)
Absolute power accuracy	±0.4 dB nominal
Power ramp relative accuracy (referenced to mean transmitted power)	
Accuracy	±0.11 dB nominal
Measurement floor	–92 dBm nominal
EDGE error vector magnitude (EVM)	
Carrier power range at RF input	+24 to –24 dBm (RF INPUT port), +33 to –24 dBm (RFIO ports)
EVM, rms	
Operating range	0 to 20% nominal
Accuracy	±0.5% nominal
Floor	0.5% nominal
Frequency error	
Initial frequency error range	±80 kHz nominal
Accuracy	±5 Hz + $tfa^2$
Trigger to T0 time offset	
Relative accuracy	±5.0 ns nominal
Output RF spectrum (ORFS) and EDGE ORFS	
Carrier power range at RF input	+24 to –14 dBm (RF INPUT port), +33 to +1 dBm (RFIO ports)
ORFS absolute RF power accuracy	±0.3 dB nominal
ORFS relative RF power accuracy	±0.3 dB nominal
GSM (GMSK)	
Dynamic range, spectrum due to modulation	
Offset frequency	
600 kHz	77.1 dB nominal
1.2 MHz	81.3 dB nominal
Dynamic range, spectrum due to switching	
Offset frequency	
1.2 MHz	–74.6 dB nominal
1.8 MHz	–76.0 dB nominal
EDGE (NSR 8PSK & narrow QPSK)	
Dynamic range, spectrum due to modulation	
Offset frequency	
600 kHz	76.6 dB nominal
1.2 MHz	80.0 dB nominal
Dynamic range, spectrum due to switching	
Offset frequency	
1.2 MHz	78.2 dB nominal
1.8 MHz	87.2 dB nominal

1. Specifications apply for frequencies between 380 to 960 MHz and 1710 to 1990 MHz.

2.  $tfa$  = transmitter frequency x frequency reference accuracy.

# U9071A GSM/EDGE/Evo Measurement Application

## Key Specifications<sup>1</sup> (con't)

Phase and frequency error (GMSK modulation)	
Carrier power range at RF input	+24 to –38 dBm (RF INPUT port), +33 to –24 dBm (RFIO ports)
Phase error, rms	
Floor	0.3° nominal
Accuracy, rms	
Phase error range 1 to 6°	±0.3° nominal
Frequency error	
Initial frequency error range	±80 kHz nominal
Accuracy	±5 Hz + tfa <sup>2</sup>
IQ origin offset	
Analyzer noise floor	–50 dBc nominal
Trigger to T0 time offset	
Relative accuracy	±5.0 ns nominal

## GSM/EDGE/Evo Source Key Specifications<sup>3</sup>

Signal quality (RF OUTPUT: 0 dBm, RF I/O 1 and 2: –10 dBm)	
Phase error (GMSK)	
RMS	< 0.3° nominal
Peak	< 2.0° nominal
EVM (EDGE)	
RMS	< 3% nominal

1. Specifications apply for frequencies between 380 to 960 MHz, and 1710 to 1990 MHz.

2. tfa = transmitter frequency x frequency reference accuracy.

3. Specifications apply for frequencies between 390 to 1990 MHz.

# U9073A W-CDMA/HSPA+ Measurement Application

## Key Specifications<sup>1</sup>

Channel power	
Absolute power accuracy	$\pm 0.36$ dB typical
Adjacent channel leakage ratio (ACLR) and adjacent channel power ratio (ACPR)	
Dynamic range	71 dB typical
Spectrum emission mask (2.515, 2.715, 3.515, 4.000, 8.000 and 12.00 MHz offset)	
Absolute accuracy	See absolute power accuracy
Relative accuracy	$\pm 0.35$ dB nominal
Dynamic range, relative	79 dB typical
Code domain ( $-25$ dBm $\leq$ mixer level $\leq -15$ dBm, 20 to 30 °C)	
Code domain power	
Relative accuracy	
Code domain power range: 0 to $-40$ dBc	$\pm 0.2$ dB nominal
Symbol power vs. time	
Symbol EVM accuracy: 0 to $-25$ dBc	$\pm 1\%$ nominal
QPSK EVM	
Carrier power range at RF input	+24 to $-34$ dBm (RF INPUT port), +33 to $-20$ dBm (RFIO ports)
EVM accuracy	1% nominal (0 to 25%)
Residual EVM	$< 1.5\%$ typical
Frequency error	
Initial frequency error range	$\pm 30$ kHz
Accuracy	$\pm 5$ Hz + $tfa^2$
IQ origin offset	
Analyzer noise floor	$-50$ dBc nominal

## W-CDMA/HSPA+ Source Key Specifications<sup>3</sup>

Signal quality (RF OUTPUT: 0 dBm, RF I/O 1 and 2: $-10$ dBm)	
Composite EVM	
RMS	$< 1.1\%$ nominal

1. Specifications apply for frequencies between 698 to 960 MHz, and 1427 to 2570 MHz.

2.  $tfa$  = transmitter frequency  $\times$  frequency reference accuracy.

3. Specifications apply for frequencies between 390 to 2715 MHz.

# U9072A cdma2000® Measurement Application and U9076A 1xEV-DO Measurement Application Key Specifications<sup>1</sup>

Channel power	
Absolute power accuracy	$\pm 0.35$ dB typical
Adjacent channel power (ACP)	
ACP relative accuracy Offset $\leq \pm 4$ MHz	$\pm 0.35$ dB nominal
ACP dynamic range 30 kHz integrating bandwidth	$> 70$ dB nominal
Spectrum emission mask (SEM)	
Relative accuracy	$\pm 0.35$ dB nominal
Absolute accuracy	See absolute power accuracy
SEM dynamic range 750 kHz offset	$> 70$ dB nominal
Code domain ( $-25$ dBm $\leq$ mixer level $\leq -15$ dBm, 20 to 30 °C)	
Code domain power	
Relative accuracy	
Code domain power range: 0 to $-40$ dBc	$\pm 0.2$ dB nominal
Symbol power vs. time	
Symbol EVM accuracy: 0 to $-25$ dBc	1% nominal
Modulation accuracy (composite rho)	
Carrier power range at RF input	$+24$ to $-34$ dBm (RF INPUT port); $+33$ to $-20$ dBm (RF I/O)
EVM accuracy	1% nominal (0 to 25%) <sup>2</sup>
Residual EVM	1.5% typical
Rho accuracy	
At rho = 0.99751 (EVM 5%)	$\pm 0.0010$ nominal
Frequency error	
Initial frequency error range	$\pm 400$ Hz
Accuracy	$\pm 10$ Hz + tfa <sup>3</sup>
IQ origin offset	
Analyzer noise floor	$-50$ dBc nominal
DUT maximum offset	$-10$ dBc nominal

1. Specifications apply for frequencies between 410 to 935 MHz, and 1710 to 1980 MHz.

2. The composite EVM accuracy specification applies when the EVM to be measured is well above the measurement floor. When the EVM does not greatly exceed the floor, the errors due to the floor add to the accuracy errors. The errors due to the floor are noise-like and add incoherently with the UUT EVM. The errors depend on the EVM of the UUT and the floor as follows:  
Error =  $\sqrt{(\text{EVM}_{\text{UUT}})^2 + (\text{EVM}_{\text{floor}})^2}$  – EVM<sub>UUT</sub>. For example, if the EVM is 7% and the floor is 2.5% the error due to the floor is 0.43%.

3. tfa = transmitter frequency x frequency reference accuracy.

# cdma2000 and 1xEV-DO Source Key Specifications<sup>1</sup>

Signal quality (RF OUTPUT: 0 dBm, RF I/O 1 and 2: –20 dBm)	
Composite EVM	
RMS	< 1.1% nominal

## U9075A Mobile WiMAX™ Measurement Application Key Specifications<sup>2</sup>

Modulation analysis	
RCE (EVM) floor CF ≤ 3 GHz	–45 dB nominal
Channel power	
Absolute accuracy	See VSA performance, nominal
Minimum power at RF input	–35 dBm nominal
Measurement floor	–79.7 dBm nominal
Spectrum emission mask	
Dynamic range, relative	77.4

1. Specifications apply for frequencies between 390 to 2170 MHz.

2. Specifications apply for frequencies between 2300 to 2800 MHz, and 3300 to 3600 MHz.

# U9080A LTE FDD Measurement Application

## Key Specifications<sup>1</sup>

Modulation accuracy (composite rho)	
3GPP standards supported	3GPP TS 36.201 V9.1.0 (2010-03), 3GPP TS 36.211 V9.1.0 (2010-03), 3GPP TS 36.212 V9.3.0 (2010-03), 3GPP TS 36.213 V9.2.0 (2010-06), 3GPP TS 36.214 V9.2.0 (2010-06), 3GPP TS 36.101 V9.4.0 (2010-06)
Signal structure	FDD frame structure Type 1
Signal bandwidth	1.4 MHz (6 RB), 3 MHz (15 RB), 5 MHz (25 RB), 10 MHz (50 RB), 15 MHz (75 RB), 20 MHz (100 RB)
Modulation formats and sequences	BPSK, BPSK with I & Q CDM, QPSK, 16QAM, 64QAM, PRS, CAZAC (Zadoff-Chu)
Physical channels	
Downlink	PBCH, PCFICH, PHICH, PDCCH, PDSCH
Uplink	PUCCH, PUSCH, PRACH
Physical signals	
Downlink	P-SS, S-SS, RS
Uplink	S-RS, PUCCH-DMRS, PUSCH-DMRS
Channel power	
Absolute power accuracy	±0.4 dB nominal
Adjacent channel power	
Minimum power at RFIO input	−5 dBm nominal
Dynamic range	
E-UTRA	70 dB nominal
UTRA	74 dB nominal
Error vector magnitude (EVM)	
Residual EVM	
Signal bandwidth	
5 MHz	−45 dB (0.45%) nominal
10 MHz	−45 dB (0.45%) nominal
Frequency error	
Frequency error, lock range	±2.5 x subcarrier spacing (nominal), default is 15 kHz
Frequency error accuracy	±1 Hz + tfa <sup>2</sup>

1. Specifications apply for frequencies between 824 to 960 MHz, and 1710 to 2690 MHz.

2. tfa = transmitter frequency x frequency reference accuracy.

# U9081A *Bluetooth*<sup>®</sup> Measurement Application

## Key Specifications<sup>1</sup>

Modulation characteristics	
Deviation range	±250 kHz nominal
Deviation resolution	100 Hz nominal
Measurement accuracy	±100 Hz + $tfa^2$ nominal
Initial carrier frequency tolerance	
Measurement range	Nominal channel freq ±100 kHz nominal
Measurement accuracy	±100 Hz + $tfa^2$ nominal
Carrier frequency drift	
Measurement range	±100 kHz nominal
Measurement accuracy	±100 Hz + $tfa^2$ nominal
EDR modulation accuracy	
Range (rms DEVM)	0 to 12% nominal
Floor	1.5% nominal
Accuracy	±1.2% <sup>3</sup> nominal

1. Specifications apply for frequencies between 2400 to 2486 MHz.

2.  $tfa$  = transmitter frequency x frequency reference accuracy.

3. The accuracy specification applies when the EVM to be measured is well above the measurement floor.



**[www.agilent.com/find/myagilent](http://www.agilent.com/find/myagilent)**

A personalized view into the information most relevant to you.



Agilent Advantage Services is committed to your success throughout your equipment's lifetime. To keep you competitive, we continually invest in tools and processes that speed up calibration and repair and reduce your cost of ownership. You can also use Infoline Web Services to manage equipment and services more effectively. By sharing our measurement and service expertise, we help you create the products that change our world.

**[www.agilent.com/find/advantageservices](http://www.agilent.com/find/advantageservices)**



cdma2000 is a US registered certification mark of the Telecommunications Industry Association..

Bluetooth and the Bluetooth logos are trademarks owned by Bluetooth SIG, Inc., U.S.A. and licensed to Agilent Technologies, Inc.

WiMAX, Mobile WiMAX, WiMAX Forum, the WiMAX Forum logo, WiMAX Forum Certified, and the WiMAX Forum Certified logo are US trademarks of the WiMAX Forum.

**[www.agilent.com](http://www.agilent.com)**

**[www.agilent.com/find/E6607B](http://www.agilent.com/find/E6607B)**

**[www.agilent.com/find/EXT](http://www.agilent.com/find/EXT)**

For more information on Agilent Technologies' products, applications or services, please contact your local Agilent office. The complete list is available at:

**[www.agilent.com/find/contactus](http://www.agilent.com/find/contactus)**

#### **Americas**

Canada	(877) 894 4414
Brazil	(11) 4197 3600
Mexico	01800 5064 800
United States	(800) 829 4444

#### **Asia Pacific**

Australia	1 800 629 485
China	800 810 0189
Hong Kong	800 938 693
India	1 800 112 929
Japan	0120 (421) 345
Korea	080 769 0800
Malaysia	1 800 888 848
Singapore	1 800 375 8100
Taiwan	0800 047 866
Other AP Countries	(65) 375 8100

#### **Europe & Middle East**

Belgium	32 (0) 2 404 93 40
Denmark	45 45 80 12 15
Finland	358 (0) 10 855 2100
France	0825 010 700*
	*0.125 €/minute
Germany	49 (0) 7031 464 6333
Ireland	1890 924 204
Israel	972-3-9288-504/544
Italy	39 02 92 60 8484
Netherlands	31 (0) 20 547 2111
Spain	34 (91) 631 3300
Sweden	0200-88 22 55
United Kingdom	44 (0) 118 927 6201

*For other unlisted countries:*

**[www.agilent.com/find/contactus](http://www.agilent.com/find/contactus)**

Revised: October 11, 2012

Product specifications and descriptions in this document subject to change without notice.

© Agilent Technologies, Inc. 2012  
Published in USA, November 13, 2012  
5990-9543EN



**Agilent Technologies**