# THANK YOU

Y1700A-002 Two-Stack Rackmount Kit for USB-Instruments Quick Start Guide

Congratulations, with this instrument you will achieve fast, accurate results with confidence.

CAUTION Please use ESD precautions when handling and operating.

2. Install rack mount support nuts 0590-0804 (x4) and install the rack mount rails (x2) using the 3030-1802 screws (x4). Tighten the screws to 2.37 N-m. to secure the rackmount rails using a 1/8 inch hex driver.

3. Remove rubber feet and set screws with T-10 Torx driver and discard.

4. Install each instrument 2-stack onto the rackmount tray by using the 0515-0372 (x4) screws. Using a T-10 Torx driver, torque the screws to 1.02 N-m.

Refer to step 6.

5. Slide tray with instruments onto rails.

Refer to step 2.

1. Remove and discard filler panel* by removing screws (not shown) and sliding down and away from the rackmount front panel.

Refer to step 2.

Refer to step 4.

Tools Needed:
- T-10 Torx driver
- Philips head driver
- 1/8 inch hex driver

6. Install front panel nuts 0590-0804 (x4) into rack and tighten the 3030-1768 screws (x4) to 2.37 N-m. to secure the rackmount tray using Phillips driver.

Installation of Two-High Rack Mount with Two Instruments
*Filler panel is only removed/discarded in a Two-unit installation.

keysight.com

KEYSIGHT TECHNOLOGIES

Find a Manual · Register Your Instrument
Browse Application Notes
Request Repair or Calibration
View Discussion Forums · Updates

www.keysight.com/find/

KEYSIGHT
TECHNOLOGIES

Y1700-90002

www.keysight.com