

Keysight N9030B PXA Signal Analyzer

Option BU7

85 MHz to 160 MHz Analysis Bandwidth

Notices

© Copyright 2016-2022 Keysight Technologies, Inc.

The information contained in this document is subject to change without notice.

Keysight Technologies makes no warranty of any kind with regard to this material, including but not limited to, the implied warranties of merchantability and fitness for a particular purpose.

Keysight Technologies shall not be liable for errors contained herein or for incidental or consequential damages in connection with the furnishing, performance, or use of this material.

Manual Part Number

N9030-90076

Edition

Edition 1, July 2022

Supersedes February 2016

Printed in USA/Malaysia

Published by:

Keysight Technologies, Inc.

1400 Fountaingrove Parkway

85 MHz to 160 MHz Analysis Bandwidth Retrofit Kit

Products Affected:	N9030B PXA Signal Analyzer with Option B85
Serial Numbers:	All
To Be Performed By:	(X) Keysight Service Center (X) Personnel Qualified by Keysight (X) Customer
Estimated Installation Time:	0.5 Hours
Estimated Adjustment and Verification Time:	0 Hours

Introduction

This kit contains the instructions required to increase the analysis bandwidth on instruments that currently have option B85. Option B85 already provides the hardware for 160 MHz analysis bandwidth. This retrofit kit installs the B1X and B1Y license files that extends the analysis bandwidth to 160 MHz.

NOTE

1. The latest revision of the X-Series signal analyzer software may be downloaded from:
http://www.keysight.com/find/Xseries_software.
2. This option is licensed for one instrument model/serial number combination. The license key will only install on the designated instrument.
3. Option BU7 is an ordering number only. The option BU7 will not appear on the instrument.
4. It is assumed that prior to this installation, option B85 is installed, and that the 85 MHz analysis bandwidth “IF path” is functional and meets all specifications.

Contents

Quantity	Description	Keysight Part Number
1	Installation Note	This note
1	Option Upgrade Entitlement Certificate	-----

Tools Required

- Personal computer with internet access and USB port.
- USB storage device with > 2 GB free memory
- Keysight Calibration and Adjustment software, N7814A TME Calibration Application version E.16.00 or later
- Test equipment and computer supported by the X-Series Performance Tests and Adjustment software.

Installation Procedure over USB

1. Locate the Option Upgrade Entitlement Certificate from the kit.
2. Redeem the Option Upgrade Entitlement Certificate by following the instructions on the Certificate.
3. After redeeming your Option Upgrade Entitlement Certificate you will receive an email with an attached License File.
4. Locate a USB storage device. Perform a virus check on this device before use.
5. Save the License File to the root directory of the USB Storage Device.
6. Connect the USB Storage Device to the signal analyzer USB port. Windows will detect the new hardware and may display the configuration menu shown in **Figure 1**. This menu may be configured according to your preferences.

Figure 1 USB Storage Device Configuration Menu



7. The signal analyzer will automatically consume the License File. (This may take a few minutes) When the License File is consumed the Keysight License Manager will display a “Successful License Installation” message similar to the one shown in **Figure 2**.

Figure 2 Successful License Installation



Alternate Installation Procedure

The License File can be manually installed over USB or LAN by placing the license file in the following folder on the signal analyzer

C:\Program Files\Agilent\licensing

Verify the Installation

1. Cycle power on the signal analyzer.
2. Press **System, Show System** to display a list of installed options.
3. Verify that the newly installed options N9030B-B1X and N9030B-B1Y appear on the list.

Functional Test

1. Tap the message balloon at the bottom of the main display. Tap **Clear Message Queue**. This will remove out-of-date errors.
2. Press **System, Alignments, Align Now, Align Now All**.
3. Watch for any errors during the instrument alignment.
4. Tap the message balloon at the bottom of the main display to view the instrument error log.
5. Verify that there were no errors during the alignment.

Optional Information

Select the 160 MHz IF Path.

1. Press **MODE/MEAS, I/Q Analyzer (Basic), OK**.
2. Press **MEAS SETUP**.
3. Press **IF Path, IF Path**.
4. The various IF path selections appear on the softkeys. Verify 160 MHz is present.

Utilities, Adjustments, and Performance Verification Tests

Calibration Software and specified test equipment is required to perform the adjustments, and can be used to automate the performance verification testing. Information on how to obtain this software can be found at

<http://www.keysight.com/find/calibrationsoftware>

Utilities Required

None

Adjustments Required

None

Performance Testing Required

- IF Frequency Response
- Noise Density
- Spurious Response

A full calibration is required to assure the instrument meets all specifications

The end user must ultimately determine whether they want a full calibration to be performed after the installation of this upgrade or not. If a full calibration is required, arrangements regarding the level of calibration must be made between the end user and the calibration provider.

For assistance, contact your nearest Keysight Technologies Sales and Service Office. To find your local Keysight office access the following URL:

<http://www.keysight.com/find/assist>

