

Specification  
Guide

M9010A, M9018B, M9019A

# Keysight PXIe Chassis Family





# Notices

© Keysight Technologies, Inc. 2018

No part of this manual may be reproduced in any form or by any means (including electronic storage and retrieval or translation into a foreign language) without prior agreement and written consent from Keysight Technologies, Inc. as governed by United States and international copyright laws.

## Manual Part Number

M9019-90015

## Edition

Third Edition, May 2018

## Printed in

Malaysia

## Published by

Keysight Technologies, Inc.  
900 S. Taft Ave.  
Loveland, CO 80537 USA

## Trademarks

PICMG<sup>®</sup>, Compact PCI<sup>®</sup> are registered trademarks of the PCI Industrial Computer Manufacturers Group.

PCI-SIG<sup>®</sup>, PCI Express<sup>®</sup>, and PCIe<sup>®</sup> are registered trademarks of PCI-SIG.

LabVIEW is a registered trademark of National Instruments

## Sales and Technical Support

To contact Keysight for sales and technical support, refer to the support links on the following Keysight websites:

[www.keysight.com/find/M9010A](http://www.keysight.com/find/M9010A)

[www.keysight.com/find/M9018B](http://www.keysight.com/find/M9018B)

[www.keysight.com/find/M9019A](http://www.keysight.com/find/M9019A)

(product-specific information and support, software and documentation updates)

[www.keysight.com/find/assist](http://www.keysight.com/find/assist) (world-wide contact information for repair and service)

## Declaration of Conformity

Declarations of Conformity for this product and for other Keysight products may be downloaded from the Web. Go to <http://keysight.com/go/conformity> and click on “Declarations of Conformity.” You can then search by product number to find the latest Declaration of Conformity.

## Technology Licenses

The hardware and/or software described in this document are furnished under a license and may be used or copied only in accordance with the terms of such license.

## Warranty

THE MATERIAL CONTAINED IN THIS DOCUMENT IS PROVIDED “AS IS,” AND IS SUBJECT TO BEING CHANGED, WITHOUT NOTICE, IN FUTURE EDITIONS. FURTHER, TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, KEYSIGHT DISCLAIMS ALL WARRANTIES, EITHER EXPRESS OR IMPLIED, WITH REGARD TO THIS MANUAL AND ANY INFORMATION CONTAINED HEREIN, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. KEYSIGHT SHALL NOT BE LIABLE FOR ERRORS OR FOR INCIDENTAL OR CONSEQUENTIAL DAMAGES IN CONNECTION WITH THE FURNISHING, USE, OR PERFORMANCE OF THIS DOCUMENT OR OF ANY INFORMATION CONTAINED HEREIN. SHOULD KEYSIGHT AND THE USER HAVE A SEPARATE WRITTEN AGREEMENT WITH WARRANTY TERMS COVERING THE MATERIAL IN THIS DOCUMENT THAT CONFLICT WITH THESE TERMS, THE WARRANTY TERMS IN THE SEPARATE AGREEMENT SHALL CONTROL.

Keysight Technologies does not warrant third-party system-level (combination of chassis, controllers, modules, etc.) performance, safety, or regulatory compliance unless specifically stated.

## DFARS/Restricted Rights Notices

If software is for use in the performance of a U.S. Government prime contract or subcontract, Software is delivered and licensed as “Commercial computer software” as defined in DFAR 252.227-7014 (June 1995), or as a “commercial item” as defined in FAR 2.101(a) or as “Restricted computer software” as defined in FAR 52.227-19 (June 1987) or any equivalent agency regulation or contract clause. Use, duplication or disclosure of Software is subject to Keysight Technologies’ standard commercial license terms, and non-DOD Departments and Agencies of the U.S. Government will receive no greater than Restricted Rights as defined in FAR 52.227-19(c)(1-2) (June 1987). U.S. Government users will receive no greater than Limited Rights as defined in FAR 52.227-14 (June 1987) or DFAR 252.227-7015 (b)(2) (November 1995), as applicable in any technical data.



# Contents

How to Use this Document . . . . .	7
Technical Specification and Characteristics . . . . .	8
Terminology definitions . . . . .	8
Requirements for Temperature Control . . . . .	8
Additional Information . . . . .	8
M9010A Technical Specifications . . . . .	9
Recommended Configuration . . . . .	13
Multi-chassis Configuration . . . . .	13
M9018B Technical Specifications . . . . .	14
Recommended Configuration . . . . .	18
Multi-chassis Configuration . . . . .	18
M9019A Technical Specifications . . . . .	19
Recommended Configuration . . . . .	23
Multi-chassis Configuration . . . . .	23



# M9010A, M9018B, M9019A PXIe Chassis Specification Guide

## How to Use this Document

This document contains technical specifications and characteristics for all versions, to the publication date of this Specification Guide, of the M9010A, M9018B, and M9019A PXIe chassis.

### **NOTE**

The specification, characteristics, and typical data in this version of the Specification Guide supersedes the information in all previous versions.

---

Some specifications in this document may apply only to a specific manufacturing version of the chassis. When a specification applies only to a specific version, the version number is listed next to that specification in the table.

# Technical Specification and Characteristics

## Terminology definitions

Term	Definition
Specification (Spec.)	<p>Warranted performance. Specifications include guard bands to account for the expected statistical performance distribution, measurement uncertainties, and changes in performance due to environmental conditions. All specifications and characteristics apply over the operating environment outlined in the “Environmental and Regulatory” sections of this specification Guide. In addition, the following conditions must be met:</p> <ul style="list-style-type: none"> <li>• Instrument is within its calibration cycle if calibration is required.</li> <li>• Instrument has been stored for a minimum of one hour within the operating temperature range prior to turn-on and after a 30 minute warm-up period.</li> </ul>
Characteristic (Char.)	<p>Characteristics describe product performance that is useful in the application of the product, but that is not covered by the warranty. Characteristics are often referred to as Typical or Nominal values.</p>
Typical (Typ.)	<p>Expected performance of an average unit when operated over a 20 to 30 °C temperature range. Typical performance is not warranted. The instrument must be within its calibration cycle if calibration is required.</p>
Nominal (Nom.)	<p>Nominal describes representative performance that is useful in the application of the product when operated over a 20 to 30 °C temperature range. Nominal performance is not warranted.</p>

## Requirements for Temperature Control

For optimal cooling and proper operating temperatures,

- Any empty module slot in the chassis should be fitted with a slot blocker (from kit Y1212A) and EMC filler panel (from kit Y1213A).
- If a PCIe Cable Interface module is used in place of a controller, the open area to the left of the interface module should be filled with the filler panel and bracket (from kit Y1214B).
- All lower and side vents should remain unobstructed.
- The chassis fan speed should be set to HIGH.

## Additional Information

- All data are measured from multiple units at room temperature and are representative of product performance within the controlled temperature range unless otherwise noted.
- The specifications contained in this document are subject to change.



TECHNICAL SPECIFICATIONS AND CHARACTERISTICS

M9010A Technical Specifications

Chassis characteristics	
Standards compliance	
	PXI-5 PXI Express hardware specification PXI-1 hardware specification rev 2.2 PICMG EXP.0 R2.0 specification
Backplane	
Module size	3U
Total slots	10
Hybrid compatible slots	8
PXIe system slot	1 (with three system expansion slots)
PXIe timing slot	1 (also accepts PXIe module)
Module compatibility	PXIe, PXI-Hybrid, PXI-1 (J1 only), and cPCI (J1 only)
System slot link configuration (fixed)	2-Link configuration: x8, x16
Backplane speed	PCIe revision 3.0 (Gen 3)
Mechanical	
Size	322.5 mm W x 194.8 mm H x 552.5 mm D (with feet installed) 322.5 mm W x 177.8 mm H x 552.5 mm D (with feet removed)
Weight (without modules)	14.02 kg (30.91 lbs)

Power supply characteristics	
AC input	
Operating voltage/power (low-line) <sup>1</sup>	100/120 V, 734 W Maximum
Operating voltage/power (high-line) <sup>1</sup>	220/240 V, 1100 W Maximum
Input frequency range	50/60 Hz
Mains supply voltage fluctuations are not to exceed $\pm 10\%$ of the nominal voltage.	
Transient over-voltages typically present on the Mains supply (installation CAT II).	
Over current protection	Internal fuse in line
Available DC output power (for module slots)	
Total DC power <sup>2</sup>	
220/240 V input:	830 W
100/120 V input:	470 W

1. Auto switching between high line and low line.

2. No derating required for temperature or altitude.

## TECHNICAL SPECIFICATIONS AND CHARACTERISTICS

Power supply characteristics (continued)					
DC Supplies					
Voltage	Maximum Current <sup>1</sup>		Load Regulation	Maximum ripple and noise (20 MHz BW)	
	45 °C, <10kft	50 °C, 10kft			
+3.3 V	58.8 A	48.8 A	5%	1.5% (pk-pk)	
+5 V	36 A	31.5 A	5%	1% (pk-pk)	
+12 V	40 A	35 A	5%	1% (pk-pk)	
-12 V	4 A	3.5 A	5%	1% (pk-pk)	
5 Vaux	2 A	2 A	5%	50mV (pk-pk)	
Backplane pin current capacity					
Slot	+3.3 V	+5 V	+12 V	-12V	5 Vaux
System controller slot	9 A	9 A	11 A	0 A	1 A
System timing/PXle slot	6 A	0 A	4 A	0 A	1 A
PXle hybrid slot	6 A	6 A	4 A	1 A	1 A
Chassis cooling and power dissipation characteristics					
Slot airflow direction			Bottom of module to top of module		
Chassis cooling intake			Rear of chassis		
Chassis cooling exhaust			Front top of chassis		
Chassis cooling fans			Two 120 cfm fans on rear panel with HIGH/AUTO speed selector		
Power dissipation, system slot			140 W max		
Power dissipation, user slot			42 W max <sup>2</sup>		
Power dissipation, timing slot			42 W max <sup>2</sup>		

1. The total power supplied for all rails must not exceed 470 W (100/120 V) or 830 W (220/240 V).

2. Maximum per slot power dissipation at 55 °C with 15 °C temperature rise; requires: a) that the chassis bottom is not blocked (1U rack space below or sitting on bench with feet extended) OR b) two air inlet modules in slots 9, 10, or 11, and a slot blocker in empty controller slots. Module cooling can be impacted by each module's resistance to air flow.

## TECHNICAL SPECIFICATIONS AND CHARACTERISTICS

Clocks and Triggers	
10 MHz system clock (PXI_CLK10)	
Maximum slot-to-slot skew	200 ps
Accuracy	30 ppm
Output amplitude (10 MHz REF Out BNC)	1 V pk-pk $\pm 20\%$ square-wave into $50\Omega$
	2 V pk-pk unloaded
Output impedance (10 MHz REF Out BNC)	$50\Omega \pm 5\Omega$
100 MHz system clock (PXIe_CLK100)	
Maximum slot-to-slot skew	125 ps
Accuracy	30 ppm
External 10 MHz clock source input requirements	
Frequency input	10 MHz $\pm 100$ ppm
Input signal (10 MHz REF In BNC)	100 mVPP to 5 Vpp (square or sine wave)
Input signal (PXI timing slot PXI_CLK10_IN)	5V or 3.3 V TTL signal
PXI star trigger	
Maximum slot-to-slot skew	250 ps
PXI differential star triggers	
Maximum slot-to-slot skew	150 ps
Maximum differential skew	25 ps
Front panel triggers (trig 1 and trig 2 SMBs)	
Direction control	Input or Output (configurable)
Output level	3.3 V CMOS (TTL Compatible, 5 V tolerant)
Output impedance	$50\Omega$ (typ)
Output trigger source	PXI_Trig0 - PXI_Trig7 (Segment 1)
Input level	3.3 V CMOS (TTL Compatible, 5 V tolerant)
Input impedance	$3\text{ k}\Omega$ (typ)
Input trigger destination	PXI_Trig0 - PXI_Trig7 (Segment 1)
Input threshold	1.65 V (typ)
Minimum swing	250 mV
Minimum pulse width	100 ns (typ)

## TECHNICAL SPECIFICATIONS AND CHARACTERISTICS

Environmental Characteristics <sup>1,2</sup>		
Operating and storage conditions		
	Operating	Storage
Temperature	0 °C to 55 °C	-40 °C to 70 °C
Altitude	Up to 10,000 ft (3048 m)	Up to 15,000 ft (4572 m)
Humidity	Type-tested at 95% (non-condensing)	
Vibration		
	Operating random vibration: type-tested at 5 to 500 Hz, 0.21 g rms	
	Survival random vibration: type-tested at 5 to 500 Hz, 2.09 g rms	
Acoustical emissions (referenced to 1 pW)		
	Auto fan (25 °C ambient)	High Fan
Sound pressure level <sup>3</sup>	45 dBA	58 dBA
Sound Power	50 dBA	66 dBA
Regulatory Characteristics		
Safety	Complies with the essential requirements of the European LVD Directive of the following standards (dates and editions are cited in the Declaration of Conformity):	
	<ul style="list-style-type: none"> <li>- IEC/EN 61010-1</li> <li>- Canada: CSA C22.2 No. 61010-1</li> <li>- USA: UL std no. 61010-1</li> </ul>	
Acoustic statement (European Machinery Directive)	Acoustic noise emission LpA < 70 dB Operator position Normal operation mode per ISO 7779	
EMC	Complies with European EMC Directive of the following standards (dates and editions are cited in the Declaration of Conformity):	
	<ul style="list-style-type: none"> <li>- IEC/EN 61326-1</li> <li>- CISPR pub 11 group 1, class A</li> <li>- AS/NZS CISPR 11</li> <li>- ICES/NMB-001</li> </ul>	
	This ISM device complies with Canadian ICES-001. Cet appareil ISM est conforme a la norme NMB-001 du Canada	

1. Samples of this product have been type tested in accordance with the Keysight Environmental Test Manual and verified to be robust against the environmental stresses of storage, transportation and end-use. Those stresses include but are not limited to temperature, humidity, shock, vibration, altitude and power line conditions.

2. Test Methods are aligned with IEC 60068-2 and levels are similar to MIL-PRF-28800F Class 3.

3. At operator position

## Recommended Configuration

### **Configure the Keysight M9010A PXIe chassis as follows:**

- Select a PXIe system module (the Keysight M9022A, M9023A or M9024A System Interface Modules are recommended) or embedded controller (M9037A).
- If an external computer is being used, select an appropriate PC interface card (the Keysight M9048B or M9049A Host Adapter Interface modules are recommended).
- Select an appropriate cable to connect the computer interface board to the chassis interface (the Y1202A is recommended to connect the M9048B and M9022A).
- Select accessories as required.

## Multi-chassis Configuration

The M9010A can be used in multi-chassis configurations with other PXIe chassis (including the M9010A, M9018A, M9018B, M9019A and the AXIe chassis (M9502A and M9505A). In general, up to four chassis can be connected together depending on the controller and operating system used. Different topologies include cascade and star.

## M9018B Technical Specifications

Chassis characteristics	
Standards compliance	
	PXI-5 PXI Express hardware specification PXI-1 hardware specification rev 2.2 PICMG EXP.0 R2.0 specification
Backplane	
Module size	3U
Total slots	18
Hybrid compatible slots	16
PXle system slot	1 (with three system expansion slots)
PXle timing slot	1 (also accepts PXle module)
Module compatibility	PXle, PXI-Hybrid, PXI-1 (J1 only), and cPCI (J1 only)
System slot link configuration (configurable)	2-Link (2x8) and 4-Link (4x4) plus M9021A configuration (1x8)
Backplane speed	PCIe revision 2.0 (Gen 2)
Mechanical	
Size	444.4 mm W x 194.8 mm H x 466 mm D (with feet installed) 444.4 mm W x 177.8 mm H x 466 mm D (with feet removed) 4U x 1 rack width
Weight (without modules)	13.5 kg (29.8 lbs)
Power supply characteristics	
AC input	
Operating voltage/power (low-line) <sup>1</sup>	100/120 V, 1200 W Maximum
Operating voltage/power (high-line) <sup>1</sup>	220/240 V, 1300 W Maximum
Input frequency range	50/60 Hz
Mains supply voltage fluctuations are not to exceed $\pm 10\%$ of the nominal voltage.	
Transient over-voltages typically present on the Mains supply (installation CAT II).	
Over current protection	Internal fuse in line
Available DC output power (for module slots)	
Total DC power <sup>2</sup>	
220/240 V input:	858 W
100/120 V input:	708 W

### Power supply characteristics

1. Auto switching between high line and low line.
2. No derating required for temperature or altitude.

DC Supplies					
Voltage	Maximum Current <sup>1</sup>		Load Regulation	Maximum ripple and noise (<20 MHz BW)	
	45 °C, <10kft	50 °C, 10kft			
+3.3 V	70 A	67 A	5%	1.5% (pk-pk)	
+5 V	60 A <sup>2</sup>	52.5 A <sup>2</sup>	5%	1% (pk-pk)	
+12 V	57.4 A <sup>2</sup>	49.9 A <sup>2</sup>	5%	1% (pk-pk)	
-12 V	4 A	4 A	5%	1% (pk-pk)	
5 Vaux	2 A	2 A	5%	50mV (pk-pk)	
Backplane pin current capacity					
Slot	+3.3 V	+5 V	+12 V	-12V	5 Vaux
System controller slot	9 A	9 A	11 A	0 A	1 A
System timing/PXle slot	6 A	0 A	4 A	0 A	1 A
PXle hybrid slot	6 A	6 A	4 A	1 A	1 A
Chassis cooling and power dissipation characteristics					
Slot airflow direction			Bottom of module to top of module		
Chassis cooling intake			Bottom of front bezel, side panels, and bottom panel of chassis		
Chassis cooling exhaust			Rear of chassis		
Chassis cooling fans			Three 186 cfm fans on rear panel with HIGH/AUTO speed selector		
Power dissipation, system slot			140 W max		
Power dissipation, user slot			42 W max <sup>3</sup>		
Power dissipation, timing slot			42 W max <sup>3</sup>		

1. The total power supplied for all rails must not exceed 708 W (100/120 V) or 858 W (220/240 V).
2. The total power supplied for 5 V and 12 V rails must not exceed 689 W at 45 °C, <10k ft, or 599 W at 50 °C, 10k ft.
3. Maximum per slot power dissipation at 55 °C with 15 °C temperature rise; requires: a) that the chassis bottom is not blocked (1U rack space below or sitting on bench with feet extended) OR b) two air inlet modules in slots 9, 10, or 11, and a slot blocker in empty controller slots. Module cooling can be impacted by each module's resistance to air flow.

Clocks and Triggers	
10 MHz system clock (PXI_CLK10)	
Maximum slot-to-slot skew	155 ps
Accuracy	30 ppm
Output amplitude (10 MHz REF Out BNC)	1 V pk-pk 20% square-wave into 50Ω
	2 V pk-pk unloaded
Output impedance (10 MHz REF Out BNC)	50Ω ±5Ω
100 MHz system clock (PXIe_CLK100)	
Maximum slot-to-slot skew	125 ps
Accuracy	30 ppm
External 10 MHz clock source input requirements	
Frequency input	10 MHz ±100 ppm
Input signal (10 MHz REF In BNC)	100 mVPP to 5 Vpp (square or sine wave)
Input signal (PXI timing slot PXI_CLK10_IN)	5V or 3.3 V TTL signal
PXI star trigger	
Maximum slot-to-slot skew	250 ps
PXI differential star triggers	
Maximum slot-to-slot skew	150 ps
Maximum differential skew	25 ps
Front panel triggers (trig 1 and trig 2 SMBs)	
Direction control	Input or Output (configurable)
Output level	3.3 V CMOS (TTL Compatible, 5 V tolerant)
Output impedance	PXI_Trig0 – PXI_Trig7 (Segment 2)
Output trigger source	316 Ω pulled up to 3.3 V
Input level	3.3 V CMOS (TTL Compatible, 5 V tolerant)
Input impedance	3 kΩ (typ)
Input trigger destination	PXI_Trig0 – PXI_Trig7 (Segment 2)
Input threshold	1.65 V (typ)
Minimum swing	250 mV
Minimum pulse width	100 ns (typ)



Environmental Characteristics <sup>1,2</sup>		
Operating and storage conditions		
	Operating	Storage
Temperature	0 °C to 55 °C	-40 °C to 70 °C
Altitude	Up to 10,000 ft (3048 m)	Up to 15,000 ft (4572 m)
Humidity	Type-tested at 95% (non-condensing)	
Vibration		
	Operating random vibration: type-tested at 5 to 500 Hz, 0.21 g rms	
	Survival random vibration: type-tested at 5 to 500 Hz, 2.09 g rms	
Acoustical emissions (referenced to 1 pW)		
	Auto fan (25°C ambient)	High Fan
Sound pressure level <sup>3</sup>	53 dBA	69 dBA
Sound Power	59 dBA	77 dBA
Regulatory Characteristics		
Safety	Complies with the essential requirements of the European EMC Directive as well as current editions of the following standards (dates and editions are cited in the Declaration of Conformity):	
	<ul style="list-style-type: none"> <li>- IEC/EN 61010-1</li> <li>- Canada: CSA C22.2 No. 61010-1</li> <li>- USA: UL std no. 61010-1</li> </ul>	
Acoustic statement (European Machinery Directive)	Acoustic noise emission LpA < 70 dB Operator position Normal operation mode per ISO 7779	
EMC	Complies with European EMC Directive of the following standards (dates and editions are cited in the Declaration of Conformity):	
	<ul style="list-style-type: none"> <li>- IEC/EN 61326-1</li> <li>- CISPR pub 11 group 1, class A</li> <li>- AS/NZS CISPR 11</li> <li>- ICES/NMB-001</li> </ul>	
	This ISM device complies with Canadian ICES-001. Cet appareil ISM est conforme a la norme NMB-001 du Canada	

1. Samples of this product have been type tested in accordance with the Keysight Environmental Test Manual and verified to be robust against the environmental stresses of storage, transportation and end-use. Those stresses include but are not limited to temperature, humidity, shock, vibration, altitude and power line conditions.

2. Test Methods are aligned with IEC 60068-2 and levels are similar to MIL-PRF-28800F Class 3.

3. At operator position

## Recommended Configuration

### **Configure the Keysight M9018B PXIe chassis as follows:**

- Select a PXIe system module (the Keysight M9022A, M9023A, or M9024A System Interface Modules are recommended) or embedded controller (M9037A).
- If an external computer is being used, select an appropriate PC interface card (the Keysight M9048B or M9049A Host Adapter Interface modules are recommended).
- Select an appropriate cable to connect the computer interface board to the chassis interface (the Y1202A is recommended to connect the M9048B and M9022A).
- Select accessories as required.

## Multi-chassis Configuration

The M9018B can be used in multi-chassis configurations with other PXIe chassis (including the M9010A, M9018A, M9018B, M9019A and the AXIe chassis (M9502A and M9505A). In general, up to four chassis can be connected together depending on the controller and operating system used. Different topologies include cascade and star.

## M9019A Technical Specifications

Chassis characteristics	
Standards compliance	
PXI-5 PXI Express hardware specification PXI-1 hardware specification rev 2.2 PICMG EXP.0 R2.0 specification	
Backplane	
Module size	3U
Total slots	18
Hybrid compatible slots	16
PXIe system slot	1 (with three system expansion slots)
PXIe timing slot	1 (also accepts PXIe module)
Module compatibility	PXIe, PXI-Hybrid, PXI-1 (J1 only), and cPCI (J1 only)
System slot link configuration (fixed)	2-link configuration (x8, x16)
Backplane speed	PCIe revision 3.0 (Gen 3)
Mechanical	
Size	444.4 mm W x 194.8 mm H x 466 mm D (with feet installed) 444.4 mm W x 177.8 mm H x 466 mm D (with feet removed) 4U x 1 rack width
Weight (without modules)	13.3 kg (29.3 lbs)
Power supply characteristics	
AC input	
Operating voltage/power (low-line) <sup>1</sup>	100/120 V, 1200 W Maximum
Operating voltage/power (high-line) <sup>1</sup>	220/240 V, 1300 W Maximum
Input frequency range	50/60 Hz
Mains supply voltage fluctuations are not to exceed $\pm 10\%$ of the nominal voltage.	
Transient over-voltages typically present on the Mains supply (installation CAT II).	
Over current protection	Internal fuse in line
Available DC output power (for module slots)	
Total DC power <sup>2</sup>	
220/240 V input:	800 W
100/120 V input:	650 W

## Power supply characteristics

1. Auto switching between high line and low line.
2. No derating required for temperature or altitude.

DC Supplies					
Voltage	Maximum Current <sup>1</sup>		Load Regulation	Maximum ripple and noise (<20 MHz BW)	
	45 °C, <10kft	50 °C, 10kft			
+3.3 V	70 A	67 A	5%	1.5% (pk-pk)	
+5 V	60 A <sup>2</sup>	52.5 A <sup>2</sup>	5%	1% (pk-pk)	
+12 V	52.5 A <sup>2</sup>	45 A <sup>2</sup>	5%	1% (pk-pk)	
-12 V	4 A	4 A	5%	1% (pk-pk)	
5 Vaux	2 A	2 A	5%	50mV (pk-pk)	
Backplane pin current capacity					
Slot	+3.3 V	+5 V	+12 V	-12V	5 Vaux
System controller slot	9 A	9 A	11 A	0 A	1 A
System timing/PXle slot	6 A	0 A	4 A	0 A	1 A
PXle hybrid slot	6 A	6 A	4 A	1 A	1 A
Chassis cooling and power dissipation characteristics					
Slot airflow direction			Bottom of module to top of module		
Chassis cooling intake			Bottom of front bezel, side panels, and bottom panel of chassis		
Chassis cooling exhaust			Rear of chassis		
Chassis cooling fans			Three 186 cfm fans on rear panel with HIGH/AUTO speed selector		
Power dissipation, system slot			140 W max		
Power dissipation, user slot			42 W max <sup>3</sup>		
Power dissipation, timing slot			42 W max <sup>3</sup>		

1. The total power supplied for all rails must not exceed 650 W (100/120 V) or 800 W (220/240 V).
2. The total power supplied for 5 V and 12 V rails must not exceed 630 W at 45 °C, <10k ft, or 540 W at 50 °C, 10k ft.
3. Maximum per slot power dissipation at 55 °C with 15 °C temperature rise; requires: a) that the chassis bottom is not blocked (1U rack space below or sitting on bench with feet extended) OR b) two air inlet modules in slots 9, 10, or 11, and a slot blocker in empty controller slots. Module cooling can be impacted by each module's resistance to air flow.

Clocks and Triggers	
10 MHz system clock (PXI_CLK10)	
Maximum slot-to-slot skew	155 ps
Accuracy	30 ppm
Output amplitude (10 MHz REF Out BNC)	1 V pk-pk 20% square-wave into 50 $\Omega$ 2 V pk-pk unloaded
Output impedance (10 MHz REF Out BNC)	50 $\Omega$ $\pm$ 5 $\Omega$
100 MHz system clock (PXIe_CLK100)	
Maximum slot-to-slot skew	125 ps
Accuracy	30 ppm
External 10 MHz clock source input requirements	
Frequency input	10 MHz $\pm$ 100 ppm
Input signal (10 MHz REF In BNC)	100 mVPP to 5 Vpp (square or sine wave)
Input signal (PXI timing slot PXI_CLK10_IN)	5V or 3.3 V TTL signal
PXI star trigger	
Maximum slot-to-slot skew	250 ps
PXI differential star triggers	
Maximum slot-to-slot skew	150 ps
Maximum differential skew	25 ps
Front panel triggers (trig 1 and trig 2 SMBs)	
Direction control	Input or Output (configurable)
Output level	3.3 V CMOS (TTL Compatible, 5 V tolerant)
Output impedance	50 $\Omega$ (typ)
Output trigger source	PXI_Trig0 – PXI_Trig7 (Segment 2)
Input level	3.3 V CMOS (TTL Compatible, 5 V tolerant)
Input impedance	3 k $\Omega$ (typ)
Input trigger destination	PXI_Trig0 – PXI_Trig7 (Segment 2)
Input threshold	1.65 V (typ)
Minimum swing	250 mV
Minimum pulse width	100 ns (typ)

Environmental Characteristics <sup>1,2</sup>		
Operating and storage conditions		
	Operating	Storage
Temperature	0 °C to 55 °C	-40 °C to 70 °C
Altitude	Up to 10,000 ft (3048 m)	Up to 15,000 ft (4572 m)
Humidity	Type-tested at 95%, +40°C (non-condensing)	
Vibration		
	Operating random vibration: type-tested at 5 to 500 Hz, 0.21 g rms	
	Survival random vibration: type-tested at 5 to 500 Hz, 2.09 g rms	
Acoustical emissions (referenced to 1 pW)		
	Auto fan (25°C ambient)	High Fan
Sound pressure level <sup>3</sup>	53 dBA	69 dBA
Sound Power	59 dBA	77 dBA
Regulatory Characteristics		
Safety	Complies with the essential requirements of the European LVD Directive of the following standards (dates and editions are cited in the Declaration of Conformity):	
	<ul style="list-style-type: none"> <li>- IEC/EN 61010-1</li> <li>- Canada: CSA C22.2 No. 61010-1</li> <li>- USA: UL std no. 61010-1</li> </ul>	
Acoustic statement (European Machinery Directive)	Acoustic noise emission LpA < 70 dB Operator position Normal operation mode per ISO 7779	
EMC	Complies with European EMC Directive of the following standards (dates and editions are cited in the Declaration of Conformity):	
	<ul style="list-style-type: none"> <li>- IEC/EN 61326-1</li> <li>- CISPR pub 11 group 1, class A</li> <li>- AS/NZS CISPR 11</li> <li>- ICES/NMB-001</li> </ul>	
	This ISM device complies with Canadian ICES-001. Cet appareil ISM est conforme a la norme NMB-001 du Canada	

1. Samples of this product have been type tested in accordance with the Keysight Environmental Test Manual and verified to be robust against the environmental stresses of storage, transportation and end-use. Those stresses include but are not limited to temperature, humidity, shock, vibration, altitude and power line conditions.

2. Test Methods are aligned with IEC 60068-2 and levels are similar to MIL-PRF-28800F Class 3.

3. At operator position

## Recommended Configuration

### **Configure the Keysight M9019A PXIe chassis as follows:**

- Select a PXIe system module (the Keysight M9022A, M9023A, or M9024A System Interface Modules are recommended) or embedded controller (M9037A).
- If an external computer is being used, select an appropriate PC interface card (the Keysight M9048B or M9049A Host Adapter Interface modules are recommended).
- Select an appropriate cable to connect the computer interface board to the chassis interface (the Y1202A is recommended to connect the M9048B and M9022A).
- Select accessories as required.

## Multi-chassis Configuration

The M9019A can be used in multi-chassis configurations with other PXIe chassis (including the M9010A, M9018A, M9018B, M9019A and the AXIe chassis (M9502A and M9505A). In general, up to four chassis can be connected together depending on the controller and operating system used. Different topologies include cascade and star.









This information is subject to change without notice.

© Keysight Technologies, 2018

Published in USA

Third Edition, May 2018



M9019-90015

[www.keysight.com](http://www.keysight.com)